




MULTI-DEVICE
WIRELESS KEYBOARD

CONNECT UP TO 4 DEVICES



USER MANUAL

BEFORE USING YOUR NEW PRODUCT, PLEASE READ
THESE INSTRUCTIONS TO PREVENT ANY DAMAGE.

SPECIFICATIONS

- Keys: 78
- Length: 287 ±0.50 mm
- Width:128 ±0.50mm
- Thickness: 20 ±0.50 mm
- Weight: 325g ±5g
- Press force: 52±7gf
- Keys switch life: 5 million times
- Key cap drawing force: 1Kg vertical pullout
- Version: English

ELECTRICAL PERFORMANCE

- Working frequency: 2.4G
- Power saving way: 2 automatically dormant mode
- Working distance:≥10m
- Battery: 2*AAA 3V built-in lithium battery
- Working current: 0.8 ~ 2.3mA

- Dormancy current:
 - Press keys dormancy: 90uA
 - No connect dormancy: 78uA;
 - Deep dormancy 25uA
- Working voltage: 1.1V-1.62V
- Compatible with Windows 98 and updated versions, Mac and Android systems.
- FN+F1 Player
- FN+F2 Volume reduction
- FN+F3 Volume increase
- FN+F4 Mute
- FN+F5 Last song
- FN+F6 Next song
- FN+F7 Play/pause
- FN+F8 Stop
- FN+F9 Web searching
- FN+F10 Mailbox
- FN+F11 Enter into “My Computer”(No function at Bluetooth mode)
- FN+F12 Collect(No function at Bluetooth mode)

- Working temperature range: 0°C to 40°C
- Working humidity range: ≤90%
- Transportation temperature range:
-15°C- 60°C
- Transportation humidity range: ≤90%

FCC

OPERATION

- Keyboard 2.4G Mode
Pull the insulator tab out, then, switch the on/off button to on state, the left green lock indicator light will flash 7 times and stop. Once connected, insert the USB dongle into the USB port of computer or laptop (a device which doesn’t support 2.4G). Then press FN+1 key simultaneously, the blue lock indicator light means 2.4G is connected successfully.
- Keyboard Bluetooth Mode
Pull the insulator tab out, then, switch the on/off button to on state, the left green lock indicator light will flash 7 times and stop, waiting for connection.

- Ensure the Bluetooth of the devices you are about to connect with Keyboard is on.
- Bluetooth 1 channel: Press FN+2 key simultaneously, the left blue lock indicator light will flash indicating it is ready to pair. Search “Monster Keyboard” on device to connect, after connecting successfully, indicator light will turn off.
- Bluetooth 2 channel: Press FN+3 key simultaneously, the left red lock indicator light will flash indicating it is ready to pair. Search “Monster keyboard 2” on device to connect, after connecting successfully, indicator light will turn off.
- Bluetooth 3 channel: Press FN+4 key simultaneously, the right red battery indicator light will flash indicating it is ready to pair, search “Monster keyboard 3” on device to connect, after connecting successfully, indicator light will turn off.



This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.
- Caution: Changes or modifications not expressly approved by the party responsible for compliance could void the user’s authority to operate this device.
- NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However,there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: Reorient or relocate the receiving antenna. Increase the separation between the equipment and receiver. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. Consult the dealer or an experienced radio/ TV technician for help.
- This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 0cm between the radiator and your body.

Safety information & specifications



**IMPORTANT SAFETY INSTRUCTIONS -
SAVE THESE INSTRUCTIONS**
CAUTION: Do not use this product for any purpose not explicitly specified by Monster®

Lifeworks shall not be held liable for any improper or incorrect use of the Product, any installation of the Product, or any modification of the Product and Lifeworks assumes no responsibility for such improper or incorrect use of the Product, the installation of the Product, or any modification to the Product. In no event shall Lifeworks be liable for any direct, indirect, incidental, special, exemplary, or consequential damages however caused and on any theory of liability, whether in contract, strict liability, or tort (including negligence or otherwise) arising in any way out of the installation of the Product, or improper or incorrect use of the Product or any modification of the Product. This disclaimer of liability applies to any damages or injury, whether based upon breach of contract, tortious behavior, negligence, or under any other cause of action.

Website: www.monsterstore.com
Support: support@monsterstore.com
Customer Service: 877-543-3540

The M Monster logo, and Powered by Monster are trademarks or registered trademarks trademark. All brands are registered trademarks of their used under license of Monster, Inc. ©2023 All rights reserved. Manufactured, marketed and distributed by Lifeworks Technology Group LLC. under license.

