

RF TEST REPORT

Applicant	Aava Mobile Oy
FCC ID	2ABVH-INARI10E2
Product	10" Tablet Computer
Brand	AAVA
Model	INARI-E-10-T5G-1
Report No.	EFTA25070216-IE-03-R17
Issue Date	March 27, 2026

Eurofins TA Technology (Shanghai) Co., Ltd. tested the above equipment in accordance with the requirements in **FCC CFR 47 Part 96E**. The test results show that the equipment tested is capable of demonstrating compliance with the requirements as documented in this report.

Prepared by: Xu Ying

Approved by: Xu Kai

Eurofins TA Technology (Shanghai) Co., Ltd.

Building 3, No.145, Jintang Rd, Pudong Shanghai, P.R.China

TEL: +86-021-50791141/2/3

FAX: +86-021-50791141/2/3-8000

TABLE OF CONTENT

1	Test Laboratory	4
1.1	Notes of the Test Report	4
1.2.	Test facility	4
1.3	Testing Location	4
2	General Description of Equipment under Test	5
2.1	Applicant and Manufacturer Information	5
2.2	General information	5
3	Applied Standards	6
4	Test Case	7
4.1	RF Power Output and Effective Isotropic Radiated Power	7
4.2	Radiated Spurious Emission	8
5	Test Results	11
5.1	RF Power Output and Effective (Isotropic) Radiated Power	11
6	Main Test Instruments	13
7	The EUT Appearance	14
8	Test Setup Photos	15

Summary of Measurement Results

Test Case	Clause in FCC rules	Limits		Verdict				
LTE Band 48								
RF Power Output and Effective Isotropic Radiated Power	96.41	<table><tr><th>Device¹⁾</th><th>Maximum EIRP²⁾ (dBm/10MHz)²⁾</th></tr><tr><td>End User Device¹⁾</td><td>23²⁾</td></tr></table>	Device ¹⁾	Maximum EIRP ²⁾ (dBm/10MHz) ²⁾	End User Device ¹⁾	23 ²⁾	PASS	Note 1
Device ¹⁾	Maximum EIRP ²⁾ (dBm/10MHz) ²⁾							
End User Device ¹⁾	23 ²⁾							
Occupied Bandwidth	Refer to the Module report (Model: FN920C04-WW; Report No.: TERF2410003184ER; FCC ID: RI7FN920C04WW, Grant date: 04/28/2025)							
Band Edge Compliance								
Peak-to-Average Power Ratio								
Frequency Stability								
Spurious Emissions at Antenna Terminals								
End User Device Additional Requirements (CBSD Protocol)	Refer to the Module report (Model: FN920C04-WW; Report No.: TERF2410003185ER; FCC ID: RI7FN920C04WW, Grant date: 04/28/2025)							
Radiated Spurious Emission	2.1051 / 96.41	Rule Part 96.41(e) (2) specifies that “Additional protection levels. Notwithstanding paragraph (e)(1) of this section, for CBSDs and End User Devices, the conducted power of emissions below 3540 MHz or above 3710 MHz shall not exceed –25 dBm/MHz, and the conducted power of emissions below 3530 MHz or above 3720 MHz shall not exceed –40dBm/MHz.”		PASS				
Date of Testing: July 16, 2025 ~ July 25, 2025 Date of Sample Received: July 16, 2025								
Note: 1. Because of the change of antenna gain, ERP/EIRP need to be re-evaluated. 2. PASS: The EUT complies with the essential requirements in the standard. 3. FAIL: The EUT does not comply with the essential requirements in the standard. All indications of Pass/Fail in this report are opinions expressed by Eurofins TA Technology (Shanghai) Co., Ltd. based on interpretations and/or observations of test results. Measurement Uncertainties were not taken into account and are published for informational purposes only.								

1 Test Laboratory

1.1 Notes of the Test Report

This report shall not be reproduced in full or partial, without the written approval of **Eurofins TA Technology (Shanghai) Co., Ltd.** The results documented in this report apply only to the tested sample, under the conditions and modes of operation as described herein. Measurement Uncertainties were not taken into account and are published for informational purposes only. This report is written to support regulatory compliance of the applicable standards stated above.

1.2. Test facility

FCC (Designation number: CN1179, Test Firm Registration Number: 446626)

Eurofins TA Technology (Shanghai) Co., Ltd. has been listed on the US Federal Communications Commission list of test facilities recognized to perform measurements.

A2LA (Certificate Number: 3857.01)

Eurofins TA Technology (Shanghai) Co., Ltd. has been listed by American Association for Laboratory Accreditation to perform measurement.

1.3 Testing Location

Company:	Eurofins TA Technology (Shanghai) Co., Ltd.
Address:	Building 3, No.145, Jintang Rd, Pudong Shanghai, P.R.China
City:	Shanghai
Post code:	201201
Country:	P. R. China
Contact:	Xu Kai
Telephone:	+86-021-50791141/2/3
Fax:	+86-021-50791141/2/3-8000
Website:	https://www.eurofins.com/electrical-and-electronics
E-mail:	Kain.Xu@cpt.eurofinscn.com

2 General Description of Equipment under Test

2.1 Applicant and Manufacturer Information

Applicant	Aava Mobile Oy
Applicant address	Nahkatehtaankatu 2, FI-90130 Oulu, Finland
Manufacturer	Aava Mobile Oy
Manufacturer address	Nahkatehtaankatu 2, FI-90130 Oulu, Finland

2.2 General information

EUT Description				
Model	INARI-E-10-T5G-1			
SN	XBBB2FC5100049			
Hardware Version	DV2			
Software Version	007			
Power Supply	Battery / AC adapter			
Antenna Type	Internal Antenna			
Rated Power Supply Voltage	3.85 VDC			
Operating Voltage	Minimum: 3.20V Maximum: 4.40V			
Operating Temperature	Lowest: -10°C Highest: +50°C			
Operating Frequency Range(s)	Mode	Tx (MHz)	Rx (MHz)	Gain (dBi)
	LTE Band 48	3550 ~ 3700	3550 ~ 3700	2.5
Power Class	3			
Maximum E.I.R.P./ E.R.P.	LTE Band 48	22.54 dBm		
EUT Accessory				
Battery	Manufacturer: Shenzhen Guangwei Electronic Technology Co., Ltd. Model: AMME5260			
Note: The EUT is sent from the applicant to Eurofins TA and the information of the EUT is declared by the applicant.				

3 Applied Standards

According to the specifications of the manufacturer, it must comply with the requirements of the following standards:

Test standards:

FCC CFR 47 Part 96E (2025)

Reference standard:

FCC CFR 47 Part 2 (2025)

ANSI C63.26-2015

KDB 971168 D01 Power Meas License Digital Systems v03r01

4 Test Case

4.1 RF Power Output and Effective Isotropic Radiated Power

Ambient condition

Temperature	Relative humidity	Pressure
15°C ~ 35°C	20% ~ 80%	86 kPa ~ 106 kPa

Methods of Measurement


During the process of the testing, The EUT was connected to the Base Station Simulator with a known loss. The EUT is controlled by the Base Station Simulator test set to ensure max power transmission with proper modulation.

ERP can then be calculated as follows:

$EIRP \text{ (dBm)} = \text{Output Power (dBm)} + \text{Antenna Gain (dBi)}$

$EIRP \text{ (dBm)} = ERP \text{ (dBm)} + 2.15 \text{ (dB.)}$

Test Setup



Measurement Uncertainty

The assessed measurement uncertainty to ensure 95% confidence level for the normal distribution is with the coverage factor $k = 2$, $U=0.4 \text{ dB}$ for RF power output, $k = 2$, $U= 1.19 \text{ dB}$ for ERP/EIRP.

Test Results

Refer to the section 6.1 of this report for test data.

4.2 Radiated Spurious Emission

Ambient condition

Temperature	Relative humidity	Pressure
15°C ~ 35°C	20% ~ 80%	86 kPa ~ 106 kPa

Method of Measurement

1. The testing follows FCC KDB 971168 D01 v03r01 Section 5.8 and ANSI C63.26-2015.
2. Below 1GHz: The EUT is placed on a turntable 0.8 meters above the ground in the chamber, 3 meter away from the antenna. The maximal emission value is acquired by adjusting the antenna height, polarisation and turntable azimuth. Normally, the height range of antenna is 1 m to 4 m, the azimuth range of turntable is 0° to 360°, and the receive antenna has two polarizations Vertical (V) and Horizontal (H). Above 1GHz: (Note: the FCC's permission to use 1.5m as an alternative per TCBC Conf call of Dec. 2, 2014.) The EUT is placed on a turntable 1.5 meters above the ground in the chamber, 3 meter away from the antenna. The maximal emission value is acquired by adjusting the antenna height, polarisation and turntable azimuth. Normally, the height range of antenna is 1 m to 4 m, the azimuth range of turntable is 0° to 360°, and the receive antenna has two polarizations Vertical (V) and Horizontal (H).
3. A loop antenna, A log-periodic antenna or horn antenna shall be substituted in place of the EUT. The log-periodic antenna will be driven by a signal generator and the level will be adjusted till the same power value on the spectrum analyzer or receiver. The level of the spurious emissions can be calculated through the level of the signal generator, cable loss, the gain of the substitution antenna and the reading of the spectrum analyzer or receiver.
4. The EUT is then put into continuously transmitting mode at its maximum power level during the test. Set Test Receiver or Spectrum RBW=100kHz, VBW=300kHz for 30MHz to 1GHz and RBW=1MHz, VBW=3MHz for above 1GHz, and the maximum value of the receiver should be recorded as (Pr).
5. The EUT shall be replaced by a substitution antenna. In the chamber, an substitution antenna for the frequency band of interest is placed at the reference point of the chamber. An RF Signal source for the frequency band of interest is connected to the substitution antenna with a cable that has been constructed to not interfere with the radiation pattern of the antenna. A power (PMea) is applied to the input of the substitution antenna, and adjust the level of the signal generator output until the value of the receiver reach the previously recorded (Pr). The power of signal source (PMea) is recorded. The test should be performed by rotating the test item and adjusting the receiving antenna polarization.
6. A amplifier should be connected to the Signal Source output port. And the cable should be connect between the Amplifier and the Substitution Antenna. The cable loss (Pcl) ,the Substitution Antenna Gain (Ga) and the Amplifier Gain (PAg) should be recorded after test.
7. The measurement results are obtained as described below:


$$\text{Power(EIRP)} = \text{PMea} - \text{PAg} - \text{Pcl} + \text{Ga}$$
The measurement results are amend as described below:

$$\text{Power(EIRP)} = \text{PMea} - \text{Pcl} + \text{Ga}$$
8. This value is EIRP since the measurement is calibrated using an antenna of known gain (2.15 dB) and known input power. ERP can be calculated from EIRP by subtracting the gain of the dipole, $\text{ERP} = \text{EIRP} - 2.15\text{dB}$.


The modulation mode and RB allocation refer to section 5.1, using the maximum output power configuration.

Test setup


9KHz~ 30MHz



30MHz~ 1GHz



Above 1GHz



Note: Area side:2.4mX3.6m

Measurement Uncertainty


The assessed measurement uncertainty to ensure 95% confidence level for the normal distribution is with the coverage factor $k = \pm 1.96$, $U = \pm 3.55$ dB.

Test Results


The detailed test data see EFTA25070216-IE-03-G.

5 Test Results


5.1 RF Power Output and Effective (Isotropic) Radiated Power




LTE B48_5M_CHMID_RB48



LTE B48_10M_CHMID_RB48



LTE B48_15M_CHMID_RB48



LTE B48_20M_CHMID_RB48

Test Data File Name	Frequency (MHz)	EIRP (dBm)
LTE B48_5M_CHMID_RB48	3622.99	21.16
LTE B48_10M_CHMID_RB48	3620.06	21.68
LTE B48_15M_CHMID_RB48	3618.41	21.87
LTE B48_20M_CHMID_RB48	3616.07	22.54

6 Main Test Instruments

Name	Manufacturer	Type	Serial Number	Calibration Date	Expiration Date
Spectrum Analyzer	R&S	FSV30	100815	2024-12-02	2025-12-01
Loop Antenna	SCHWARZBECK	FMZB1519	1519-047	2023-04-16	2026-04-15
TRILOG Broadband Antenna	SCHWARZBECK	VULB 9163	391	2022-09-29	2025-09-28
Horn Antenna	SCHWARZBECK	BBHA 9120D	1594	2023-12-05	2026-12-04
Software	R&S	EMC32	10.35.10	/	/

7 The EUT Appearance

Refer to *EUT Appearance*.

8 Test Setup Photos

Refer to *Part96 Test Setup*.

***** END OF REPORT *****