

Magnetic Power Bank Air 5000mAh

User Guide & Safety and Warranty

OnePlus Magnetic Power Bank Air 5000mAh (Customer invoice)

Dear user, thank you for using this product. To better serve your needs, please read and fill out the warranty card.

User Information

Name:

Phone No.:

E-mail:

Address:

Product Information

Model:

S/N:

Dealer Information

Date of Purchase:

Dealer's Name:

Dealer's Address:

OnePlus Magnetic Power Bank Air 5000mAh (Stub invoice)

Dear user, thank you for using this product. To better serve your needs, please read and fill out the warranty card.

User Information

Name:

Phone No.:

E-mail:

Address:

Product Information

Model:

S/N:

Dealer Information

Date of Purchase:

Dealer's Name:

Dealer's Address:

Product overview

Interfaces:

- Input Interface: Type-C(IN)
- Output Interface: Type-C(OUT), Wireless Output


Key:

- Click to check the remaining battery level;
- Double-click to activate Low-Current Mode (for charging small devices such as smartwatches, fitness trackers, or earbuds). LED indicators will flash sequentially. Click again to exit the mode, or it will automatically exit after 6 hours.
- Press and hold the key for 10 seconds to reset the power bank.

Indicator:

- When you charge the power bank, its LED indicators flash sequentially, and all four indicators remain constantly on after the power bank is fully charged;
- When you use the power bank to charge another device, the number of constantly on indicators represents the current battery level.

To prevent malfunctions during use, the power bank should be used together with the officially provided magnetic protective case.



Package contents

- Power Bank × 1
- Data cable × 1
- User Manual × 1

Specifications

Model: MPBV02

Rechargeable lithium-ion Cell

Rated Energy: 19.35Wh

Cell Typical Capacity: 5100mAh Cell Rated Capacity: 5000mAh

Rated Capacity: 2700mAh (5V=2A)

Input: 5V=2.4A 12W(Max)

Type-C Output: 5V=2A 10W(Max)

Wireless Output: 10W(Max)

* Li-ion batteries experience capacity and power fade with time and use. The battery capacity marked on the product is the rated capacity when the product is shipped.

* When the outputs of both charging ports are 5V=2A, the conversion efficiency of useful output energy is greater than or equal to 65%.

Safety information

- Keep the product dry and avoid exposing it to high humidity, high temperatures, or dusty environments.
- When not in use, store the product in a cool, dry place.
- Do not hit, squeeze, drop, or disassemble the product.
- Do not use the product during a thunderstorm. Thunderstorms can result in device malfunction and increase the risk of electric shocks.
- Ideal operating temperatures are +5°C to +35°C, and ideal storage temperatures (for the product and accessories) are -5°C to +45°C.
Extreme heat or cold may damage this product.
- If using a charger to charge the product, the output of the charger must match the specifications of the product, and the charger must conform to the latest IEC60950-1/IEC62368-1 standards.
- It is recommended to charge this product using chargers and cables that conform to the USB charging specifications. To ensure safety when using chargers and cables that do not conform to the specifications, the maximum charging output should not exceed 5V/500mA.

- If using the product with a USB cable other than the one supplied with it, make sure that the connector on the cable bears the USB logo, and that the cable is USB-IF certified.
- Keep the product away from high-temperature environments (such as direct sunlight) and heating sources (such as heaters and ovens). The product may explode if overheated.
- Do not disassemble or refit the product, insert foreign objects into it, or expose it to liquids. Doing so may result in battery fluid leakage, overheating, fire, or explosion.
- Do not use unapproved or incompatible power supplies or chargers with the product. Doing so may result in fire, explosion, or other hazards.
- Do not expose the product to fire. Dispose of product accessories in accordance with local laws and regulations. These accessories can be recycled. Dispose of the product itself in accordance with local laws and regulations. Do not dispose of the product alongside household waste. Improper disposal of the product may result in explosion.
- Do not drop, squeeze, or puncture the product. Applying excessive external pressure to the product may cause short circuits or overheating. Do not use a non-standard USB cable to charge or discharge the product, as this could cause fire or explosion.
- When charging the product, plug the charger into a power socket that is close to the product and within easy reach. Disconnect the charger from the power socket when the product is fully charged or is not being charged.
- Keep the product and its accessories out of reach of children and pets to prevent them from accidentally swallowing and choking on small parts of this product.
- The battery in the product cannot be replaced. Do not attempt to replace the battery yourself, as doing so may damage the battery or product.
- Keep the product away from high-temperature environments (such as direct sunlight) and heating sources (such as heaters and ovens). The product may explode if overheated.
- Do not disassemble or refit the product, insert foreign objects into it, or expose it to liquids. Doing so may result in battery fluid leakage, overheating, fire, or explosion.
- Do not use unapproved or incompatible power supplies or chargers with the product. Doing so may result in fire, explosion, or other hazards.
- Do not expose the product to fire. Dispose of product accessories in accordance with local laws and regulations. These accessories can be recycled. Dispose of the product itself in accordance with local laws and regulations. Do not dispose of the product alongside household waste. Improper disposal of the product may result in explosion.
- Do not drop, squeeze, or puncture the product. Applying excessive external pressure to the product may cause short circuits or overheating. Do not use a non-standard USB cable to charge or discharge the product, as this could cause fire or explosion.

- When charging the product, plug the charger into a power socket that is close to the product and within easy reach. Disconnect the charger from the power socket when the product is fully charged or is not being charged.
- Keep the product and its accessories out of reach of children and pets to prevent them from accidentally swallowing and choking on small parts of this product.
- The battery in the product cannot be replaced. Do not attempt to replace the battery yourself, as doing so may damage the battery or product.
- In medical and other places where the use of wireless devices is expressly prohibited, please follow the rules of the place.
- The electromagnetic waves generated by the magnets and some components contained in this product may affect the normal operation of implanted medical devices or personal medical devices, such as pacemakers, cochlear implants, hearing aids or other medical devices. If you use these medical devices, please consult the manufacturer or physician about the restrictions on use of this product. If there are no restrictions from the medical device manufacturer, maintain a distance of at least 30cm.
- Do not place any metal object on the surface of the wireless charge to avoid device failure or heating.
- This product is not intended for use in an automobile. In certain cases it may interfere with automotive electronic systems.
- When using the product, maintain a distance of 20 cm from the body to ensure compliance with RF exposure requirements.

Reduction of hazardous substances

This device and any electrical accessories are compliant with local applicable rules on the restriction of the use of certain hazardous substances in electrical and electronic equipment. For declarations of conformity about REACH, please visit our web site: <https://service.oneplus.com/global/search/reach-regulation>

Waste Electrical and Electronic Equipment (WEEE)



This symbol (with or without a solid bar) means that according to local laws and regulations, your product and/or its battery shall be disposed of separately from household waste. When this product reaches the end of its life, you can give it to a competent recycling organization for handling. Proper recycling of your product will protect human health and the environment.

If you are not sure what to do with e-waste, please contact your local authorities, retailer, or household waste disposal service.

EU Declaration of Conformity



Hereby, OnePlus Technology (Shenzhen) Co., Ltd. declares that the Power bank (MPBV01) is in compliance with Directive 2014/35/EU, 2014/30/EU and 2011/65/EU. The full text of the EU declaration of conformity is available at the following internet address: <https://www.oneplus.com/support/manuals>.

RF exposure information

RF exposure assessment has been performed below to prove that this unit will not generate the harmful EM emission above the reference level as specified in EC Council Recommendation (1999/519/EC).

When using this device as a wireless charger it is intended for use as a desktop device and should not be carried when in this mode. To comply with RF exposure requirements when using in the wireless charging mode please place the device at a minimum distance of 0mm from persons.

WPT (111KHz~148.5KHz): -6.47 dBuA/m@10m

FCC Regulatory Conformance

FCC Statement

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference; and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

NOTE: The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications or changes to this equipment. Such modifications or changes could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful to part interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC Caution

- Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
- The antenna(s) used for this transmitter must not be collocated or operate in conjunction with any other antenna or transmitter.

RF Exposure Information (SAR)

- This device is designed and manufactured not to exceed the emission limits for exposure to radio frequency (RF) energy set by the Federal Communications Commission of the U.S. Government.
- The SAR limit set by the FCC is 1.6W/kg. The highest SAR value of this device type complies with this limit. And please see the "Quick Start Guide" card to find the highest SAR value reported to FCC.
- Tests for SAR are conducted using standard operating positions accepted by the FCC with the device transmitting at its highest certified power level in all tested frequency bands.
- Although the SAR is determined at the highest certified power level, the actual SAR level of the device while operating can be well below the maximum value. This is because the device is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the power output.
- While there may be differences between the SAR levels of various devices and at various positions, they all meet the government requirement.
- During testing, device radios are set to their highest transmission levels and placed in positions that simulate use near the body without distance. Accessories with metal parts may change the RF performance of the device and use such accessories should be avoided.

Limited Warranty

Dear user, thank you for using this product. In case of any damage that is not caused by human factors, we will provide comprehensive warranty services according to local laws and regulations.

To protect your legal interests, please read the following notes carefully:

- A valid Proof of Purchase shall be issued by the seller at the time of purchase.
- Please keep your Warranty Card and Proof of Purchase for future reference.
- In case of any damage to the product that is not due to human factors, consumers are entitled to enjoy customer service free of charge by providing Warranty Card and Proof of Purchase within the warranty period.

The warranty is not applicable in the following cases:

1. The valid warranty period expires.
2. The product is damaged because it is accidentally dropped or immersed in water when in use.
3. Damages are caused by human factors such as unauthorized disassembly, modification, etc.

4. Damages are caused by force majeure (e.g. fires, earthquakes, and lightning).
 5. Damages are caused by improper usage that does not conform to the user guide or operation manual.
 6. Damages are caused by usage in environments not conforming to product specifications.
 7. Information on Warranty Card or Proof of Purchase is inconsistent with the product serial number or has been altered.
 8. The SN code of the product is missing, damaged, or blurred beyond recognition.
- For more details about our warranty policy, please visit <https://support.oppo.com>.

Statement

 and OnePlus are trademarks or registered trademarks of OnePlus Technology (Shenzhen) Co., Ltd.

Other trademarks and trade names are the property of their respective owners.
Copyright © 2024 OnePlus Technology (Shenzhen) Co., Ltd. All rights reserved.