

1. Effective (Isotropic) Radiated Power Output Data

1.1 Test Result

1.1.1 PCS1900_EIRP

Band: PCS1900								
ENV	Mode		Frequency (MHz)	Conducted Power (dBm)	Gain (dBi)	EIRP (dBm)		Verdict
	Network	Subset				Result	Limit	
NTNV	GSM	GSM	1850.2	29.15	-0.91	28.24	<=33.01	Pass
			1880	29.39	-0.91	28.48	<=33.01	Pass
			1909.8	29.58	-0.91	28.67	<=33.01	Pass
	GPRS	1 TX Slot	1850.2	29.27	-0.91	28.36	<=33.01	Pass
		2 TX Slots	1850.2	26.66	-0.91	25.75	<=33.01	Pass
		3 TX Slots	1850.2	24.97	-0.91	24.06	<=33.01	Pass
		4 TX Slots	1850.2	22.82	-0.91	21.91	<=33.01	Pass
		1 TX Slot	1880	29.41	-0.91	28.50	<=33.01	Pass
		2 TX Slots	1880	26.47	-0.91	25.56	<=33.01	Pass
		3 TX Slots	1880	24.72	-0.91	23.81	<=33.01	Pass
		4 TX Slots	1880	22.51	-0.91	21.60	<=33.01	Pass
		1 TX Slot	1909.8	29.55	-0.91	28.64	<=33.01	Pass
		2 TX Slots	1909.8	26.41	-0.91	25.50	<=33.01	Pass
		3 TX Slots	1909.8	24.65	-0.91	23.74	<=33.01	Pass
		4 TX Slots	1909.8	22.52	-0.91	21.61	<=33.01	Pass
	EGPRS	1 TX Slot	1850.2	25.46	-0.91	24.55	<=33.01	Pass
		2 TX Slots	1850.2	23.64	-0.91	22.73	<=33.01	Pass
		3 TX Slots	1850.2	21.15	-0.91	20.24	<=33.01	Pass
		4 TX Slots	1850.2	18.79	-0.91	17.88	<=33.01	Pass
		1 TX Slot	1880	25.73	-0.91	24.82	<=33.01	Pass
		2 TX Slots	1880	23.81	-0.91	22.90	<=33.01	Pass
		3 TX Slots	1880	21.30	-0.91	20.39	<=33.01	Pass
		4 TX Slots	1880	18.90	-0.91	17.99	<=33.01	Pass
		1 TX Slot	1909.8	25.66	-0.91	24.75	<=33.01	Pass
		2 TX Slots	1909.8	23.58	-0.91	22.67	<=33.01	Pass
		3 TX Slots	1909.8	21.17	-0.91	20.26	<=33.01	Pass
		4 TX Slots	1909.8	18.85	-0.91	17.94	<=33.01	Pass

Note1: EIRP=Conducted Power+Antenna Gain

---End---