

Be responsible and please power on the BLINC unit before riding for your own safety.

Thank you for using BLINC™ BL200 Bluetooth Adapter!

This manual contains a quick guide on how to operate BLINC™ BL200 Bluetooth Adapter and information on installation, and setting of the device. Please read carefully before using the product.

FCC ID: 2ADN5BL200



Package content

Please check following content in package:

Bluetooth Adapter.
Walkie talkie Adapter cable. (Accessories please refer to the actual item not include for some version)
USB Cable

Power on and Power off

Power on

Switch to "ON" position of the power button to power on the adapter. The LED flashes blue when in ready status.

Power off

Switch to "OFF" position of the power button to power off the adapter. The LED turns off when powered off.

Pairing

Pairing with BL100 integrated Bluetooth system.

Please turn BL100 into pairing mode first *. Then Power on BL200 adapter, then push and hold the blue pairing button for 2 seconds until the LED flashes red and blue which indicates it is in pairing mode. In pairing mode, the adapter will search and connect with BL100 automatically. Once paired with BL100, the LED light will flash blue.

Pairing with BL300 multi-functional RC

Power on the BL200 adapter first, then push and hold the blue pairing button for at least 6 seconds. The stable blue LED light indicates the adapter is in pairing mode. Push any button in the BL300 RC, then push and hold any three buttons in the RC until the blue LED light turns off in BL200 adapter, which indicates pairing between two devices is a success.

Note: Blinc BL100 integrated Blinc Bluetooth system can pair with most Bluetooth devices in the market.
Check the user manual on how to turn the BL100 into pairing mode.
Check the user manual on how to turn BL300 into pairing mode.

Pairing with Walkie Talkie or personal intercom system

After pairing the BL100 successfully, please use the walkie talkie/intercom cable in the package to connect the adapter with your radio. The Mini USB end of the cable is used to connect with multi-function port, while the other end is connected with the PTT port of the walkie talkie. The Velcro can be attached to the Walkie Talkie via 3M double side sticker.



Connection illustration

Note: The Walkie talkie/ intercom cable in the package is only compatible with a standardized Kenwood PTT cable. You should contact your local dealer if the standard PTT cable in the package is not compatible with your Walkie Talkie. For other kind of PTT please contact your local dealer for different walkie talkie intercom cable.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules.

Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and**
- (2) this device must accept any interference received, including interference that may cause undesired operation.**