

# --3.2X1.6X0.5 (mm) WiFi/Bluetooth Ceramic Chip Antenna (FH100A)


## Engineering Specification

### 1. Product Number

**FH 3216 S1 P 2G45 01**

1 2 3 4 5 6

**1 2 3 4 5 6**



|                 |              |
|-----------------|--------------|
| (1)Product Type | Chip Antenna |
| (2)Size Code    | 3.2x1.6mm    |
| (3)Type Code    | S1           |
| (4)Packing      | Paper Tape   |
| (5)Frequency    | 2.45GHz      |



深圳市福汇科技有限公司  
SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis

Approved by : MR.MENG

**TITLE : 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip  
Antenna (FH100A) Engineering Specification**

**DOCUMENT  
NO.**

**FH3216S1P2G4501**

**REV.  
B**

## 2. Features

- \*Stable and reliable in performances
- \*Low temperature coefficient of frequency
- \*Low profile, compact size
- \*RoHS compliance
- \*SMT processes compatible

## 3. Applications

- \*Bluetooth earphone systems
- \*Hand-held devices when WiFi /Bluetooth functions are needed, e.g., Smart phone.
- \*IEEE802.11 b/g/n
- \*ZigBee
- \*Wireless PCMCIA cards or USB dongle

## 4. Description

Yingfeng chip antenna series are specially designed for WiFi/Bluetooth applications. Based on yingfeng proprietary design and processes, this chip antenna has excellent stability and sensitivity to consistently provide high signal reception efficiency.

## 5. Electrical Specifications (80 x 40 mm<sup>2</sup> ground plane)

5-1. Electrical Table

| Characteristics    |            | Specifications      | Unit |
|--------------------|------------|---------------------|------|
| Outline Dimensions |            | 3.2x1.6x0.5         | mm   |
| Working Frequency  |            | 2400~2500           | MHz  |
| VSWR               |            | 2 Max.              |      |
| Impedance          |            | 50                  | Ω    |
| Polarization       |            | Linear Polarization |      |
| Gain               | Peak       | 2.5 (typical)       | dBi  |
|                    | Efficiency | 78 (typical)        | %    |



深圳市福汇科技有限公司  
SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis

Approved by : MR.MENG

**TITLE :** 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip  
Antenna (FH100A) Engineering Specification


**DOCUMENT**  
**NO.**

**FH3216S1P2G4501**


**REV.**  
**B**

## 5-2. Return Loss & VSWR

Return Loss (S11)




VSWR(S11)



## 6. Antenna Dimensions & Test Board (unit: mm)

### a. Antenna Dimensions

#### Dimension and Terminal Configuration



| Dimension (mm) |           |
|----------------|-----------|
| L              | 3.15±0.15 |
| W              | 1.55±0.15 |
| T              | 0.50±0.10 |
| A              | 0.35±0.10 |

| No. | Terminal Name |
|-----|---------------|
| 1   | Feeding point |
| 2   | GND           |



深圳市福汇科技有限公司  
SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis

Approved by : MR.MENG

TITLE : 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip  
Antenna (FH100A) Engineering Specification


DOCUMENT  
NO.

FH3216S1P2G4501

REV.

B


b. Test Board with Antenna



Unit: mm

## 7. Radiation Pattern (80 x 40 mm<sup>2</sup> ground plane)

### 7-1. 3D Gain Pattern @ 2442 MHz



深圳市福汇科技有限公司  
SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis

Approved by : MR.MENG

**TITLE :** 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip  
Antenna (FH100A) Engineering Specification

**DOCUMENT**  
**NO.**


**FH3216S1P2G4501**

**REV.**



**B**

**PAGE 4 OF12**

Azimuth = -180.0  
 Elevation = -5.1  
 Roll = 180.0



Azimuth = 0.0  
 Elevation = -90.0  
 Roll = 180.0



7-2. 3D Efficiency Table

| Frequency( MHz) | 2400 | 2410 | 2420 | 2430 | 2442 | 2450 | 2460 | 2470 | 2480 | 2490 | 2500 |
|-----------------|------|------|------|------|------|------|------|------|------|------|------|
| Efficiency (dB) | -1.4 | -1.0 | -0.9 | -0.7 | -0.7 | -0.8 | -0.9 | -1.1 | -1.2 | -1.3 | -1.4 |
| Efficiency (%)  | 72.8 | 73.7 | 74.3 | 74.4 | 75.5 | 75.0 | 74.0 | 73.6 | 73.1 | 72.6 | 71.5 |
| Gain (dBi)      | 2.1  | 2.2  | 2.3  | 2.4  | 2.5  | 2.5  | 2.4  | 1.8  | 1.7  | 1.6  | 1.4  |



深圳市福汇科技有限公司  
 SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis

Approved by : MR.MENG


**TITLE :** 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip  
 Antenna (FH100A) Engineering Specification

DOCUMENT  
 NO.

**FH3216S1P2G4501**

REV.  
 B


### 7-3. 3D Efficiency vs. Frequency



## 8. Layout Guide

### a. Solder Land Pattern:

Land pattern for soldering (gray marking areas) is as shown below. Depending on Customer's requirement, matching circuit as shown below is also recommended.



深圳市福汇科技有限公司  
SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis

Approved by : MR.MENG


**TITLE :** 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip  
Antenna (FH100A) Engineering Specification

**DOCUMENT**  
**NO.**

**FH3216S1P2G4501**

**REV.**  
**B**

PAGE 6 OF12



深圳市福汇科技有限公司  
SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis

Approved by : MR.MENG

**TITLE :** 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip  
Antenna (FH100A) Engineering Specification


DOCUMENT  
NO.

**FH3216S1P2G4501**


REV.  
**B**

## 9. Frequency tuning

a. Chip antenna tuning scenario:



b. Matching circuit : (Center frequency is about 2442 MHz @ 80 x 40 mm<sup>2</sup> ground plane)



| System Matching Circuit Component |             |               |           |
|-----------------------------------|-------------|---------------|-----------|
| Location                          | Description | Vendor        | Tolerance |
| 1                                 | 1.2 pF*     | Murata (0402) | ±0.1 pF   |
| 2                                 | 10PF*       | Murata(0402)  | ±0.5 PF   |
| 3                                 | N/A*        | -             | -         |
| Fine tuning element 4             | 1.5 pF*     | Murata (0402) | ±0.1 pF   |

\*Typical reference values which may need to be changed when circuit boards or part vendors are different.



深圳市福汇科技有限公司  
SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis

Approved by : MR.MENG


TITLE : 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip  
Antenna (FH100A) Engineering Specification

DOCUMENT  
NO.

**FH3216S1P2G4501**


REV.  
**B**

c. Fine tuning element vs. Center frequency



## 10. Soldering Conditions

a. Typical Soldering Profile for Lead-free Process



深圳市福汇科技有限公司  
SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis

Approved by : MR.MENG

TITLE : 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip  
Antenna (FH100A) Engineering Specification

DOCUMENT  
NO.

FH3216S1P2G4501


REV.  
B

## 11. Packing

(1) Quantity/Reel: 5000 pcs/Reel:


### Reel and Taping Specification

#### Reel Specification



| TYPE | SIZE |         | A       | $\phi B$ | $\phi C$ | $\phi D$ | W        | $\phi M$ |
|------|------|---------|---------|----------|----------|----------|----------|----------|
| 3216 | 7"   | 5K/Reel | 2.0±0.5 | 13.5±1.0 | 21±1.0   | 60±1.0   | 11.5±2.0 | 178±2.0  |

#### Tapping Specification



| Packaging  | Type | A         | B         | W        | E         | F        | G        | H        | T         | $\phi D$            | P       |
|------------|------|-----------|-----------|----------|-----------|----------|----------|----------|-----------|---------------------|---------|
| Paper Type | 3216 | 1.90±0.20 | 3.50±0.20 | 8.0±0.20 | 1.75±0.10 | 3.5±0.05 | 4.0±0.10 | 2.0±0.05 | 0.75±0.10 | 1.50<br>+0.10<br>-0 | 4.0±0.1 |



深圳市福汇科技有限公司  
SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis

Approved by : MR.MENG

**TITLE :** 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip  
Antenna (FH100A) Engineering Specification

**DOCUMENT**  
**NO.**

**FH3216S1P2G4501**

**REV.**  
**B**

## Reliability Table

| Test Item                             | Procedure                                                                                                                                                                                                                                                                                         | Requirements<br>Ceramic Type                                                | Remark<br>(Reference)     |
|---------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------|---------------------------|
| Electrical<br>Characterization        |                                                                                                                                                                                                                                                                                                   | Fulfill the electrical<br>specification                                     | User Spec.                |
| Thermal<br>Shock                      | 1. Preconditioning:<br>50 ± 10°C / 1 hr, then keep for 24 ± 1 hrs at room temp.<br>2. Initial measure: Spec: refer Initial spec.<br>3. Rapid change of temperature test:<br>-30°C to +85°C; 100 cycles;<br>15 minutes at Lower category temperature;<br>15 minutes at Upper category temperature. | No Visible Damage.<br>Fulfill the electrical<br>specification.              | MIL-STD-202<br>107        |
| Temperature<br>Cycling                | 1. Initial measure: Spec: refer Initial spec.<br>2. 100 Cycles (-30°C to +85°C), Soak Mode=1 (2 Cycle/hours).<br>3. Measurement at 24 ± 2Hours after test condition.                                                                                                                              | No Visible Damage.<br>Fulfill the electrical<br>specification.              | JESD22<br>JA104           |
| High Temperature<br>Exposure          | 1. Initial measure: Spec: refer Initial spec.<br>2. Unpowered; 500hours @ T=+85°C.<br>3. Measurement at 24 ± 2 hours after test.                                                                                                                                                                  | No Visible Damage.<br>Fulfill the electrical<br>specification.              | MIL-STD-202<br>108        |
| Low Temperature<br>Storage            | 1. Initial measure: Spec: refer Initial spec.<br>2. Unpowered; 500hours @ T= -30°C.<br>3. Measurement at 24 ± 2 hours after test.                                                                                                                                                                 | No Visible Damage.<br>Fulfill the electrical<br>specification.              | MIL-STD-202<br>108        |
| Solderability<br>(SMD Bottom Side)    | Dipping method:<br>a. Temperature: 235 ± 5°C<br>b. Dipping time: 3 ± 0.5s                                                                                                                                                                                                                         | The solder should cover<br>over 95% of the critical<br>area of bottom side. | IEC 60384-21/22<br>4.10   |
| Soldering Heat<br>Resistance<br>(RSH) | Preheating temperature: 150 ± 10°C.<br>Preheating time: 1~2 min.<br>Solder temperature: 260 ± 5°C.<br>Dipping time: 5 ± 0.5s                                                                                                                                                                      | No Visible Damage.                                                          | IEC 60384-21/22<br>4.10   |
| Vibration                             | 5g's for 20 min., 12 cycles each of 3 orientations<br>Note: Use 8"X5" PCB .031" thick 7 secure points on, one long<br>side and 2 secure points at corners of opposite sides. Parts<br>mounted within 2" from any secure point. Test from 10-2000<br>Hz.                                           | No Visible Damage.                                                          | MIL-STD-202<br>Method 204 |
| Mechanical<br>Shock                   | Three shocks in each direction shall be applied along the three<br>mutually perpendicular axes of the test specimen (18 shocks)<br>Peak value: 1,500g's<br>Duration: 0.5ms<br>Velocity change: 15.4 ft/s<br>Waveform: Half-sine                                                                   | No Visible Damage.                                                          | MIL-STD-202<br>Method 213 |
| Humidity<br>Bias                      | 1. Humidity: 85% R.H., Temperature: 85 ± 2 °C.<br>2. Time: 500 ± 24 hours.<br>3. Measurement at 24 ± 2hrs after test condition.                                                                                                                                                                   | No Visible Damage.<br>Fulfill the electrical<br>specification.              | MIL-STD-202<br>Method 106 |



深圳市福汇科技有限公司  
SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis



Approved by : MR.MENG

**TITLE : 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip  
Antenna (FH100A) Engineering Specification**

**DOCUMENT  
NO.**

**FH3216S1P2G4501**

**REV.  
B**

|                    |                                                                                                                                                                                                                                              |                                                                                                                                                                          |              |
|--------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------|
| Board Flex (SMD)   | <p>1. Mounting method:<br/>IR-Reflow. PCB Size (L:100 × W:40 × T:1.6mm)</p> <p>2. Apply the load in direction of the arrow until bending reaches 2 mm.</p>  | No Visible Damage.                                                                                                                                                       | AEC-Q200 005 |
| Adhesion           | <p>Force of 1.8Kg for 60 seconds.</p>                                                                                                                      | No Visible Damage<br>Magnification of 20X or greater may be employed for inspection of the mechanical integrity of the device body terminals and body/terminal junction. | AEC-Q200 006 |
| Physical Dimension | Any applicable method using x10 magnification, micrometers, calipers, gauges, contour projectors, or other measuring equipment, capable of determining the actual specimen dimensions.                                                       | In accordance with specification.                                                                                                                                        | JESD22 JB100 |



深圳市福汇科技有限公司  
SHENZHEN FUHUI TECHNOLOGY CO., LTD

Prepared by :Davis

Designed by :Lewis

Checked by : Lewis

Approved by : MR.MENG

**TITLE : 3.2 x 1.6 x 0.5(mm) WiFi/Bluetooth Ceramic Chip**  
**Antenna (FH100A) Engineering Specification**

**DOCUMENT**  
**NO.**

**FH3216S1P2G4501**

**REV.**  
**B**