

MPE REPORT

Prediction of MPE Limit 47 CFR § 2.1091/ § 2.1093

$$S_{20} = \frac{P_A G_N}{4\pi R_{20}^2} \quad S_C = \frac{P_A G_N}{4\pi R_C^2} \quad R_C = \sqrt{\frac{P_A G_N}{4\pi S_L}}$$

$$S_L = \frac{180}{f^2} \text{ (mW/cm}^2\text{)}$$

S_{20} = Power Density of the Device at 20cm
 S_L = Power Density Limit
 S_C = Power Density of the Device at the Compliance Distance R_C
 R_{20} = 20cm
 R_C = Minimum Distance to the Radiating Element to Meet Compliance
 P_T = Power Input to Antenna
 P_A = Adjust Power
 G_N = Numeric Gain of the Antenna
 f = Transmit Frequency


Transmit Duty Cycle = 75%

Use Group = General Population

Transmit Duty Cycle:	75.00	(%)
Tx Frequency (f):	27.40	(MHz)
RF Power at Antenna Input Port (P_T):	4000.00	(mW)
Antenna Gain:	3.00	(dBi)
Numeric Antenna Gain (G_N):	2.00	(numeric)
Cable or Other Loss:	0.00	(dB)
Duty Cycle/Loss Adjusted Power (P_A):	3000.00	(mW)

S_L =	0.240	(mW/cm ²)
S_{20} at 20cm =	1.191	(mW/cm ²)
R_C =	44.6	(cm)
S_C =	0.24	(mW/cm ²)

User's Manual must indicate a minimum separation distance of: **45cm**

Art Voss		Senior Engineer	Celltech Labs Inc.
----------	---	-----------------	--------------------

Note: This device is capable of operating in a mobile/fixed application as well as a portable application. This MPE report addresses the RF Exposure for the mobile/fixed use case. A separate SAR report accompanying this application address the RF Exposure for the Portable use case.

Note: The MPE calculations differ between the FCC and ISED. The ISED calculations yield a more conservative separation distance of 53cm and this is the reported separation distance.