

User Guide
Spotlight Cam Pro | R1414H

Quick Start

- 1. Download and open Ring app.**
Select Set Up a Device
- 2. Scan QR code with Ring app.**
Use the code on the one on your device to continue setup.



Hardware included

- A** Mounting screws
 Wall anchors
- B** Cable clips
 Wall anchors

Tools needed

- Phillips screwdriver
- Drill (optional)


Remove protective film from device.
This ensures your device works properly.

Choose a location with the view you want.
Your camera can be mounted on an outdoor wall, eave, or overhang.

Make sure your camera is positioned close enough to an outlet for the length of the included power cable.


If installing on a wall...

Your camera comes ready to mount, with the ball joint pointing down. No adjustments are needed.




If installing on an eave or overhang...

Remove the battery compartment cover by twisting it counter-clockwise and insert the ball joint plate with the ball joint pointing up.



Remove the mounting plate.

Slide it down to remove it from the camera mount.



ring



YUTO
ShenZhen YUTO Packaging Technology Co., Ltd.

Customer: Ring	PN: 22-003744-02	
Unit: MM	SIZE: 67x125,5mm	
Date: 11/06/2022	ISSUE:	

Install the mounting plate.

For wall installation, the UP arrow should point up. For an eave or overhang, the arrow should point toward the area you want to monitor for motion.

If installing on a wood surface, screw the plate directly into the wall.

If installing on a masonry surface, mark four screw holes using the plate as a guide. Drill pilot holes using a 1/4" (6mm) drill bit. Insert the included wall anchors, then drive the four mounting screws through the mounting plate into the wall anchors.


- WARNING!**
Only use the included mounting screws when securing the mounting plate.
- CAUTION!**
DO NOT drill into your home's electrical wiring.




8

Attach the camera mount.

Slide it onto the mounting plate.




Then, tighten the security screw.



9

Plug the power adapter into your camera.


Insert the USB-C end of the power adapter into the back of your camera.



Attach your camera to the camera mount.

Loosen the metal collar on the camera mount using a Phillips-head screwdriver (not included).

Push the ball joint into the socket until it snaps into place.



10

Turn on your camera.


Plug the power adapter into a power outlet.

Adjust the camera angle.

Rotate the camera to focus on the area of your choice. Look at Live View in the Ring app to make sure it's positioned at your desired angle.

Tighten the security screws.

Tighten the security screws on the metal collar to secure the camera position.



Then, tighten the security screw on the bottom of your camera to secure the battery compartment.



11

Secure the power cable.

Use the provided cable clips to secure the cable on your wall.


Use a 1/4" (6mm) drill bit to pre-drill holes in the wall and insert the provided anchors first if installing on a masonry surface, like stucco or brick.



The power cable can be painted to match your wall.

Secure the adapter.

Secure the power adapter to the wall with the included mounting screws.



12

Free Ring Protect Plan for 30 days.

Your new device comes with a free, 30-day trial of Ring Protect. This comprehensive subscription service lets you review, save, and share your video and photo history anytime so you never miss a moment.*

To continue using Ring Protect after your free trial ends, visit ring.com/protect-plans to compare plans and pricing.



*Your device isn't eligible for features with an existing Ring Protect subscription. See ring.com/protect-plans to learn more about your plan's features and plan.

ring

For additional help, visit ring.com/help or give us a call.

US 1 800 635 1918

Canada 1 855 300 7289

Worldwide +1 310 929 7085

For a list of all our customer support numbers, visit ring.com/callus.

For information on our warranty, data protection, and Ring Protect Plan, visit ring.com/legal.
© 2023 Ring LLC or its affiliates. Ring and all other marks are trademarks of Ring LLC or its affiliates.

