




802.11ac(HT20) U-NII-3 High channel




802.11ac(HT40) U-NII-3 Low channel



802.11ac(HT40) U-NII-3 High channel



802.11ac(HT80) U-NII-3 Low channel



13 Conducted Output Power

Test Requirement:	FCC CFR47 Part 15 Section 15.407(a) KDB662911 D01 Multiple Transmitter Output v02r01
Test Method:	KDB789033 D02 General U-NII Test Procedures New Rules v02r01 Section E
Test Limit:	U-NII-1 250mW(24dBm) U-NII-3 1W(30dBm)
Test Result:	PASS Conducted output power= measurement power+10log(1/x)
Remark:	X is duty cycle=1, so 10log(1/1)=0 Conducted output power= measurement power

13.1 Test Procedure:

1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum.
2. Set the spectrum analyzer: RBW = 1 MHz. VBW = 3 MHz. Sweep = auto; Detector Function = Peak, Set the span to fully encompass the DTS bandwidth.
3. Keep the EUT in transmitting at lowest, medium and highest channel individually. Record the max value.


13.2 Test Result :

Band	Operation mode	Conducted Output Power (dBm)		
		Low	Middle	High
U-NII-1	802.11a	10.91	10.72	10.60
	802.11n(HT20)	10.93	10.34	10.22
	802.11n(HT40)	11.15	/	10.92
	802.11ac(HT20)	10.73	10.36	10.21
	802.11ac(HT40)	11.10	/	10.53
	802.11ac(HT80)	10.57	/	/
U-NII-3	802.11a	11.21	10.41	9.75
	802.11n(HT20)	10.50	9.59	9.37
	802.11n(HT40)	10.29	/	9.75
	802.11ac(HT20)	10.50	9.47	9.56
	802.11ac(HT40)	10.37	/	9.77
	802.11ac(HT80)	9.94	/	/


* All transmit signals are completely uncorrelated with each other, Directional gain = G_{ANT} which is less than 6dBi. So the limit does not be reduced.

Test result plots shown as follows:


802.11a U-NII-1 Low channel




802.11a U-NII-1 Middle channel




802.11a U-NII-1 High channel




802.11n(HT20) U-NII-1 Low channel




802.11n(HT20) U-NII-1 Middle channel




802.11n(HT20) U-NII-1 High channel




802.11n(HT40) U-NII-1 Low channel




802.11n(HT40) U-NII-1 High channel




802.11ac(HT20) U-NII-1 Low channel




802.11ac(HT20) U-NII-1 Middle channel




802.11ac(HT20) U-NII-1 High channel




802.11ac(HT40) U-NII-1 Low channel




802.11ac(HT40) U-NII-1 High channel




802.11ac(HT80) U-NII-1 Low channel




802.11a U-NII-3 Low channel




802.11a U-NII-3 Middle channel




802.11a U-NII-3 High channel




802.11n(HT20) U-NII-3 Low channel




802.11n(HT20) U-NII-3 Middle channel




802.11n(HT20) U-NII-3 High channel




802.11ac(HT20) U-NII-3 Low channel




802.11ac(HT20) U-NII-3 Middle channel




802.11ac(HT20) U-NII-3 High channel




802.11ac(HT40) U-NII-3 Low channel



802.11ac(HT40) U-NII-3 High channel



802.11ac(HT80) U-NII-3 Low channel



14 Power Spectral density

Test Requirement:	FCC CFR47 Part 15 Section 15.407(a) KDB662911 D01 Multiple Transmitter Output v02r01
Test Method:	KDB789033 D02 General U-NII Test Procedures New Rules v02r01, Section F
Test Limit:	$\leq 11.00\text{dBm/MHz}$ for Operation in the U-NII-1(5150MHz-5250MHz)of mobile device $\leq 30.00\text{dBm/500KHz}$ for Operation in the U-NII-3(5725MHz- 5850MHz)of device
Test Result:	PASS

14.1 Test Procedure:

1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum.
2. Set the spectrum analyzer:
U-NII-1
RBW = 1MHz, VBW ≥ 3 * RBW Sweep = auto; Detector Function = Peak. Trace = Max hold.
U-NII-3
RBW = 510KHz, VBW ≥ 3 * RBW Sweep = auto; Detector Function = Peak. Trace = Max hold.
3. Allow the trace to stabilize. Use the marker-delta function to determine the separation between the peaks of the adjacent channels. The limit is specified in one of the subparagraphs of this Section
Submit this plot.

14.2 Test Result:


Band	Operation mode	Power Spectral Density (dBm/MHz)		
		Low	Middle	High
U-NII-1	802.11a	4.273	3.407	3.270
	802.11n(HT20)	3.077	3.287	3.284
	802.11n(HT40)	0.732	/	0.632
	802.11ac(HT20)	3.562	2.960	3.066
	802.11ac(HT40)	0.765	/	0.717
	802.11ac(HT80)	-1.838	/	/
	Limit	$\leq 11.00 \text{ dBm/MHz}$		

Band	Operation mode	Power Spectral Density (dBm/MHz)		
		Low	Middle	High
U-NII-3	802.11a	3.578	2.998	2.611
	802.11n(HT20)	3.253	2.232	2.341
	802.11n(HT40)	0.747	/	0.213
	802.11ac(HT20)	3.341	2.641	2.581
	802.11ac(HT40)	0.820	/	-0.013
	802.11ac(HT80)	-2.807	/	/
	Limit	$\leq 30.00 \text{ dBm/500kHz}$		


* All transmit signals are completely uncorrelated with each other, Directional gain = G_{ANT} which is less than 6dBi. So the limit does not be reduced.

Test result plots shown as follows:


802.11a U-NII-1 Low channel




802.11a U-NII-1 Middle channel




802.11a U-NII-1 High channel




802.11n(HT20) U-NII-1 Low channel




802.11n(HT20) U-NII-1 Middle channel




802.11n(HT20) U-NII-1 High channel




802.11n(HT40) U-NII-1 Low channel




802.11n(HT40) U-NII-1 High channel




802.11ac(HT20) U-NII-1 Low channel




802.11ac(HT20) U-NII-1 Middle channel




802.11ac(HT20) U-NII-1 High channel




802.11ac(HT40) U-NII-1 Low channel




802.11ac(HT40) U-NII-1 High channel




802.11ac(HT80) U-NII-1 Low channel




802.11a U-NII-3 Low channel




802.11a U-NII-3 Middle channel




802.11a U-NII-3 High channel




802.11n(HT20) U-NII-3 Low channel




802.11n(HT20) U-NII-3 Middle channel




802.11n(HT20) U-NII-3 High channel




802.11n(HT40) U-NII-3 Low channel




802.11n(HT40) U-NII-3 High channel




802.11ac(HT20) U-NII-3 Low channel




802.11ac(HT20) U-NII-3 Middle channel




802.11ac(HT20) U-NII-3 High channel




802.11ac(HT40) U-NII-3 Low channel



802.11ac(HT40) U-NII-3 High channel



802.11ac(HT80) U-NII-3 Low channel



15 Frequency Stability

Test Requirement:	FCC CFR47 Part 15 Section 15.407(g)
Test Method:	ANSI C63.10:2013
Test Limit:	Manufacturers of U-NII devices are responsible for ensuring frequency stability such that an emission is maintained within the band of operation under all conditions of normal operation as specified in the users manual or 20ppm.
Test Result:	PASS

15.1 Test Procedure:

1. The transmitter output (antenna port) was connected to the spectrum analyzer.
EUT have transmitted absence of unmodulation signal and fixed channelise. Set the spectrum analyzer span to view the entire absence of modulation emissions bandwidth. Set RBW = 10 kHz, VBW = 10 kHz with peak detector and maxhold settings. f_c is declaring of channel frequency. Then the frequency error formula is $(f_c - f)/f_c \times 10^6$ ppm and the limit is less than ± 20 ppm. The test extreme voltage is to change the primary supply voltage from 85 to 115 percent of the nominal value.
2. Extreme temperature rule is $-15^{\circ}\text{C} \sim 45^{\circ}\text{C}$.

15.2 Test Result:

U-NII-1 Test Frequency:5180MHz				
Temperature (°C)	Power Supply (VAC)	Frequency Error (Hz)	Frequency Error (ppm)	Limit (ppm)
45	120	1512	0.2919	20
30		1523	0.2940	20
20		1516	0.2927	20
10		1521	0.2936	20
0		1524	0.2942	20
-10		1520	0.2934	20
-15		1521	0.2936	20
20	108	1529	0.2952	20
20	132	1518	0.2931	20

U-NII-3 Test Frequency:5785MHz				
Temperature (°C)	Power Supply (VAC)	Frequency Error (Hz)	Frequency Error (ppm)	Limit (ppm)
45	120	1720	0.2973	20
30		1706	0.2949	20
20		1714	0.2963	20
10		1711	0.2958	20
0		1713	0.2961	20
-10		1716	0.2966	20
-15		1702	0.2942	20
20	108	1712	0.2959	20
20	132	1712	0.2959	20

16 Antenna Requirement

An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator shall be considered sufficient to comply with the provisions of this section. The manufacturer may design the unit so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited. This requirement does not apply to carrier current devices or to devices operated under the provisions of §15.211, §15.213, §15.217, §15.219, or §15.221. Further, this requirement does not apply to intentional radiators that must be professionally installed, such as perimeter protection systems and some field disturbance sensors, or to other intentional radiators which, in accordance with §15.31(d), must be measured at the installation site. However, the installer shall be responsible for ensuring that the proper antenna is employed so that the limits in this part are not exceeded.

This device uses of two antennas that uses a specified coupling to the intentional radiator. Antenna connectors complied with the requirement.

17 RF Exposure

Remark: refer to SAR test report: WTS20S01001728W001.

18 Photographs of test setup and EUT.

Note: Please refer to appendix: Appendix-X655-Photos.

=====End of Report=====