105克的铜板纸

尺寸:90*100mm

Wireless Keyboard for iPad

User Manual

HB245

Thank you for using the keyboard provided by BOW, please read this manual carefully before using this product.

Product Display



Keyboard Indicator	Color	Indicator state
Power on sate: power indicator	Green	Keeping light 3 seconds
Pairing state: Bluetooth indicator	Blue	5 flash each second, keeping light when paired
Caps indicator	Green	Pressing Caps Lock and the indicator light all time
Low power indicator: Low power indicator	Red	Flicker a second time (Voltage blow 3.3V)
Charging state: charging indicator	Red	keeping light all the time (full charging will be green)
Battery indicator	Green	3.3-3.0V will flicker one time; 3.6-3.3V-2 times ; 3.9-3.6V-3 times ; 4.2-3.9V-4 times

Connecting Steps

Step 1. Turning on the tablet PC , the keyboard will be on by automatic, power indicator will be on within 3 seconds.

Step 2. Pressing FN+pairing to be pairing state, and the Bluetooth indicator will flicker all the time.

Step 3. Being on Bluetooth and searching, the tablet PC will search by automatic or by hand to find the Bluetooth named B.O.W , clicking and connected it, it means connected succeed when the Bluetooth extinguished

(The Tablet PC which had been paired succeed before will be connected automatic)

Function Keys

	Home		Lightness -		Lightness +
	Cope		Paste		Searching
	Show Keyboard		Vhangeable Input		Last
▶II	Play/Pause	▶▶I	Next		Mute
	Volume -		Volume +	Fn+	Pairing
	Lock Screen	Fn+	Battery state	delete	Delete

Saving Energy Module

It will be sleeping module when it do not has been any touched within 30 minutes, but it will be reworking when you press any key; Keyboard will stop pairing when keyboard has not pairing succeed after 3 minutes later , and it need pressing FN+( )pairing again to pairing.

Charging

When the battery power is below 3.3V, and the power indicator will flicker, its time to charge.

1. Connect keyboard USB B port to keyboard charge port.
2. Connect USB A port to power adapter or PC USB port.
3. when charging , the red light will be on until at the end of charging.

Tip

1. Magnet on-off, and open the tablet PC, the keyboard will be on , too. Closed the tablet PC the keyboard will be off .
2. For others Bluetooth which can be pairing, please check Bluetooth standard and compatibility.
3. We suggest that the keyboard should charging when the low power indicator flickered.
4. When connected failed, cancel some pairing record and matching again.
5. With standard keyboard, special Bluetooth Keyboard for iPad. Max rotating degree is 127°

Specification of Keyboard

Bluetooth version	Bluetooth 3.0
Bluetooth working distance	10meters
Control	GFSK
Working voltage	3.0V~4.2V
Working current	≤5mA
Charging current	≤250mA
Sleeping current	≤0.1mA
Re-connect time	≥3s
Reworking time	≤5s
Charging time	≤2 hours
Lithium battery	≥250mAh
Working time	≥50 hours
Standby time	≥100days
Working temperature	-10°C~+50°C
Support	IOS

Questions

1. Can iPhone and tablet PC both support the third inputting way?

When connect with IOS system, just support "simple pinyin" which build-in iPhone. Do not support Baidu ,sogou and wubi inputting way.

2. How to use "enter key "to send message?

WeChat --Me--settings-chant-enter key to send massage(turn on)
Found QQ settings in QQ --miscellaneous function--enter key to send massage(turn on)
Some kind of soft which are not update can not set enter-key to send massage.

3. How to deal with keyboard retard ?

When the keyboard are working and retard, first to check keyboard power, second to check whether there are too many connected equipment in your Bluetooth keyboard, third to check drive of computer.

Safety Caution

Warning: If you do not with the way of safety state, maybe you will get fire breaking out , electric shock, breakdown the keyboard and so on.

Dangerous (be careful of highly dangerous)

Warning (be careful of mid dangerous)

Caution (slight dangerous should be noted)

1)Keep the keyboard away from sharp objects.
2)Do not Microwave the keyboard.
3) Do not place heavy object on the keyboard.
4) Do not force or distorted the keyboard.
5) Keep away from oil, chemical or any other organic liquid.

FCC Warnning:
This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
• Reorient or relocate the receiving antenna.
• Increase the separation between the equipment and receiver.
• Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
• Consult the dealer or an experienced radio/TV technician for help.
Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.
This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1)This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
The device has been evaluated to meet general RF exposure requirement. The device can be used in portable condition without restriction.