






SwitchBot Remote 	Option 3: Use a strap-hole and add a lanyard for portable uses. You need to purchase a lanyard separately. 
In the Box  remote  manual  CR2450 Button Battery (In the Remote)  Add-on Hook & Loop	Pairing You can pair a Remote to control your target device like a Bot or a Curtain. Please place your phone, Remote and the target device close to each other before pairing. The rule of thumb for the distance would be within your eye sight. Tap the Remote icon on the App Home Page, and select setup/edit. The Remote will start scanning the target devices around. Follow the App instruction and map the keys to actions.
Device Instruction  Concave Key  Convex Key  Battery Box  Strap-hole	Mapping Keys You can set the keys on the Remote to map one action. One key on the Remote Button can trigger one action of your target device. For example, the Convex Key can trigger the Curtain to close OR open. And Concave Key can trigger the Bot to press once.
Installation 1. Before using, please install the SwitchBot App and sign up/sign in your SwitchBot account. Then open the Battery Box. 	Low Battery  When you see a red battery icon on the App Home Page next to the Remote, you need to change the battery.
2. Remove the plastic battery isolation tab, and you should see the light flashes once.  Light	Factory Reset Long press both keys together for 15 seconds until the light stop flashing. You should see the light lights up for 1.5s after releasing the button.  Caution: You may lose all the settings after Factory Reset and you may need to add the device and pair again.
3. Put back the Battery Box and turn on the Bluetooth on your phone. Tap Add Device in the left side menu and choose Remote. Follow the App instruction and add your device. 	Specification Model Number: W0301700 Color: White Material: ABS plastic with UV-Resistant coating Product Size: 37.1mm x 43.1mm x 13.4mm Product Net Weight (with battery): 17.7 g Power: CR2450 Connectivity: Bluetooth 5.0 Long Range
Placement After you add the Remote, you may place it anywhere Option 1: Place it on your table. 	Return and Refund Policy SwitchBot Curtain has one-year warranty (start from the purchasing day). The situations below do not fit the Return and Refund Policy Intended damage or abuse. Inappropriate storage (drop down or soaking in water). User modify or repair. Using loss. Force majeure damage (Natural disasters). The batteries are not in the warranty.
Option 2: Use the Add-on Hook & Loop to place it on a vertical surface. 	Contact and Support Setup and Troubleshooting: support.switch-bot.com Support Email: support@wondertechlabs.com Feedback: Please send feedback via the SwitchBot App in the left side menu with the details of the issue.
FCC Warning This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference	CE Warning Manufacturer's Name: Woan Technology (Shenzhen) Co., Ltd. This product is a fixed location. To comply with RF exposure requirements, a minimum separation distance of 5cm must be maintained between the user's body and the device, including the antenna. Use only the supplied or an approved antenna. This device in compliance with the essential requirements and other relevant provisions of Directive 2014/53/EU. All essential radio test suites have been carried out.
to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: -Reorient or relocate the receiving antenna. -Increase the separation between the equipment and receiver. -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. -Consult the dealer or an experienced radio/TV technician for help. The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.	1. CAUTION : RISK OF EXPLOSION IF BATTERY IS REPLACED BY AN INCORRECT TYPE. DISPOSE OF USED BATTERIES ACCORDING TO THE INSTRUCTIONS 2. The device complies with RF specifications when the device used at 5cm from your body

- 1.Max operation temperature: 40 degree C. Min operation temperature: -10 degree C.
- 2.This product can be used in UK. This device can be used in UK.
- 3.Products can be sold in UK Declaration of conformity Trimble Transportation declares that Micro system with SwitchBot Remoteis in compliance with the essential requirements and other relevant provisions of Directive SI 2017/1206.
- 4. This product can be used in EU member states. This device can be used in European Union.
- 5. Products can be sold in all EU countries Declaration of conformity Trimble Transportation declares that Micro system with SwitchBot Remote is in compliance with the essential requirements and other relevant provisions of Directive 2014/53/EU.
- 6 . This equipment should be installed and operated with minimum distance of 5cm the radiator your body.

Applicant: Woan Technology (Shenzhen) Co., Ltd.
Address: Room 1101, Qiancheng Commercial Center, No. 5 Haicheng Road, Mabu Community, Xixiang Sub-district, Bao’an District, Shenzhen, Guangdong, P.R.China, 518100

Manufacturer: Woan Technology (Shenzhen) Co., Ltd.
Address: Room 1101, Qiancheng Commercial Center, No. 5 Haicheng Road, Mabu Community, Xixiang Sub-district, Bao’an District, Shenzhen, Guangdong, P.R.China, 518100

EUImporter Name： Amazon Services Europe
Importer Address： 38 Avenue John F Kennedy, L-1855 Luxembourg

Frequency band： 2402 MHz ~ 2480 MHz

DECLARATION OF CONFORMITY

I hereby declare that the product

SwitchBot Remote

Model: W0301700, W0301701, W0301702, W0301703, W0301704, W0301705

Trade Mark: SwitchBot

(Name of product, type or model, batch or serial number)

Hardware Version: V1.1, Software Version: V4.3

DC 3V from battery

satisfies all the technical regulations applicable to the product within the scope of Council Directives 2014/53/EU, 2014/35/EU and 2014/30/EU:and declare that the same application has not been lodged with any other notified body.

EMC:	
ETSI EN 301 489-1 V2.2.3 (2019-11)/	
ETSI EN 301 489-17 V3.2.4 (2020-09)/	
EN 55032:2015 + A1:2020 + A11:2020/	
EN 55035:2017 + A11:2020	
LVD: EN IEC 62368-1:2020 + A11:2020	
EMF: EN 62479:2010/EN 50663:2017	
RF:	
ETSI EN 300 328 V2.2.2 (2019-07)	
(Title(s) of regulations, standards, etc.)	

All essential radio test suites have been carried out.

NOTIFIED BODY: MiCOM Labs Inc

– **Address:**

575 Boulder Court,

Pleasanton, California 94566

USA

Identification Number: 2280

MANUFACTURER or AUTHORISED REPRESENTATIVE: Woan Technology (Shenzhen) Co., Ltd.

Address:

Room 1101, Qiancheng Commercial Center, No. 5

Haicheng Road,

Mabu Community, Xixiang Sub-district, Bao'an

District,

Shenzhen, Guangdong, P.R.China, 518100

This declaration is issued under the sole responsibility of the manufacturer and, if applicable, his authorised representative.

Point of contact:

(Name, telephone and fax number)

Shenzhen, Guangdong, **Feb. 23, 2022**

(Place, date of issue)

(Signature)

Yang Pan

(Name and title in block letters)