

RF Exposure Evaluation

FCC ID: 2ALAA-MBS14102

1. Client Information

Applicant : SHENZHEN JIAXINGWEI DIGITAL TECHNOLOGY CO.LTD
Address : 4F, 3Block, YuYe District, Zhoushi Road, XiXiang, BaoAn, Shenzhen, China
Manufacturer : DongGuan JiaXing Electronic&Technology Co.,Ltd
Address : No.4 Xing Sheng Road, HuangNiuPu Industri, HuangJiang, Town GongGuan, China

2. General Description of EUT

EUT Name	:	BLUETOOTH SPEAKER	
Models No.	:	MBS14102, SD-005B, SD-002	
Model Difference	:	All these models are identical in the same PCB, layout and electrical circuit, the only difference is model name for commercial.	
Product Description	:	Operation Frequency:	Bluetooth V2.0+EDR: 2402~2480 MHz
	:	Number of Channel:	Bluetooth: 79 Channels See Note 2
	:	Max Peak Output Power:	Bluetooth: 0.814 dBm(GFSK)
	:	Antenna Gain:	0.94 dBi PCB Antenna
	:	Modulation Type:	GFSK 1Mbps(1 Mbps) π /4-DQPSK(2 Mbps) 8-DPSK(3 Mbps)
Power Supply	:	DC power by USB cable. DC power by Li-ion battery.	
Power Rating	:	DC 5.0V by USB cable. DC 3.7V by 1200mAh Li-ion battery.	
Connecting I/O Port(S)	:	Please refer to the User's Manual	

Note: More test information about the EUT please refer the RF Test Report.

SAR Test Exclusion Calculations

1. FCC: According to KDB 447498 D01 Mobile and Portable Devices RF Exposure Procedures and Equipment Authorization Policies v06.

- (1) Clause 4.3: General SAR test reduction and exclusion guidance

- Sub clause 4.31: Standalone SAR test exclusion considerations

- 1) The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6GHz at test separation distance ≤ 5 mm are determined by:

- [(max. power of channel, including tune-up tolerance, mW)/(min. test separation, mm)] * $[\sqrt{f_{\text{GHz}}}] \leq 3.0$ for 1-g SAR

- [(max. power of channel, including tune-up tolerance, mW)/(min. test separation, mm)] * $[\sqrt{f_{\text{GHz}}}] \leq 7.5.0$ for 10-g SAR

2.

Calculation:

Test separation: 5mm						
Bluetooth Mode (GFSK)						
Frequency (GHz)	Conducted Power (dBm)	Turn-up Power Tolerance (dB)	Max power of tune up tolerance (dbm)	Max power of tune up tolerance (mw)	Calculation Value	Threshold Value
2.402	0.814	0 ± 1	1	1.259	0.390	3.0
2.441	0.590	0 ± 1	1	1.259	0.393	3.0
2.480	0.112	0 ± 1	1	1.259	0.397	3.0
Bluetooth Mode ($\pi/4$ -DQPSK)						
Frequency (GHz)	Conducted Power (dBm)	Turn-up Power Tolerance (dB)	Max power of tune up tolerance (dbm)	Max power of tune up tolerance (mw)	Calculation Value	Threshold Value
2.402	0.199	0 ± 1	1	1.259	0.390	3.0
2.441	-0.149	0 ± 1	1	1.259	0.393	3.0
2.480	-0.587	0 ± 1	1	1.259	0.397	3.0
Bluetooth Mode (8-DPSK)						
Frequency (GHz)	Conducted Power (dBm)	Turn-up Power Tolerance (dB)	Max power of tune up tolerance (dbm)	Max power of tune up tolerance (mw)	Calculation Value	Threshold Value
2.402	0.105	0 ± 1	1	1.259	0.390	3.0
2.441	-0.259	0 ± 1	1	1.259	0.393	3.0
2.480	-0.688	0 ± 1	1	1.259	0.397	3.0

So standalone SAR measurements are not required.

-----END OF REPORT-----