



- **Step 1:** Turn the terminal upside down and open the battery cover. You should remove the battery first if there is a battery.(fig. 5)
- **Step 2:** According to the SIM/SAM/MicroSD card position of the engraved marks, or pasted on the lower housing, load the required cards. Be sure to put the cut corner as indicated on the engraved or pasted marks.(fig. 6)(fig. 7)

- **Power on:** Press power button for about 2 seconds until the LCD is lit to switch on.
- **Power off:** Press and hold power button to see a pop-up window, touch the screen to select "Power off" to power off the terminal.
(Or to select "Reboot" and then "OK" to reboot the terminal.)
- **Note:** If there is a crash, please press power button for about 10 seconds to reboot the terminal forcefuly or re-plug the battery then boot the terminal.

- Place the terminal on the charging base (if available) or connected to the adapter to charge the battery.

1. Only original batteries and power adapters can be used. Using other batteries or power adapters may cause damage to the device or battery, or even explosion.
2. Do not put device with lithium batteries into fire or exposed to high temperatures for a long time, must be away from heat sources, such as sun, heater, microwave oven or water heater. Overheating of the battery may cause an explosion.
3. If the lithium battery is soaked, the lithium battery cannot continue to be used, water in the lithium battery may cause a fire.
4. It is recommended to unplug the charger after full charge in normal use to avoid long-term charging or long-term high power state to accelerate the aging of the lithium battery to extend the battery life.
5. If the device has not been used for more than a month, please take out the battery and charge the lithium battery every 3 months to keep it at 50%-80% power.

Do not connect any peripheral equipment that has not been authenticated by the Newland to avoid damage.

- 1. Please be sure to take to comply with the specifications in this document.
- 2. Do not use in proximity of potentially flammable gases or substances.
- 3. Do not disassemble the terminal, power adapter or battery.
- 4. Cut off the power immediately, when there is unusual heat, overvoltage or smoke.
- 5. There is a risk of explosion if the battery is incorrectly replaced or is placed in a fire. Life-sized batteries must be disposed of at the appropriated sites.
- 6. Do not use in a near water or humid environment to prevent water and from getting in.
- 7. Do not use the terminal in extremely cold or hot zones, such as near a fire.
- 8. Do not drop, throw or bend the device.
- 9. Use in the environment to avoid entry of small objects into POS.
- 10. Do not use near hospital equipment without permission.
- 11. Do not use terminals with radio communication on or near aircraft, or in any other place where radio communication is prohibited.

Your terminal fulfills current applicable PCI PTS security requirements. Upon receipt of your terminal you should check for signs of tampering. It is strongly advised that these checks are performed daily after receipt (Be sure the circumference is brightness or you may use a light tool as well).

- **CE Marking**
The CE marking indicates N750 complies the requirements of European Directive 2014/53/EU of 16 April, 2014 on Radio and Telecommunications Terminal Equipment for:
 1. The protection of the health and the safety of the user and any other person.
 2. The protection requirements with respect to electromagnetic compatibility.
- **Operating Frequency Band** (only for CE)

5 GHz band (W52, W53): Indoor use only



BE	BG	CZ	DK	DE	EE	IE	EL
ES	FR	HR	IT	CY	LV	LT	LU
HU	MT	NL	AT	PL	PT	RO	SI
SK	FI	SE	NO	IS	LI	CH	TR

The functions of Wireless Access Systems including Radio Local Networks (WAS/RLANs) within the band 5150-5350 MHz for this device are restricted to indoor use only within all European Union countries. (BE/BG/CZ/DK/DE/EE/IE/EL/ES/FR/HR/IT/CY/LV/LT/LU/HU/MT/NL/AT/PL/PT/RO/SI/SK/FI/SE/NO/IS/LI/CH/TR)

- **I. The terminal does not turn on**
 - 1. Check that the battery is installed correctly.
 - 2. Please charge the battery to check if it is fully charged.
- **II. Battery life is significantly reduced**
 - 1. Check if the battery is fully charged.
 - 2. Battery life expires, please replace the battery.
- **III. Can't read the magnetic card or the card swiping has a low success rate**
 - 1. Check that the magnetic card is swiped correctly (with magnetic band facing down).
 - 2. Check if there are any bags or dirt on the magnetic head. Please clean it.
- **IV. IC cards can't be read**
 - 1. Make sure you have inserted correctly the Chip card into the chip card reader (with the chip facing up).
 - 2. Check if the chip slot is blocked or if the card is in correct position.

For body – worn operation, the device has been tested and meets the FCC/ISED exposure guidelines.

Non – compliance with the above restrictions may result in violation of RF exposure guidelines.

The device should be operated with minimum distances 10 mm from the body. Pour une utilisation corporelle, l'appareil doit être testé et respecté à l'exposition FCC/ISED.

FCC/ISED EXPOSURE GUIDELINES

The non – respect des restrictions ci – dessus peut entraîner une violation de l' exposition aux RF Lignes directrices.

Le dispositif doit être utilisé à une distance minimale de 10 mm du corps.

For limb worn operation, this device has been tested and meets the FCC/ISED RF exposure guidelines.

For use in location sur les membres, cet appareil a été testé et conforme aux directives d' exposition RF de la FCC/ISED.

This device contains licence-exempt transmitter(s)/ receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

- (1) This device may not cause interference.
- (2) This device must accept any interference, including interference that may cause undesired operation of the device.

L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence.

(1) L' appareil ne doit pas produire de brouillage;
(2) L' appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en

The device for operation in the band 5150-5350 MHz is only for indoor use to reduce the potential for harmful interference to co-channel mobile satellite systems.

le dispositif utilisé dans la bande 5150-5350 MHz est réservé à une utilisation en intérieur afin de réduire le risque de brouillage préjudiciable aux systèmes mobiles par satellite dans le même canal.

HVIN
ND_01_12_01_01
ND_01_13_01_01
ND_01_12_01_02
ND_01_13_01_03