

XQ800X_NA

LTE Cat.1 Communication Module

The XQ800X_NA is a multi-mode LTE Cat.1 wireless communication module, supporting data rates up to 10 Mbps Downlink and 5 Mbps Uplink. The module features compact form factor, comprehensive functionality, and optimized performance characteristics.

It supports standard communication protocols (TCP, UDP, FTP, HTTP, HTTPS, MQTT), 3GPP standard AT commands, and enhanced AT extension commands. With extensive peripheral interfaces, the module enables seamless integration with terminal devices and sensors to meet IoT application requirements. It can be widely deployed in mobile payment, smart home, security monitoring, smart metering, environmental monitoring, asset tracking, shared equipment, and other applications.

The XQ800X_NA module utilizes a 101-pin LGA package, with compact dimensions of only 19.3 x 17.4 x 2.2mm.

LTE Cat1		XQ800X_NA
Basic Information		
Module Dimensions (mm)		19.3 x 17.4 x 2.2
Weight (g)		4.0
Operating Temperature		-20°C to 70°C
Extended Temperature		-40°C to 85°C
Frequency Band Information		
LTE-FDD		B2/B4/B5/B7/B12/B14/B17/B25/B26/B41/B66
LTE-TDD		/
Wi-Fi		Wi-Fi Scan support
Max Data Transfer Rates (Mbps)		
LTE-FDD		5 (UL) / 10 (DL)
LTE-TDD		/
Interfaces		
(U)SIM		x1
UART		x4
CAN_UART		x1
USB2.0		x1
I2C		x2
ADC		x2
SSP (configurable as PCM or SPI)		x1
Analog Audio Input		x1#
Analog Audio Output		x1#
Main Antenna (compatible with Wi-Fi Scan)		x1
Key Features		
FOTA		Supported
Audio Playback / Recording		Supported#
Software Features		
Protocol Stack		TCP/UDP/PPP/NITZ/PING/FILE/MQTT/NTP/ HTTP/HTTPS/SSL/FTP/FTPS/CMUX/MMS
Driver Support		
RNDIS		Windows 7/8/10, Linux 2.6-5.10
ECM		Linux 2.6-5.10
RIL		Android 4.x-10.x
USB		Windows 7/8/8.1/10, Linux 2.6-5.10, Android 4.x-10.x
Electrical Characteristics		
Supply Voltage (VCC)		3.4V to 4.5V (typical: 3.8V)
Power Consumption (Typical)		3.5uA @ Power-off mode
		35uA @ Sleep mode*
		280uA @ Idle mode*

Note:

1. Functions marked with # are optional.
2. Power consumption values marked with * are measured with recording function disabled.

FCC regulatory compliance statement

§15.19 Statement

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

§15.21 Information to user

Warning: changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

- **List of applicable FCC rules:**

47 CFR Part 22, 24, 27, 90

- **Summarize the specific operational use conditions**

This module can be used in IOT devices, the input voltage to the module is nominally 3.8V.

- **Limited module procedures**

This module is a Single Modular.

- **Trace antenna designs**

The antenna is not a trace antenna.

- **RF exposure considerations**

This Module complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of 20cm between the radiator and your body. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

- **Antennas**

If you desire to increase antenna gain and either change antenna type or use same antenna type certified, a Class II permissive change application is required to be filed by us, or you (host manufacturer) can take responsibility through the change in FCC ID (new application) procedure followed by a Class II permissive change application.

- **Label and compliance information**

Please notice that if the FCC identification number is not visible when the module is installed inside another device, then the outside of the device into which the module is installed must also display a label referring to the enclosed module. This exterior label can use wording such as the following: "Contains FCC ID: 2AMLF-XQ800X-NA" any similar wording that expresses the same meaning may be used.

§ 15.19 Labelling requirements shall be complied on end user device.

Labelling rules for special device, please refer to §2.925, § 15.19 (a)(5) and relevant KDB publications. For E-label, please refer to §2.935.

- **Information on test modes and additional testing requirements**

The OEM integrator is responsible for ensuring that the end-user has no manual instruction to remove or install module.

The module is limited to installation in mobile application, a separate approval is required for all other operating configurations, including portable configurations with respect to §2.1093 and difference antenna configurations.

- **FCC other Parts, Part 15B Compliance Requirements for Host product manufacturer**

This modular transmitter is only FCC authorized for the specific rule parts listed on our grant, host product manufacturer is responsible for compliance to any other FCC rules that apply to the host not covered by the modular transmitter grant of certification.

Host manufacturer in any case shall ensure host product which is installed and operating with the module is in compliant with Part 15B requirements.

Please note that For a Class B or Class A digital device or peripheral, the instructions furnished the user manual of the end-user product shall include statement set out in *§15.105 Information to the user* or such similar statement and place it in a prominent location in the text of host product manual. Original texts as following:

For Class B

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

RF Exposure Compliance

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.