

Barcode Scanner

Quick Start Guide

- ▶ Bluetooth wireless transmission
- ▶ Built-in FLASH memory, supports breakpoint resume
- ▶ Can store more than 5,000 entries of 50-digit 2D barcode information
- ▶ Supports Windows XP/7/8/10 PC and Android, iOS devices

Packing list:

Barcode scanner -> 1 unit
USB cable -> 1 piece.
Quick Start Guide
Certificate of Approval
Setup Card for inventory function
Power Adapter(optional)


Note: The device is not equipped with a charging device.
Please charge the device via USB output charging equipment.

V1.0

1 Barcode Scanner Overview

It integrates high-performance processor and decoding board, it has fast decoding, high-precision reading ability, and high anti-interference ability. It can easily read barcodes on screen, paper, goods and other media. The scanning distance is a great improvement compared with similar products. It also boosts high scanning speed and powerful reading ability with high accuracy.

Appearance:



- Bluetooth Wireless mode

Functions Setup:

Barcode Scanner can setup all default functions through reading the setup barcodes.

[Enter Setup] → [Read function barcode] → [Exit with Save]

One-key Pairing Mode without PIN Code

Scan the barcode below directly, and search for pairing.



Pairing without PIN Code

- Note:**
- 1.If you want to setup the function of barcode scanner. Read 'Enter Setup' barcode, then 'Function Setup' barcode, and close with the 'Exit with Save' bar code.
 - 2.If the device has been paired with a Bluetooth device and needs to be paired with another one, pressing 10s power key when scanner is power off to pair with another Bluetooth device.

2 Pairing with another device

Pressing 10s power key when scanner is power off, when you hear two beeps, and then a long beep, it can be paired with another Bluetooth device.

3 Pairing with Windows 7/8/10

- 1.Start barcode scanner, the indicator is blue, on/off flashing ratio is 1:1
- 2.In the PC with Win7 OS, click 'Start > Devices and printers > Add a device', search for barcode scanner.
Turn on the Bluetooth in Win8/10, search for barcode scanner.
- 3.Double click barcode scanner, no need to input PIN code in the Bluetooth pairing request dialog.
- 4.Click 'Next' or 'OK', after a beeper, paired successfully, then the indicator turns blue and is always on.

4 Pairing with Android devices

1. Turn on the barcode scanner, the blue indicator is flashing with on/off ratio 1:1
2. Turn on the Bluetooth in Android devices, search for barcode scanner
3. Click the one you want to connect, click Next or OK, after a beeper, paired successfully. You will find it shows "connected" on the Android device, then the indicator turns blue and is always on.

5 Pairing with iOS devices

1. Turn on the barcode scanner, the blue indicator is flashing with on/off ratio 1:1.
2. Turn on the Bluetooth in iOS device, search for barcode scanner.
3. Click the one you want to connect, click Next or OK, after a beeper, paired successfully. You will find it shows "connected" in the iOS device, then the indicator turns blue and is always on.

6 PIN Code Pairing Mode

If some devices can not pair without PIN code, directly scan the barcode below, then search CTXX on the device, and enter "0000" for pairing.



PIN Code Pairing

Note: When pairing with iOS devices, you need to restart the barcode after setting

LED Indicators

Indicator Colour

Red LED always on

Blue LED flashing

Blue LED always on

Meaning

Charging, red LED will off when the battery full charged

Bluetooth unpaired

Bluetooth paired

Beeper

Beeping

Two long beeps
One short beep
One long beep
Two short beeps
Two short beeps, low-high tone
Two short beeps, high-low tone

Three short beeps, tone descending from high to low
Three short beeps, tone ascending from low to high

Meaning

Power on
Read barcode
Configuration error or the cache is full
Power off
Bluetooth successfully connected
Bluetooth out of range or suspended with blue LED flashing (on/off ratio 1:1)
Enter or exit setting mode

Configuration correct

Common Function Barcodes



Enter Setup



Enable SPP



Factory Reset

FCC Statement

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment should be installed and operated with a minimum distance of 0mm between the radiator and your body.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.

-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.

DISCLAIMER

> WE DISCLAIM ANY AND ALL LIABILITY FOR THE DAMAGES CAUSED BY NATURE DISASTER, SUCH AS EARTHQUAKE, FLOOD ETC.
> UNDER NO CIRCUMSTANCE, CILICO DISCLAIMS ANY AND ALL LIABILITY FOR ANY DAMAGES WHICH IS CAUSED BY THE USE OF OUR PRODUCTS (INCLUDING THE DAMAGES CAUSED BY USING THE QUICK START GUIDE), SUCH AS THE COMPANY PROFIT LOSS, CREDIT LOSS, INTERRUPTION OF BUSINESS, STORAGE DATA LOSS / CHANGES OR ANY OTHER PARTICULAR, DIRECT / INDIRECT LOSS CAUSED BY THIS.
> WE DISCLAIM ANY AND ALL LIABILITY FOR THE DAMAGES WHICH IS CAUSED BY THE MISUSE OF COMMUNICATIONS HARDWARE OR SOFTWARE WE DON'T SPECIFIED.
> FOR THE INFORMATION, DATA, FILES OR ANY OTHER PRODUCTS AND SERVICES WHICH ARE ACCESSED BY USING OF OUR DEVICES, WE DO NOT PROVIDE ANY FORM OF GUARANTEE OR TECHNICAL SUPPORT. AND WE DISCLAIM ANY AND ALL LIABILITY FOR THE USING OF ABOVE MENTIONED BY THE USERS.
> WE DISCLAIM ANY TYPE OF GUARANTEE AND TECHNICAL SUPPORT LIABILITY FOR THE THIRD-PARTY SOFTWARE WHICH IS USED BASED ON OUR PRODUCTS.
> THIS MANUAL IS DELIVERED ON AN "AS-IS" AND "AS-AVAILABLE" BASIS. EXCEPT WHERE PROHIBITED BY LAW, WE DO NOT MAKE ANY TYPE OF SPECIFIC PROMISES TO THE ACCURACY OR RELIABILITY OF THE CONTENT.



Warning:

1. Please remove the power and USB cable under thunderstorm weather conditions, to avoid damage from thunder and lightning.
2. Keep away from heat sources, please ensure sufficient air circulation.
3. Pay attention that the scanner is waterproof during storage, transportation and running.
4. Please use DC 5V500mA power adapter offered by the authorised producer.