



11AC40SISO_Ant1_5230



11AC80SISO_Ant1_5210



3.4 Conducted Output Power

3.4.1 Limit

FCC Part15, Subpart E (15.407)			
Section	Test Item	Limit	Frequency Range (MHz)
15.407(a)	Conducted Output Power	Master device: 1 Watt (30 dBm) Client device: 250 mW (23.98 dBm)	5150-5250
		250 mW (23.98 dBm)	5250-5350
		250 mW (23.98 dBm)	5470-5725
		1 Watt (30dBm)	5725-5850

Note:

a. For an indoor access point operating in the band 5.15-5.25 GHz, the maximum conducted output power over the frequency band of operation shall not exceed 1 W provided the maximum antenna gain does not exceed 6 dBi. In addition, the maximum power spectral density shall not exceed 17 dBm in any 1 megahertz band. If transmitting antennas of directional gain greater than 6 dBi are used, both the maximum conducted output power and the maximum power spectral density shall be reduced by the amount in dB that the directional gain of the antenna exceeds 6 dBi.

b. For the 5.25-5.35 GHz and 5.47-5.725 GHz bands, the maximum conducted output power over the frequency bands of operation shall not exceed the lesser of 250 mW or 11 dBm + 10log B, where B is the 26dB Bandwidth in megahertz.

3.4.2 Test Procedure

Test Method	
●Conducted Measurement	○Radiated Measurement
Test Channels	
●Lowest, Middle and Highest Channel	○ Lowest and Highest Channel
Environmental conditions	
●Normal	○Normal and Extreme
Note:●:Test ○:No Test	

a) The EUT was directly connected to the power meter and antenna output port as show in the block diagram below.

b) Test was performed in accordance with method of FCC KDB 789033 D02 General UNII Test Procedures New Rules v02r01.

3.4.3 Test Setup



3.4.4 Table of Parameters of Text Software Setting

UNII-1			
Test Software Version	Command		
Frequency (MHz)	5180	5200	5240
IEEE 802.11a	default	default	default
IEEE 802.11n(HT20)	default	default	default
IEEE 802.11ac(VHT20)	default	default	default
Frequency (MHz)	5190	5230	
IEEE 802.11n(HT40)	default	default	
IEEE 802.11ac(VHT40)	default	default	
Frequency (MHz)	5210		
IEEE 802.11ac(VHT80)	default		

3.4.5 The Result

Test Mode	Antenna	Freq(MHz)	Result [dBm]	Limit [dBm]	Verdict
11A	Ant1	5180	12.41	≤23.98	PASS
		5200	13.74	≤23.98	PASS
		5240	11.54	≤23.98	PASS
11N20SISO	Ant1	5180	11.22	≤23.98	PASS
		5200	12.46	≤23.98	PASS
		5240	12.31	≤23.98	PASS
11N40SISO	Ant1	5190	14.01	≤23.98	PASS
		5230	15.05	≤23.98	PASS
11AC20SISO	Ant1	5180	13.26	≤23.98	PASS
		5200	13.52	≤23.98	PASS
		5240	12.79	≤23.98	PASS
11AC40SISO	Ant1	5190	13.87	≤23.98	PASS
		5230	14.65	≤23.98	PASS
11AC80SISO	Ant1	5210	14.15	≤23.98	PASS

3.5 Power Spectral Density

3.5.1 Limit

FCC Part15, Subpart E (15.407)			
Section	Test Item	Limit	Frequency Range (MHz)
15.407(a)	Power Spectral Density	Master device: 17 dBm/MHz Client device: 11 dBm/MHz	5150-5250
		11 dBm/MHz	5250-5350
		11 dBm/MHz	5470-5725
		30 dBm/500 kHz	5725-5850

Note:

- For UNII-3, according to KDB publication 789033 D02 General UNII Test Procedures New Rules v02r01, section II.F.5., it is acceptable to set RBW at 300kHz and VBW at 1500kHz if the spectrum analyzer does not have 500 kHz RBW. Then, add $10 \log (500 \text{ kHz}/300 \text{ kHz})$ to the measured result, i.e. 2.22 dB.
- During the test of U-NII 3 PSD, the measurement result with RBW=300kHz has been added 2.22 dB by compensating offset, offset=cable loss+duty factor+ $10\log(500\text{kHz}/300\text{kHz})$.


3.5.2 Test Procedure

Test Method	
●Conducted Measurement	○Radiated Measurement
Test Channels	
●Lowest, Middle and Highest Channel	○ Lowest and Highest Channel
Environmental conditions	
●Normal	○Normal and Extreme
Note:●:Test ○:No Test	

a) The EUT was directly connected to the tonscond test system and antenna output port as show in the block diagram below. Spectrum analyser settings as following:

Centre Frequency	The centre frequency of the channel under test
RBW	= 1 MHz (Band1/2/3); = 500kHz (Band4)
VBW	$\geq 3 \times \text{RBW}$
Frequency span	2 x Nominal Channel Bandwidth
Detector Mode	RMS
Trace Mode	Max Hold
Sweep Time	Auto Couple


3.5.3 Test Setup




3.5.4 The Result

Test Mode	Antenna	Freq(MHz)	Result [dBm/MHz]	Limit[dBm/MHz]	Verdict
11A	Ant1	5180	2.20	≤11.00	PASS
		5200	3.52	≤11.00	PASS
		5240	0.96	≤11.00	PASS
11N20SISO	Ant1	5180	0.67	≤11.00	PASS
		5200	1.76	≤11.00	PASS
		5240	1.52	≤11.00	PASS
11N40SISO	Ant1	5190	0.71	≤11.00	PASS
		5230	1.32	≤11.00	PASS
11AC20SISO	Ant1	5180	2.53	≤11.00	PASS
		5200	2.74	≤11.00	PASS
		5240	1.85	≤11.00	PASS
11AC40SISO	Ant1	5190	0.12	≤11.00	PASS
		5230	0.85	≤11.00	PASS
11AC80SISO	Ant1	5210	-2.67	≤11.00	PASS


11A_Ant1_5180




11A_Ant1_5200




11A_Ant1_5240




11N20SISO_Ant1_5180




11N20SISO_Ant1_5200




11N20SISO_Ant1_5240




11N40SISO_Ant1_5190




11N40SISO_Ant1_5230




11AC20SISO_Ant1_5180




11AC20SISO_Ant1_5200




11AC20SISO_Ant1_5240




11AC40SISO_Ant1_5190



11AC40SISO_Ant1_5230



11AC80SISO_Ant1_5210



(END OF REPORT)