



Compact Size High Waterproof

M4PB Asset Button Tag

The M4PB is a compact asset tag equipped with a large button. This button is used to mark the asset requiring maintenance or repair, helping quickly spot and minimizing downtime. Featuring the drawer-type battery replacement design and IP67 waterproof rating, M4PB is ideal for valuable assets tracking in various environments like healthcare facilities, warehouses, and more.

Application



Warehouse



Hospital

*Battery lifespan estimates are based on the default settings without any sensors under 25°C conditions ~ 1 active slot, 1000ms ADV interval and 0dBm Tx Power.



IP67 waterproof



Replaceable battery




Compact size



Programmable button

General Specs

Connectivity:	BLE 5.0
Dimension (mm):	43.4*26.0*6.9
Color:	Body - White Button - Red
Material:	Nylon
IP rating:	IP67
Sensor:	Accelerometer
LED:	Red
Battery capacity:	220mAh Replaceable battery
Battery lifespan:	1.5 years*
Operating temperature:	-20°C/60°C
Transmission range:	Up to 150m (Without any obstacles)
Installation:	Sticker Zip Tie
Certification:	FCC CE RoHS WEEE



Replace battery

FCC STATEMENT

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference.

(2) This device must accept any interference received, including interference that may cause undesired operation.

2. any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

RF warning statement:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.