Smart Life

Thank you for using flood light

D5

## 1.Basic Parameters

Product Name: Smart flood light
Pixel: 2 MP
Video compression: H.264 high profile
Lens field angle: 110 degrees
Local storage: Micro TF Card (up to 128G)
Support platform: Android / IOS
Motion detection: 4-9M
Wireless encryption: WEP / WPA / WPA2 encryption
Power input: 5v2.5a 50 / 60Hz
Power consumption of the whole machine: 10W
Wireless connection: 2.4G 802.11 B / g / n
Lighting distance: radius 5m

**Component Description:**

Reset Button: Long press "reset" hole 5sec to reset

Recommend to put 16-128GB class10 Micro SD card, otherwise it will not be able to store, p l a y b a c k and support important functions such as firmware upgrading.

01

## 2.Install APP

- Scan the QR code below to download and install the APP
- Register and log in according to the prompts.

02

## 3.1. Add The Device-Scan QR code mode

- Make sure that Wi Fi is available and work
  Connect thedevice to the power
- Open the app, click "+" on the main screen (Figure 01); select "security& Sensor", click" smart camera "(Figure 02) to add the device; then click" nxt " Figure 03);



03

- If the mobile phone is not connected to Wi Fi, please click "connect" (Figure 04) according to the interface prompt (Figure 05)
- Note: only support 2.4G Wi Fi network ;
- If the mobile phone is connected to Wi Fi (Figure 06), click "confirm";

04

(Figure 08) Scan QR code via camera lens

- Scan QR code via camera lens and click "continue" (Figure 07);
- The mobile app will generate a QR code and use the QR code to aim at the flood light camera ( about20-30cm), click "hear prompt sound" (Figure 08);
- The device is connecting (as shown in Figure 09);



05

- When the progress reaches 100%, complete the connection (Figure 10), click "finish"
- The interface jumps to the device preview interface (Figure 11)
- After closing the device preview interface, the interface will return to the app home page. At this time, the connected devices will appear on the app home page (Figure 12). Later, you can enter the device interface to view the monitoring situation without adding again. Click directly to enter the device interface.



06

## 3.2.Add device - Wi Fi fast connect

- Make sure that Wi Fi is available and works
  Connect the device to the power
- Open the APP, add the device on the main screen (Figure 13), select " security & sensor" and click the "smart camera"(Figure 14). Then select "distribution network mode" (Figure 15)



07

- The interface jumps to select "Wi Fi fast connection" (Figure 16)
- The interface jumps to compatibility mode, and click "nxt" button(Figure 17).
- Then you need to connect Wi Fi at home and click "replace network" (Figure 18);



08

- Select home Wi Fi connection (Figure 19);
- Click back, the interface will display the connected Wi Fi name, please input the password, and click "confirm" (Figure 20);
- At this time, the interface displays "connecting" connection process, which takes about 1 minute and 30 seconds (Figure 21);



09

- When the progress reaches 100%, complete the connection (as shown in Figure 22), click "finish";
- The interface jumps to the device preview interface ( Figure 23)
- After closing the device preview interface, the interface will return to the app home page. At this time, the connected devices (Figure 24) will appear on the app home page. Later, you can enter the device interface to view the monitoring situation without adding again. Click directly to enter the device interface.



10

## 4.APP Video Browsing Details




11

## 5.Matters Need Attention

Try to keepaway from the metal space;
Avoid the feniture , microwave oven blocked;
Avoid the space where the audio, video and data lines are wound, and keep the space away from them as large as possible;
Ensure this as close as possible to the coverage of wireless Wi-Fi signals. Switching network environment;
In the new network environment, please press the reset hole about 5 seconds, then connect to the network.

12

The name and content of the harmful substances in the product

| Part Name | Harmful Substance | | | | | |
|---|---|---|---|---|---|---|
| | Pb | Hg | Cd | Cr(VI) | PBB | PBDE |
| shell | ○ | ○ | ○ | ○ | ○ | ○ |
| Board | X | ○ | ○ | ○ | ○ | ○ |
| charger | ○ | ○ | ○ | ○ | ○ | ○ |
| annex | ○ | ○ | ○ | ○ | ○ | ○ |

This form is based on the provisions of SJ/T 11364。

This product conforms to RoHS environmental protection requirements. At present, there is no mature technology in the world to replace or reduce the lead content in the electronic ceramics, porcelain, optical glass, steel and copper alloy.

13

Maintenance records：

Maintenance time：

Fault conditions：

Fault cause：

Troubleshooting：

Retrn and exchange proof:

Dat of validity：

Orignal device ID:

Nes device ID：

maintenance personnel signature：

Maintenance Department seal：

14

Maintenance voucher of intelligent

Customer:　　Mobile:

Address:

Model:　　Camera ID:

Device store:　　Date of purchase:

Store address:

Store contact number:

Maintenance voucher of intelligent

Customer:　　Mobile:

Address:

Model:　　Camera ID:

Device store:　　Date of purchase:

Store address:

Store contact number:

15

Maintenance voucher of intelligent

Customer:　　Mobile:

Address:

Model:　　Camera ID:

Device store:　　Date of purchase:

Store address:

Store contact number:

Maintenance voucher of intelligent

Customer:　　Mobile:

Address:

Model:　　Camera ID:

Device store:　　Date of purchase:

Store address:

Store contact number:

16

## FCC Statement

This equipment has been testad and found to comply wit the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipmentdoes cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the users encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCCRules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

RF Exposure Information

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator &your body.

17