

RF Exposure Report

FCC ID: 2AQ7Q-DBA0027

RF Exposure Measurement

The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The gain of the antennas used in the product is extracted from the Antenna data sheets provided and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis Transmission formula is far field assumption, the calculated result of that is an over-prediction for near field power density. It is taken as worst case to specify the safety range.

RF Exposure Limit

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of the human exposure to radio-frequency (RF) radiation as specified in 1.1307 (b)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)
Limits for Occupational / controlled Exposures			
300 - 1500	--	--	F/300
1500 – 100000	--	--	5.0
Limits for General population / Uncontrolled Exposure			
300 - 1500	--	--	F/1500
1500 – 100000	--	--	1.0

Limits for Maximum Permissible Exposure (MPE)

F= Frequency in MHz

Friss Formula

Friss Transmission Formula: $P_d = (P_{out} * G) / (4 * \pi * r^2)$

Where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = Distance between observation point and the center of radiator in cm

If we know the maximum gain of the antenna and the total output power to the antenna, through calculation, we will know MPE value at distance 20cm.

EUT Operation condition

EUT was enabled to transmit and receive at lowest, middle and highest channels.

Classification

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. Warning statement to the user for keeping at least 20cm or more separation distance from the antenna should be included in the User manual. So, this device is classified as Mobile device.

BT5.0+EDR

Mode	2402-2480MHz
Detector	PEAK
GFSK	7±1dBm
$\pi/4$ -DQPSK	5±1dBm
8DPSK	5±1dBm

ANT Gain (G)

Antenna gain : 5.68dBi (gain of antenna in linear scale=3.70)

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
GFSK	3.70	2441	8	6.30957	0.00465	1
$\pi/4$ -DQPSK	3.70	2441	6	3.98107	0.00293	1
8DPSK	3.70	2441	6	3.98107	0.00293	1

BT5.0

Mode	2402-2480MHz
Detector	PEAK
GFSK(1M PHY)	5±1dBm
GFSK(2M PHY)	5±1dBm

ANT Gain (G)

Antenna gain : 5.68dBi (gain of antenna in linear scale=3.70)

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
GFSK(1 M PHY)	3.70	2440	6	3.98107	0.00293	1
GFSK(2 M PHY)	3.70	2440	6	3.98107	0.00293	1

2.4G WIFI

Mode	802.11b/g/n20:2412-2462MHz 802.11n40:2422-2452MHz
Detector	PEAK
802.11b	13.5±1dBm
802.11g	20±1dBm
802.11n20(mimo)	24±1dBm
802.11n40(mimo)	23±1dBm

ANT Gain (G)

Antenna number: 2

Antenna A gain : 5.68dBi

Antenna B gain : 7.82dBi

(gain of antenna in linear scale=6.05)

MIMO technology Directional gain= 9.83dBi

(gain of antenna in linear scale=9.62)

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
802.11 b	6.05	2437	14.5	28.1838	0.03394	1
802.11 g	6.05	2437	21	125.8925	0.15160	1
802.11 n20(mimo)	9.62	2462	25	316.2278	0.60552	1
802.11 n40(mimo)	9.62	2422	24	251.1886	0.48098	1

5.2G WIFI

Mode	802.11a/n20/n40/ac20/ac40/ac80: 5.15-5.25GHz
Detector	AV
802.11a	6±1dBm
802.11n20 (mimo)	9±1dBm
802.11 n40 (mimo)	8±1dBm
802.11ac20 (mimo)	9±1dBm
802.11ac40 (mimo)	8±1dBm
802.11ac80 (mimo)	9±1dBm

ANT Gain (G)

Antenna number: 2

Antenna A gain : 5.4dBi

Antenna B gain : 4.49dBi

(gain of antenna in linear scale=3.47)

MIMO technology Directional gain= 7.97dBi

(gain of antenna in linear scale=6.27)

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
802.11 a	3.47	5180	7	5.0119	0.09999	1
802.11 n20(mimo)	6.27	5180	10	10.0000	0.09999	1
802.11 n40(mimo)	6.27	5190	9	7.9433	0.00991	1
802.11 ac20(mimo)	6.27	5180	10	10.0000	0.09999	1
802.11 ac40(mimo)	6.27	5190	9	7.9433	0.09999	1
802.11 ac80(mimo)	6.27	5210	10	10.0000	0.09999	1

5.3G WIFI

Mode	802.11a/n20/n40/ac20/ac40/ac80: 5.25-5.35GHz
Detector	AV
802.11a	6±1dBm
802.11n20 (mimo)	9±1dBm
802.11 n40 (mimo)	8±1dBm

802.11ac20 (mimo)	8±1dBm
802.11ac40 (mimo)	8±1dBm
802.11ac80 (mimo)	7±1dBm

ANT Gain (G)

Antenna number: 2

Antenna A gain : 5.4dBi

Antenna B gain : 4.49dBi

(gain of antenna in linear scale=3.47)

MIMO technology Directional gain= 7.97dBi

(gain of antenna in linear scale=6.27)

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
802.11 a	3.47	5260	7	5.0119	0.09999	1
802.11 n20(mimo)	6.27	5260	10	10.0000	0.09999	1
802.11 n40(mimo)	6.27	5270	9	7.9433	0.00991	1
802.11 ac20(mimo)	6.27	5260	9	7.9433	0.09999	1
802.11 ac40(mimo)	6.27	5270	9	7.9433	0.09999	1
802.11 ac80(mimo)	6.27	5290	8	6.3096	0.09999	1

5.6G WIFI

Mode	802.11a/n20/n40/ac20/ac40/ac80: 5.47-5.725GHz
Detector	AV
802.11a	Low Channel: 6.1±1dBm; Mid Channel/High Channel: 7.5±1dBm;
802.11n20 (mimo)	10.5±1dBm
802.11 n40 (mimo)	10±1dBm
802.11ac20 (mimo)	10.5±1dBm
802.11ac40 (mimo)	10.5±1dBm
802.11ac80 (mimo)	10±1dBm

ANT Gain (G)

Antenna number: 2

Antenna A gain : 5.4dBi

Antenna B gain : 4.49dBi

(gain of antenna in linear scale=3.47)

MIMO technology Directional gain= 7.97dBi

(gain of antenna in linear scale=6.27)

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
802.11 a	3.47	5700	8.5	7.0795	0.09999	1
802.11 n20(mimo)	6.27	5700	11.5	14.1254	0.09999	1
802.11 n40(mimo)	6.27	5670	11	12.5893	0.01571	1
802.11 ac20(mimo)	6.27	5700	11.5	14.1254	0.09999	1
802.11 ac40(mimo)	6.27	5670	11.5	14.1254	0.09999	1
802.11 ac80(mimo)	6.27	5610	11	12.5893	0.09999	1

5.8G WIFI

Mode	802.11a/n20/n40/ac20/ac40/ac80: 5.525-5.85GHz
Detector	AV
802.11a	Ant A: 7.5±1dBm; Ant B: 10±1dBm;
802.11n20 (mimo)	12±1dBm
802.11 n40 (mimo)	12±1dBm
802.11ac20 (mimo)	12±1dBm
802.11ac40 (mimo)	12±1dBm
802.11ac80 (mimo)	11±1dBm

ANT Gain (G)

Antenna number: 2

Antenna A gain : 5.4dBi

Antenna B gain : 4.49dBi

(gain of antenna in linear scale=3.47)

MIMO technology Directional gain= 7.97dBi

(gain of antenna in linear scale=6.27)

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
802.11 a	3.47	5745	11	12.5893	0.09999	1
802.11 n20(mimo)	6.27	5745	13	19.9526	0.09999	1
802.11 n40(mimo)	6.27	5755	13	19.9526	0.02490	1
802.11 ac20(mimo)	6.27	5745	13	19.9526	0.09999	1
802.11 ac40(mimo)	6.27	5755	13	19.9526	0.09999	1
802.11 ac80(mimo)	6.27	5775	12	15.8489	0.09999	1

According to the maximum gain of the antenna and the total output power to the antenna, through calculation, we will know max MPE value 0.60552 at distance 20cm. This is less than the limit 1. So SAR testing is not required.