

3WOLVES

1. Menu.....	1
1.1 File manager.....	1
1.2 Phone Book.....	2
1.3 Fun & Games.....	3
1.4 Call Center.....	3
1.5 Messages.....	5
1.6 Multimedia.....	8
1.7 Organizer.....	11
1.8 Settings.....	12
1.9 User profiles.....	13
1.10 Extra.....	14
1.11 Services.....	15
1.12 Shortcuts.....	15

1. Menu

1.1 File manager

External phone support (T-FLASH memory card), mobile phones, there are 250K of space, the passage of this modules picture, MP3, MP4 and folder management.

[Phone] - storage for mobile phones storage.

[Open]: Audio, Images, Photos, Video folder

Audio - audio folder

*player: play the selected content."

*send:" sent to the profile.

*For more information: the date and size of new" documents.

*Rename: change the current name."

*copy: You can copy files" to the folder Audio, Images, Photos, Video, or a specified file.

*mobile:" You can move files to the folder Audio, Images, Photos, Video, or a specified file.

*Delete: delete the current record."

*delete all files: delete" the current folder where all the records.

*sort: by name, type, time, size" of order, can also choose "no" to sort.

*Images - pictures (including graphics editor to edit the picture and copy the picture, etc.) storage folder

*View: Show the curreper, screen saver, bontly selected picture"

*send: sent to the" wallpaot animation, shutdown animation, phone book.

" For more information: the date and size of new documents.

*Rename: change" the current name.

*copy: You can copy files to the folder Audio, Images," Photos, Video, or a specified file.

*mobile: You can move files to the" folder Audio, Images, Photos, Video, or a specified file. size of order, can also choose" "no" to sort.

*Photos - photo storage folder

*View: Show the current" photo.

*Editor: artists of the p

*Delete: delete" the current record.

*delete all files: delete the current folder where all" the records.

*sort: by name, type, time,hotos into the photo editing."

*send:" sent to the wallpaper, screen saver, boot animation, shutdown animation, phone book.

*For more information: the date and size of new documents."

*Rename: change the current name.

*copy: You can copy files to the folder" Audio, Images, Photos, Video, or a specified file.

*mobile: You can move" files to the folder Audio, Images, Photos, Video, or a specified file.

*Delete: delete the current record.

*delete all files: delete the current" folder where all the records.

*sort: by name, type, time, size of order," can also choose "no" to sort.

1.2 Phone Book

Your phone card with the use of clip-on phone book, into every cell phone contact information containing the names of: the three phone numbers (mobile, home phone and business phone), company name, e-mail address, fax number, birthday, Big Head paste, ring tones to choose, video connection, calls the group (provided by the five group types: family, friends, important people, colleagues and other); into the SIM card can only be stored for each contact name and phone number.

Support 250 group phone numbers.

Quick Find

Specified in the cursor position or enter the first letter of the English alphabet the first letter, you can locate a large number of numbers to the first record to satisfy the conditions, such as search, "Zhang" name, enter in the input zone "z" you can quickly find the letters .

Find contactor

Find the names of input, and then in the phone book in the "Search" to find the most matching records.

Add Contacter

In the SIM card: a record of entries can be recorded: name, phone number.

Mobile phone: a record of entries can be recorded: name, telephone number, home phone, company name, e-mail address, company phone, fax number, birthday, stickers, video link, choose ring tones, caller groups.

Note: If a record at the same time set up a picture link, link rings, caller groups, video link, the group call function is invalid.

All Copy: Copy the respective mobile phone SIM card or all records.

Delete: delete the respective SIM cards, mobile phone and one by one to delete all records.

Call group: Groups of five calls were set up ring tones, pictures, video links, and other group members.

Other numbers

Set the local number, service and emergency telephone numbers (including emergency services telephone and SIM card numbers to be supported by specific details please consult network operator).

Set

storage state: View the current use of the phone book," including the SIM card and phone memory. Display format as follows: "has the capacity to use Volume / total capacity.

the preferred storag location: Choose the path of the current number of storage.

card set:" Select the phone book entries in the record shows that the interface and add the records show that at the time of entry.

my card: edit, send my card."

Call ID picture show

set to display images in calls.

Caller ringtones

Set the tone when the caller.

1.3 Fun & Games

Game: The game provides a built machine (smart puzzle) Please check the specific operation of the game comes with instructions.

Game Setting

background sound: on / off the game sound.

sound: on / off the game sound.

game vibration: on / off vibration game.

1.4 Call Center

Call history

You can record two phone SIM cards did not answer the phone, have to answer the phone and dial the phone number, can also record all the time and cost of the call. If mobile phones switched on and within the network service area, in network support, it can not answer the phone records and have to answer the phone. Not answer the phone, have to answer the phone and call list function, you can view the date and time of the call, edit, or delete the phone number list will be saved to the phone book numbers.

Did not answer the phone: You can view the most recent calls you did not list the phone number (network service).

Tip: When the phone display does not answer the phone when prompted, click "read" is not allowed to enter the phone number list. Scroll to the need to call back the number, then press the call key to dial the number.

Have been allowed to make phone calls: to see you have recently called or attempted to call off a list of telephone numbers. Have to answer the phone: to view the recent calls list of telephone numbers. Delete call records: most recent call records could be deleted. You can choose to delete the recent call records of all telephone numbers, or did not answer the phone to delete only has to answer the phone, dialed telephone numbers in the list.

Talk time:

Last call time: This feature is available through the last call duration;

Total calls: This feature is available through all of the words have been called long;

total answer calls: This feature is available through all of the phone has been connected to long;

zero for all time: With this feature you can clear record of all calls.

Note: The service provider actual invoice for calls and services may vary, depending on network features, to zero from the accounting and tax factors such as the whole.

Call billing: the need to support network service providers.

Last call cost: This feature is available through the last calls;

the cost of all calls: This feature is available through all of the charges;

the cost of zero-call: this function to remove all calls can be recorded;

restrictions cost: the cost of the call can be limited to a specified quantity of currency-denominated unit or units. Call cost settings enter the PIN2 code is required.

prices and rates: need network support this feature, the specific details, please contact the network operator.

SMS Counter: View has been sent information and has received a record amount of information, and delete messages and to receive the amount of information.

GPRS traffic:

last transmission: See the last link to send traffic.

receive: See the last link to receive traffic.

all send: View All link to send traffic.

all receive: View all links receive traffic.

counter zero: button to remove all access" traffic.

General call settings:

Local number: the system" default, the hidden number, send the number.

1. system default: call when the system default by way of sending the local number.

2. hidden number: call when the system does not send the local number. If the system does not support this feature may lead to not call.

3. number: calls to the system to send the local number.

Note: This feature is network support required.

call waiting: Set to open or close the call waiting feature, when multiple calls to maintain and when to call this function must be activated can be realized, the realization of the specific needs of network support.

call transfer: is a network function, you need to network operators to apply for this business in order to use the following functions. This feature can meet the conditions of the call transfer to your designated phone number on another.

Name	Specifications
Unconditional transfer	network will be unconditionally transfer all of your calls
transfer when can't contact	when the network can not be found when your phone (off or out of service area), the network will transfer your call
non-response transfer	when you phone in a certain period of time did not answer a call, the network will transfer your call
When busy, transfer call	network will transfer your call when you are on call
Need to transfer all the data	network support calls
abolition of the transfer	Cancel all transfer call.

call restrictions:

1. All calls: prohibit all outgoing calls.

2. International call: Prohibition of making international calls.

3. international excursive domestic: in foreign countries can only call the telephone number of the country and national (that is, your service provider for the country) the telephone number.

Calls prohibited

1. A ban on all phones

2. To prohibit all roaming calls

The abolition of restrictions: the abolition of all restrictions on the call or call

Change Password: replacement of the original Old Password

line switch: Select line 1 or line 2."

close group: The required network support functions, the details may consult the local network operator.

Note: Some settings need to network support. Restrictions such as the need to call the local network and the SIM card to open the function to make settings effective.

Automatic redial: This function can be set" automatically redial the "open or closed." When your phone call is not successful in a trial after a maximum of 10 additional test call to try to connect to a phone number.

speed dial: set whether or not open the speed" dial function, and edit the

corresponding speed dial number. If the speed dial "on", you can stand through the interface, click on the corresponding one-touch live (2-9 keys) to dial the designated number to the keys.

IP Dial-up: add" or edit the IP number.

more: You can open the call time display, talk time" suggest that automatically limit

1.5 Messages

SMS

SMS functionality is a network service, you may need to first network operator to apply, (both the general SIM card this feature by default) to send and receive SMS. Your phone supports the sending of short messages. Short message to the network is the first of the short message center, and then again the purpose of the network users (GSM users) to send. If the user does not boot, or can not receive text messages (memory full), the network will temporarily save this information, the retention period from sending the user to set up and service operators to a common decision. The use of short message service, your phone can send and receive text messages chain, sending the chain of information that may affect the cost of information. For more details, please check with your service provider.

If the short message capacity is full, the top line on the screen displays a flashing message icon; to be carried out on the short message has been deleted, in order to receive normal text messages.

If the other party has received text messages, you can hear the news of the report phone tone (if the short message is set to open to receive prompt) Note: When you send a text message network service information, the phone may display "has been sent." This means that information sent to mobile phones has set up an information center for the mailbox. It does not mean that the recipient has received the information specified. For more information about services, please contact your network provider.

Reply: docking received short text messages back.

Delete: delete the current short message.

Editors: short message on the" current editor to edit or send.

Forward: You can directly forward or edit" the message after forwarding this to others.

Copy to phone / SIM: will be" copied to the mobile phone SMS / SIM on.

transfer to mobile phone / SIM:" this SMS to mobile phone / SIM on.

Chat: Chat is set up each other's names" and numbers, send text messages to send or reply to the same

Remove All:" You can delete all inbox SMS.

copy of all: You can copy the phone / SIM" card all the short message.

all: can mobile phone / SIM card all"Mobile the short message.

use number: docking received short message number, text" messages in the preservation of digital information, or dial-up.

URL:" receiving text messages saved in the URL.

Outbox

Choose to send a message in the "Save and Send", storage of information will be saved in the Outbox; you can also directly edit the information stored in the Outbox, the Outbox at this time in the show as "no number" shall be no transmission destination; if you fail to send the information, this information will be saved in the Outbox. And to preserve in the Outbox to send SMS, edit, delete, copy to mobile phones, mobile to mobile phones, all the delete, copy all, mobile all, the use of numbers, use the web site

Write SMS

In this menu you can create a short message.

Each SMS capacity up to 670 characters, but bearing in mind that in some cities or regions do not support more than 70 characters (or 1530 characters in the English word length) the length of the information. Written information, available input and handwriting input button, click on the main screen with the stylus in the upper left "input method" icon or directly on the stand-by "#" key to switch input method, using simulated stylus clicks on the keyboard "" icon or press " * " button to select the symbol type: Click the " Clear " to delete the cursor in front of a word or cleared by the return key, point to live the " Clear " or by the return key to delete all characters; hang up button to return to standby mode; about the direction button to select the characters, click to select the input characters. (You can also directly select the input pen touch screen characters.)

Your phone supports the sending of more than 70 characters (The number of words in ordinary text message limit) of the chain of information. If the information contained in the number of characters in excess of 70, it will be as two or more of the issued ordinary text message.

Item	Function introductions
use template	there has been 10 preset SMS in Mobile phone
Insert the object	can insert a picture, my pictures, the default animation, I animated, ringtones, my ring tones, ring tones by default
text Forma	Set alignment, new paragraph
Insert the number	inserted numbers in the phone book
Insert name	Insert name in the phone book
Insert bookmark	inserted in the content of WAP bookmarks
Input method	Intelligent capital input, intelligent English lowercase, Pinyin input, input strokes, smart spelling, capital letters, lowercase letters, numbers, etc.

Note: only if your network operator or service provider can be used to support the only function of picture information. Only when we have a picture messaging mobile phone can receive and display picture messages. However, some image information display must support the phone.

Commonly used phrase

to edit or delete Phrase commonly used.

SMS settings

In this menu you can with the information on the SIM card 1 or 2 messages SIM card to set up some parameters.

* **mode:** To send text messages, you must first enter the local messaging center number.

NOTE: SMS center number provided by the network operators.

*status settings:"

#news reports: the network has received a notice to the other messages, asu well as the time of receipt.

#return path: the path will be available to answer client transferred to the network, the functions required to support the SMS Center.

*storage status: you can view SIM card or mobile phone short" message storage space usage.

* store location: set location information is" stored (SIM card or mobile phone).

MMS

MMS can contain text, sound clips and pictures. Your phone supports up to 100K (network support) of the MMS. If the color

MMS may display different receiving equipment to another.

Note: only if the network operator or service provider support, you can use this feature. Compatible only with MMS or e-mail features can receive and display multimedia messages.

Written information

Recipient

*Add number - Enter the phone number to send the object.

*Add E-mail - Enter to" send targeted e-mail.

Copy

number - Enter the phone number to send"Add the object.

Add E-mail - Enter to send targeted e-mail."

Copy of postcode

*Add number - Enter the phone number to send the object.

*Add E-mail - Enter to" send targeted e-mail.

Subject: MMS can edit the theme.

Content:

MMS text editor, press OK to enter the options:

*completed

*input method:" Select the required input information input method

*Insert Photo: Insert" picture

*voice: Insert sound"Insert

*Annex: Insert Annex"Add

*add a new page in the former: in this page before adding a new page

*Add a new follows: After this page to add a new page page in

text:"Add bookmark Insert the contents of WAP bookmarks

*preview: You can preview the effect" of MMS editor

*time: You can set the player when the page of time MMS."

Inbox: you can view in your inbox MMS received, and do the following:

*Show: Show this message, and save images, sound files and attachments;"

*information: View the details of this information Details

*Extraction number: docking received numbers and MMS content to the preservation of" digital information, or dial-up.

*Re: direct reply to the sender"MMS information and respond to every message sender;

Re: reply by SMS to"SMS the sender;

*forward: You can forward this message to others;"

" receive: receive MMS;

*disconnect: disconnect receive MMS;"

*Delete: delete the current MMS;

*Delete all: You can delete all MMS inbox;"

Outbox: View and save and send the message have not been issued, and implementation of view, transfer, delete, delete all, keep a template saved, the information details, the use of the project.

Draft: Save the message editor, you can also Drafts of the information on the implementation of view, send, edit, delete, delete all, keep a template saved, the information details, the use of the project.

Template: User-defined: user-defined message in the editor when the preservation of information into a template

Default values: cell phone built-in MMS messages

MMS settings: You can MMS menu of some of the parameters set.

Editors settings:

- *edit mode - restricted / not restricted

- *narrow picture - can narrow the choices for" the 160 * 120,320 * 240 and the closure of

- *automatic signature - can be" turned on or off the signature editor

Send Settings:

- * use during" the period - set in the short message service center storage and delivery time. Are: maximum, 1 hour, 6 hours for 12 hours, 1 day, 1 week.

- *return -"Send on / off Send tips return.

- *return - on / off read prompt return."Read

- *priority - the priority of sending MMS normal, low, high."

- *interval -" set up the other side to receive MMS multi-page viewing time interval.

Default as

- *follows: 5 seconds Maximum settings: 60 seconds time - real-time,"Send one hour, within 12 hours, within 24 hours

Receive Settings:

- the main network - immediate, refused to delay."

- roaming network -" the same as the main network, delay, refuse.

- Send to read the report -" asked to send, not send.

- allowed to send the report - to identify and shut" down.

Filter:

- *anonymous sender - permission to return."

- " advertising information - permission to return.

Server settings:

- *file rename settings: China Mobile MMS"

- *Home:" <http://mmsc.monternet.com>

- *data account: CHINA MOBIL GPRS"

- *connection" type: HTTP

Storage status: Article shows the total number of MMS and the largest number of articles, MMS has used space and remaining space

Voicemail server

Voice mail is a network service, you may need to apply for the opening of the service. For more information and voice-mail number, please check with your service provider.

Editor: can edit, delete your voice mail number, in accordance with the" confirmation number can be stored.

connected to the voice: You can call" your voicemail number in the menu are stored in the voice mailbox number. If you have two phone numbers, each number can have their own voice mailbox number.

Tip: In standby mode, set up voice mail number, press and hold the 1 key to call voicemail.

Broadcast message

Cell broadcast by network operators in a particular region to region, all GSM users to send a number of similar weather forecasts, traffic conditions and other information services.

[Receive Mode]: On / Off function to receive messages.

[Read information]: If the broadcast message has been opened in order to read the news has been received, need to open the corresponding services.

[Language]: set the language to receive messages.

[Channel Settings]: Select or add and edit and delete the channel number.

1.6 Multimedia

***Camera**

Through this menu, you can use the built-in camera phone photos, and can adjust the camera settings. Camera lens is located at the back of mobile phones and mobile phone screen as a viewfinder window. Camera generated JPG format photos are. If downloaded to a computer, use the appropriate software to view! If the phone is not sufficient storage space in the new photo shoot, you will need to remove some old photos or "file management" menu of the other documents in order to release storage space.

Camera Options Help

options	Specifications
Camera select	Back, Front
photo	View the saving picture
Setting	Flash: on / off
	Shutter Sound: Sound One, two, three, close
	EV:EV0, EV+0.5, EV+1, EV+1.5, EV+2.0, EV-0.5, EV-1, EV-1.5, EV-2.0
	Anti-flicker: 50Hz (default), 60 Hz
	Contrast: low, high, medium
	Delayed shooting: 5 seconds, 10 seconds, 15seconds, off
Image setting	Cont. short: the three-shot, five-shot on or off
	Image Size: 80 * 60, 160 * 120, 320 * 240, 640 * 480, 240 * 320, 176 * 220
	Image Quality: normal, good, low
White Balance	Auto, daylight, tungsten lights, fluorescent, cloudy, incandescent light
Scene mode	Automatic, night mode
Effects settings	six kinds of effects to choose
Frame	provide 2 frame to choice to users on or off frame
Storage location	mobile phones, memory card
Restore default settings	the user to restore the default settings

Album: The pictures are saved to the album.

Album Option Description

options	Specifications
Browse	View the selected picture / photo
Browse mode	offers two views mode, namely, a list of model and matrix model
Transmitted sent	to the wallpaper, screen saver, boot animation, shutdown animation, telephone directories, MMS, Bluetooth
Rename	to rename the selected picture / photo name
Delete	to delete the selected picture / photo
Delete all files	to delete all the picture albums / photos
Ways to sort	sort photos by album name, type, time, size, , so easier to find
storage path	Choice of image save the file to a mobile phone or memory card

***Image viewer**

View the saving picture

Storage path: the option is stored in the phone / memory card

***Video recording**

Access to the film recorder interface, click the middle button or press the video button to start recording MP3 playback operation, the video recording time is limited in the time limit set and memory card / mobile phone the capacity of the size, enter the option settings on the recorder as follows

options	Specifications
Switch camera	has camera1, camera 2
player	To support to play 3gp and mp4 video clips compressed file format.
Video settings	In video mode, you can make the following settings, white balance, exposure compensation, night shoot mode,
Video setting	can set the video quality
Effects settings	six kinds of effects to choose
Storage location	to choose the video file to a mobile phone or memory card
To restore the default	in video mode the user settings back to original settings

***Video player**

Support 3gp and mp4 format video clip files, in this mode can also be specified in 3GP format on the following documents.

Star Cinema election description

options	Specifications
play	Support 3GP and MP4 player video format file, not file size limit, click-to-play interface can be full-screen playback
Transfer	video can be sent to the specified phone book to the screen to start animation, to shut down animation, to MMS, and Bluetooth
Rename	Can rename the movie file to the specified name
delete	Delete to delete the specified 3GP or MP4 format movie file
Delete all	to delete the file management directory Video file all documents
Sort order	Sort according to the demand for name, type, time, size, sort, easier to find
Storage location	to choose the video file path (phone or memory card)

***Audio player**

Mobile phone in the shutdown state, use USB line connected to the computer and cell phone, the computer will find new hardware message and generate a removable hard drive, will select the MP3 can be downloaded to any directory of mobile hard disk. (File suffix for only support MP3, AMR, WAV, IMY music format).

options	Specifications
Play	to play the currently selected song
Detail	view the file name, channel, sound quality, file size, song time.
adding ringtones	added songs to the selected tone settings
Playlist update	the list to enter the music player is updated
Settings	broadcast path, automatically generated lists, repeat, random, background playback, Bluetooth stereo output, Bluetooth stereo headphones, audio settings, lyrics display settings

***Sound recorder**

Check the "sound recording" Click OK to enter, you can view the document prior to recording. Click on "Options", the operation can be carried out as follows:

recording: to" record a new audio file player: play the selected audio file"

" attached: The documents referred to higher level directory for additional recording (only AMR format for recording audio files can be attached

" rename: selected audio file name to rename

Delete: delete the selected" audio file

delete all files: Remove all of sound recordings"

set: Set" audio file storage, there are mobile phones and memory cards can choose two ways; At the same time, document file format for audio settings, and AMR, WAV formats to choose from two transponder: add to the scene mode, MMS," Bluetooth

***FM radio**

options	Specifications
Channel list	can be added here Channel 9 records
Manual input	can directly enter the channel you want
Automatically search	after set up the phone can automatically select the search frequency in the automatic channel search before empty list
Setting	turned on or off the background trumpet player and mobile phone

1.7 Organizer

***Calendar**

This feature can be arranged through the alarm to remind you of the trip, but also record your itinerary. Scroll to highlight the necessary pieces to date, the date of the day will be marked in a gray box. If a date has been set up a memorandum, the date will increase the green box; To view a certain day all the Memo, please click on a certain date, you can view the To Do List. At this time the operation can be carried out as follows:

schedule: Select the date to" view Do Added matters: See the cursor where the date of journey, the" journey can be the time, date, content, whether or not to open and ringing alarm, location, priority setting. When editing of the schedule, use the arrow keys left and right button to select the alarm mode. Can also delete the trip, as well as to the date of operation of all trips, as well as add a new itinerary. And can be

mass calendar into a file or through SMS, MMS, Bluetooth sent.: Go to the specified calendar date."Jump to a specified date" by Week / Month view: After entering, you can view the weekly or monthly to do things matters Lunar: View calendar, choose whether or not to open or close the Lunar New Year.

***Alarm**

The time format for the alarm clock is identical to that of clock. When the mobile phone is off, the alarm clock can still work provided the battery is sufficient. The system has set 5 alarm clock options and the defaulted is off. You can activate one option or all options according to the actual demand. Every alarm clock option can set independent time and date. When the time is reached, the mobile phone will give out alert tone and flicker the current time and date on the screen. Press Stop to stop alarm clock; press Sleep, then the mobile phone will pause ringing and continue after 4min. If alarm time is reached but the mobile phone is switched off, then the mobile phone will be switch on automatically and ring. If Stop is pressed, then the mobile phone will ask you whether to switch on the mobile phone. Press "No" to switch off the mobile phone and "Yes" to register at the network and switch on the mobile phone..

1.8 Settings

***Dual SIM Settings**

Open mode: open the dual-mode mobile phone after the two cards at the same time knowledge

SIM cards only 1 open: open only SIM card 1

SIM card only 2 open: open SIM card only 2

Flight modes: normal mode, flight mode, when asked about the boot; Among them, the flight pattern of the user for use in aircraft

***Phone settings**

In this menu you can phone language, standby wallpaper, time set option.

the time and date: This menu can be set" through the city, set the time format and date format. urban settings: setv up different cities.

NOTE: This option is automatically updated with the time required to use, and network support in order to automatically update the time and date.

Time Settings: Set the current time and date.v

Timev format settings: Set the time and date display format.

Note: If you remove the battery from the phone or battery has been depleted for a very long time, then reload the battery when you charge the battery or re-boot, you may need to re-setup time.

Special Reminder: ban on the use of mobile phones in a specific area (such as inside the cabin), please be sure before entering the region from time to time to confirm whether the closure of the boot features in order to avoid abnormal incidents.

machine timer switch: set up a" designated phone open, the shutdown time.

language: Choose mobile phone" shows the language used (the phone support: English, Simplified Chinese), defaults to English.

default input method: operations may be based on your" habits, the default input method set up phone.

default encoding: BLG5," GB2312

standby display menu: Menu display can be set up standby wallpaper" images, screen savers, pictures, animation boot, shutdown animation, whether to display the date of the time, does this mean that the local number, whether the service type name and the clock.. (Local number to be set up in the phone book)

greeting: Set boot-up screen displayed on the main greeting."

" shortcut functions: the user according to individual needs, their own shortcuts.

Note: The shortcut function to be set // phone settings // specified set function keys for quick feature in order to use a specific menu.

Automatic" Update Time: To set the phone automatically updates the time zone based on the current time and date, select "Open." Automatic Updates will not affect your alarm clock, calendar or alarm clock, set a reminder time. They are created based on the time used. But the automatic update may cause some alarms expired.

handwritten set: set of hand-written, including hand-speed, color, such as "a stylus.
other settings: to set LCD backlight brightness and the length" of time

Note: Contact your network operator or service provider of the service and more information.

***Security Settings**

* SIM lock: open or close the SIM lock (PIN code)."

*fixed dial-up: This feature may require SIM cards and network operator support.

This feature is activated, you can only call in the list of *fixed dial-up number; activate fixed dialing, you will need to enter the PIN2 code.

*ban on dial-up: Set restrictions on all or part of the phone features turned on or off. (Needs SIM card support)

* Change Password: If you want to change your" password, you can lock prompted to enter your password, click Change Password to confirm.

phone lock: lock to open or close the phone. Phone lock is a 4-8" digit password, the factory default password is "1122", you can change your password.

keyboard lock: lock the keyboard open or closed. Your machine" provides a keypad lock function, when a certain period of time to automatically lock the keyboard, including: 5 seconds, 30 seconds, 60 seconds, 5 minutes.

Change Password: You can be the default code of the mobile phone or phone" book information and locked "1122" to their own easy-to-remember symbol-digit 4-8. If the lock and opened the cell phone, cell phone in the boot you will be prompted to "mobile phone has been locked."

To restore the factory settings: the number of mobile phone settings back to factory condition. Factory set password is "1122"

***Connectivity**

You can connect other phones by bluetooth and set GSM/GPRS data accounts. In bluetooth mode, the other phones must support bluetooth too.

***Restore factory setting**

Be careful to use this function. when use it, everything will restore to default factory status.

1.9 User profiles

Your phone provides a wide range of settings group, that is, the scene mode, so that you, depending on the definition of events and the environment from a number of mobile phone set. First of all, depending on your preferences on personalized profile settings, and then you only need to activate the profile. Can be divided into the general profile, meeting, outdoor, indoor, headphones, power-saving mode and Bluetooth.

Each profile can edit the following:

*tone settings: calls respectively, boot, shutdown, news, sound" settings button.

*volume: the respective keys on the ring tone and set the" size of the sound.

*ringing type: with the bell to ring, vibration,"Ringing vibration and ringing, ringing after the four types of vibration.

*ring type: Set ring type, are out, three kinds of continuous and growing strong.

*Voice: with a warning tone, error, network connection to connect four call" tone.

*response mode: to provide any key answer mode."

Personal settings, in the "Options" select "Open" option.

Description: mobile phone headset automatically inserted into a headphones mode. Open the power-saving mode, the system will be mandatory for configuration (see: energy explanation) Click on standby to live under the "#" key to switch to silent mode, long press again to return to the original model

***Bluetooth**

Activate Bluetooth: Bluetooth function turned on and off

Search-free devices: search for matching Bluetooth headset

My Device: Select the device has been connected to on-line

Link in the device: the device would not be required to break

Set The machine could be search: after the boot may be other mobile search to the

local The local device name: You can change the name of the machine

Certification requirements: On / off authentication Voice path settings: You can choose to remain in cell phones or headphones File Transfer settings: can be divided into share directory / directory permissions Storage path: the option is stored in the phone / memory card My Bluetooth: Bluetooth device address display

Note: The only support dual-channel Bluetooth headset to listen to MP3

1.10 Extra

***Calculator**

keyboard" simulation provided four +, -, ×, ÷ operator;
click "OK" results obtained."

Note: This calculator has limited accuracy and can only be used for simple calculations.

Unit conversion

Your phone provides you with some of the weight, as well as the basic unit of length of inter-conversion functions. Enter the appropriate parameters, it can be carried out, such as kilograms and pounds, kilograms and ounces, miles and meters, meters and yards, meters and feet, such as conversion

***currency converter**

You can set currency rate between any two country's currency

***Stopwatch**

This menu includes two functions, Typical Stopwatch and nWay Stopwatch.

Typical Stopwatch: you can have such options as Split Timing, Lap Timing and View Records.

Split Timing: From beginning to end, at most you can save 20pcs of entries and save them as one.

Lap Timing: You can respectively record the time of every lap; at most you can save the time of 20 laps and save them as one.

View Records: You can view, delete or delete all timing records.

nWay Stopwatch: You can press the up/down/ left/right direction key to time respectively.

***Ebook reader**

In standby, choose [Menu/Extras/E-book Reader]. After e-book is activated, the e-book list will be displayed. If no e-book, click Options to have such submenus as Clean Up Bookshelf and Global Settings.

If there are e-books, you can choose one e-book and press Options to have such submenus as Open E-book, Update, System Preset, Details, Delete, Delete All, Ranking, Execute System Preset and Help.

Open E-book: Activate the current e-book and enter the reading menu.

Clean up bookshelf:

Global settings: You can set Font Style, Font Size, Scroll By, Auto Scroll, Scroll Speed, Full Screen, Encoding, alignment and Storage Priority.

Book info: Display the detailed information about the current e-book.

Delete: Delete the current e-book.

Delete All files: Delete all e-books.

Sort by: You can have such options as As per Name, As per Type, As per Time, As per Size or None to rank e-books.

Apply global settings: You can execute the options for the preset system.

Help: You can have some operation instructions. Use key 0 to go to book settings

screen; use key 1 for help; use key 2 to add a bookmark; use key 3 to go to find screen; use key 4 to go to jump to screen; use key 5 to go to bookmark; use key 6 to find next; use key 7 to toggle the auto scroll; use key 8 to remove bookmark; use key 9 to toggle full screen mode.

1.11 Services

To use this feature, you can visit a wide range of services on the Internet. Such services may include weather forecasts, news, and financial information. The functions provided by network providers, according to the services provided by SIM card, there will be a new menu option appears. If the SIM card and network provider does not support the kinds of services will not be able to use this feature. For more information, please contact the vendor of the network.

WAP

Home - Start the connection settings of the selected file URL.

Bookmark - yahoo, sina; into the options menu, can bookmark the following management

enter: visit the web site of choice."

Editor: " Edit the selected bookmark name and URL.

sending: You can choose to SMS or" MMS approach

Delete: delete the selected bookmark."

All Delete: " Delete all bookmarks.

add a new bookmark: Add bookmark"

Document: save page when browsing net

Page history: recently viewed pages

Saved pages: In the page select "Saved pages" directly into the web site here

Please enter Address: enter here the need to enter the WAP address

Inbox services: information services inbox for network information

Set edit settingsv file: China Mobile

browser options: a long wait to show picturev

news service settings: closed / open

Clear cache: clear the new record intov

vRemoval of personal data

Data account

GSM data (dial-up)

v Name: china mobile

number: 17266v

user account: wapv

password:v wap

line type: ISDN, analogv

speed: 9.6Kbps, 14.4 Kbps, 4.8 Kbpsv

Domain: 000.000.000.000v

GPRS

Name: CHINA MOBILE GPRSv

GPRSv link points: cmwap

password: wapv authentication modes: general,v encryption.

Note: charges related to specific settings and consult thev local network service operators. China Mobile provides mobile phone settings document, the user can use network services in accordance with the different advice to local network operators

1.12 Shortcuts

You can set the idle shortcuts, or delete it .in this phone all the shortcuts have seted in idle screen.

FCC Statement

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference.

(2) This device must accept any interference received, including interference that may cause undesired operation.

2. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

SAR Information Statement

Your wireless phone is a radio transmitter and receiver. It is designed and manufactured not to exceed the emission limits

for exposure to radiofrequency (RF) energy set by the Federal Communications Commission of the U.S. Government. These limits are part of comprehensive guidelines and establish permitted levels of RF energy for the general population. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons, regardless of age and health. The exposure standard for wireless mobile phones employs a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit set by the FCC is 1.6 W/kg. * Tests for SAR are conducted with the phone transmitting at its highest certified power level in all tested frequency bands. Although the SAR is determined at the highest certified power level, the actual SAR level of the phone while operating can be well below the maximum value. This is because the phone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a wireless base station antenna, the lower the power output. Before a phone model is available for sale to the public, it must be tested and certified to the FCC that it does not exceed the limit established by the government adopted requirement for safe exposure. The tests are performed in positions and locations (e.g., at the ear and worn on the body) as required by the FCC for each model. The highest SAR value for this model phone when tested for use at the ear is 0.786 **W/Kg** and when worn on the body, as described in this user guide, is 0.697 **W/Kg**(Body-worn measurements differ among phone models, depending upon available accessories and FCC requirements). The maximum scaled SAR in hotspot mode is 0.773 W/Kg. While there may be differences between the SAR levels of various phones and at various positions, they all meet the government requirement for safe exposure. The FCC has granted an Equipment Authorization for this model phone with all reported SAR levels evaluated as in compliance with the FCC RFexposure guidelines. SAR information on this model phone is on file with the FCC and can be found under the Display Grant section of <http://www.fcc.gov/oet/fccid> after searching on

FCC ID: 2ARTMM2 Additional information on Specific Absorption Rates (SAR) can be found on the Cellular Telecommunications Industry Association (CTIA) web-site at <http://www.wow-com.com>. * In the United States and Canada,

the SAR limit for mobile phones used by the public is 1.6 watts/kg (W/kg) averaged over one gram of tissue. The standard incorporates a sub-stantial margin of safety to give additional protection for the public and to account for any variations in measurements.

Body-worn Operation

This device was tested for typical body-worn operations. To comply with RF exposure requirements, a minimum separation distance

of 10 mm must be maintained between the user's body and the handset, including the antenna. Third-party belt-clips, holsters,

and similar accessories used by this device should not contain any metallic components. Body-worn accessories that do not meet these requirements may not comply with RF exposure requirements and should be avoided. Use only the supplied or an approved antenna.