

MPE Calculation : Field Disturbance Sensor

Mode	Tx Frequency (GHz)	Max tune-up EIRP(dBm) ^{Note1}	Antenna gain (dBi)	Maximum EIRP (dBm)	Maximum EIRP (mW)	Maximum power density (mW/cm ²)	Requiriment (mW/cm ²)
Field Disturbance Sensor	10.525	14.00	7.30	14.00	25.119	0.005	1.000

Note1: Please refer to the operation description.

The EUT will only be used with a separation of 20 centimeters or greater between the antenna and the body of the user.

The MPE sample calculation for this exposure is shown below.

$$\begin{aligned}
 S &= \text{EIRP} / (4 R^2 \pi) \\
 &= 25.1189 / (4 \times 20^2 \times \pi) \\
 &= 0.005 \text{ mW/cm}^2
 \end{aligned}$$

- Note

S= Maximum power density(mW/cm²)

EIRP= Equivalent Isotropic Radiated Power(mW)

R= Distance to the center of the radiation of the antenna(20cm)

▪ Limits for General Population/Uncontrolled Exposure

Frequency range (MHz)	Electric Field strength (V/m)	Magnetic field strength (A/m)	Power Density (mW/cm ²)	Averageing time (minutes)
0.3 ~ 1.34	614	1.63	*100	30
1.34 ~ 30	824/f	2.19 / f	*180 / f ²	30
30 ~ 300	27.5	0.073	0.2	30
300 ~ 1,500			f / 1500	30
1,500 ~ 100,000			1.0	30

f = frequency in MHz * = Plane-wave equivalent power density

Conclusion : The exposure condition of this device is compliant with FCC