TEST REPORT

Product	:	Car multimedia player
Trade mark	:	Dual, Jensen, AXXERA
Model/Type reference	:	See to Clause 6.2
Serial Number	:	N/A
Report Number	:	EED32L00204801
FCC ID	:	2AT9B-AV1188
Date of Issue	:	Sep. 09, 2019
Test Standards	:	47 CFR Part 15 Subpart C
Test result	:	PASS

Prepared for:

MAXMADE AUTO ELECTRONICS Co., LTD
Building 2, GIEC Industrial Park, Puzai Road, Pingdi,
Longgang District, Shenzhen. China

Prepared by:

Centre Testing International Group Co., Ltd.
Hongwei Industrial Zone, Bao'an 70 District,
Shenzhen, Guangdong, China
TEL: +86-755-3368 3668
FAX: +86-755-3368 3385

Tested By:	Jay Zheng	Compiled by:	Alex Wu
Reviewed by:	Ware Xin	Approved by:	Kevin Yang
Date:	Sep. 09, 2019		

Check No.:3096321298

2 Version

Version No.	Date	Description
00	Sep. 09, 2019	Original

3 Test Summary

Test Item	Test Requirement	Test method	Result
Antenna Requirement	47 CFR Part 15 Subpart C Section 15.203/15.247 (c)	ANSI C63.10-2013	PASS
AC Power Line Conducted Emission	47 CFR Part 15 Subpart C Section 15.207	ANSI C63.10-2013	N/A
Conducted Peak Output Power	47 CFR Part 15 Subpart C Section 15.247 (b)(1)	ANSI C63.10-2013	PASS
20dB Occupied Bandwidth	47 CFR Part 15 Subpart C Section 15.247 (a)(1)	ANSI C63.10-2013	PASS
Carrier Frequencies Separation	47 CFR Part 15 Subpart C Section 15.247 (a)(1)	ANSI C63.10-2013	PASS
Hopping Channel Number	47 CFR Part 15 Subpart C Section 15.247 (b)	ANSI C63.10-2013	PASS
Dwell Time	47 CFR Part 15 Subpart C Section 15.247 (a)(1)	ANSI C63.10-2013	PASS
Pseudorandom Frequency Hopping Sequence	47 CFR Part 15 Subpart C Section 15.247(b)(4)&TCB Exclusion List (7 July 2002)	ANSI C63.10-2013	PASS
Band-edge for RF Conducted Emissions	47 CFR Part 15Subpart C Section 15.247(d)	ANSI C63.10-2013	PASS
RF Conducted Spurious Emissions	47 CFR Part 15 Subpart C Section 15.247(d)	ANSI C63.10-2013	PASS
Radiated Spurious emissions	47 CFR Part 15 Subpart C Section 15.205/15.209	ANSI C63.10-2013	PASS
Restricted bands around fundamental frequency (Radiated Emission)	47 CFR Part 15Subpart C Section 15.205/15.209	ANSI C63.10-2013	PASS

Remark:
Test according to ANSI C63.4-2014 & ANSI C63.10-2013.
The tested samples and the sample information are provided by the client.
Model No.:XDCPA11BT, DMCPA11BT, DMCPA210, XDCPA210,CAR10, CAR1000 ,CAR101XL, AVM2210H
All models are the same except for the model name. The test model is XDCPA11BT and the test results are applicable to the others.

4 Content

1 COVER PAGE 1

2 VERSION 2

3 TEST SUMMARY 3

4 CONTENT 4

5 TEST REQUIREMENT 5

5.1 TEST SETUP 5
5.1.1 For Conducted test setup 5
5.1.2 For Radiated Emissions test setup 5
5.1.3 For Conducted Emissions test setup 6
5.2 TEST ENVIRONMENT 6
5.3 TEST CONDITION 6

6 GENERAL INFORMATION 7

6.1 CLIENT INFORMATION 7
6.2 GENERAL DESCRIPTION OF EUT 7
6.3 PRODUCT SPECIFICATION SUBJECTIVE TO THIS STANDARD 8
6.4 DESCRIPTION OF SUPPORT UNITS 9
6.5 TEST LOCATION 9
6.6 DEVIATION FROM STANDARDS 9
6.7 ABNORMALITIES FROM STANDARD CONDITIONS 9
6.8 OTHER INFORMATION REQUESTED BY THE CUSTOMER 9
6.9 MEASUREMENT UNCERTAINTY (95% CONFIDENCE LEVELS, K=2) 10

7 EQUIPMENT LIST 11

8 Radio Technical Requirements Specification 14
Appendix A): 20dB Occupied Bandwidth 16
Appendix B): Carrier Frequency Separation 20
Appendix C): Dwell Time 24
Appendix D): Hopping Channel Number 29
Appendix E): Conducted Peak Output Power 31
Appendix F): Band-edge for RF Conducted Emissions 35
Appendix G): RF Conducted Spurious Emissions 40
Appendix H): Pseudorandom Frequency Hopping Sequence 50
Appendix I): Antenna Requirement 51
Appendix J): Restricted bands around fundamental frequency (Radiated) 52
Appendix K): Radiated Spurious Emissions 77

PHOTOGRAPHS OF TEST SETUP 89

PHOTOGRAPHS OF EUT CONSTRUCTIONAL DETAILS 91

5 Test Requirement

5.1 Test setup

5.1.1 For Conducted test setup



5.1.2 For Radiated Emissions test setup

Radiated Emissions setup:



Figure 1. Below 30MHz



Figure 2. 30MHz to 1GHz



Figure 3. Above 1GHz

5.1.3 For Conducted Emissions test setup

Conducted Emissions setup



5.2 Test Environment

Operating Environment:	
Temperature:	24°C
Humidity:	56 % RH
Atmospheric Pressure:	1010mbar

5.3 Test Condition

Test Mode	Tx	RF Channel		
		Low(L)	Middle(M)	High(H)
GFSK/π/4DQPSK/ 8DPSK(DH1,DH3, DH5)	2402MHz ~2480 MHz	Channel 1	Channel 40	Channel79
		2402MHz	2441MHz	2480MHz
TX mode: The EUT transmitted the continuous modulation test signal at the specific channel(s).				

6 General Information

6.1 Client Information

Applicant:	MAXMADE AUTO ELECTRONICS Co., LTD
Address of Applicant:	Building 2, GIEC Industrial Park, Puzai Road, Pingdi, Longgang District, Shenzhen. China
Manufacturer:	MAXMADE AUTO ELECTRONICS Co., LTD
Address of Manufacturer:	Building 2, GIEC Industrial Park, Puzai Road, Pingdi, Longgang District, Shenzhen. China
Factory:	Dual Electronics Corporation
Address of Factory:	Namsung America . Inc.250 International Parkway Suite 230 Heathrow. FL 32746

6.2 General Description of EUT

Product Name:	Car multimedia player
Model No.(EUT):	XDCPA11BT, DMCPA11BT, DMCPA210, XDCPA210, CAR10, CAR1000 , CAR101XL, AVM2210H
Test Model No:	XDCPA11BT
Trade mark:	Dual, Jensen, AXXERA
EUT Supports Radios application:	BT V2.1 + EDR Single mode
Power Supply:	DC 12V/15A 180W
Sample Received Date:	Jul. 30, 2019
Sample tested Date:	Jul. 30, 2019 to Sep. 04, 2019

6.3 Product Specification subjective to this standard

Operation Frequency:	2402MHz~2480MHz
Bluetooth Version:	BT V2.1 + EDR
Modulation Technique:	Frequency Hopping Spread Spectrum(FHSS)
Modulation Type:	GFSK, π/4DQPSK, 8DPSK
Number of Channel:	79
Hopping Channel Type:	Adaptive Frequency Hopping systems
Test Power Grade:	Default
Test Software of EUT:	HC_Data_Test
Antenna Type:	PCB antenna
Antenna Gain:	3.45 dBi
Test Voltage:	DC 12V/15A 180W

Operation Frequency each of channel

Channel	Frequency	Channel	Frequency	Channel	Frequency	Channel	Frequency
1	2402MHz	21	2422MHz	41	2442MHz	61	2462MHz
2	2403MHz	22	2423MHz	42	2443MHz	62	2463MHz
3	2404MHz	23	2424MHz	43	2444MHz	63	2464MHz
4	2405MHz	24	2425MHz	44	2445MHz	64	2465MHz
5	2406MHz	25	2426MHz	45	2446MHz	65	2466MHz
6	2407MHz	26	2427MHz	46	2447MHz	66	2467MHz
7	2408MHz	27	2428MHz	47	2448MHz	67	2468MHz
8	2409MHz	28	2429MHz	48	2449MHz	68	2469MHz
9	2410MHz	29	2430MHz	49	2450MHz	69	2470MHz
10	2411MHz	30	2431MHz	50	2451MHz	70	2471MHz
11	2412MHz	31	2432MHz	51	2452MHz	71	2472MHz
12	2413MHz	32	2433MHz	52	2453MHz	72	2473MHz
13	2414MHz	33	2434MHz	53	2454MHz	73	2474MHz
14	2415MHz	34	2435MHz	54	2455MHz	74	2475MHz
15	2416MHz	35	2436MHz	55	2456MHz	75	2476MHz
16	2417MHz	36	2437MHz	56	2457MHz	76	2477MHz
17	2418MHz	37	2438MHz	57	2458MHz	77	2478MHz
18	2419MHz	38	2439MHz	58	2459MHz	78	2479MHz
19	2420MHz	39	2440MHz	59	2460MHz	79	2480MHz
20	2421MHz	40	2441MHz	60	2461MHz		

6.4 Description of Support Units

The EUT has been tested independently.

6.5 Test Location

All tests were performed at:

Centre Testing International Group Co., Ltd
Building C, Hongwei Industrial Park Block 70, Bao'an District, Shenzhen, China
Telephone: +86 (0) 755 33683668 Fax:+86 (0) 755 33683385
No tests were sub-contracted.
FCC Designation No.: CN1164

6.6 Deviation from Standards

None.

6.7 Abnormalities from Standard Conditions

None.

6.8 Other Information Requested by the Customer

None.

6.9 Measurement Uncertainty (95% confidence levels, k=2)

No.	Item	Measurement Uncertainty
1	Radio Frequency	7.9×10^{-8}
2	RF power, conducted	0.46dB (30MHz-1GHz)
		0.55dB (1GHz-18GHz)
3	Radiated Spurious emission test	4.3dB (30MHz-1GHz)
		4.5dB (1GHz-12.75GHz)
4	Conduction emission	3.5dB (9kHz to 150kHz)
		3.1dB (150kHz to 30MHz)
5	Temperature test	0.64°C
6	Humidity test	3.8%
7	DC power voltages	0.026%

7 Equipment List

RF test system					
Equipment	**Manufacturer**	**Model No.**	**Serial Number**	**Cal. Date (mm-dd-yyyy)**	**Cal. Due date (mm-dd-yyyy)**
Signal Generator	Keysight	E8257D	MY53401106	03-01-2019	02-29-2020
Spectrum Analyzer	Keysight	N9010A	MY54510339	03-01-2019	02-29-2020
Signal Generator	Keysight	N5182B	MY53051549	03-01-2019	02-29-2020
High-pass filter	Sinoscite	FL3CX03WG18NM12-0398-002	---	01-09-2019	01-08-2020
High-pass filter	MICRO-TRONICS	SPA-F-63029-4	---	01-09-2019	01-08-2020
DC Power	Keysight	E3642A	MY54426035	03-01-2019	02-29-2020
PC-1	Lenovo	R4960d	---	03-01-2019	02-29-2020
BT&WI-FI Automatic control	R&S	OSP120	101374	03-01-2019	02-29-2020
RF control unit	JS Tonscend	JS0806-2	15860006	03-01-2019	02-29-2020
RF control unit	JS Tonscend	JS0806-1	15860004	03-01-2019	02-29-2020
RF control unit	JS Tonscend	JS0806-4	158060007	03-01-2019	02-29-2020
BT&WI-FI Automatic test software	JS Tonscend	JS1120-2	---	03-01-2019	02-29-2020
Temperature/ Humidity Indicator	biaozhi	HM10	1804186	10-12-2018	10-11-2019

Equipment	Manufacturer	Model No.	Serial Number	Cal. date (mm-dd-yyyy)	Cal. Due date (mm-dd-yyyy)
3M Chamber & Accessory Equipment	TDK	SAC-3	---	05-24-2019	05-23-2022
TRILOG Broadband Antenna	Schwarzbeck	VULB9163	9163-401	12-21-2018	12-20-2019
TRILOG Broadband Antenna	Schwarzbeck	VULB9163	9163-618	07-26-2019	07-25-2020
Microwave Preamplifier	Agilent	8449B	3008A02425	07-12-2019	07-11-2020
Microwave Preamplifier	Tonscend	EMC051845 SE	980380	01-16-2019	01-15-2020
Horn Antenna	Schwarzbeck	BBHA 9120D	9120D-1869	04-25-2018	04-24-2021
Horn Antenna	ETS-LINDGREN	3117	00057410	06-05-2018	06-04-2021
Double ridge horn antenna	A.H.SYSTEMS	SAS-574	374	06-05-2018	06-04-2021
Pre-amplifier	A.H.SYSTEMS	PAP-1840-60	6041.6042	07-26-2019	07-25-2020
Loop Antenna	Schwarzbeck	FMZB 1519B	1519B-076	04-25-2018	04-24-2021
Spectrum Analyzer	R&S	FSP40	100416	04-28-2019	04-27-2020
Receiver	R&S	ESCI	100435	05-20-2019	05-19-2020
Receiver	R&S	ESCI7	100938-003	11-23-2018	11-22-2019
Multi device Controller	maturo	NCD/070/10711112	---	01-09-2019	01-08-2020
Signal Generator	Agilent	E4438C	MY45095744	03-01-2019	02-29-2020
LISN	Schwarzbeck	NNBM8125	81251547	05-08-2019	05-07-2020
LISN	Schwarzbeck	NNBM8125	81251548	05-08-2019	05-07-2020
Signal Generator	Keysight	E8257D	MY53401106	03-01-2019	02-29-2020
Temperature/ Humidity Indicator	Shanghai qixiang	HM10	1804298	10-12-2018	10-11-2019
Communication test set	Agilent	E5515C	GB47050534	03-01-2019	02-28-2022
Cable line	Fulai(7M)	SF106	5219/6A	01-09-2019	01-08-2020
Cable line	Fulai(6M)	SF106	5220/6A	01-09-2019	01-08-2020
Cable line	Fulai(3M)	SF106	5216/6A	01-09-2019	01-08-2020
Cable line	Fulai(3M)	SF106	5217/6A	01-09-2019	01-08-2020
Communication test set	R&S	CMW500	104466	01-18-2019	01-17-2020
High-pass filter	Sinoscite	FL3CX03WG18NM12-0398-002	---	01-09-2019	01-08-2020
High-pass filter	MICRO-TRONICS	SPA-F-63029-4	---	01-09-2019	01-08-2020
band rejection filter	Sinoscite	FL5CX01CA09CL12-0395-001	---	01-09-2019	01-08-2020
band rejection filter	Sinoscite	FL5CX01CA08CL12-0393-001	---	01-09-2019	01-08-2020
band rejection filter	Sinoscite	FL5CX02CA04CL12-0396-002	---	01-09-2019	01-08-2020
band rejection filter	Sinoscite	FL5CX02CA03CL12-0394-001	---	01-09-2019	01-08-2020

3M full-anechoic Chamber					
Equipment	**Manufacturer**	**Model No.**	**Serial Number**	**Cal. date (mm-dd-yyyy)**	**Cal. Due date (mm-dd-yyyy)**
RSE Automatic test software	JS Tonscend	JS36-RSE	10166	06-19-2019	06-18-2020
Receiver	Keysight	N9038A	MY57290136	03-27-2019	03-26-2020
Spectrum Analyzer	Keysight	N9020B	MY57111112	03-27-2019	03-26-2020
Spectrum Analyzer	Keysight	N9030B	MY57140871	03-27-2019	03-26-2020
Loop Antenna	Schwarzbeck	FMZB 1519B	1519B-075	04-25-2018	04-24-2021
Loop Antenna	Schwarzbeck	FMZB 1519B	1519B-076	04-25-2018	04-24-2021
TRILOG Broadband Antenna	Schwarzbeck	VULB 9163	9163-1148	04-25-2018	04-24-2021
Horn Antenna	Schwarzbeck	BBHA 9170	9170-832	04-25-2018	04-24-2021
Horn Antenna	Schwarzbeck	BBHA 9170	9170-829	04-25-2018	04-24-2021
Communication Antenna	Schwarzbeck	CLSA 0110L	1014	02-14-2019	02-13-2020
Biconical antenna	Schwarzbeck	VUBA 9117	9117-381	04-25-2018	04-24-2021
Horn Antenna	ETS-LINDGREN	3117	00057407	07-10-2018	07-09-2021
Preamplifier	EMCI	EMC184055SE	980596	05-22-2019	5-21-2020
Communication test set	R&S	CMW500	102898	01-18-2019	01-17-2020
Preamplifier	EMCI	EMC001330	980563	05-08-2019	05-07-2020
Preamplifier	Agilent	8449B	3008A02425	07-12-2019	07-11-2020
Temperature/ Humidity Indicator	biaozhi	GM1360	EE1186631	04-30-2019	04-29-2020
Signal Generator	KEYSIGHT	E8257D	MY53401106	03-01-2019	02-29-2020
Fully Anechoic Chamber	TDK	FAC-3	---	01-17-2018	01-16-2021
Filter bank	JS Tonscend	JS0806-F	188060094	04-10-2018	04-09-2021
Cable line	Times	SFT205-NMSM-2.50M	394812-0001	01-09-2019	01-08-2020
Cable line	Times	SFT205-NMSM-2.50M	394812-0002	01-09-2019	01-08-2020
Cable line	Times	SFT205-NMSM-2.50M	394812-0003	01-09-2019	01-08-2020
Cable line	Times	SFT205-NMSM-2.50M	393495-0001	01-09-2019	01-08-2020
Cable line	Times	EMC104-NMNM-1000	SN160710	01-09-2019	01-08-2020
Cable line	Times	SFT205-NMSM-3.00M	394813-0001	01-09-2019	01-08-2020
Cable line	Times	SFT205-NMNM-1.50M	381964-0001	01-09-2019	01-08-2020
Cable line	Times	SFT205-NMSM-7.00M	394815-0001	01-09-2019	01-08-2020
Cable line	Times	HF160-KMKM-3.00M	393493-0001	01-09-2019	01-08-2020

8 Radio Technical Requirements Specification

No.	Identity	Document Title
1	FCC Part15C	Subpart C-Intentional Radiators
2	ANSI C63.10-2013	American National Standard for Testing Unlicesed Wireless Devices

Reference documents for testing:

Test Results List:

Test requirement	Test method	Test item	Verdict	Note
Part15C Section 15.247 (a)(1)	ANSI 63.10	20dB Occupied Bandwidth	PASS	Appendix A)
Part15C Section 15.247 (a)(1)	ANSI 63.10	Carrier Frequencies Separation	PASS	Appendix B)
Part15C Section 15.247 (a)(1)	ANSI 63.10	Dwell Time	PASS	Appendix C)
Part15C Section 15.247 (b)	ANSI 63.10	Hopping Channel Number	PASS	Appendix D)
Part15C Section 15.247 (b)(1)	ANSI 63.10	Conducted Peak Output Power	PASS	Appendix E)
Part15C Section 15.247(d)	ANSI 63.10	Band-edge for RF Conducted Emissions	PASS	Appendix F)
Part15C Section 15.247(d)	ANSI 63.10	RF Conducted Spurious Emissions	PASS	Appendix G)
Part15C Section 15.247 (a)(1)	ANSI 63.10	Pseudorandom Frequency	PASS	Appendix H)
Part15C Section 15.203/15.247 (c)	ANSI 63.10	Antenna Requirement	PASS	Appendix I)
Part15C Section 15.207	ANSI 63.10	AC Power Line Conducted	N/A	
Part15C Section 15.205/15.209	ANSI 63.10	Restricted bands around fundamental frequency	PASS	Appendix J)
Part15C Section 15.205/15.209	ANSI 63.10	Radiated Spurious Emissions	PASS	Appendix K)

Duty Cycle			
Configuration	**TX ON(ms)**	**TX ALL(ms)**	**Duty Cycle(%)**
BDR-1Mbps	**2.866**	**2.97**	**96.5%**
EDR-3Mbps	**2.880**	**2.9864**	**96.44%**

BDR-1Mbps	EDR-3Mbps
	

Appendix A): 20dB Occupied Bandwidth

Test Result

Mode	Channel.	20dB Bandwidth [MHz]	99% OBW [MHz]	Verdict
GFSK	LCH	0.8414	0.76496	PASS
GFSK	MCH	0.8457	0.76755	PASS
GFSK	HCH	0.8488	0.77259	PASS
π /4DQPSK	LCH	1.548	1.3979	PASS
π /4DQPSK	MCH	1.377	1.2637	PASS
π /4DQPSK	HCH	1.289	1.2154	PASS
8DPSK	LCH	1.462	1.3384	PASS
8DPSK	MCH	1.315	1.2437	PASS
8DPSK	HCH	1.323	1.2296	PASS

Test Graph

Graphs			
GFSK/LCH			
GFSK/MCH			
GFSK/HCH			

π/4DQPSK/LCH			
π/4DQPSK/MCH			
π/4DQPSK/HCH			

8DPSK/LCH			
8DPSK/MCH			
8DPSK/HCH			

Appendix B): Carrier Frequency Separation

Result Table

Mode	Channel.	Carrier Frequency Separation [MHz]	Verdict
GFSK	LCH	1.000	PASS
GFSK	MCH	1.000	PASS
GFSK	HCH	1.000	PASS
π/4DQPSK	LCH	1.002	PASS
π/4DQPSK	MCH	1.178	PASS
π/4DQPSK	HCH	0.990	PASS
8DPSK	LCH	1.000	PASS
8DPSK	MCH	0.958	PASS
8DPSK	HCH	1.012	PASS

Test Graph

Graphs			
GFSK/LCH			
GFSK/MCH			
GFSK/HCH			

π/4DQPSK/LCH			
π/4DQPSK/MCH			
π/4DQPSK/HCH			

8DPSK/LCH			
8DPSK/MCH			
8DPSK/HCH			

Appendix C): Dwell Time

Result Table

Mode	Packet	Channel	Burst Width [ms/hop/ch]	Total Hops[hop*ch]	Dwell Time[s]	Duty Cycle [%]	Verdict
GFSK	DH1	LCH	0.407863	320	0.131	0.33	PASS
GFSK	DH1	MCH	0.406603	320	0.13	0.33	PASS
GFSK	DH1	HCH	0.4066	320	0.13	0.33	PASS
GFSK	DH3	LCH	1.68213	160	0.269	0.67	PASS
GFSK	DH3	MCH	1.684663	160	0.27	0.67	PASS
GFSK	DH3	HCH	1.683397	160	0.269	0.67	PASS
GFSK	DH5	LCH	2.9164	106.7	0.311	0.78	PASS
GFSK	DH5	MCH	2.9164	106.7	0.311	0.78	PASS
GFSK	DH5	HCH	2.9164	106.7	0.311	0.78	PASS

The GFSK is worst case mode.

Test Graph

Graphs			
GFSK_DH1/LCH			
GFSK_DH1/MCH			
GFSK_DH1/HCH			

GFSK_DH3/LCH			
GFSK_DH3/MCH			
GFSK_DH3/HCH			

GFSK_DH5/LCH			
GFSK_DH5/MCH			
GFSK_DH5/HCH			

Appendix D): Hopping Channel Number

Result Table

Mode	Channel.	Number of Hopping Channel	Verdict
GFSK	Hop	79	PASS
π/4DQPSK	Hop	79	PASS
8DPSK	Hop	79	PASS

Test Graph

Graphs			
GFSK/Hop			
π/4DQPSK/Hop			
8DPSK/Hop			

Appendix E): Conducted Peak Output Power

Result Table

Mode	Channel.	Maximum Peak Output Power [dBm]	Verdict
GFSK	LCH	3.386	PASS
GFSK	MCH	3.153	PASS
GFSK	HCH	2.460	PASS
π/4DQPSK	LCH	1.694	PASS
π/4DQPSK	MCH	1.352	PASS
π/4DQPSK	HCH	0.446	PASS
8DPSK	LCH	1.966	PASS
8DPSK	MCH	1.628	PASS
8DPSK	HCH	0.730	PASS

Test Graph

Graphs			
GFSK/LCH			
GFSK/MCH			
GFSK/HCH			

π/4DQPSK/LCH			
π/4DQPSK/MCH			
π/4DQPSK/HCH			

8DPSK/LCH			
8DPSK/MCH			
8DPSK/HCH			

Appendix F): Band-edge for RF Conducted Emissions

Result Table

Mode	Channel	Carrier Frequency [MHz]	Carrier Power [dBm]	Frequency Hopping	Max Spurious Level [dBm]	Limit [dBm]	Verdict
GFSK	LCH	2402	1.556	Off	-59.608	-18.44	PASS
			2.132	On	-52.474	-17.87	PASS
GFSK	HCH	2480	0.408	Off	-57.158	-19.59	PASS
			1.459	On	-57.242	-18.54	PASS
π/4DQPSK	LCH	2402	-3.016	Off	-60.282	-23.02	PASS
			2.221	On	-53.990	-17.78	PASS
π/4DQPSK	HCH	2480	-4.703	Off	-53.745	-24.7	PASS
			1.579	On	-55.188	-18.42	PASS
8DPSK	LCH	2402	-3.090	Off	-60.399	-23.09	PASS
			2.239	On	-53.206	-17.76	PASS
8DPSK	HCH	2480	-4.660	Off	-45.242	-24.66	PASS
			1.480	On	-47.757	-18.52	PASS

Test Graph

Graphs			
GFSK/LCH/No Hop			
GFSK/LCH/Hop			
GFSK/HCH/No Hop			

GFSK/HCH/Hop			
π/4DQPSK/LCH/No Hop			
π/4DQPSK/LCH/Hop			

π/4DQPSK/HCH/No Hop			
π/4DQPSK/HCH/Hop			
8DPSK/LCH/No Hop			

8DPSK/LCH/Hop		
8DPSK/HCH/No Hop		
8DPSK/HCH/Hop		

Appendix G): RF Conducted Spurious Emissions

Result Table

Mode	Channel	Pref [dBm]	Puw[dBm]	Verdict
GFSK	LCH	1.272	<Limit	PASS
GFSK	MCH	0.893	<Limit	PASS
GFSK	HCH	0.119	<Limit	PASS
π/4DQPSK	LCH	-3.207	<Limit	PASS
π/4DQPSK	MCH	-3.858	<Limit	PASS
π/4DQPSK	HCH	-4.914	<Limit	PASS
8DPSK	LCH	-3.279	<Limit	PASS
8DPSK	MCH	-3.93	<Limit	PASS
8DPSK	HCH	-5.021	<Limit	PASS

Test Graph

GFSK_LCH_Graphs			
Pref			
Puw			

GFSK_MCH_Graphs			
Pref			
Puw			

GFSK_HCH_Graphs			
Pref			
Puw			

π/4DQPSK_LCH_Graphs			
Pref			
Puw			

π/4DQPSK_MCH_Graphs			
Pref			
Puw			

π/4DQPSK_HCH_Graphs			
Pref			
Puw			

8DPSK_LCH_Graphs			
Pref			
Puw			

8DPSK_MCH_Graphs			
Pref			
Puw			

8DPSK_HCH_Graphs			
Pref			
Puw			

Appendix H): Pseudorandom Frequency Hopping Sequence

Test Requirement:	47 CFR Part 15**C Section 15.247 (a)(1) requirement:**

Frequency hopping systems shall have hopping channel carrier frequencies separated by a minimum of 25 kHz or the 20 dB bandwidth of the hopping channel, whichever is greater.
Alternatively. Frequency hopping systems operating in the 2400-2483.5 MHz band may have hopping channel carrier frequencies that are separated by 25 kHz or two-thirds of the 20 dB bandwidth of the hopping channel, whichever is greater, provided the systems operate with an output power no greater than 125 mW.
The system shall hop to channel frequencies that are selected at the system hopping rate from a Pseudorandom ordered list of hopping frequencies. Each frequency must be used equally on the average by each transmitter. The system receivers shall have input bandwidths that match the hopping channel bandwidths of their corresponding transmitters and shall shift frequencies in synchronization with the transmitted signals.

EUT Pseudorandom Frequency Hopping Sequence

The pseudorandom sequence may be generated in a nine-stage shift register whose 5th and 9th stage outputs are added in a modulo-two addition stage. And the result is fed back to the input of the first stage. The sequence begins with the first ONE of 9 consecutive ONEs; i.e. the shift register is initialized with nine ones.

- Number of shift register stages: 9
- Length of pseudo-random sequence: 2^9 -1 = 511 bits
- Longest sequence of zeros: 8 (non-inverted signal)



Linear Feedback Shift Register for Generation of the PRBS sequence

An example of Pseudorandom Frequency Hopping Sequence as follow:



Each frequency used equally on the average by each transmitter.
The system receivers have input bandwidths that match the hopping channel bandwidths of their Corresponding transmitters and shift frequencies in synchronization with the transmitted signals.

The device does not have the ability to be coordinated with other FHSS systems in an effort to avoid the simultaneous occupancy of individual hopping frequencies by multiple transmitters.

Appendix I): Antenna Requirement

15.203 requirement:

An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator, the manufacturer may design the unit so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited.

15.247(b) (4) requirement:

The conducted output power limit specified in paragraph (b) of this section is based on the use of antennas with directional gains that do not exceed 6 dBi. Except as shown in paragraph (c) of this section, if transmitting antennas of directional gain greater than 6 dBi are used, the conducted output power from the intentional radiator shall be reduced below the stated values in paragraphs (b)(1), (b)(2), and (b)(3) of this section, as appropriate, by the amount in dB that the directional gain of the antenna exceeds 6 dBi.

EUT Antenna:



The antenna is PIFA Antenna and no consideration of replacement. The best case gain of the antenna is 3.45dBi.

Appendix J): Restricted bands around fundamental frequency (Radiated)

Receiver Setup:

Frequency	Detector	RBW	VBW	Remark
30MHz-1GHz	Quasi-peak	120kHz	300kHz	Quasi-peak
Above 1GHz	Peak	1MHz	3MHz	Peak
	Peak	1MHz	10Hz	Average

Test Procedure:

Below 1GHz test procedure as below:

a. The EUT was placed on the top of a rotating table 0.8 meters above the ground at a 3 meter semi-anechoic camber. The table was rotated 360 degrees to determine the position of the highest radiation.
b. The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.
c. The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.
d. For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters and the rotatable table was turned from 0 degrees to 360 degrees to find the maximum reading.
e. The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode.
f. Place a marker at the end of the restricted band closest to the transmit frequency to show compliance. Also measure any emissions in the restricted bands. Save the spectrum analyzer plot. Repeat for each power and modulation for lowest and highest channel

Above 1GHz test procedure as below:

g. Different between above is the test site, change from Semi- Anechoic Chamber to fully Anechoic Chamber and change form table 0.8 meter to 1.5 meter(Above 18GHz the distance is 1 meter and table is 1.5 meter).
h. b. Test the EUT in the lowest channel , the Highest channel
i. The radiation measurements are performed in X, Y, Z axis positioning for Transmitting mode, and found the X axis positioning which it is worse case.
j. Repeat above procedures until all frequencies measured was complete.

Limit:

Frequency	Limit (dBμV/m @3m)	Remark
30MHz-88MHz	40.0	Quasi-peak Value
88MHz-216MHz	43.5	Quasi-peak Value
216MHz-960MHz	46.0	Quasi-peak Value
960MHz-1GHz	54.0	Quasi-peak Value
Above 1GHz	54.0	Average Value
	74.0	Peak Value

Test plot as follows:

Mode:	DH5	Channel:	2402
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2389.0676	32.24	13.38	-42.43	56.86	60.05	74.00	13.95	Pass	Horizontal
2	2390.0000	32.25	13.37	-42.44	56.05	59.23	74.00	14.77	Pass	Horizontal
3	2401.9086	32.26	13.31	-42.43	75.31	78.45	74.00	-4.45	Pass	Horizontal

Mode:	DH5	Channel:	2402
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2389.6621	32.25	13.38	-42.45	55.93	59.11	74.00	14.89	Pass	Vertical
2	2390.0000	32.25	13.37	-42.44	54.09	57.27	74.00	16.73	Pass	Vertical
3	2401.7897	32.26	13.31	-42.43	74.96	78.10	74.00	-4.10	Pass	Vertical

Mode:	DH5	Channel:	2402
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2389.1865	32.24	13.38	-42.43	41.46	44.65	54.00	9.35	Pass	Horizontal
2	2390.0000	32.25	13.37	-42.44	40.58	43.76	54.00	10.24	Pass	Horizontal
3	2401.9086	32.26	13.31	-42.43	72.18	75.32	54.00	-21.32	Pass	Horizontal

Mode:	DH5	Channel:	2412
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2389.1865	32.24	13.38	-42.43	41.12	44.31	54.00	9.69	Pass	Vertical
2	2390.0000	32.25	13.37	-42.44	40.25	43.43	54.00	10.57	Pass	Vertical
3	2401.9086	32.26	13.31	-42.43	71.28	74.42	54.00	-20.42	Pass	Vertical

Mode:	DH5	Channel:	2480
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2479.8473	32.37	13.39	-42.39	75.42	78.79	74.00	-4.79	Pass	Horizontal
2	2483.5000	32.38	13.38	-42.40	50.43	53.79	74.00	20.21	Pass	Horizontal

Mode:	DH5	Channel:	2480
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2479.7998	32.37	13.39	-42.39	77.31	80.68	74.00	-6.68	Pass	Vertical
2	2483.5000	32.38	13.38	-42.40	50.22	53.58	74.00	20.42	Pass	Vertical

Mode:	DH5	Channel:	2480
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2479.8473	32.37	13.39	-42.39	75.44	78.81	54.00	-24.81	Pass	Horizontal
2	2483.5000	32.38	13.38	-42.40	36.88	40.24	54.00	13.76	Pass	Horizontal

Mode:	DH5	Channel:	2480
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2479.8473	32.37	13.39	-42.39	77.33	80.70	54.00	-26.70	Pass	Vertical
2	2483.5000	32.38	13.38	-42.40	36.89	40.25	54.00	13.75	Pass	Vertical

Mode:	2DH5	Channel:	2402
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2389.4243	32.25	13.38	-42.45	56.82	60.00	74.00	14.00	Pass	Horizontal
2	2390.0000	32.25	13.37	-42.44	53.85	57.03	74.00	16.97	Pass	Horizontal
3	2402.1464	32.26	13.31	-42.43	89.06	92.20	74.00	-18.20	Pass	Horizontal

Mode:	2DH5	Channel:	2402
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2389.3054	32.25	13.38	-42.44	59.63	62.82	74.00	11.18	Pass	Vertical
2	2390.0000	32.25	13.37	-42.44	57.57	60.75	74.00	13.25	Pass	Vertical
3	2402.1464	32.26	13.31	-42.43	88.88	92.02	74.00	-18.02	Pass	Vertical

Mode:	2DH5	Channel:	2402
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2389.3054	32.25	13.38	-42.44	43.02	46.21	54.00	7.79	Pass	Horizontal
2	2390.0000	32.25	13.37	-42.44	41.61	44.79	54.00	9.21	Pass	Horizontal
3	2402.0275	32.26	13.31	-42.43	83.30	86.44	54.00	-32.44	Pass	Horizontal

Mode:	2DH5	Channel:	2402
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2389.3054	32.25	13.38	-42.44	43.53	46.72	54.00	7.28	Pass	Vertical
2	2390.0000	32.25	13.37	-42.44	42.00	45.18	54.00	8.82	Pass	Vertical
3	2402.0275	32.26	13.31	-42.43	82.59	85.73	54.00	-31.73	Pass	Vertical

Mode:	2DH5	Channel:	2480
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2479.7998	32.37	13.39	-42.39	88.67	92.04	74.00	-18.04	Pass	Horizontal
2	2483.5000	32.38	13.38	-42.40	53.83	57.19	74.00	16.81	Pass	Horizontal

Mode:	2DH5	Channel:	2480
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2480.1327	32.37	13.39	-42.40	90.57	93.93	74.00	-19.93	Pass	Vertical
2	2483.5000	32.38	13.38	-42.40	54.96	58.32	74.00	15.68	Pass	Vertical

Mode:	2DH5	Channel:	2402
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2480.0375	32.37	13.39	-42.39	84.26	87.63	54.00	-33.63	Pass	Horizontal
2	2483.5000	32.38	13.38	-42.40	38.30	41.66	54.00	12.34	Pass	Horizontal

Mode:	2DH5	Channel:	2402
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2480.0375	32.37	13.39	-42.39	88.79	92.16	54.00	-38.16	Pass	Vertical
2	2483.5000	32.38	13.38	-42.40	39.24	42.60	54.00	11.40	Pass	Vertical

Mode:	3DH5	Channel:	2402
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2390.0000	32.25	13.37	-42.44	55.06	58.24	74.00	15.76	Pass	Horizontal
2	2402.0275	32.26	13.31	-42.43	88.58	91.72	74.00	-17.72	Pass	Horizontal

Mode:	3DH5	Channel:	2402
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2390.0000	32.25	13.37	-42.44	57.29	60.47	74.00	13.53	Pass	Vertical
2	2402.1464	32.26	13.31	-42.43	88.90	92.04	74.00	-18.04	Pass	Vertical

Mode:	3DH5	Channel:	2402
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2390.0000	32.25	13.37	-42.44	41.47	44.65	54.00	9.35	Pass	Horizontal
2	2402.0275	32.26	13.31	-42.43	83.07	86.21	54.00	-32.21	Pass	Horizontal

Mode:	3DH5	Channel:	2402
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2390.0000	32.25	13.37	-42.44	42.01	45.19	54.00	8.81	Pass	Vertical
2	2402.0275	32.26	13.31	-42.43	82.70	85.84	54.00	-31.84	Pass	Vertical

Mode:	3DH5	Channel:	2480
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2480.0375	32.37	13.39	-42.39	88.44	91.81	74.00	-17.81	Pass	Horizontal
2	2483.5000	32.38	13.38	-42.40	60.30	63.66	74.00	10.34	Pass	Horizontal

Mode:	3DH5	Channel:	2480
Remark:	PK		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2480.0375	32.37	13.39	-42.39	90.74	94.11	74.00	-20.11	Pass	Vertical
2	2483.5000	32.38	13.38	-42.40	63.25	66.61	74.00	7.39	Pass	Vertical

Mode:	3DH5	Channel:	2480
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2480.0375	32.37	13.39	-42.39	84.52	87.89	54.00	-33.89	Pass	Horizontal
2	2483.5000	32.38	13.38	-42.40	38.96	42.32	54.00	11.68	Pass	Horizontal

Mode:	3DH5	Channel:	2480
Remark:	AV		

Test Graph



NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity
1	2479.9900	32.37	13.39	-42.39	88.69	92.06	54.00	-38.06	Pass	Vertical
2	2483.5000	32.38	13.38	-42.40	40.01	43.37	54.00	10.63	Pass	Vertical

Note:
1) Through Pre-scan transmitter mode with all kind of modulation and all kind of data type, find the 1-DH5 of data type is the worse case of GFSK modulation type, the 2-DH5 of data type is the worse case of π/4DQPSK modulation type, the 3-DH5 of data type is the worse case of 8DPSK modulation type in charge + transmitter mode.
2) As shown in this section, the field strength limits are based on average limits. However, the peak field strength of any emission shall not exceed the maximum permitted average limits specified above by more than 20 dB under any condition of modulation. So, only the peak values are measured.
3) The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:
Final Test Level =Receiver Reading -Correct Factor

Correct Factor = Preamplifier Factor– Antenna Factor–Cable Factor

Appendix K): Radiated Spurious Emissions

Receiver Setup:

Frequency	Detector	RBW	VBW	Remark
0.009MHz-0.090MHz	Peak	10kHz	30kHz	Peak
0.009MHz-0.090MHz	Average	10kHz	30kHz	Average
0.090MHz-0.110MHz	Quasi-peak	10kHz	30kHz	Quasi-peak
0.110MHz-0.490MHz	Peak	10kHz	30kHz	Peak
0.110MHz-0.490MHz	Average	10kHz	30kHz	Average
0.490MHz -30MHz	Quasi-peak	10kHz	30kHz	Quasi-peak
30MHz-1GHz	Quasi-peak	120kHz	300kHz	Quasi-peak
Above 1GHz	Peak	1MHz	3MHz	Peak
	Peak	1MHz	10Hz	Average

Test Procedure:

Below 1GHz test procedure as below:

a. The EUT was placed on the top of a rotating table 0.8 meters above the ground at a 3 meter semi-anechoic camber. The table was rotated 360 degrees to determine the position of the highest radiation.
b. The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.
c. The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.
d. For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters (for the test frequency of below 30MHz, the antenna was tuned to heights 1 meter) and the rotatable table was turned from 0 degrees to 360 degrees to find the maximum reading.
e. The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode.
f. If the emission level of the EUT in peak mode was 10dB lower than the limit specified, then testing could be stopped and the peak values of the EUT would be reported. Otherwise the emissions that did not have 10dB margin would be re-tested one by one using peak, quasi-peak or average method as specified and then reported in a data sheet.

Above 1GHz test procedure as below:

g. Different between above is the test site, change from Semi- Anechoic Chamber to fully Anechoic Chamber and change form table 0.8 meter to 1.5 meter(Above 18GHz the distance is 1 meter and table is 1.5 meter).
h. Test the EUT in the lowest channel ,the middle channel ,the Highest channel
i. The radiation measurements are performed in X, Y, Z axis positioning for Transmitting mode, and found the X axis positioning which it is worse case.
j. Repeat above procedures until all frequencies measured was complete.

Limit:

Frequency	Field strength (microvolt/meter)	Limit (dBμV/m)	Remark	Measurement distance (m)
0.009MHz-0.490MHz	2400/F(kHz)	-	-	300
0.490MHz-1.705MHz	24000/F(kHz)	-	-	30
1.705MHz-30MHz	30	-	-	30
30MHz-88MHz	100	40.0	Quasi-peak	3
88MHz-216MHz	150	43.5	Quasi-peak	3
216MHz-960MHz	200	46.0	Quasi-peak	3
960MHz-1GHz	500	54.0	Quasi-peak	3
Above 1GHz	500	54.0	Average	3

Note: 15.35(b), Unless otherwise specified, the limit on peak radio frequency emissions is 20dB above the maximum permitted average emission limit applicable to the equipment under test. This peak limit applies to the total peak emission level radiated by the device.

Radiated Spurious Emissions test Data:
Radiated Emission below 1GHz

Mode:		GFSK Transmitting					Channel:		2402		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	36.6937	11.24	0.67	-32.11	39.70	19.50	40.00	20.50	Pass	H	PK
2	55.3195	12.35	0.84	-32.07	34.05	15.17	40.00	24.83	Pass	H	PK
3	165.0375	8.18	1.50	-31.97	36.30	14.01	43.50	29.49	Pass	H	PK
4	208.8859	11.13	1.71	-31.94	40.11	21.01	43.50	22.49	Pass	H	PK
5	687.5318	19.70	3.14	-32.06	38.55	29.33	46.00	16.67	Pass	H	PK
6	892.9983	22.02	3.59	-31.62	43.25	37.24	46.00	8.76	Pass	H	PK
7	54.8345	12.43	0.84	-32.09	40.14	21.32	40.00	18.68	Pass	V	PK
8	120.0250	9.20	1.30	-32.07	35.85	14.28	43.50	29.22	Pass	V	PK
9	208.8859	11.13	1.71	-31.94	49.28	30.18	43.50	13.32	Pass	V	PK
10	439.9630	16.04	2.48	-31.88	31.47	18.11	46.00	27.89	Pass	V	PK
11	649.9890	19.40	3.10	-32.07	37.97	28.40	46.00	17.60	Pass	V	PK
12	875.0515	21.80	3.55	-31.70	36.40	30.05	46.00	15.95	Pass	V	PK

Mode:		GFSK Transmitting					Channel:		2441		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	36.6937	11.24	0.67	-32.11	39.61	19.41	40.00	20.59	Pass	H	PK
2	54.6405	12.46	0.84	-32.09	31.48	12.69	40.00	27.31	Pass	H	PK
3	208.8859	11.13	1.71	-31.94	39.40	20.30	43.50	23.20	Pass	H	PK
4	334.8045	13.97	2.18	-31.80	35.44	19.79	46.00	26.21	Pass	H	PK
5	687.5318	19.70	3.14	-32.06	37.37	28.15	46.00	17.85	Pass	H	PK
6	875.0515	21.80	3.55	-31.70	37.13	30.78	46.00	15.22	Pass	H	PK
7	36.8877	11.30	0.68	-32.11	39.02	18.89	40.00	21.11	Pass	V	PK
8	54.6405	12.46	0.84	-32.09	41.00	22.21	40.00	17.79	Pass	V	PK
9	208.8859	11.13	1.71	-31.94	49.49	30.39	43.50	13.11	Pass	V	PK
10	337.9088	14.03	2.19	-31.81	30.99	15.40	46.00	30.60	Pass	V	PK
11	649.9890	19.40	3.10	-32.07	37.61	28.04	46.00	17.96	Pass	V	PK
12	898.0428	22.08	3.60	-31.60	40.82	34.90	46.00	11.10	Pass	V	PK

Mode:		GFSK Transmitting					Channel:		2480		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	36.6937	11.24	0.67	-32.11	39.87	19.67	40.00	20.33	Pass	H	PK
2	56.5807	12.15	0.86	-32.07	33.07	14.01	40.00	25.99	Pass	H	PK
3	123.0323	8.75	1.31	-32.06	34.55	12.55	43.50	30.95	Pass	H	PK
4	208.8859	11.13	1.71	-31.94	39.07	19.97	43.50	23.53	Pass	H	PK
5	649.9890	19.40	3.10	-32.07	38.47	28.90	46.00	17.10	Pass	H	PK
6	874.4694	21.79	3.54	-31.70	37.02	30.65	46.00	15.35	Pass	H	PK
7	37.6638	11.55	0.69	-32.11	40.06	20.19	40.00	19.81	Pass	V	PK
8	55.2225	12.36	0.84	-32.07	41.34	22.47	40.00	17.53	Pass	V	PK
9	159.7020	7.89	1.47	-31.98	40.66	18.04	43.50	25.46	Pass	V	PK
10	208.8859	11.13	1.71	-31.94	49.77	30.67	43.50	12.83	Pass	V	PK
11	649.9890	19.40	3.10	-32.07	38.97	29.40	46.00	16.60	Pass	V	PK
12	892.9013	22.01	3.59	-31.61	41.80	35.79	46.00	10.21	Pass	V	PK

Mode:		π/4DQPSK Transmitting					Channel:		2402		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	36.6937	11.24	0.67	-32.11	40.10	19.90	40.00	20.10	Pass	H	PK
2	44.5515	13.12	0.75	-32.12	33.92	15.67	40.00	24.33	Pass	H	PK
3	208.8859	11.13	1.71	-31.94	40.01	20.91	43.50	22.59	Pass	H	PK
4	270.0020	12.60	1.96	-31.88	35.68	18.36	46.00	27.64	Pass	H	PK
5	687.5318	19.70	3.14	-32.06	37.17	27.95	46.00	18.05	Pass	H	PK
6	908.0348	22.15	3.60	-31.50	37.49	31.74	46.00	14.26	Pass	H	PK
7	36.6937	11.24	0.67	-32.11	39.91	19.71	40.00	20.29	Pass	V	PK
8	54.5435	12.47	0.84	-32.08	40.57	21.80	40.00	18.20	Pass	V	PK
9	71.9082	8.64	0.97	-32.05	40.31	17.87	40.00	22.13	Pass	V	PK
10	208.8859	11.13	1.71	-31.94	49.78	30.68	43.50	12.82	Pass	V	PK
11	649.9890	19.40	3.10	-32.07	37.14	27.57	46.00	18.43	Pass	V	PK
12	896.0056	22.05	3.59	-31.59	38.72	32.77	46.00	13.23	Pass	V	PK

Mode:		π/4DQPSK Transmitting					Channel:		2441		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	36.6937	11.24	0.67	-32.11	39.53	19.33	40.00	20.67	Pass	H	PK
2	124.4874	8.53	1.31	-32.05	34.64	12.43	43.50	31.07	Pass	H	PK
3	208.8859	11.13	1.71	-31.94	39.70	20.60	43.50	22.90	Pass	H	PK
4	649.9890	19.40	3.10	-32.07	37.55	27.98	46.00	18.02	Pass	H	PK
5	687.5318	19.70	3.14	-32.06	37.28	28.06	46.00	17.94	Pass	H	PK
6	906.3856	22.14	3.60	-31.52	45.43	39.65	46.00	6.35	Pass	H	PK
7	36.7907	11.27	0.68	-32.12	39.88	19.71	40.00	20.29	Pass	V	PK
8	54.5435	12.47	0.84	-32.08	40.40	21.63	40.00	18.37	Pass	V	PK
9	163.0973	8.07	1.49	-31.97	40.26	17.85	43.50	25.65	Pass	V	PK
10	208.8859	11.13	1.71	-31.94	49.58	30.48	43.50	13.02	Pass	V	PK
11	649.9890	19.40	3.10	-32.07	36.91	27.34	46.00	18.66	Pass	V	PK
12	875.0515	21.80	3.55	-31.70	36.31	29.96	46.00	16.04	Pass	V	PK

Mode:		π/4DQPSK Transmitting					Channel:		2480		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	36.6937	11.24	0.67	-32.11	39.80	19.60	40.00	20.40	Pass	H	PK
2	44.5515	13.12	0.75	-32.12	35.21	16.96	40.00	23.04	Pass	H	PK
3	208.8859	11.13	1.71	-31.94	39.90	20.80	43.50	22.70	Pass	H	PK
4	584.9925	18.70	2.91	-31.95	34.54	24.20	46.00	21.80	Pass	H	PK
5	687.5318	19.70	3.14	-32.06	37.47	28.25	46.00	17.75	Pass	H	PK
6	875.0515	21.80	3.55	-31.70	37.36	31.01	46.00	14.99	Pass	H	PK
7	36.6937	11.24	0.67	-32.11	39.82	19.62	40.00	20.38	Pass	V	PK
8	55.0285	12.40	0.84	-32.08	40.34	21.50	40.00	18.50	Pass	V	PK
9	169.0149	8.40	1.52	-31.96	39.90	17.86	43.50	25.64	Pass	V	PK
10	208.8859	11.13	1.71	-31.94	49.67	30.57	43.50	12.93	Pass	V	PK
11	649.9890	19.40	3.10	-32.07	36.17	26.60	46.00	19.40	Pass	V	PK
12	896.0056	22.05	3.59	-31.59	46.16	40.21	46.00	5.79	Pass	V	PK

Mode:		8DPSK Transmitting					Channel:		2402		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	36.6937	11.24	0.67	-32.11	40.99	20.79	40.00	19.21	Pass	H	PK
2	57.9388	11.93	0.88	-32.06	31.25	12.00	40.00	28.00	Pass	H	PK
3	165.6196	8.21	1.50	-31.97	36.87	14.61	43.50	28.89	Pass	H	PK
4	208.8859	11.13	1.71	-31.94	39.24	20.14	43.50	23.36	Pass	H	PK
5	687.5318	19.70	3.14	-32.06	37.44	28.22	46.00	17.78	Pass	H	PK
6	875.1485	21.80	3.55	-31.70	37.04	30.69	46.00	15.31	Pass	H	PK
7	37.6638	11.55	0.69	-32.11	38.91	19.04	40.00	20.96	Pass	V	PK
8	54.3494	12.50	0.83	-32.08	41.84	23.09	40.00	16.91	Pass	V	PK
9	163.0003	8.07	1.49	-31.98	39.48	17.06	43.50	26.44	Pass	V	PK
10	208.8859	11.13	1.71	-31.94	49.85	30.75	43.50	12.75	Pass	V	PK
11	649.9890	19.40	3.10	-32.07	36.99	27.42	46.00	18.58	Pass	V	PK
12	875.0515	21.80	3.55	-31.70	35.86	29.51	46.00	16.49	Pass	V	PK

Mode:		8DPSK Transmitting					Channel:		2441		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	36.6937	11.24	0.67	-32.11	40.45	20.25	40.00	19.75	Pass	H	PK
2	54.6405	12.46	0.84	-32.09	32.16	13.37	40.00	26.63	Pass	H	PK
3	159.7020	7.89	1.47	-31.98	35.70	13.08	43.50	30.42	Pass	H	PK
4	208.8859	11.13	1.71	-31.94	40.51	21.41	43.50	22.09	Pass	H	PK
5	649.9890	19.40	3.10	-32.07	38.00	28.43	46.00	17.57	Pass	H	PK
6	875.0515	21.80	3.55	-31.70	35.61	29.26	46.00	16.74	Pass	H	PK
7	37.2757	11.43	0.68	-32.11	40.62	20.62	40.00	19.38	Pass	V	PK
8	54.7375	12.44	0.84	-32.08	41.10	22.30	40.00	17.70	Pass	V	PK
9	166.2016	8.24	1.51	-31.97	41.26	19.04	43.50	24.46	Pass	V	PK
10	208.8859	11.13	1.71	-31.94	49.46	30.36	43.50	13.14	Pass	V	PK
11	649.9890	19.40	3.10	-32.07	36.91	27.34	46.00	18.66	Pass	V	PK
12	896.1026	22.05	3.59	-31.59	39.20	33.25	46.00	12.75	Pass	V	PK

Mode:		8DPSK Transmitting					Channel:		2480		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	36.6937	11.24	0.67	-32.11	39.01	18.81	40.00	21.19	Pass	H	PK
2	123.1293	8.73	1.31	-32.05	34.19	12.18	43.50	31.32	Pass	H	PK
3	208.8859	11.13	1.71	-31.94	40.31	21.21	43.50	22.29	Pass	H	PK
4	649.9890	19.40	3.10	-32.07	38.04	28.47	46.00	17.53	Pass	H	PK
5	687.5318	19.70	3.14	-32.06	37.53	28.31	46.00	17.69	Pass	H	PK
6	907.9378	22.15	3.60	-31.50	37.50	31.75	46.00	14.25	Pass	H	PK
7	37.5668	11.52	0.69	-32.12	42.55	22.64	40.00	17.36	Pass	V	PK
8	54.2524	12.52	0.83	-32.08	40.09	21.36	40.00	18.64	Pass	V	PK
9	163.2913	8.08	1.49	-31.97	39.31	16.91	43.50	26.59	Pass	V	PK
10	208.8859	11.13	1.71	-31.94	49.66	30.56	43.50	12.94	Pass	V	PK
11	649.9890	19.40	3.10	-32.07	36.87	27.30	46.00	18.70	Pass	V	PK
12	896.0056	22.05	3.59	-31.59	40.73	34.78	46.00	11.22	Pass	V	PK

Transmitter Emission above 1GHz

Mode:		GFSK Transmitting					Channel:		2402		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	2862.7863	32.98	4.27	-42.20	50.69	45.74	74.00	28.26	Pass	H	PK
2	4804.0000	34.50	4.55	-40.66	47.03	45.42	74.00	28.58	Pass	H	PK
3	7206.0000	36.31	5.81	-41.02	44.94	46.04	74.00	27.96	Pass	H	PK
4	9608.0000	37.64	6.63	-40.76	41.95	45.46	74.00	28.54	Pass	H	PK
5	12010.0000	39.31	7.60	-41.21	42.60	48.30	74.00	25.70	Pass	H	PK
6	14310.7541	40.01	8.62	-41.89	46.59	53.33	74.00	20.67	Pass	H	PK
7	3186.0124	33.27	4.63	-42.01	51.24	47.13	74.00	26.87	Pass	V	PK
8	4804.0000	34.50	4.55	-40.66	45.86	44.25	74.00	29.75	Pass	V	PK
9	7206.0000	36.31	5.81	-41.02	44.73	45.83	74.00	28.17	Pass	V	PK
10	9608.0000	37.64	6.63	-40.76	44.11	47.62	74.00	26.38	Pass	V	PK
11	12010.0000	39.31	7.60	-41.21	43.11	48.81	74.00	25.19	Pass	V	PK
12	14318.7546	40.02	8.62	-41.90	45.63	52.37	74.00	21.63	Pass	V	PK

Mode:		GFSK Transmitting					Channel:		2441		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	3000.0000	33.20	4.93	-42.12	50.28	46.29	74.00	27.71	Pass	H	PK
2	4882.0000	34.50	4.81	-40.60	44.58	43.29	74.00	30.71	Pass	H	PK
3	7323.0000	36.42	5.85	-40.92	43.38	44.73	74.00	29.27	Pass	H	PK
4	9764.0000	37.71	6.71	-40.62	40.93	44.73	74.00	29.27	Pass	H	PK
5	12205.0000	39.42	7.67	-41.16	42.96	48.89	74.00	25.11	Pass	H	PK
6	14928.7953	40.37	9.12	-42.31	46.31	53.49	74.00	20.51	Pass	H	PK
7	2789.7790	32.86	4.22	-42.23	53.87	48.72	74.00	25.28	Pass	V	PK
8	4882.0000	34.50	4.81	-40.60	45.02	43.73	74.00	30.27	Pass	V	PK
9	7323.0000	36.42	5.85	-40.92	44.34	45.69	74.00	28.31	Pass	V	PK
10	9764.0000	37.71	6.71	-40.62	41.96	45.76	74.00	28.24	Pass	V	PK
11	12205.0000	39.42	7.67	-41.16	42.76	48.69	74.00	25.31	Pass	V	PK
12	14875.7917	40.35	9.15	-42.30	45.32	52.52	74.00	21.48	Pass	V	PK

Mode:		GFSK Transmitting					Channel:		2480		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	3567.0378	33.45	4.41	-41.68	49.88	46.06	74.00	27.94	Pass	H	PK
2	4960.0000	34.50	4.82	-40.53	45.30	44.09	74.00	29.91	Pass	H	PK
3	7440.0000	36.54	5.85	-40.82	43.57	45.14	74.00	28.86	Pass	H	PK
4	9920.0000	37.77	6.79	-40.48	42.74	46.82	74.00	27.18	Pass	H	PK
5	12400.0000	39.54	7.86	-41.12	42.74	49.02	74.00	24.98	Pass	H	PK
6	15542.8362	40.99	9.50	-43.03	45.75	53.21	74.00	20.79	Pass	H	PK
7	3000.0000	33.20	4.93	-42.12	48.35	44.36	74.00	29.64	Pass	V	PK
8	4960.0000	34.50	4.82	-40.53	46.00	44.79	74.00	29.21	Pass	V	PK
9	7440.0000	36.54	5.85	-40.82	43.43	45.00	74.00	29.00	Pass	V	PK
10	9920.0000	37.77	6.79	-40.48	41.72	45.80	74.00	28.20	Pass	V	PK
11	12400.0000	39.54	7.86	-41.12	44.85	51.13	74.00	22.87	Pass	V	PK
12	14888.7926	40.36	9.17	-42.31	45.73	52.95	74.00	21.05	Pass	V	PK

Mode:		π/4DQPSK Transmitting					Channel:		2402		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	3186.0124	33.27	4.63	-42.01	49.72	45.61	74.00	28.39	Pass	H	PK
2	4804.0000	34.50	4.55	-40.66	42.50	40.89	74.00	33.11	Pass	H	PK
3	7206.0000	36.31	5.81	-41.02	43.48	44.58	74.00	29.42	Pass	H	PK
4	9608.0000	37.64	6.63	-40.76	42.32	45.83	74.00	28.17	Pass	H	PK
5	12010.0000	39.31	7.60	-41.21	42.67	48.37	74.00	25.63	Pass	H	PK
6	14231.7488	39.93	8.61	-41.73	46.25	53.06	74.00	20.94	Pass	H	PK
7	2389.5390	32.25	3.90	-42.44	55.57	49.28	74.00	24.72	Pass	V	PK
8	4804.0000	34.50	4.55	-40.66	42.64	41.03	74.00	32.97	Pass	V	PK
9	7206.0000	36.31	5.81	-41.02	43.08	44.18	74.00	29.82	Pass	V	PK
10	9608.0000	37.64	6.63	-40.76	42.91	46.42	74.00	27.58	Pass	V	PK
11	12010.0000	39.31	7.60	-41.21	42.56	48.26	74.00	25.74	Pass	V	PK
12	14222.7482	39.92	8.62	-41.71	45.80	52.63	74.00	21.37	Pass	V	PK

Mode:		π/4DQPSK Transmitting					Channel:		2441		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	2913.7914	33.06	4.39	-42.17	50.60	45.88	74.00	28.12	Pass	H	PK
2	4882.0000	34.50	4.81	-40.60	42.46	41.17	74.00	32.83	Pass	H	PK
3	7323.0000	36.42	5.85	-40.92	43.27	44.62	74.00	29.38	Pass	H	PK
4	9764.0000	37.71	6.71	-40.62	41.17	44.97	74.00	29.03	Pass	H	PK
5	12205.0000	39.42	7.67	-41.16	43.09	49.02	74.00	24.98	Pass	H	PK
6	14932.7955	40.37	9.10	-42.30	45.77	52.94	74.00	21.06	Pass	H	PK
7	3588.0392	33.47	4.36	-41.63	49.20	45.40	74.00	28.60	Pass	V	PK
8	4882.0000	34.50	4.81	-40.60	43.56	42.27	74.00	31.73	Pass	V	PK
9	7323.0000	36.42	5.85	-40.92	43.08	44.43	74.00	29.57	Pass	V	PK
10	9764.0000	37.71	6.71	-40.62	40.94	44.74	74.00	29.26	Pass	V	PK
11	12205.0000	39.42	7.67	-41.16	42.59	48.52	74.00	25.48	Pass	V	PK
12	14349.7567	40.05	8.63	-41.97	45.63	52.34	74.00	21.66	Pass	V	PK

Mode:		π/4DQPSK Transmitting					Channel:		2480		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	3268.0179	33.31	4.50	-41.97	49.41	45.25	74.00	28.75	Pass	H	PK
2	4960.0000	34.50	4.82	-40.53	43.62	42.41	74.00	31.59	Pass	H	PK
3	7440.0000	36.54	5.85	-40.82	42.29	43.86	74.00	30.14	Pass	H	PK
4	9920.0000	37.77	6.79	-40.48	43.48	47.56	74.00	26.44	Pass	H	PK
5	12400.0000	39.54	7.86	-41.12	42.81	49.09	74.00	24.91	Pass	H	PK
6	15481.8321	40.88	9.17	-42.97	45.71	52.79	74.00	21.21	Pass	H	PK
7	3195.0130	33.28	4.64	-42.00	51.13	47.05	74.00	26.95	Pass	V	PK
8	4960.0000	34.50	4.82	-40.53	42.99	41.78	74.00	32.22	Pass	V	PK
9	7440.0000	36.54	5.85	-40.82	42.47	44.04	74.00	29.96	Pass	V	PK
10	9920.0000	37.77	6.79	-40.48	42.50	46.58	74.00	27.42	Pass	V	PK
11	12400.0000	39.54	7.86	-41.12	44.04	50.32	74.00	23.68	Pass	V	PK
12	15385.8257	40.79	9.40	-42.84	45.58	52.93	74.00	21.07	Pass	V	PK

Mode:		8DPSK Transmitting					Channel:		2402		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	3036.0024	33.21	4.86	-42.10	50.19	46.16	74.00	27.84	Pass	H	PK
2	4804.0000	34.50	4.55	-40.66	42.61	41.00	74.00	33.00	Pass	H	PK
3	7206.0000	36.31	5.81	-41.02	43.82	44.92	74.00	29.08	Pass	H	PK
4	9608.0000	37.64	6.63	-40.76	42.24	45.75	74.00	28.25	Pass	H	PK
5	12010.0000	39.31	7.60	-41.21	42.64	48.34	74.00	25.66	Pass	H	PK
6	13606.7071	39.46	8.16	-41.19	46.87	53.30	74.00	20.70	Pass	H	PK
7	3015.0010	33.21	4.90	-42.12	50.56	46.55	74.00	27.45	Pass	V	PK
8	4804.0000	34.50	4.55	-40.66	44.07	42.46	74.00	31.54	Pass	V	PK
9	7206.0000	36.31	5.81	-41.02	42.44	43.54	74.00	30.46	Pass	V	PK
10	9608.0000	37.64	6.63	-40.76	41.64	45.15	74.00	28.85	Pass	V	PK
11	12010.0000	39.31	7.60	-41.21	43.15	48.85	74.00	25.15	Pass	V	PK
12	14964.7977	40.39	9.05	-42.32	45.98	53.10	74.00	20.90	Pass	V	PK

Mode:		8DPSK Transmitting					Channel:		2441		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	2917.1917	33.07	4.39	-42.17	51.12	46.41	74.00	27.59	Pass	H	PK
2	4882.0000	34.50	4.81	-40.60	42.76	41.47	74.00	32.53	Pass	H	PK
3	7323.0000	36.42	5.85	-40.92	43.64	44.99	74.00	29.01	Pass	H	PK
4	9764.0000	37.71	6.71	-40.62	42.95	46.75	74.00	27.25	Pass	H	PK
5	12205.0000	39.42	7.67	-41.16	43.28	49.21	74.00	24.79	Pass	H	PK
6	14399.7600	40.10	8.68	-42.06	45.92	52.64	74.00	21.36	Pass	H	PK
7	3193.0129	33.28	4.64	-42.01	50.94	46.85	74.00	27.15	Pass	V	PK
8	4882.0000	34.50	4.81	-40.60	42.59	41.30	74.00	32.70	Pass	V	PK
9	7323.0000	36.42	5.85	-40.92	43.06	44.41	74.00	29.59	Pass	V	PK
10	9764.0000	37.71	6.71	-40.62	40.80	44.60	74.00	29.40	Pass	V	PK
11	12205.0000	39.42	7.67	-41.16	42.84	48.77	74.00	25.23	Pass	V	PK
12	15309.8207	40.71	9.60	-42.74	45.72	53.29	74.00	20.71	Pass	V	PK

Mode:		8DPSK Transmitting					Channel:		2480		
NO	Freq. [MHz]	Ant Factor [dB]	Cable loss [dB]	Pream gain [dB]	Reading [dBμV]	Level [dBμV/m]	Limit [dBμV/m]	Margin [dB]	Result	Polarity	Remark
1	2994.3994	33.19	4.53	-42.12	54.64	50.24	74.00	23.76	Pass	H	PK
2	4960.0000	34.50	4.82	-40.53	48.38	47.17	74.00	26.83	Pass	H	PK
3	7440.0000	36.54	5.85	-40.82	51.18	52.75	74.00	21.25	Pass	H	PK
4	9920.0000	37.77	6.79	-40.48	41.68	45.76	74.00	28.24	Pass	H	PK
5	12400.0000	39.54	7.86	-41.12	43.69	49.97	74.00	24.03	Pass	H	PK
6	15915.8611	41.73	10.16	-43.30	45.22	53.81	74.00	20.19	Pass	H	PK
7	2997.9998	33.20	4.54	-42.12	56.66	52.28	74.00	21.72	Pass	V	PK
8	4960.0000	34.50	4.82	-40.53	47.79	46.58	74.00	27.42	Pass	V	PK
9	7440.0000	36.54	5.85	-40.82	53.08	54.65	74.00	19.35	Pass	V	PK
10	9920.0000	37.77	6.79	-40.48	41.58	45.66	74.00	28.34	Pass	V	PK
11	12400.0000	39.54	7.86	-41.12	43.83	50.11	74.00	23.89	Pass	V	PK
12	14326.7551	40.03	8.63	-41.93	47.09	53.82	74.00	20.18	Pass	V	PK

Note:

1) Through Pre-scan transmitter mode with all kind of modulation and all kind of data type, find the 1-DH5 of data type is the worse case of GFSK modulation type, the 2-DH5 of data type is the worse case of π/4DQPSK modulation type, he 3-DH5 of data type is the worse case of 8DPSKmodulation type in transmitter mode.

2) As shown in this section, for frequencies above 1GHz, the field strength limits are based on average limits. H owever, the peak field strength of any emission shall not exceed the maximum permitted average limits specifie d above by more than 20 dB under any condition of modulation. So, only the peak values are measured.

3) The field strength is calculated by adding the Antenna Factor, Cable Factor & Preamplifier. The basic equation with a sample calculation is as follows:

Final Test Level =Receiver Reading -Correct Factor

Correct Factor = Preamplifier Factor– Antenna Factor–Cable Factor

4) Scan from 9kHz to 25GHz, the disturbance above 15GHz and below 30MHz was very low, and the above harmonics were the highest point could be found when testing, so only the above harmonics had been displayed. The amplitude of spurious emissions from the radiator which are attenuated more than 20dB below the limit need not be reported.