

1. RF Exposure Requirements

1.1 General Information

Client Information

Applicant:	FERMAX ELECTRONICA, S.A.U.
Address of applicant:	AV. TRES CRUCES, 133, VALENCIA 46017, Spain
Manufacturer:	FERMAX ELECTRONICA, S.A.U.
Address of manufacturer:	AV. TRES CRUCES, 133, VALENCIA 46017, Spain

General Description of EUT:

Product Name:	1/W MILO VIDEO PANEL WITH PROX MEET POE
Trade Name:	FERMAX
Model No.:	9534
Adding Model(s):	9533, 9535, 953303, 953403
Rated Voltage:	DC12V
Power Adapter Model:	/
FCC ID:	2ATDU-F09534
Equipment Type:	Fixed device

Technical Characteristics of EUT:

Support Standards:	NFC
Frequency Range:	13.56MHz
Max. Field Strength:	44.09dBuV/m (at 3m)
Antenna Type:	Coil Antenna
Antenna Gain	0dBi

1.2 RF Exposure Exemption

According to §1.1307(b)(3) and KDB 447498 D04 Interim General RF Exposure Guidance v01, system operating under the provisions of this section shall be operating in a manner that the public is not exposed to radio frequency energy level in excess limit for maximum permissible exposure.

Option A: FCC Rule Part 1.1307 (b)(3)(i)(A): The available maximum time-averaged power is no more than 1mW, regardless of separation distance.

Option B: FCC Rule Part 1.1307 (b)(3)(i)(B): The available maximum time-averaged power or effective radiated power (ERP), whichever is greater, is less than or equal to the threshold P_{th} (mW) described in the following formula. P_{th} is given by:

$$P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}} (d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases}$$

Where

$$x = -\log_{10} \left(\frac{60}{ERP_{20 \text{ cm}} \sqrt{f}} \right) \text{ and } f \text{ is in GHz;}$$

and

$$ERP_{20 \text{ cm}} \text{ (mW)} = \begin{cases} 2040f & 0.3 \text{ GHz} \leq f < 1.5 \text{ GHz} \\ 3060 & 1.5 \text{ GHz} \leq f \leq 6 \text{ GHz} \end{cases}$$

d = the separation distance (cm);

Option C: FCC Rule Part 1.1307 (b)(3)(i)(C): The minimum separation distance (R in meters) from the body of a nearby person for the frequency (f in MHz) at which the source operates, the ERP (watts) is no more than the calculated value prescribed for that frequency. R must be at least $\lambda/2\pi$, where λ is the free-space operating wavelength in meters.

Single RF Sources Subject to Routine Environmental Evaluation	
RF Source frequency (MHz)	Threshold ERP (watts)
0.3-1.34	$1,920 R^2$
1.34-30	$3,450 R^2/f^2$
30-300	$3.83 R^2$
300-1,500	$0.0128 R^2 f$
1,500-100,000	$19.2 R^2$

For Multiple RF sources: FCC Rule Part 1.1307(b)(3)(ii):

- (A) The available maximum time-averaged power of each source is no more than 1 mW and there is a separation distance of two centimeters between any portion of a radiating structure operating and the nearest portion of any other radiating structure in the same device, except if the sum of multiple sources is less than 1 mW during the time-averaging period, in which case they may be treated as a single source (separation is not required).
- (B) In the case of fixed RF sources operating in the same time-averaging period, or of multiple mobile or portable RF sources within a device operating in the same time averaging period, if the sum of the fractional contributions to the applicable thresholds is less than or equal to 1 as indicated in the following equation.

$$\sum_{i=1}^a \frac{P_i}{P_{th,i}} + \sum_{j=1}^b \frac{ERP_j}{ERP_{th,j}} + \sum_{k=1}^c \frac{Evaluated_k}{Exposure Limit_k} \leq 1$$

1.3 Calculated Result

Radio Access Technology	Prediction Frequency (MHz)	Max. Field Strength (dBuV/m)	Antenna Gain (dBi)	Output Power (dBm)	Tune-Up Power (dBm)	ERP (dBm)
NFC	13.56	44.09	0	-51.17	-51.00	-53.15

Frequency (MHz)	Option	Min. Distance (cm)	Max. Power (dBm)	Max. Power (mW)	Exposure Limit (mW)	Ratio	Result Pass/Fail
13.56	B	20	-51.00	0.00	27.66	0.1	Pass

Note: 1. $EIRP = E - 104.8 + 20 \log D$; Output Power = EIRP - Antenna Gain;

$ERP = EIRP - 2.15 \text{ dB}$

2. Option A, B and C refers as clause 1.2.

3. For option B, Max (time-averaged power, effective radiated power (ERP)) converts to Max. Power.

For option C, ERP converts to Max. Power;

4. For option B, P_{th} (mW) converts to Exposure Limit (mW); For option C, ERP (W) converts to Exposure Limit (mW).

5. Ratio = Tune-Up ERP (mW) / Exposure Limit (mW)

Mode for Simultaneous Multi-band Transmission:

Radio Access Technology	Ratio 1	Ratio 2	Ratio 3	Simultaneous Ratio	Limit	Result Pass/Fail
/	/	/	/	/	/	/

Result: Pass