

**RF EXPOSURE EVALUATION METHOD****FCC ID: 2ATI7STK-I5****SAR Test Exclusion Thresholds for 100 MHz - 6 GHz and ≤ 50 mm**

Approximate SAR Test Exclusion Power Thresholds at Selected Frequencies and Test Separation Distances are illustrated in the following Table.

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances ≤ 50 mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0$ for 1-g SAR and ≤ 7.5 for 10-g extremity SAR, where $f(\text{GHz})$ is the RF channel transmit frequency in GHz

Power and distance are rounded to the nearest mW and mm before calculation

The result is rounded to one decimal place for comparison

The test exclusions are applicable only when the minimum test separation distance is ≤ 50 mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.

Maximum measured transmitter power.

BT Right Controller

1Mbps			
Test Channel	Frequency (MHz)	Peak Output Power (dBm)	Peak Output Power (mW)
CH00	2402	-1.444	0.717
CH39	2441	-3.026	0.498
CH78	2480	-4.374	0.365
2Mbps			
CH00	2402	0.966	1.249
CH39	2441	-0.756	0.840
CH78	2480	-2.159	0.608
3Mbps			
CH00	2402	1.361	1.368
CH39	2441	-0.368	0.919
CH78	2480	-1.769	0.665



BT Left Controller

1Mbps			
Test Channel	Frequency (MHz)	Peak Output Power (dBm)	Peak Output Power (mW)
CH00	2402	-1.571	0.696
CH39	2441	-3.127	0.487
CH78	2480	-4.469	0.357
2Mbps			
CH00	2402	0.839	1.213
CH39	2441	-0.815	0.829
CH78	2480	-2.233	0.598
3Mbps			
CH00	2402	1.282	1.343
CH39	2441	-0.433	0.905
CH78	2480	-1.827	0.657

Remark: The best case gain of the antenna is -1.42dBi.

-1.42dBi logarithmic terms convert to numeric result is nearly 0.72

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances ≤ 50 mm are determined by:

$$\left[\frac{\text{(max. power of channel, including tune-up tolerance, mW)}}{\text{(min. test separation distance, mm)}} \right] \cdot \left[\sqrt{f(\text{GHz})} \right]$$

BT Right Controller

Test Channel	Range	tune up max power (dBm)	[(max. power of channel, including tune-up tolerance, mW)]	(min. test separation distance, mm)]	[f(GHz)]	Result	Limit
1Mbps							
CH00	-1~-3	-1	0.794	5	2.402	0.246	3
CH39	-3~-5	-3	0.501	5	2.441	0.157	3
CH78	-3~-5	-3	0.501	5	2.480	0.158	3
2Mbps							
CH00	2~0	2	1.585	5	2.402	0.491	3
CH39	0~-2	0	1.000	5	2.441	0.312	3
CH78	-1~-3	-1	0.794	5	2.480	0.250	3
3Mbps							
CH00	2~0	2	1.585	5	2.402	0.491	3
CH39	0~-2	0	1.000	5	2.441	0.312	3
CH78	-1~-3	-1	0.794	5	2.480	0.250	3



BT Left Controller

Test Channel	Range	tune up max power (dBm)	[(max. power of channel, including tune-up tolerance, mW)	(min. test separation distance,mm)]	[f(GHz)]	Result	Limit
1Mbps							
CH00	-1~-3	-1	0.794	5	2.402	0.246	3
CH39	-3~-5	-3	0.501	5	2.441	0.157	3
CH78	-3~-5	-3	0.501	5	2.480	0.158	3
2Mbps							
CH00	2~0	2	1.585	5	2.402	0.491	3
CH39	0~-2	0	1.000	5	2.441	0.312	3
CH78	-1~-3	-1	0.794	5	2.480	0.250	3
3Mbps							
CH00	2~0	2	1.585	5	2.402	0.491	3
CH39	0~-2	0	1.000	5	2.441	0.312	3
CH78	-1~-3	-1	0.794	5	2.480	0.250	3

The test Result is less than 3.0 for 1-g SAR and ≤ 7.5 for 10-g extremity SAR.

Conclusion: No SAR is required.