

FCC Appendix RF Test Data for 5.5GWIFI

Product Name: Smart Diagnostic System

Test Model: P701

Environmental Conditions


Temperature:	23.6° C
Relative Humidity:	54.2%
ATM Pressure:	100.0 kPa
Test Engineer:	Zoey Cao
Supervised by:	Eric Wang

1 -26dB Bandwidth


Condition	Mode	Frequency (MHz)	Antenna	-26 dB Bandwidth (MHz)	Limit -26 dB Bandwidth (MHz)	Verdict
NVNT	a	5500	Ant1	28.39	---	Pass
NVNT	a	5580	Ant1	24.091	---	Pass
NVNT	a	5700	Ant1	23.95	---	Pass
NVNT	n20	5500	Ant1	28.491	---	Pass
NVNT	n20	5580	Ant1	29.026	---	Pass
NVNT	n20	5700	Ant1	27.395	---	Pass
NVNT	n40	5510	Ant1	51.127	---	Pass
NVNT	n40	5550	Ant1	49.498	---	Pass
NVNT	n40	5670	Ant1	49.353	---	Pass
NVNT	ac20	5500	Ant1	28.322	---	Pass
NVNT	ac20	5580	Ant1	28.51	---	Pass
NVNT	ac20	5700	Ant1	28.897	---	Pass
NVNT	ac40	5510	Ant1	50.14	---	Pass
NVNT	ac40	5550	Ant1	46.596	---	Pass
NVNT	ac40	5670	Ant1	47.459	---	Pass
NVNT	ac80	5530	Ant1	84.677	---	Pass
NVNT	ac80	5610	Ant1	86.045	---	Pass

Test Graphs


-26dB Bandwidth NVNT a 5500MHz Ant1




-26dB Bandwidth NVNT a 5580MHz Ant1




-26dB Bandwidth NVNT a 5700MHz Ant1




-26dB Bandwidth NVNT n20 5500MHz Ant1




-26dB Bandwidth NVNT n20 5580MHz Ant1




-26dB Bandwidth NVNT n20 5700MHz Ant1




-26dB Bandwidth NVNT n40 5510MHz Ant1




-26dB Bandwidth NVNT n40 5550MHz Ant1




-26dB Bandwidth NVNT n40 5670MHz Ant1




-26dB Bandwidth NVNT ac20 5500MHz Ant1




-26dB Bandwidth NVNT ac20 5580MHz Ant1




-26dB Bandwidth NVNT ac20 5700MHz Ant1




-26dB Bandwidth NVNT ac40 5510MHz Ant1




-26dB Bandwidth NVNT ac40 5550MHz Ant1




-26dB Bandwidth NVNT ac40 5670MHz Ant1



-26dB Bandwidth NVNT ac80 5530MHz Ant1



-26dB Bandwidth NVNT ac80 5610MHz Ant1



2 Maximum Conducted Output Power


Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Duty Factor (dB)	Total Power (dBm)	Limit (dBm)	Verdict
NVNT	a	5500	Ant1	13.91	0.24	14.15	24	Pass
NVNT	a	5580	Ant1	13.48	0.24	13.72	24	Pass
NVNT	a	5700	Ant1	13.06	0.24	13.3	24	Pass
NVNT	n20	5500	Ant1	12.34	0.12	12.46	24	Pass
NVNT	n20	5580	Ant1	12.09	0.12	12.21	24	Pass
NVNT	n20	5700	Ant1	11.6	0.12	11.72	24	Pass
NVNT	n40	5510	Ant1	12	0.24	12.24	24	Pass
NVNT	n40	5550	Ant1	11.64	0.24	11.88	24	Pass
NVNT	n40	5670	Ant1	11.48	0.24	11.72	24	Pass
NVNT	ac20	5500	Ant1	12.42	0.12	12.54	24	Pass
NVNT	ac20	5580	Ant1	12.08	0.12	12.2	24	Pass
NVNT	ac20	5700	Ant1	11.66	0.12	11.78	24	Pass
NVNT	ac40	5510	Ant1	12.02	0.24	12.26	24	Pass
NVNT	ac40	5550	Ant1	11.62	0.24	11.86	24	Pass
NVNT	ac40	5670	Ant1	11.5	0.24	11.74	24	Pass
NVNT	ac80	5530	Ant1	11.54	0.47	12.01	24	Pass
NVNT	ac80	5610	Ant1	11.45	0.47	11.92	24	Pass

3 Maximum Power Spectral Density Level


Condition	Mode	Frequency (MHz)	Antenna	Conducted PSD (dBm/MHz)	Duty Factor (dB)	Total PSD (dBm/MHz)	Limit (dBm/MHz)	Verdict
NVNT	a	5500	Ant1	3.3	0.24	3.54	11	Pass
NVNT	a	5580	Ant1	2.83	0.24	3.07	11	Pass
NVNT	a	5700	Ant1	2.58	0.24	2.82	11	Pass
NVNT	n20	5500	Ant1	1.56	0.12	1.68	11	Pass
NVNT	n20	5580	Ant1	1.3	0.12	1.42	11	Pass
NVNT	n20	5700	Ant1	0.93	0.12	1.05	11	Pass
NVNT	n40	5510	Ant1	-1.17	0.24	-0.93	11	Pass
NVNT	n40	5550	Ant1	-1.86	0.24	-1.62	11	Pass
NVNT	n40	5670	Ant1	-2.35	0.24	-2.11	11	Pass
NVNT	ac20	5500	Ant1	1.55	0.12	1.67	11	Pass
NVNT	ac20	5580	Ant1	1.33	0.12	1.45	11	Pass
NVNT	ac20	5700	Ant1	0.92	0.12	1.04	11	Pass
NVNT	ac40	5510	Ant1	-1.53	0.24	-1.29	11	Pass
NVNT	ac40	5550	Ant1	-2.07	0.24	-1.83	11	Pass
NVNT	ac40	5670	Ant1	-2.41	0.24	-2.17	11	Pass
NVNT	ac80	5530	Ant1	-4.97	0.47	-4.5	11	Pass
NVNT	ac80	5610	Ant1	-5.03	0.47	-4.56	11	Pass

Test Graphs


PSD NVNT a 5500MHz Ant1




PSD NVNT a 5580MHz Ant1




PSD NVNT a 5700MHz Ant1




PSD NVNT n20 5500MHz Ant1




PSD NVNT n20 5580MHz Ant1




PSD NVNT n20 5700MHz Ant1




PSD NVNT n40 5510MHz Ant1




PSD NVNT n40 5550MHz Ant1




PSD NVNT n40 5670MHz Ant1




PSD NVNT ac20 5500MHz Ant1




PSD NVNT ac20 5580MHz Ant1




PSD NVNT ac20 5700MHz Ant1




PSD NVNT ac40 5510MHz Ant1




PSD NVNT ac40 5550MHz Ant1




PSD NVNT ac40 5670MHz Ant1



PSD NVNT ac80 5530MHz Ant1





4 Restrict Band

Condition	Mode	Frequency (MHz)	Antenna	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	Duty Factor (dB)	E (dBuV/m)	Detector	Limit (dBuV/m)	Verdict
NVNT	a	5500	Ant1	5460	-50.27	2	-	46.96	Peak	68.2	Pass
NVNT	a	5500	Ant1	5460	-57.96	2	0.24	39.51	Average	54	Pass
NVNT	a	5500	Ant1	5470	-45.41	2	-	51.82	Peak	68.2	Pass
NVNT	a	5500	Ant1	5467.6	-56.83	2	0.24	40.64	Average	54	Pass
NVNT	a	5500	Ant1	5470	-57.63	2	0.24	39.84	Average	54	Pass
NVNT	a	5700	Ant1	5725	-42.03	2	-	55.2	Peak	68.2	Pass
NVNT	a	5700	Ant1	5725	-55.37	2	0.24	42.1	Average	54	Pass
NVNT	a	5700	Ant1	5725.4	-54.86	2	0.24	42.61	Average	54	Pass
NVNT	a	5700	Ant1	5735	-48.63	2	-	48.6	Peak	68.2	Pass
NVNT	a	5700	Ant1	5735	-57.62	2	0.24	39.85	Average	54	Pass
NVNT	n20	5500	Ant1	5460	-48.98	2	-	48.25	Peak	68.2	Pass
NVNT	n20	5500	Ant1	5460	-57.66	2	0.12	39.69	Average	54	Pass
NVNT	n20	5500	Ant1	5468.4	-41.54	2	-	55.69	Peak	68.2	Pass
NVNT	n20	5500	Ant1	5469.4	-55.89	2	0.12	41.46	Average	54	Pass
NVNT	n20	5500	Ant1	5470	-43.76	2	-	53.47	Peak	68.2	Pass
NVNT	n20	5500	Ant1	5470	-56.64	2	0.12	40.71	Average	54	Pass
NVNT	n20	5700	Ant1	5725	-41.52	2	-	55.71	Peak	68.2	Pass
NVNT	n20	5700	Ant1	5725	-53.25	2	0.12	44.1	Average	54	Pass
NVNT	n20	5700	Ant1	5725.4	-37.53	2	-	59.7	Peak	68.2	Pass
NVNT	n20	5700	Ant1	5725.6	-52.58	2	0.12	44.77	Average	54	Pass
NVNT	n20	5700	Ant1	5735	-50.95	2	-	46.28	Peak	68.2	Pass
NVNT	n20	5700	Ant1	5735	-57.44	2	0.12	39.91	Average	54	Pass
NVNT	n40	5510	Ant1	5460	-49.62	2	-	47.61	Peak	68.2	Pass
NVNT	n40	5510	Ant1	5460	-57.69	2	0.24	39.78	Average	54	Pass
NVNT	n40	5510	Ant1	5465.2	-42.37	2	-	54.86	Peak	68.2	Pass
NVNT	n40	5510	Ant1	5469.4	-56.04	2	0.24	41.43	Average	54	Pass
NVNT	n40	5510	Ant1	5470	-47.03	2	-	50.2	Peak	68.2	Pass
NVNT	n40	5510	Ant1	5470	-56.22	2	0.24	41.25	Average	54	Pass
NVNT	n40	5670	Ant1	5725	-49.59	2	-	47.64	Peak	68.2	Pass
NVNT	n40	5670	Ant1	5725	-57.78	2	0.24	39.69	Average	54	Pass
NVNT	n40	5670	Ant1	5729.4	-47.39	2	-	49.84	Peak	68.2	Pass
NVNT	n40	5670	Ant1	5727.8	-57.53	2	0.24	39.94	Average	54	Pass
NVNT	n40	5670	Ant1	5735	-49.78	2	-	47.45	Peak	68.2	Pass
NVNT	n40	5670	Ant1	5735	-58.08	2	0.24	39.39	Average	54	Pass
NVNT	ac20	5500	Ant1	5460	-49.03	2	-	48.2	Peak	68.2	Pass
NVNT	ac20	5500	Ant1	5460	-57.15	2	0.12	40.2	Average	54	Pass
NVNT	ac20	5500	Ant1	5469.6	-43.71	2	-	53.52	Peak	68.2	Pass
NVNT	ac20	5500	Ant1	5469.8	-56.14	2	0.12	41.21	Average	54	Pass
NVNT	ac20	5500	Ant1	5470	-48.25	2	-	48.98	Peak	68.2	Pass

NVNT	ac20	5500	Ant1	5470	-56.21	2	0.12	41.14	Average	54	Pass
NVNT	ac20	5700	Ant1	5725	-40.44	2	-	56.79	Peak	68.2	Pass
NVNT	ac20	5700	Ant1	5725	-54.74	2	0.12	42.61	Average	54	Pass
NVNT	ac20	5700	Ant1	5725.6	-40.18	2	-	57.05	Peak	68.2	Pass
NVNT	ac20	5700	Ant1	5725.2	-52.98	2	0.12	44.37	Average	54	Pass
NVNT	ac20	5700	Ant1	5735	-50.43	2	-	46.8	Peak	68.2	Pass
NVNT	ac20	5700	Ant1	5735	-57.18	2	0.12	40.17	Average	54	Pass
NVNT	ac40	5510	Ant1	5460	-50.61	2	-	46.62	Peak	68.2	Pass
NVNT	ac40	5510	Ant1	5460	-58.24	2	0.24	39.23	Average	54	Pass
NVNT	ac40	5510	Ant1	5469.4	-42.82	2	-	54.41	Peak	68.2	Pass
NVNT	ac40	5510	Ant1	5468	-55.87	2	0.24	41.6	Average	54	Pass
NVNT	ac40	5510	Ant1	5470	-45.95	2	-	51.28	Peak	68.2	Pass
NVNT	ac40	5510	Ant1	5470	-56.37	2	0.24	41.1	Average	54	Pass
NVNT	ac40	5670	Ant1	5725	-49.34	2	-	47.89	Peak	68.2	Pass
NVNT	ac40	5670	Ant1	5725	-57.9	2	0.24	39.57	Average	54	Pass
NVNT	ac40	5670	Ant1	5734	-48.22	2	-	49.01	Peak	68.2	Pass
NVNT	ac40	5670	Ant1	5727.2	-57.43	2	0.24	40.04	Average	54	Pass
NVNT	ac40	5670	Ant1	5735	-51.25	2	-	45.98	Peak	68.2	Pass
NVNT	ac40	5670	Ant1	5735	-57.68	2	0.24	39.79	Average	54	Pass
NVNT	ac80	5530	Ant1	5460	-48.38	2	-	48.85	Peak	68.2	Pass
NVNT	ac80	5530	Ant1	5460	-57.67	2	0.47	40.03	Average	54	Pass
NVNT	ac80	5530	Ant1	5469.8	-43.04	2	-	54.19	Peak	68.2	Pass
NVNT	ac80	5530	Ant1	5468.8	-55.65	2	0.47	42.05	Average	54	Pass
NVNT	ac80	5530	Ant1	5470	-44.92	2	-	52.31	Peak	68.2	Pass
NVNT	ac80	5530	Ant1	5470	-55.78	2	0.47	41.92	Average	54	Pass
NVNT	ac80	5610	Ant1	5725	-50.3	2	-	46.93	Peak	68.2	Pass
NVNT	ac80	5610	Ant1	5725	-58.57	2	0.47	39.13	Average	54	Pass
NVNT	ac80	5610	Ant1	5730.9	-47.95	2	-	49.28	Peak	68.2	Pass
NVNT	ac80	5610	Ant1	5726.39	-57.33	2	0.47	40.37	Average	54	Pass
NVNT	ac80	5610	Ant1	5735	-49.84	2	-	47.39	Peak	68.2	Pass
NVNT	ac80	5610	Ant1	5735	-58.26	2	0.47	39.44	Average	54	Pass

5 Frequency Stability

Condition	Mode	Frequency (MHz)	Antenna	Measured Frequency (MHz)	Frequency Error (Hz)	Deviation (ppm)	Limit (ppm)	Verdict
NVNT	a	5500	Ant1	5499.98	-20000	-3.64	25	Pass
NVNT	a	5580	Ant1	5580	0	0	25	Pass
NVNT	a	5700	Ant1	5699.98	-20000	-3.51	25	Pass
NVNT	n20	5500	Ant1	5499.98	-20000	-3.64	25	Pass
NVNT	n20	5580	Ant1	5579.98	-20000	-3.58	25	Pass
NVNT	n20	5700	Ant1	5699.98	-20000	-3.51	25	Pass
NVNT	n40	5510	Ant1	5510	0	0	25	Pass
NVNT	n40	5550	Ant1	5550	0	0	25	Pass
NVNT	n40	5670	Ant1	5670	0	0	25	Pass
NVNT	ac20	5500	Ant1	5499.98	-20000	-3.64	25	Pass
NVNT	ac20	5580	Ant1	5579.98	-20000	-3.58	25	Pass
NVNT	ac20	5700	Ant1	5700	0	0	25	Pass
NVNT	ac40	5510	Ant1	5510	0	0	25	Pass
NVNT	ac40	5550	Ant1	5550	0	0	25	Pass
NVNT	ac40	5670	Ant1	5669.96	-40000	-7.05	25	Pass
NVNT	ac80	5530	Ant1	5530	0	0	25	Pass
NVNT	ac80	5610	Ant1	5610	0	0	25	Pass

6 Duty Cycle

Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	a	5500	Ant1	94.65	0.24	0.91
NVNT	a	5580	Ant1	94.56	0.24	0.91
NVNT	a	5700	Ant1	94.65	0.24	0.91
NVNT	n20	5500	Ant1	97.33	0.12	0.44
NVNT	n20	5580	Ant1	97.29	0.12	0.44
NVNT	n20	5700	Ant1	97.33	0.12	0.44
NVNT	n40	5510	Ant1	94.71	0.24	0.9
NVNT	n40	5550	Ant1	94.71	0.24	0.9
NVNT	n40	5670	Ant1	94.71	0.24	0.9
NVNT	ac20	5500	Ant1	97.34	0.12	0.44
NVNT	ac20	5580	Ant1	97.34	0.12	0.44
NVNT	ac20	5700	Ant1	97.34	0.12	0.44
NVNT	ac40	5510	Ant1	94.72	0.24	0.9
NVNT	ac40	5550	Ant1	94.72	0.24	0.9
NVNT	ac40	5670	Ant1	94.72	0.24	0.9
NVNT	ac80	5530	Ant1	89.65	0.47	1.86
NVNT	ac80	5610	Ant1	89.65	0.47	1.86

