Appendix B

RF Test Data for 5.2G WIFI (Conducted Measurement)

Product Name: WIFI Receiver

Test Model: 600M Wireless USB Adapter

Environmental Conditions

Temperature:	23.8 ° C
Relative Humidity:	52.1%
ATM Pressure:	100.0 kPa
Test Engineer:	Nick Peng
Supervised by:	Ling Zhu

B.1 -26dB Bandwidth

Condition	Mode	Frequency (MHz)	Antenna	-26 dB Bandwidth (MHz)	Limit -26 dB Bandwidth (MHz)	Verdict
NVNT	a	5180	Ant1	20.578	>=0.5	Pass
NVNT	a	5200	Ant1	20.642	>=0.5	Pass
NVNT	a	5240	Ant1	20.73	>=0.5	Pass
NVNT	n20	5180	Ant1	21.024	>=0.5	Pass
NVNT	n20	5200	Ant1	20.922	>=0.5	Pass
NVNT	n20	5240	Ant1	21.086	>=0.5	Pass
NVNT	n40	5190	Ant1	41.977	>=0.5	Pass
NVNT	n40	5230	Ant1	42.696	>=0.5	Pass
NVNT	ac20	5180	Ant1	21.146	>=0.5	Pass
NVNT	ac20	5200	Ant1	20.855	>=0.5	Pass
NVNT	ac20	5240	Ant1	21.489	>=0.5	Pass
NVNT	ac40	5190	Ant1	42.508	>=0.5	Pass
NVNT	ac40	5230	Ant1	43.163	>=0.5	Pass
NVNT	ac80	5210	Ant1	82.169	>=0.5	Pass

Test Graphs

-26dB Bandwidth NVNT a 5180MHz Ant1



-26dB Bandwidth NVNT a 5200MHz Ant1



-26dB Bandwidth NVNT a 5240MHz Ant1



-26dB Bandwidth NVNT n20 5180MHz Ant1



-26dB Bandwidth NVNT n20 5200MHz Ant1



-26dB Bandwidth NVNT n20 5240MHz Ant1



-26dB Bandwidth NVNT n40 5190MHz Ant1



-26dB Bandwidth NVNT n40 5230MHz Ant1



-26dB Bandwidth NVNT ac20 5180MHz Ant1



-26dB Bandwidth NVNT ac20 5200MHz Ant1



-26dB Bandwidth NVNT ac20 5240MHz Ant1



-26dB Bandwidth NVNT ac40 5190MHz Ant1



-26dB Bandwidth NVNT ac40 5230MHz Ant1



-26dB Bandwidth NVNT ac80 5210MHz Ant1



B.2 Maximum Conducted Output Power

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Duty Factor (dB)	Total Power (dBm)	Limit (dBm)	Verdict
NVNT	a	5180	Ant1	11.30	0.17	11.47	24	Pass
NVNT	a	5200	Ant1	10.93	0.17	11.10	24	Pass
NVNT	a	5240	Ant1	10.86	0.17	11.03	24	Pass
NVNT	n20	5180	Ant1	11.34	0.18	11.52	24	Pass
NVNT	n20	5200	Ant1	11.22	0.18	11.40	24	Pass
NVNT	n20	5240	Ant1	11.26	0.18	11.44	24	Pass
NVNT	n40	5190	Ant1	11.33	0.35	11.68	24	Pass
NVNT	n40	5230	Ant1	11.02	0.35	11.37	24	Pass
NVNT	ac20	5180	Ant1	11.32	0.18	11.50	24	Pass
NVNT	ac20	5200	Ant1	11.52	0.18	11.70	24	Pass
NVNT	ac20	5240	Ant1	11.47	0.18	11.65	24	Pass
NVNT	ac40	5190	Ant1	11.56	0.35	11.91	24	Pass
NVNT	ac40	5230	Ant1	10.89	0.35	11.24	24	Pass
NVNT	ac80	5210	Ant1	11.18	0.67	11.85	24	Pass

B.3 Maximum Power Spectral Density Level

Condition	Mode	Frequency (MHz)	Antenna	Conducted PSD (dBm)	Duty Factor (dB)	Total PSD (dBm)	Limit (dBm)	Verdict
NVNT	a	5180	Ant1	-1.92	0.17	-1.75	11	Pass
NVNT	a	5200	Ant1	-3.13	0.17	-2.96	11	Pass
NVNT	a	5240	Ant1	-2.61	0.17	-2.44	11	Pass
NVNT	n20	5180	Ant1	-1.67	0.18	-1.49	11	Pass
NVNT	n20	5200	Ant1	-2.12	0.18	-1.94	11	Pass
NVNT	n20	5240	Ant1	-1.53	0.18	-1.35	11	Pass
NVNT	n40	5190	Ant1	-6.35	0.35	-6	11	Pass
NVNT	n40	5230	Ant1	-7.14	0.35	-6.79	11	Pass
NVNT	ac20	5180	Ant1	-2.13	0.18	-1.95	11	Pass
NVNT	ac20	5200	Ant1	-1.14	0.18	-0.96	11	Pass
NVNT	ac20	5240	Ant1	-1.72	0.18	-1.54	11	Pass
NVNT	ac40	5190	Ant1	-6.6	0.35	-6.25	11	Pass
NVNT	ac40	5230	Ant1	-6.26	0.35	-5.91	11	Pass
NVNT	ac80	5210	Ant1	-11.1	0.67	-10.43	11	Pass

Test Graphs

PSD NVNT a 5180MHz Ant1



PSD NVNT a 5200MHz Ant1



PSD NVNT a 5240MHz Ant1



PSD NVNT n20 5180MHz Ant1



PSD NVNT n20 5200MHz Ant1



PSD NVNT n20 5240MHz Ant1



PSD NVNT n40 5190MHz Ant1



PSD NVNT n40 5230MHz Ant1



PSD NVNT ac20 5180MHz Ant1



PSD NVNT ac20 5200MHz Ant1



PSD NVNT ac20 5240MHz Ant1



PSD NVNT ac40 5190MHz Ant1



PSD NVNT ac40 5230MHz Ant1



PSD NVNT ac80 5210MHz Ant1



B.4 Restrict Band

Condition	Mode	Frequency (MHz)	Antenna	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	E (dBuV/m)	Detector	Limit (dBuV/m)	Verdict
NVNT	a	5180	Ant1	4500	-49.66	2	47.57	Peak	68.2	Pass
NVNT	a	5180	Ant1	4500	-59.58	2	37.65	Average	54	Pass
NVNT	a	5180	Ant1	5141.9	-45.82	2	51.41	Peak	68.2	Pass
NVNT	a	5180	Ant1	5149.6	-56.88	2	40.35	Average	54	Pass
NVNT	a	5180	Ant1	5150	-48.72	2	48.51	Peak	68.2	Pass
NVNT	a	5180	Ant1	5150	-56.86	2	40.37	Average	54	Pass
NVNT	a	5240	Ant1	5350	-50.36	2	46.87	Peak	68.2	Pass
NVNT	a	5240	Ant1	5350	-58.74	2	38.49	Average	54	Pass
NVNT	a	5240	Ant1	5385.12	-46.27	2	50.96	Peak	68.2	Pass
NVNT	a	5240	Ant1	5353.92	-58.55	2	38.68	Average	54	Pass
NVNT	a	5240	Ant1	5460	-49.05	2	48.18	Peak	68.2	Pass
NVNT	a	5240	Ant1	5460	-59.23	2	38	Average	54	Pass
NVNT	n20	5180	Ant1	4500	-49.03	2	48.2	Peak	68.2	Pass
NVNT	n20	5180	Ant1	4500	-59.73	2	37.5	Average	54	Pass
NVNT	n20	5180	Ant1	5014.5	-45.03	2	52.2	Peak	68.2	Pass
NVNT	n20	5180	Ant1	5148.2	-56.71	2	40.52	Average	54	Pass
NVNT	n20	5180	Ant1	5150	-47.63	2	49.6	Peak	68.2	Pass
NVNT	n20	5180	Ant1	5150	-56.86	2	40.37	Average	54	Pass
NVNT	n20	5240	Ant1	5350	-50.39	2	46.84	Peak	68.2	Pass
NVNT	n20	5240	Ant1	5350	-58.72	2	38.51	Average	54	Pass
NVNT	n20	5240	Ant1	5423.28	-46.5	2	50.73	Peak	68.2	Pass
NVNT	n20	5240	Ant1	5355.36	-58.46	2	38.77	Average	54	Pass
NVNT	n20	5240	Ant1	5460	-50.51	2	46.72	Peak	68.2	Pass
NVNT	n20	5240	Ant1	5460	-59.17	2	38.06	Average	54	Pass
NVNT	n40	5190	Ant1	4500	-50.42	2	46.81	Peak	68.2	Pass
NVNT	n40	5190	Ant1	4500	-59.49	2	37.74	Average	54	Pass
NVNT	n40	5190	Ant1	5149.7	-33.53	2	63.7	Peak	68.2	Pass
NVNT	n40	5190	Ant1	5149.7	-49.72	2	47.51	Average	54	Pass
NVNT	n40	5190	Ant1	5150	-33.53	2	63.7	Peak	68.2	Pass
NVNT	n40	5190	Ant1	5150	-49.72	2	47.51	Average	54	Pass
NVNT	n40	5230	Ant1	5350	-47.88	2	49.35	Peak	68.2	Pass
NVNT	n40	5230	Ant1	5350	-58.5	2	38.73	Average	54	Pass
NVNT	n40	5230	Ant1	5425.44	-46.65	2	50.58	Peak	68.2	Pass
NVNT	n40	5230	Ant1	5356.86	-58.08	2	39.15	Average	54	Pass
NVNT	n40	5230	Ant1	5460	-48.97	2	48.26	Peak	68.2	Pass
NVNT	n40	5230	Ant1	5460	-58.51	2	38.72	Average	54	Pass
NVNT	ac20	5180	Ant1	4500	-51.34	2	45.89	Peak	68.2	Pass

NVNT	ac20	5180	Ant1	4500	-59.55	2	37.68	Average	54	Pass
NVNT	ac20	5180	Ant1	5006.8	-45.02	2	52.21	Peak	68.2	Pass
NVNT	ac20	5180	Ant1	5148.2	-56.82	2	40.41	Average	54	Pass
NVNT	ac20	5180	Ant1	5150	-47	2	50.23	Peak	68.2	Pass
NVNT	ac20	5180	Ant1	5150	-56.68	2	40.55	Average	54	Pass
NVNT	ac20	5240	Ant1	5350	-49.8	2	47.43	Peak	68.2	Pass
NVNT	ac20	5240	Ant1	5350	-58.51	2	38.72	Average	54	Pass
NVNT	ac20	5240	Ant1	5436.24	-45.53	2	51.7	Peak	68.2	Pass
NVNT	ac20	5240	Ant1	5355.84	-58.43	2	38.8	Average	54	Pass
NVNT	ac20	5240	Ant1	5460	-48.53	2	48.7	Peak	68.2	Pass
NVNT	ac20	5240	Ant1	5460	-59.19	2	38.04	Average	54	Pass
NVNT	ac40	5190	Ant1	4500	-50.23	2	47	Peak	68.2	Pass
NVNT	ac40	5190	Ant1	4500	-59.36	2	37.87	Average	54	Pass
NVNT	ac40	5190	Ant1	5149.7	-34.57	2	62.66	Peak	68.2	Pass
NVNT	ac40	5190	Ant1	5149.7	-48.36	2	48.87	Average	54	Pass
NVNT	ac40	5190	Ant1	5150	-34.57	2	62.66	Peak	68.2	Pass
NVNT	ac40	5190	Ant1	5150	-48.36	2	48.87	Average	54	Pass
NVNT	ac40	5230	Ant1	5350	-48.43	2	48.8	Peak	68.2	Pass
NVNT	ac40	5230	Ant1	5350	-58.61	2	38.62	Average	54	Pass
NVNT	ac40	5230	Ant1	5371.17	-46.66	2	50.57	Peak	68.2	Pass
NVNT	ac40	5230	Ant1	5374.95	-57.95	2	39.28	Average	54	Pass
NVNT	ac40	5230	Ant1	5460	-50.11	2	47.12	Peak	68.2	Pass
NVNT	ac40	5230	Ant1	5460	-58.9	2	38.33	Average	54	Pass
NVNT	ac80	5210	Ant1	5350	-48.4	2	48.83	Peak	68.2	Pass
NVNT	ac80	5210	Ant1	5350	-56.93	2	40.3	Average	54	Pass
NVNT	ac80	5210	Ant1	5358.03	-44.63	2	52.6	Peak	68.2	Pass
NVNT	ac80	5210	Ant1	5355.72	-56.93	2	40.3	Average	54	Pass
NVNT	ac80	5210	Ant1	5460	-48.89	2	48.34	Peak	68.2	Pass
NVNT	ac80	5210	Ant1	5460	-58.11	2	39.12	Average	54	Pass
NVNT	ac80	5210	Ant1	4500	-49.95	2	47.28	Peak	68.2	Pass
NVNT	ac80	5210	Ant1	4500	-59.15	2	38.08	Average	54	Pass
NVNT	ac80	5210	Ant1	5122.52	-31.1	2	66.13	Peak	68.2	Pass
NVNT	ac80	5210	Ant1	5149.38	-43.68	2	53.55	Average	54	Pass
NVNT	ac80	5210	Ant1	5150	-34.63	2	62.6	Peak	68.2	Pass
NVNT	ac80	5210	Ant1	5150	-44	2	53.23	Average	54	Pass

Test Graphs

Restrict Band NVNT a 5180MHz Ant1 Peak



Restrict Band NVNT a 5180MHz Ant1 Average



Restrict Band NVNT a 5240MHz Ant1 Peak



Restrict Band NVNT a 5240MHz Ant1 Average



Restrict Band NVNT n20 5180MHz Ant1 Peak



Restrict Band NVNT n20 5180MHz Ant1 Average



Restrict Band NVNT n20 5240MHz Ant1 Peak



Restrict Band NVNT n20 5240MHz Ant1 Average



Restrict Band NVNT n40 5190MHz Ant1 Peak



Restrict Band NVNT n40 5190MHz Ant1 Average



Restrict Band NVNT n40 5230MHz Ant1 Peak



Restrict Band NVNT n40 5230MHz Ant1 Average



Restrict Band NVNT ac20 5180MHz Ant1 Peak



Restrict Band NVNT ac20 5180MHz Ant1 Average



Restrict Band NVNT ac20 5240MHz Ant1 Peak



Restrict Band NVNT ac20 5240MHz Ant1 Average



Restrict Band NVNT ac40 5190MHz Ant1 Peak



Restrict Band NVNT ac40 5190MHz Ant1 Average



Restrict Band NVNT ac40 5230MHz Ant1 Peak



Restrict Band NVNT ac40 5230MHz Ant1 Average



Restrict Band NVNT ac80 5210MHz Ant1 Peak



Restrict Band NVNT ac80 5210MHz Ant1 Average



Restrict Band NVNT ac80 5210MHz Ant1 Peak



Restrict Band NVNT ac80 5210MHz Ant1 Average



B.5 Frequency Stability

Condition	Mode	Frequency (MHz)	Antenna	Measured Frequency (MHz)	Frequency Error (Hz)	Deviation (ppm)	Limit (ppm)	Verdict
NVNT	n40	5190	Ant1	5189.96	-40000	-7.71	25	Pass
NVNT	n40	5230	Ant1	5229.96	-40000	-7.65	25	Pass
NVNT	ac20	5180	Ant1	5179.96	-40000	-7.72	25	Pass
NVNT	ac20	5200	Ant1	5199.94	-60000	-11.54	25	Pass
NVNT	ac20	5240	Ant1	5239.96	-40000	-7.63	25	Pass
NVNT	ac40	5190	Ant1	5189.96	-40000	-7.71	25	Pass
NVNT	ac40	5230	Ant1	5229.96	-40000	-7.65	25	Pass
NVNT	ac80	5210	Ant1	5210	0	0	25	Pass

Test Graphs

Freq. Stability NVNT n40 5190MHz Ant1



Freq. Stability NVNT n40 5230MHz Ant1



Freq. Stability NVNT ac20 5180MHz Ant1



Freq. Stability NVNT ac20 5200MHz Ant1



Freq. Stability NVNT ac20 5240MHz Ant1



Freq. Stability NVNT ac40 5190MHz Ant1



Freq. Stability NVNT ac40 5230MHz Ant1



Freq. Stability NVNT ac80 5210MHz Ant1



B.6 Duty Cycle

Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	a	5180	Ant1	96.25	0.17	0.73
NVNT	a	5200	Ant1	96.25	0.17	0.73
NVNT	a	5240	Ant1	96.25	0.17	0.73
NVNT	n20	5180	Ant1	96	0.18	0.79
NVNT	n20	5200	Ant1	96	0.18	0.79
NVNT	n20	5240	Ant1	95.93	0.18	0.79
NVNT	n40	5190	Ant1	92.27	0.35	1.58
NVNT	n40	5230	Ant1	92.27	0.35	1.58
NVNT	ac20	5180	Ant1	95.99	0.18	0.78
NVNT	ac20	5200	Ant1	96.02	0.18	0.78
NVNT	ac20	5240	Ant1	96.01	0.18	0.78
NVNT	ac40	5190	Ant1	92.31	0.35	1.57
NVNT	ac40	5230	Ant1	92.31	0.35	1.57
NVNT	ac80	5210	Ant1	85.64	0.67	3.16

Test Graphs

Duty Cycle NVNT a 5180MHz Ant1



Duty Cycle NVNT a 5200MHz Ant1



Duty Cycle NVNT a 5240MHz Ant1



Duty Cycle NVNT n20 5180MHz Ant1



Duty Cycle NVNT n20 5200MHz Ant1



Duty Cycle NVNT n20 5240MHz Ant1



Duty Cycle NVNT n40 5190MHz Ant1



Duty Cycle NVNT n40 5230MHz Ant1



Duty Cycle NVNT ac20 5180MHz Ant1



Duty Cycle NVNT ac20 5200MHz Ant1



Duty Cycle NVNT ac20 5240MHz Ant1



Duty Cycle NVNT ac40 5190MHz Ant1



Duty Cycle NVNT ac40 5230MHz Ant1



Duty Cycle NVNT ac80 5210MHz Ant1