

Bluetooth headphones user manual



Product diagram

Packing list

Bluetooth headphones host

real wireless headset charging box

TYPE-C charging cable

Size earcap

instruction manual

Product specification

True wireless version: V5.4

Battery specification: earphone 3.7v ; Charging bin 3.7v

Supported mode: HFP/HSP/ A2DP/AVRCP

Sensitivity: 105dB $\pm$ 3dB S.P.L at 1KHz

Signal distance: 10 m (in an ideal environment without any large obstacles)

Playing time: about 3.5 hours

Talk time: approximately 3.5hours

Standby time: about 80 hours

Charging time: charge the charging warehouse for about 1.5hours,
and charge the headset for about 1 hour

Charging times for the headset: about 2 times

Functional instructions

1.Boot

Take the headset out of the charging bin and start it automatically or long press the left and right multi-function button of the headset for 3 seconds.

2. Shut down

Put the earphone into the charging chamber and turn it off automatically. Long press the left and right earphone multifunction keys for 5 seconds to turn it off

3. Boot back

When the pairing is successful, the bluetooth headset will first enter the state of reconnect when the second time is started and automatically reconnect the connected phone.

4. Play/pause

In standby state, click the left or right earphone multifunction button to play music directly, while click the left or right earphone multifunction button to pause playing.

5. Switch songs

When playing music, double-click the left headphone multifunction button for 2 seconds to switch to the previous track, and double-click the right headphone multifunction button for 2 seconds to switch to the next track.6. Answer incoming calls

When the phone calls, click on the multi-function key around earphones can answer the phone, earphones with voice noise reduction function, make the call more clear.

7. Call hang up

When talking on the mobile phone, you can hang up the phone by clicking the left or right earphone multifunction button.

8. Call rejection

When the phone calls, long press the left and right earphone multifunction button for 2 seconds to reject the call.

9. Redial

When you are on standby or playing music, you can make the last call in your phone record by three clicks of the left earphone multifunction button.

10. Start voice assistant

Three clicks on the right earphone multifunction button can activate apple's Siri or Google voice assistant for voice control of the phone operation.

11. Low battery alert

When the battery is low, the ear will play the warning tone until the headset is turned off.

12 . Turn on transparency and noise reduction mode

Long touch the right/left earphone multifunction button for 1.5 seconds to simultaneously activate transparency mode. The second long touch of the right/left earphone multifunction button for 1.5 seconds to simultaneously activate noise reduction mode. The third long touch of the right/left earphone multifunction button for 1.5 seconds to simultaneously activate normal mode.

Common pairing style

1. Take it out from the charging bin or press the left and right multi-function area for 3 seconds at the same time, turn it on until the indicator light flashes alternately, enter the pair-ear search matching state, enter the pair-ear automatic matching state, after the successful matching, the main ear indicator lights flash alternately, the auxiliary ear indicator lights turn off, and the pair ear matching success cue tone is played simultaneously.

2. Enable wireless capabilities on your phone or other devices. If it's an android phone or device, click the "Search for wireless devices" option on your phone. If It's an IOS phone or device, it will search for devices automatically After searching for the

model of the wireless headset, click enter the match. After the match is successful, the headset will give a notification tone that the connection is successful. The left and right headset lights will turn off and enter the connection standby mode, the right ear was the right vocal tract and the left ear was the left vocal tract.

3. The two headphones can also be paired with the mobile phone separately. The operation method can be operated according to the operation method of STEP 2 above.

Charging Operation

1. Plug the TYPE-C charging cable into the charging bin and the Charger at one end. The Charger uses a standard 5V 1A charger to charge the bin.

2. Charging the headphones: the headphones can be automatically charged into the charging bin, charging the headphone indicator light will be lit, full of electricity after the extinguishment;

Precautions

1. Please charge in a safe environment. When charging the charging bin, the charging bin should be separated from the charger as soon as possible, so as to avoid damage to the charging bin caused by charging for a long time.

2. When the music is playing, please adjust the music to the appropriate volume to avoid long-term damage to the hearing under the condition of high volume.

3. Try to avoid using the earphone where there is interference source, otherwise it may affect the earphone signal.

4. Try to avoid using the earphone in a corrosive environment, so as not to affect the function of the earphone.

Tips: when you use this bluetooth headset to listen to music or talk, please pay attention to adjust the volume, so as not to affect your listening too much!

FCC WARNING

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Note: The Grantee is not responsible for any changes or modifications not expressly approved by the party responsible for compliance. such modifications could void the user's authority to operate the equipment.

The device has been evaluated to meet general RF exposure requirement.

This equipment complies with FCC's RF radiation exposure limits set forth for an uncontrolled environment. This device and its antenna(s) must not be co-located or conjunction with any other antenna or transmitter.

The device can be used in portable exposure conditions without restriction.