美版——美国工厂

Portable Power Station

Type: Gendome Home 3000
Battery capacity: DC 51.2V, 60Ah, 3072Wh
AC input: 120V ~ 50/60Hz 15A 1800W max.
PV input x 1: 12-75V ⎓ 45A 1500W max.
Wind input x 1: 12-75V ⎓ 10A 200W max.
DC 5521 output x2: 12V ⎓ 3A 36W max
Cigarette lighter socket output: 12V ⎓ 10A 120W max
RV×1: 12V ⎓ 30A 360W max
DC 5521, Cigarette lighter socket and RV Share power 360W max
USB-A DC output x 4: 5V ⎓ 3A/9V = 2A/12V ⎓ 1.5A
USB-C DC output x 2: 5V ⎓ 3A/9V = 3A/12V ⎓ 3A/15V = 3A/20V = A/28V = 5A (140W max.)
AC output x4: Pure sine wave, 120V-15A 50/60Hz, total 3000W
AC output x1: Pure sine wave, 120V-30A 50/60Hz, total 3000W
Wireless charge×2: 5W/7.5W/10W/15W
Total output power: 3742W
Discharge temperature: 0-45°C
Charge temperature: 0-45°C
Date code: MM-DD-YYYY

RoHS Li-ion

FC UN38.3 CE BC UL Energy Verified PSE

Gotion Inc.

Made in America
with imported parts

⚠ CAUTION:

1. Risk of Electric Shock. Do not remove cover. No user serviceable parts inside. Refer servicing to qualified service personnel.
2. For continued protection against risk of fire, replace only with same type and rating of fuse. Refer replacement to qualified service personnel.
3. Risk of Electric Shock. Connect only to properly grounded outlets.
4. Risk of Injury to Persons. Do not use this product if the power cord or the battery cables are damaged in any way.
5. This device is not intended for use in a commercial repair facility.

⚠ WARNING:

1. Do not overcharge the internal battery. See Instruction Manual.
2. Do not smoke, strike a match, or cause a spark in the vicinity of the power pack.
3. Only charge the internal battery in a well ventilated area.
4. Risk of Electric Shock and Risk of Fire. This device is not to be stored in a vehicle.

⚠ DANGER:

This device is intended to be used indoors only. Do not use outdoors.

⚠ MISE EN GARDE:

1. Risque de décharge électrique. Ne pas enlever le couvercle. Aucune des pièces à l'intérieur ne peut être réparée par l'utilisateur. L'entretien courant doit être effectué par un personnel d'entretien qualifié.
2. Pour une protection continue contre le risque d'incendie, remplacer seulement par des fusibles du même type et calibre. Le remplacement doit être effectué par un personnel d'entretien qualifié.
3. Risque de décharge électrique. Brancher l'unité uniquement à des prises de courant correctement mises à la masse.
4. Risque de blessure aux personnes. Ne pas utiliser ce produit si le cordon d'alimentation ou les câbles de batterie sont endommagés de quelque facon.
5. Le dispositif n'est pas destiné à être utilisé dans un atelier de réparation commercial.

⚠ AVERTISSEMENT:

1. Ne pas surcharger la batterie interne. Consulter le manuel d'utilisation.
2. Il ne faut pas fumer, allumer une allumette ou produire des étincelles à proximité du bloc d'alimentation.
3. Charger la batterie uniquement dans un endroit bien aéré.
4. Risques de décharge électrique et d'incendie. Le dispositif ne doit pas être rangé dans un véhicule.

⚠ DANGER:

Le dispositif est destiné à être utilisé à l'intérieur seulement. Ne pas l'utiliser à l'extérieur.

FCC ID: 2BBUJ-HOME3000
IC：31058-HOME3000NA

FCC COMPLIANCE STATEMENT

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that may cause undesired operation.

CONTAINS FCC ID: 2AC7Z-ESPC3WROOM
CONTAINS IC: 21098-ESPC3WROOM

Location