



UL Listed MagClick™ 10000 mAh Light Up Power Bank
Instruction manual
7122-40



- Functions:**
1. Power ON/OFF button
 2. Wireless Charging LED indicator
 3. LED Indicators
 4. Type-C Input/Output
 5. USB-A Output
 6. Wireless charging surface



What's included:
1 x Wireless Power Bank
1 x Charging cable

Tech Specifications:
Type-C Input: DC5V/2.8A, DC9V/2A, DC12V/1.5A; (18W Max)
Type-C Output: DC5V/2.4A, DC9V/2A, DC12V/1.5A; (18W Max)
USB-A Output: DC5V/2.4A, DC9V/2A, DC12V/1.5A; (18W Max)
Wireless Output: 5W/7.5W/10W/15W
Multi-Port Simultaneous Output: DC5V/3A (15W Max)
Built-in battery/Cell Capacity: 37Wh, 3.7V/10000mAh
Rechargeable lithium battery
Product Capacity (Type-C): 5V/5800mAh, 29Wh; 9V/2500mAh, 22.5Wh;
12V/1700mAh, 20.4Wh
Product Capacity (USB-A): 5V/5800mAh, 29Wh; 9V/2500mAh, 22.5Wh;
12V/1700mAh, 20.4Wh,
Product Capacity (Wireless):
5.5W Mode/4800mAh, 24Wh;
7.5W Mode/3000mAh, 22.5Wh;
10W Mode/2200mAh, 19.8Wh;
15W Mode/1600mAh, 14.4Wh;
Operating temperature: 5~40°C for Charging
0~40°C for Discharging

Instructions:

- 1. Charging the Power Bank:**
 - Insert the type-C tip of the cable into a certified AC adapter and the other end into the type-C input port (4) to begin charging.
 - The LED indicator (3) will flash WHITE when the device is charging.
 - Once fully charged, the LED indicator will glow WHITE.
- 2. Cable Charging Your Mobile Device**
 - Connect the desired cable to your mobile phone or device, using the appropriate connector.
 - Insert the USB-A or Type-C tip of the desired cable to the USB-A Output Port (5) or Type-C Output Port (4).
 - The LED indicators (3) will illuminate during the charging process.
 - Once fully charged, remove the device.
- 3. Wireless Charging Mobile phones and other electronic Devices:**
 - Tap the ON/OFF button (1) to turn ON the power bank.
 - Place the wireless charging supported mobile device on the wireless charging surface (6), wireless charging LED indicator (2) will glow GREEN when device is charging.
 - Phone will begin to charge automatically. Once fully charged remove the device.

- Power bank can be turned OFF by double pressing the ON/OFF button (1).

Note: When wireless charging, if the LED indicator flashes, the device is either NOT a wireless charging device or there is an object between the device and charging surface interfering with the charging process.

4. LED Indicators (3):

Power Button: Press once to view the remaining power capacity. Press twice to power off.

Safety Precautions:

WARNING-When using this product, basic precautions should always be followed.

1. Read all the instructions before use. Charge the power bank fully before initial use. The unit's full performance is achieved only after 2 or 3 completed charge and discharge cycles.
2. Never store or use this product in temperatures below 32°F(0°C) or above 104°F(40°C).
3. To reduce the risk of injury, close supervision is necessary when the product is used near children.
4. Do not expose the device to moisture.
5. Do not use the device in excess of its output rating. Overload outputs above rating may result in a risk of fire or injury.
6. Do not use the device if damaged or modified.
7. Damaged or modified batteries may exhibit unpredictable behavior resulting in fire, explosion or risk of injury.
8. Do not disassemble the device. Take it to a qualified service person when service or repair is required. Incorrect reassembly may result in a risk of fire or injury.
9. Do not expose the device to fire or excessive temperature. Exposure to fire or temperatures above 104°F may cause explosion.
10. Have servicing performed by a qualified repair person using only identical replacement parts.
11. This will ensure that the safety of the product is maintained.
12. Do not overcharge Phone. Unit may get hot with excessive use. Remove Phone when it is fully charged. Never charge for more than 7 hours at a time.
13. Attachments on the back of your phone can impede the effectiveness of the wireless charger, and lead to overheating. Please remove attachments from the phone before charging on this device.

FCC STATEMENT

This device complies with Part 15 of the FCC Rules. Operation is subject to the

following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

Warning: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

RF Statement

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

IC Statement:

ICES-003 CLASS B NOTICE-AVIS NMB-003, CLASSE B
This Class B digital apparatus complies with Canadian ICES-003
Cet appareil numérique de la classe B est conforme à la norme NMB-003 du Canada.

- English: "

This device complies with Industry Canada licence exempt RSS standard(s). Operation is subject to the following two conditions:

- (1) this device may not cause interference, and
- (2) this device must accept any interference, including interference that may cause undesired operation of the device."

- French: "

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

- (1) l'appareil ne doit pas produire de brouillage, et
- (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement."

EN

Risk of Fire and Burns, don't open, crush, disassemble and dispose of in fire. Accessible surfaces held or touched for short periods only. Don't heat above 45 °C or Incinerate. Follow Manufacturer's Instructions.

FR

DANGER: risque d'incendie et de brûlures, ne pas ouvrir, démonter, écraser ni jeter au feu. Ne pas toucher ou tenir les surfaces accessibles sur une longue durée.

Name of the Distributor:

Leedsworld Inc

Address of the Distributor:

400 Hunt Valley Road,

New Kensington,

PA 15088 USA.

FCC ID: 2BCEV0050

Model #: SP0653

Made in China

