

FCC RF Exposure

EUT Description: Wireless monitoring system

Model No.: RW2090 2 waist bags 550.1~599.85 (CYS) ,RW2090 4 waist bags 550.1~599.85 (CYS)

RW2090 5 waist bags 550.1~599.85 (CYS) ,RW2090 6 waist bags 550.1~599.85 (CYS)

RW2090 8 waist bags 550.1~599.85 (CYS) ,RW2090 10 waist bags 550.1~599.85 (CYS)

FCC ID: 2BDIS-RW2090

Equipment type: fixed equipment

1. Limits

The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) radiation as specified in 1.1307(b)

Limits for Maximum Permissible Exposure (MPE)

Frequency range (MHz)	Electric field strength (V/m)	Magnetic field strength (A/m)	Power density (mW/cm ²)	Averaging time (minutes)
(A)Limits for Occupational/Controlled Exposures				
0.3-3.0	614	1.63	(100)	6
3.0-30	1842/f	4.89/f	*(900/F)	6
30-300	61.4	0.163	1.0	6
300-1500			f/300	6
1500-100,000			5	6
(B)Limits for General Population/Uncontrolled Exposure				
0.3-1.34	614	1.63	(100)	30
1.34-30	824/f	2.19/f	(180/)	30
30-300	27.5	0.073	0.2	30
300-1500			f/1500	30
1500-100,000			f/1500	30

F = frequency in MHz

Formula: $P_d = (P_{out} * G) / (4 * \pi * r^2)$

Where :

P_d = power density in mW/cm²,

P_{out} = output power to antenna in mW;

G = gain of antenna in linear scale,

π = 3.14;

R = distance between observation point and center of the radiator in cm

P_d is the limit of MPE, 1 mW/cm². If we know the maximum gain of the antenna and the total power input to the antenna, through the calculation, we will know the distance r where the MPE

limit is reached.

2. Test Procedure

Software provided by client enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

3. Test Result of RF Exposure Evaluation

ANT 1	
CH/Frequency	Output power (dBm/mW)
Channel 21 599.85MHz	3.12/2.05

ANT 2	
CH/Frequency	Output power (dBm/mW)
Channel 21 575.15MHz	3.38/2.18

	Output power (dBm/ mW)	Antenna Gain(dBi)	Power Density at R=20cm (mW/cm ²)	Limit (mW/cm ²)	Result
ANT1	3.12/2.05	-2.09	0.00025	0.3667	Pass
ANT2	3.38/2.18	-2.09	0.00027	0.3667	Pass

Frequency(MHz)	Field strength(dBu V/m)	EIRP(dBm)	Max tune- up(mW)	Antenna Gain(dBi)	Power Density at R=20cm (mW/cm ²)	Limit (mW/cm ²)
2402	93.61	- 1.5476	0.7002	1.7	0.00021	1.0
2440	93.52	- 1.6376	0.6859	1.7	0.00020	1.0
2480	91.82	-3.3376	0.4637	1.7	0.00014	1.0

$$BT+ANT1+ANT2=0.00025/0.367+0.00027/0.367+0.00021/1=0.00163 \leq 1$$

Conclusion: No SAR is required