

11AC20SISO_Ant1_5500



11AC20SISO_Ant1_5580



11AC20SISO_Ant1_5700



11AC20SISO_Ant1_5745




11AC20SISO_Ant1_5785



11AC20SISO_Ant1_5825



11AC40SISO_Ant1_5190



11AC40SISO_Ant1_5230




11AC40SISO_Ant1_5270



11AC40SISO_Ant1_5310



11AC40SISO_Ant1_5510



11AC40SISO_Ant1_5550




11AC40SISO_Ant1_5670




11AC40SISO_Ant1_5755



11AC40SISO_Ant1_5795



11AC80SISO_Ant1_5210




11AC80SISO_Ant1_5290



11AC80SISO_Ant1_5530



11AC80SISO_Ant1_5610



11AC80SISO_Ant1_5775



8.2 MAXIMUM CONDUCTED OUTPUT POWER

8.2.1 Applicable Standard

According to FCC Part 15.407(a)(1) for UNII Band I
According to FCC Part 15.407(a)(2) for UNII Band II-A and UNII Band II-C
According to FCC Part 15.407(a)(3) for UNII Band III
According to 789033 D02 Section II(E)
According to RSS 247, 6.2

8.2.2 Conformance Limit

FCC Limit:

■ For the band 5.15-5.25 GHz

(a)(1) (i) For an outdoor access point, the maximum conducted output power over the frequency band of operation shall not exceed 1 W provided the maximum antenna gain does not exceed 6 dBi. If transmitting antennas of directional gain greater than 6 dBi are used, the maximum conducted output power shall be reduced by the amount in dB that the directional gain of the antenna exceeds 6 dBi. The maximum e.i.r.p. at any elevation angle above 30 degrees as measured from the horizon must not exceed 125 mW (21 dBm).

(a) (1) (ii) For an indoor access point, the maximum conducted output power over the frequency band of operation shall not exceed 1 W provided the maximum antenna gain does not exceed 6 dBi. If transmitting antennas of directional gain greater than 6 dBi are used, the maximum conducted output power shall be reduced by the amount in dB that the directional gain of the antenna exceeds 6 dBi.

(a) (1) (iii) For fixed point-to-point access points, the maximum conducted output power over the frequency band of operation shall not exceed 1 W. Fixed point-to-point U-NII devices may employ antennas with directional gain up to 23 dBi without any corresponding reduction in the maximum conducted output power. For fixed point-to-point transmitters that employ a directional antenna gain greater than 23 dBi, a 1 dB reduction in maximum conducted output power is required for each 1 dB of antenna gain in excess of 23 dBi. Fixed, point-to-point operations exclude the use of point-to-multipoint systems, omnidirectional applications, and multiple collocated transmitters transmitting the same information. The operator of the U-NII device, or if the equipment is professionally installed, the installer, is responsible for ensuring that systems employing high gain directional antennas are used exclusively for fixed, point-to-point operations.

(a) (1) (iv) For client devices, the maximum conducted output power over the frequency band of operation shall not exceed 250 mW provided the maximum antenna gain does not exceed 6 dBi. If transmitting antennas of directional gain greater than 6 dBi are used, the maximum conducted output power shall be reduced by the amount in dB that the directional gain of the antenna exceeds 6 dBi.

■ For the 5.25-5.35 GHz and 5.47-5.725 GHz bands

(a) (2) The maximum conducted output power over the frequency bands of operation shall not exceed the lesser of 250 mW or $11 \text{ dBm} + 10 \log B$, where B is the 26 dB emission bandwidth in megahertz. If transmitting antennas of directional gain greater than 6 dBi are used, the maximum conducted output power shall be reduced by the amount in dB that the directional gain of the antenna exceeds 6 dBi.

■ For the band 5.725-5.85 GHz

(a) (3) The maximum conducted output power over the frequency band of operation shall not exceed 1 W. If transmitting antennas of directional gain greater than 6 dBi are used, the maximum conducted output power shall be reduced by the amount in dB that the directional gain of the antenna exceeds 6 dBi. However, fixed point-to-point U-NII devices operating in this band may employ transmitting antennas with directional gain greater than 6 dBi without any corresponding reduction in transmitter conducted power. Fixed, point-to-point operations exclude the use of point-to-multipoint systems, omnidirectional applications, and multiple collocated transmitters transmitting the same information. The operator of the U-NII device, or if the equipment is professionally installed, the installer, is responsible for ensuring that systems employing high gain directional antennas are used exclusively for fixed, point-to-point operations

IC Limit:

■ Frequency band 5150-5250 MHz

The maximum e.i.r.p. shall not exceed 200 mW or $10 + 10 \log_{10} B$, dBm, whichever power is less. B is the 99% emission bandwidth in megahertz.

■ Frequency band 5250-5350 MHz

The maximum conducted output power shall not exceed 250 mW or $11 + 10 \log_{10} B$, dBm, whichever is less.

The maximum e.i.r.p. shall not exceed 1.0 W or $17 + 10 \log_{10} B$, dBm, whichever is less. B is the 99% emission bandwidth in megahertz. Note that devices with a maximum e.i.r.p. greater than 500 mW shall implement TPC in order to have the capability to operate at least 6 dB below the maximum permitted e.i.r.p. of 1 W.

■ Frequency bands 5470-5600 MHz and 5650-5725 MHz

The maximum conducted output power shall not exceed 250 mW or $11 + 10 \log_{10} B$, dBm, whichever is less.

The maximum e.i.r.p. shall not exceed 1.0 W or $17 + 10 \log_{10} B$, dBm, whichever is less. B is the 99% emission bandwidth in megahertz. Note that devices with a maximum e.i.r.p. greater than 500 mW shall implement TPC in order to have the capability to operate at least 6 dB below the maximum permitted e.i.r.p. of 1 W.

■ Frequency band 5725-5850 MHz

The maximum conducted output power shall not exceed 1 W. If transmitting antennas of directional gain greater than 6 dBi are used, the maximum conducted output power shall be reduced by the amount in dB that the directional gain of the antenna exceeds 6 dBi. However, fixed point-to-point devices operating in this band may employ transmitting antennas with directional gain greater than 6 dBi without any corresponding reduction in transmitter conducted power. Fixed point-to-point operations exclude the use of point-to-multipoint systems, omnidirectional applications and multiple collocated transmitters transmitting the same information.

8.2.3 Test Configuration

Test according to clause 6.1 radio frequency test setup

8.2.4 Test Procedure

The maximum average conducted output power can be measured using Method PM-G (Measurement using a gated RF average power meter):

Measurements may be performed using a wideband gated RF power meter provided that the gate parameters are adjusted such that the power is measured only when the EUT is transmitting at its maximum power control level. Since the measurement is made only during the ON time of the transmitter, no duty cycle correction factor is required.

- The Transmitter output (antenna port) was connected to the power meter.
- Turn on the EUT and power meter and then record the power value.
- Repeat above procedures on all channels needed to be tested.

8.2.5 Test Results

Temperature:	25 °C
Relative Humidity:	45%
ATM Pressure:	1011 mbar


Note: N/A

TestMode	Antenna	Frequency[MHz]	Transmission Duration [ms]	Transmission Period [ms]	Duty Cycle [%]
11A	Ant1	5180	1.40	1.44	97.22
		5200	1.40	1.44	97.22
		5240	1.40	1.44	97.22
		5260	1.39	1.43	97.20
		5280	1.39	1.43	97.20
		5320	1.40	1.44	97.22
		5500	1.39	1.43	97.20
		5580	1.40	1.44	97.22
		5700	1.40	1.44	97.22
		5745	1.39	1.43	97.20
		5785	1.40	1.44	97.22
		5825	1.40	1.44	97.22
11N20SISO	Ant1	5180	1.30	1.35	96.30
		5200	1.30	1.35	96.30
		5240	1.31	1.35	97.04
		5260	1.31	1.35	97.04
		5280	1.31	1.35	97.04
		5320	1.31	1.35	97.04
		5500	1.30	1.34	97.01
		5580	1.31	1.35	97.04
		5700	1.31	1.35	97.04
		5745	1.31	1.35	97.04
		5785	1.31	1.35	97.04
		5825	1.31	1.35	97.04
11N40SISO	Ant1	5190	0.65	0.69	94.20
		5230	0.65	0.69	94.20
		5270	0.65	0.69	94.20
		5310	0.65	0.69	94.20
		5510	0.65	0.69	94.20
		5550	0.65	0.69	94.20
		5670	0.65	0.69	94.20
		5755	0.65	0.69	94.20
		5795	0.65	0.69	94.20
11AC20SISO	Ant1	5180	1.31	1.36	96.32
		5200	1.32	1.36	97.06
		5240	1.31	1.36	96.32
		5260	1.32	1.36	97.06
		5280	1.32	1.36	97.06
		5320	1.32	1.36	97.06
		5500	1.32	1.36	97.06
		5580	1.32	1.36	97.06
		5700	1.32	1.36	97.06
		5745	1.31	1.35	97.04
		5785	1.32	1.36	97.06
		5825	1.32	1.36	97.06
11AC40SISO	Ant1	5190	0.66	0.70	94.29
		5230	0.65	0.70	92.86
		5270	0.66	0.70	94.29
		5310	0.66	0.70	94.29
		5510	0.66	0.70	94.29
		5550	0.66	0.70	94.29
		5670	0.66	0.70	94.29


		5755	0.66	0.70	94.29
		5795	0.66	0.70	94.29
11AC80SISO	Ant1	5210	1.31	1.35	97.04
		5290	1.31	1.36	96.32
		5530	0.65	0.69	94.20
		5610	1.32	1.36	97.06
		5775	0.65	0.70	92.86




11A_Ant1_5180




11A_Ant1_5200




11A_Ant1_5240




11A_Ant1_5260




11A_Ant1_5280




11A_Ant1_5320




11A_Ant1_5500




11A_Ant1_5580




11A_Ant1_5700




11A_Ant1_5745




11A_Ant1_5785




11A_Ant1_5825




11N20SISO_Ant1_5180




11N20SISO_Ant1_5200




11N20SISO_Ant1_5240




11N20SISO_Ant1_5260




11N20SISO_Ant1_5280




11N20SISO_Ant1_5320




11N20SISO_Ant1_5500




11N20SISO_Ant1_5580




11N20SISO_Ant1_5700




11N20SISO_Ant1_5745




11N20SISO_Ant1_5785




11N20SISO_Ant1_5825




11N40SISO_Ant1_5190




11N40SISO_Ant1_5230




11N40SISO_Ant1_5270




11N40SISO_Ant1_5310




11N40SISO_Ant1_5510




11N40SISO_Ant1_5550




11N40SISO_Ant1_5670




11N40SISO_Ant1_5755




11N40SISO_Ant1_5795




11AC20SISO_Ant1_5180




11AC20SISO_Ant1_5200




11AC20SISO_Ant1_5240




11AC20SISO_Ant1_5260




11AC20SISO_Ant1_5280




11AC20SISO_Ant1_5320




11AC20SISO_Ant1_5500




11AC20SISO_Ant1_5580




11AC20SISO_Ant1_5700




11AC20SISO_Ant1_5745




11AC20SISO_Ant1_5785




11AC20SISO_Ant1_5825




11AC40SISO_Ant1_5190




11AC40SISO_Ant1_5230




11AC40SISO_Ant1_5270




11AC40SISO_Ant1_5310




11AC40SISO_Ant1_5510




11AC40SISO_Ant1_5550




11AC40SISO_Ant1_5670




11AC40SISO_Ant1_5755




11AC40SISO_Ant1_5795




11AC80SISO_Ant1_5210




11AC80SISO_Ant1_5290




11AC80SISO_Ant1_5530



11AC80SISO_Ant1_5610



11AC80SISO_Ant1_5775



Test Mode	Antenna	Frequency [MHz]	Channel Power [dBm]	Duty Cycle [%]	DC Factor [dBm]	Result [dBm]	Limit [dBm]	Gain [dBi]	EIRP [dBm]	EIRP Limit [dBm]	Verdict
11A	Ant1	5180	14.41	97.22	0.12	14.53	≤21.68	8.30	22.83	---	PASS
		5200	14.51	97.22	0.12	14.63	≤21.68	8.30	22.93	---	PASS
		5240	14.54	97.22	0.12	14.66	≤21.68	8.30	22.96	---	PASS
		5260	11.97	97.20	0.12	12.09	≤21.68	8.30	20.39	---	PASS
		5280	12.22	97.20	0.12	12.34	≤21.68	8.30	20.64	---	PASS
		5320	11.88	97.22	0.12	12.00	≤21.68	8.30	20.30	---	PASS
		5500	11.98	97.20	0.12	12.10	≤21.68	8.30	20.40	---	PASS
		5580	12.24	97.22	0.12	12.36	≤21.68	8.30	20.66	---	PASS
		5700	11.24	97.22	0.12	11.36	≤21.68	8.30	19.66	---	PASS
		5745	14.76	97.20	0.12	14.88	≤27.70	8.30	23.18	---	PASS
		5785	14.39	97.22	0.12	14.51	≤27.70	8.30	22.81	---	PASS
11N20SISO	Ant1	5180	13.87	96.30	0.16	14.03	≤21.68	8.30	22.33	---	PASS
		5200	14.09	96.30	0.16	14.25	≤21.68	8.30	22.55	---	PASS
		5240	14.21	97.04	0.13	14.34	≤21.68	8.30	22.64	---	PASS
		5260	14.88	97.04	0.13	15.01	≤21.68	8.30	23.31	---	PASS
		5280	13.83	97.04	0.13	13.96	≤21.68	8.30	22.26	---	PASS
		5320	13.49	97.04	0.13	13.62	≤21.68	8.30	21.92	---	PASS
		5500	13.73	97.01	0.13	13.86	≤21.68	8.30	22.16	---	PASS
		5580	13.89	97.04	0.13	14.02	≤21.68	8.30	22.32	---	PASS
		5700	12.76	97.04	0.13	12.89	≤21.68	8.30	21.19	---	PASS
		5745	13.50	97.04	0.13	13.63	≤27.70	8.30	21.93	---	PASS
		5785	12.92	97.04	0.13	13.05	≤27.70	8.30	21.35	---	PASS
11N40SISO	Ant1	5190	13.05	94.20	0.26	13.31	≤21.68	8.30	21.61	---	PASS
		5230	13.26	94.20	0.26	13.52	≤21.68	8.30	21.82	---	PASS
		5270	13.47	94.20	0.26	13.73	≤21.68	8.30	22.03	---	PASS
		5310	11.09	94.20	0.26	11.35	≤21.68	8.30	19.65	---	PASS
		5510	11.56	94.20	0.26	11.82	≤21.68	8.30	20.12	---	PASS
		5550	11.70	94.20	0.26	11.96	≤21.68	8.30	20.26	---	PASS
		5670	11.04	94.20	0.26	11.30	≤21.68	8.30	19.60	---	PASS
		5755	11.23	94.20	0.26	11.49	≤27.70	8.30	19.79	---	PASS
		5795	10.69	94.20	0.26	10.95	≤27.70	8.30	19.25	---	PASS
11AC20SISO	Ant1	5180	11.05	96.32	0.16	11.21	≤21.68	8.30	19.51	---	PASS
		5200	11.05	97.06	0.13	11.18	≤21.68	8.30	19.48	---	PASS
		5240	11.44	96.32	0.16	11.60	≤21.68	8.30	19.90	---	PASS
		5260	11.63	97.06	0.13	11.76	≤21.68	8.30	20.06	---	PASS
		5280	11.74	97.06	0.13	11.87	≤21.68	8.30	20.17	---	PASS
		5320	11.54	97.06	0.13	11.67	≤21.68	8.30	19.97	---	PASS
		5500	11.69	97.06	0.13	11.82	≤21.68	8.30	20.12	---	PASS
		5580	12.04	97.06	0.13	12.17	≤21.68	8.30	20.47	---	PASS
		5700	10.89	97.06	0.13	11.02	≤21.68	8.30	19.32	---	PASS
		5745	11.49	97.04	0.13	11.62	≤27.70	8.30	19.92	---	PASS
		5785	11.04	97.06	0.13	11.17	≤27.70	8.30	19.47	---	PASS
11AC40SISO	Ant1	5190	10.92	94.29	0.26	11.18	≤21.68	8.30	19.48	---	PASS
		5230	11.11	92.86	0.32	11.43	≤21.68	8.30	19.73	---	PASS
		5270	11.50	94.29	0.26	11.76	≤21.68	8.30	20.06	---	PASS
		5310	11.39	94.29	0.26	11.65	≤21.68	8.30	19.95	---	PASS
		5510	11.61	94.29	0.26	11.87	≤21.68	8.30	20.17	---	PASS
		5550	11.72	94.29	0.26	11.98	≤21.68	8.30	20.28	---	PASS
		5670	11.00	94.29	0.26	11.26	≤21.68	8.30	19.56	---	PASS

11AC80SI SO	Ant1	5755	11.11	94.29	0.26	11.37	≤27.70	8.30	19.67	---	PASS
		5795	10.65	94.29	0.26	10.91	≤27.70	8.30	19.21	---	PASS
		5210	10.66	100.0 0	0.00	10.66	≤21.68	8.30	18.96	---	PASS
		5290	11.00	100.0 0	0.00	11.00	≤21.68	8.30	19.30	---	PASS
		5530	11.31	100.0 0	0.00	11.31	≤21.68	8.30	19.61	---	PASS
		5610	11.41	100.0 0	0.00	11.41	≤21.68	8.30	19.71	---	PASS
		5775	10.51	100.0 0	0.00	10.51	≤27.70	8.30	18.81	---	PASS



11A_Ant1_5180



11A_Ant1_5200



11A_Ant1_5240



11A_Ant1_5260



11A_Ant1_5280



11A_Ant1_5320



11A_Ant1_5500




11A_Ant1_5580




11A_Ant1_5700



11A_Ant1_5745




11A_Ant1_5785



11A_Ant1_5825



11N20SISO_Ant1_5180



11N20SISO_Ant1_5200



11N20SISO_Ant1_5240



11N20SISO_Ant1_5260



11N20SISO_Ant1_5280



11N20SISO_Ant1_5320



11N20SISO_Ant1_5500



11N20SISO_Ant1_5580




11N20SISO_Ant1_5700



11N20SISO_Ant1_5745



11N20SISO_Ant1_5785



11N20SISO_Ant1_5825



11N40SISO_Ant1_5190




11N40SISO_Ant1_5230




11N40SISO_Ant1_5270



11N40SISO_Ant1_5310



11N40SISO_Ant1_5510



11N40SISO_Ant1_5550

