

 Split time	Click [Split time] to enter the setting of the video segmentation time. Video segmentation time is optional: 1 minute / 3 minutes / 5 minutes <i>The system defaults to 3 minutes</i>
 Collision Sensitivity	Click [Collision Sensitivity] to set the sensitivity Off / Low / Middle / High
 Microphone	Click [Microphone] to turn on/off audio recording.
 Rear mirror image	Click [Rear Mirror Image] to turn on/off the mirroring function, which can adjust 180° flip the rear view image horizontally, making it easier for customers to install the camera flexibly.
 Reverse Line Calibration	Click [Reverse Line Calibration] to enter the reversing settings. The screen will display the status and the reversing line frame on/off when reversing. You can adjust the reversing line according to the size of your car.

c) System Setting



 Language	Click [Language] to set the display Language to Simplified Chinese/Traditional Chinese/English/Russian/Spanish/French/German/Japanese/Korean/Arabic/Italian/Portuguese
 Screen Rotation	Click[Screen Rotation] to rotate the screen 180 degrees for easy installation
 Tip sound	Click [Tip sound] to turn off/on the touch and boot sound.
 Date & Time	Click [Date & Time] to set the screen display time and timestamp of the video recorded by the camera at the same time. You can setup separately year/month/day/time/minutes/seconds/12H system/24H system.

 Storage info	Click [Storageinfo] to view the SD card storage space
 Format	Click[Format] to format all data information.We recommend manually formatting the TF card When first inserted to ensure sufficient card capacity. Note:We recommend that user manually format the TF card regularly.
 Factory reset	Click[Factory reset] to enter the Restore the factory settings.You can restore all the settings to the initial state
 Firmware version	Click on[Firmware version] to view the version information of the device.Please provide this interface to the after-sales customer service staff when you need our help.

6.Parking Monitor

This function will be triggered when the hardwire kit is connected,(as photo)

Option: Off/Low/Middle/High

ZKCAMSPY Hardwire Kit:
ASIN: **B0BZP4HT5V**





Made in China