


Appendix Test Data

Report No.:	1812C50297012501	Test Sample No.:	1-2-2
Start Test Date:	2025.6.19	Finish Test Date:	2025.6.20
Test Engineer:	<i>Liangfei Yang</i>	Auditor:	<i>Justin Feng</i>
Temperature:	23.5°C	Relative Humidity:	45%
Pressure:	101kPa		



Appendix A: -6dB Bandwidth

Condition	Antenna	Rate	Frequency (MHz)	-6dB BW(kHz)	limit(kHz)	Result
NVNT	ANT1	1Mbps	2402.00	504.92	500	Pass
NVNT	ANT1	1Mbps	2440.00	508.10	500	Pass
NVNT	ANT1	1Mbps	2480.00	507.02	500	Pass

-6dB_Bandwidth_NVNT_ANT1_1Mbps_2402



-6dB_Bandwidth_NVNT_ANT1_1Mbps_2440



Appendix B: 99% Occupied Bandwidth


Condition	Antenna	Rate	Frequency (MHz)	99%BW(MHz)
NVNT	ANT1	1Mbps	2402.00	1.019
NVNT	ANT1	1Mbps	2440.00	1.019
NVNT	ANT1	1Mbps	2480.00	1.019

99%_Occupied_Bandwidth_NVNT_ANT1_1Mbps_2402



99%_Occupied_Bandwidth_NVNT_ANT1_1Mbps_2440





Shenzhen Anbotek Compliance Laboratory Limited


Address: Sogood Industrial Zone Laboratory & 1/F. of Building D, Sogood Science and Technology Park,
Sanwei Community, Hangcheng Subdistrict, Bao'an District, Shenzhen, Guangdong, China
Tel: (86) 0755-26066440 Email: service@anbotek.com

Hotline
400-003-0500
www.anbotek.com


Appendix C: Duty Cycle


Condition	Antenna	Rate	Frequency (MHz)	Dutycycle(%)	Duty_factor
NVNT	ANT1	1Mbps	2402.00	16.13	7.92
NVNT	ANT1	1Mbps	2440.00	19.35	7.13
NVNT	ANT1	1Mbps	2480.00	15.63	8.06

Duty_Cycle_NVNT_ANT1_1Mbps_2402



Duty_Cycle_NVNT_ANT1_1Mbps_2440





Shenzhen Anbotech Compliance Laboratory Limited

Address: Sogood Industrial Zone Laboratory & 1/F. of Building D, Sogood Science and Technology Park,
Sanwei Community, Hangcheng Subdistrict, Bao'an District, Shenzhen, Guangdong, China
Tel: (86) 0755-26066440 Email: service@anbotech.com

Hotline
400-003-0500
www.anbotech.com

Appendix D: Peak Output Power

Condition	Antenna	Rate	Frequency (MHz)	Max. Conducted Power(dBm)	Max. Conducted Power(mW)	Limit(mW)	Result
NVNT	ANT1	1Mbps	2402.00	-0.69	0.85	1000	Pass
NVNT	ANT1	1Mbps	2440.00	-1.14	0.77	1000	Pass
NVNT	ANT1	1Mbps	2480.00	-1.36	0.73	1000	Pass


Peak_Output_Power_NVNT_ANT1_1Mbps_2402



Peak_Output_Power_NVNT_ANT1_1Mbps_2440



Peak_Output_Power_NVNT_ANT1_1Mbps_2480



Shenzhen Anbotek Compliance Laboratory Limited

Address: Sogood Industrial Zone Laboratory & 1/F. of Building D, Sogood Science and Technology Park,
Sanwei Community, Hangcheng Subdistrict, Bao'an District, Shenzhen, Guangdong, China
Tel: (86)0755-26066440 Email: service@anbotek.com



Hotline
400-003-0500
www.anbotek.com

Appendix E: Power Spectral Density

Condition	Antenna	Rate	Frequency (MHz)	Power Spectral Density(dBm/3kHz)	Limit(dBm/3kHz)	Result
NVNT	ANT1	1Mbps	2402.00	-18.70	8	Pass
NVNT	ANT1	1Mbps	2440.00	-19.43	8	Pass
NVNT	ANT1	1Mbps	2480.00	-19.91	8	Pass


Power_Spectral_Density_NVNT_ANT1_1Mbps_2402



Power_Spectral_Density_NVNT_ANT1_1Mbps_2440



Power_Spectral_Density_NVNT_ANT1_1Mbps_2480



Shenzhen Anbotech Compliance Laboratory Limited

Address: Sogood Industrial Zone Laboratory & 1/F. of Building D, Sogood Science and Technology Park,
Sanwei Community, Hangcheng Subdistrict, Bao'an District, Shenzhen, Guangdong, China
Tel: (86) 0755-26066440 Email: service@anbotech.com



Hotline
400-003-0500
www.anbotech.com

Appendix F: Bandedge


Condition	Antenna	Modulation	TX_Frequency (MHz)	Max. Mark_freq(MHz)	Ref_level (dBm)	Spurious level(dBm)	limit(dBm)	Result
NVNT	ANT1	1Mbps	2402.00	2399.300	-0.756	-45.253	-20.756	Pass
NVNT	ANT1	1Mbps	2480.00	2483.600	-1.402	-50.933	-21.402	Pass

Remark:1. Regarding the spurious emissions from 30MHz to 26.5GHz, the cable lose have been set in the 'offset' of the Spectrum Analyzer during the test.

1_Reference_Level_NVNT_ANT1_1Mbps_2402



2_Bandedge_NVNT_ANT1_1Mbps_2402



Shenzhen Anbotek Compliance Laboratory Limited


Address: Sogood Industrial Zone Laboratory & 1/F. of Building D, Sogood Science and Technology Park, Sanwei Community, Hangcheng Subdistrict, Bao'an District, Shenzhen, Guangdong, China
Tel: (86) 0755-26066440 Email: service@anbotek.com

Hotline 400-003-0500
www.anbotek.com

1_Reference_Level_NVNT_ANT1_1Mbps_2480



2_Bandedge_NVNT_ANT1_1Mbps_2480



Shenzhen Anbotek Compliance Laboratory Limited

Address: Sogood Industrial Zone Laboratory & 1/F. of Building D, Sogood Science and Technology Park,
Sanwei Community, Hangcheng Subdistrict, Bao'an District, Shenzhen, Guangdong, China
Tel: (86) 0755-26066440 Email: service@anbotek.com

Hotline
400-003-0500
www.anbotek.com

Appendix G: Spurious Emission


Condition	Antenna	Modulation	TX_Frequency (MHz)	Ref_level(dBm)	Spurious level(dBm)	limit(dBm)	Result
NVNT	ANT1	1Mbps	2402.00	-0.928	-47.307	-20.928	Pass
NVNT	ANT1	1Mbps	2440.00	-1.158	-46.888	-21.158	Pass
NVNT	ANT1	1Mbps	2480.00	-1.157	-47.962	-21.157	Pass

Note: Regarding the spurious emissions from 30MHz to 26.5GHz, the cable lose have been set in the 'Input Correction' of the Spectrum Analyzer during the test.


1_Reference_Level_NVNT_ANT1_1Mbps_2402



2_Spurious_Emission_NVNT_ANT1_1Mbps_2402




1_Reference_Level_NVNT_ANT1_1Mbps_2440




2_Spurious_Emission_NVNT_ANT1_1Mbps_2440



1_Reference_Level_NVNT_ANT1_1Mbps_2480



2_Spurious_Emission_NVNT_ANT1_1Mbps_2480



---END---

Shenzhen Anbotek Compliance Laboratory Limited

Address: Sogood Industrial Zone Laboratory & 1/F. of Building D, Sogood Science and Technology Park,
Sanwei Community, Hangcheng Subdistrict, Bao'an District, Shenzhen, Guangdong, China
Tel: (86) 0755-26066440 Email: service@anbotek.com



Hotline
400-003-0500
www.anbotek.com