# Appendix A

## RF Test Data for BT (Conducted Measurement)

**Product Name: Touch all in one**

**Test Model: 1561E-IDT-C02F-ECM10**

**Environmental Conditions**

| | |
|---|---|
| Temperature: | 23.8 ° C |
| Relative Humidity: | 52.3% |
| ATM Pressure: | 100.0 kPa |
| Test Engineer: | Eason Zhou |
| Supervised by: | Nick Peng |

# A.1 -20dB Bandwidth

| Condition | Mode | Frequency (MHz) | Antenna | -20 dB Bandwidth (MHz) | Limit -20 dB Bandwidth (MHz) | Verdict |
|---|---|---|---|---|---|---|
| NVNT | 1-DH5 | 2402 | Ant1 | 1.031 | N/A | Pass |
| NVNT | 1-DH5 | 2441 | Ant1 | 0.963 | N/A | Pass |
| NVNT | 1-DH5 | 2480 | Ant1 | 0.954 | N/A | Pass |
| NVNT | 2-DH5 | 2402 | Ant1 | 1.28 | N/A | Pass |
| NVNT | 2-DH5 | 2441 | Ant1 | 1.284 | N/A | Pass |
| NVNT | 2-DH5 | 2480 | Ant1 | 1.284 | N/A | Pass |
| NVNT | 3-DH5 | 2402 | Ant1 | 1.298 | N/A | Pass |
| NVNT | 3-DH5 | 2441 | Ant1 | 1.295 | N/A | Pass |
| NVNT | 3-DH5 | 2480 | Ant1 | 1.294 | N/A | Pass |

Test Graphs

-20dB Bandwidth NVNT 1-DH5 2402MHz Ant1




-20dB Bandwidth NVNT 1-DH5 2441MHz Ant1



-20dB Bandwidth NVNT 1-DH5 2480MHz Ant1




-20dB Bandwidth NVNT 2-DH5 2402MHz Ant1



-20dB Bandwidth NVNT 2-DH5 2441MHz Ant1




-20dB Bandwidth NVNT 2-DH5 2480MHz Ant1



-20dB Bandwidth NVNT 3-DH5 2402MHz Ant1




-20dB Bandwidth NVNT 3-DH5 2441MHz Ant1



-20dB Bandwidth NVNT 3-DH5 2480MHz Ant1



# A.2 Maximum Conducted Output Power

| Condition | Mode | Frequency (MHz) | Antenna | Conducted Power (dBm) | Limit (dBm) | Verdict |
|---|---|---|---|---|---|---|
| NVNT | 1-DH5 | 2402 | Ant1 | 0.2 | 21 | Pass |
| NVNT | 1-DH5 | 2441 | Ant1 | 0.4 | 21 | Pass |
| NVNT | 1-DH5 | 2480 | Ant1 | 0.55 | 21 | Pass |
| NVNT | 2-DH5 | 2402 | Ant1 | -0.3 | 21 | Pass |
| NVNT | 2-DH5 | 2441 | Ant1 | 0.15 | 21 | Pass |
| NVNT | 2-DH5 | 2480 | Ant1 | 0.33 | 21 | Pass |
| NVNT | 3-DH5 | 2402 | Ant1 | -0.13 | 21 | Pass |
| NVNT | 3-DH5 | 2441 | Ant1 | 0.31 | 21 | Pass |
| NVNT | 3-DH5 | 2480 | Ant1 | 0.45 | 21 | Pass |

Test Graphs

Power NVNT 1-DH5 2402MHz Ant1




Power NVNT 1-DH5 2441MHz Ant1



Power NVNT 1-DH5 2480MHz Ant1




Power NVNT 2-DH5 2402MHz Ant1



Power NVNT 2-DH5 2441MHz Ant1




Power NVNT 2-DH5 2480MHz Ant1



Power NVNT 3-DH5 2402MHz Ant1




Power NVNT 3-DH5 2441MHz Ant1



Power NVNT 3-DH5 2480MHz Ant1



# A.3 Carrier Frequencies Separation

| Condition | Mode | Antenna | Hopping Freq1 (MHz) | Hopping Freq2 (MHz) | HFS (MHz) | Limit (MHz) | Verdict |
|---|---|---|---|---|---|---|---|
| NVNT | 1-DH5 | Ant1 | 2402.012 | 2403.004 | 0.992 | 0.687 | Pass |
| NVNT | 2-DH5 | Ant1 | 2402.008 | 2402.996 | 0.988 | 0.856 | Pass |
| NVNT | 3-DH5 | Ant1 | 2402.142 | 2403.162 | 1.02 | 0.865 | Pass |

Test Graphs

CFS NVNT 1-DH5 2402MHz Ant1




CFS NVNT 2-DH5 2402MHz Ant1



CFS NVNT 3-DH5 2402MHz Ant1



# A.4 Dwell Time

| Condition | Mode | Frequency (MHz) | Antenna | Pulse Time (ms) | Total Dwell Time (ms) | Burst Count | Period Time (ms) | Limit (ms) | Verdict |
|---|---|---|---|---|---|---|---|---|---|
| NVNT | 1-DH5 | 2402 | Ant1 | 2.881 | 285.219 | 99 | 31600 | 400 | Pass |
| NVNT | 2-DH5 | 2402 | Ant1 | 2.88 | 299.52 | 104 | 31600 | 400 | Pass |
| NVNT | 3-DH5 | 2402 | Ant1 | 2.887 | 294.474 | 102 | 31600 | 400 | Pass |

Test Graphs

Dwell NVNT 1-DH5 2402MHz Ant1 One Burst




Dwell NVNT 1-DH5 2402MHz Ant1 Accumulated



Dwell NVNT 2-DH5 2402MHz Ant1 One Burst




Dwell NVNT 2-DH5 2402MHz Ant1 Accumulated



Dwell NVNT 3-DH5 2402MHz Ant1 One Burst




Dwell NVNT 3-DH5 2402MHz Ant1 Accumulated



# A.5 Number of Hopping Channel

| Condition | Mode | Antenna | Hopping Number | Limit | Verdict |
|---|---|---|---|---|---|
| NVNT | 1-DH5 | Ant1 | 79 | 15 | Pass |
| NVNT | 2-DH5 | Ant1 | 79 | 15 | Pass |
| NVNT | 3-DH5 | Ant1 | 79 | 15 | Pass |

Test Graphs

Hopping No. NVNT 1-DH5 2402MHz Ant1




Hopping No. NVNT 2-DH5 2402MHz Ant1



Hopping No. NVNT 3-DH5 2402MHz Ant1



# A.6 Band Edge

| Condition | Mode | Frequency (MHz) | Antenna | Hopping Mode | Max Value (dBc) | Limit (dBc) | Verdict |
|---|---|---|---|---|---|---|---|
| NVNT | 1-DH5 | 2402 | Ant1 | No-Hopping | -56.65 | -20 | Pass |
| NVNT | 1-DH5 | 2480 | Ant1 | No-Hopping | -56.92 | -20 | Pass |
| NVNT | 2-DH5 | 2402 | Ant1 | No-Hopping | -52.65 | -20 | Pass |
| NVNT | 2-DH5 | 2480 | Ant1 | No-Hopping | -55.16 | -20 | Pass |
| NVNT | 3-DH5 | 2402 | Ant1 | No-Hopping | -54.47 | -20 | Pass |
| NVNT | 3-DH5 | 2480 | Ant1 | No-Hopping | -56.16 | -20 | Pass |

Test Graphs

Band Edge NVNT 1-DH5 2402MHz Ant1 No-Hopping Ref




Band Edge NVNT 1-DH5 2402MHz Ant1 No-Hopping Emission



Band Edge NVNT 1-DH5 2480MHz Ant1 No-Hopping Ref




Band Edge NVNT 1-DH5 2480MHz Ant1 No-Hopping Emission



Band Edge NVNT 2-DH5 2402MHz Ant1 No-Hopping Ref




Band Edge NVNT 2-DH5 2402MHz Ant1 No-Hopping Emission



Band Edge NVNT 2-DH5 2480MHz Ant1 No-Hopping Ref




Band Edge NVNT 2-DH5 2480MHz Ant1 No-Hopping Emission



Band Edge NVNT 3-DH5 2402MHz Ant1 No-Hopping Ref




Band Edge NVNT 3-DH5 2402MHz Ant1 No-Hopping Emission



Band Edge NVNT 3-DH5 2480MHz Ant1 No-Hopping Ref




Band Edge NVNT 3-DH5 2480MHz Ant1 No-Hopping Emission



## (Hopping)

| Condition | Mode | Frequency (MHz) | Antenna | Hopping Mode | Max Value (dBc) | Limit (dBc) | Verdict |
|---|---|---|---|---|---|---|---|
| NVNT | 1-DH5 | 2402 | Ant1 | Hopping | -56.36 | -20 | Pass |
| NVNT | 1-DH5 | 2480 | Ant1 | Hopping | -55.34 | -20 | Pass |
| NVNT | 2-DH5 | 2402 | Ant1 | Hopping | -54.25 | -20 | Pass |
| NVNT | 2-DH5 | 2480 | Ant1 | Hopping | -54.62 | -20 | Pass |
| NVNT | 3-DH5 | 2402 | Ant1 | Hopping | -53.95 | -20 | Pass |
| NVNT | 3-DH5 | 2480 | Ant1 | Hopping | -55.15 | -20 | Pass |

Test Graphs

Band Edge(Hopping) NVNT 1-DH5 2402MHz Ant1 Hopping Ref




Band Edge(Hopping) NVNT 1-DH5 2402MHz Ant1 Hopping Emission



Band Edge(Hopping) NVNT 1-DH5 2480MHz Ant1 Hopping Ref




Band Edge(Hopping) NVNT 1-DH5 2480MHz Ant1 Hopping Emission



Band Edge(Hopping) NVNT 2-DH5 2402MHz Ant1 Hopping Ref




Band Edge(Hopping) NVNT 2-DH5 2402MHz Ant1 Hopping Emission



Band Edge(Hopping) NVNT 2-DH5 2480MHz Ant1 Hopping Ref




Band Edge(Hopping) NVNT 2-DH5 2480MHz Ant1 Hopping Emission