







10. 20 dB Bandwidth

10.1 Block Diagram Of Test Setup



10.2 Limit


N/A



10.3 Test procedure



1. Set RBW = 30kHz.
2. Set the video bandwidth (VBW) $\geq 3 \times$ RBW.
3. Detector = Peak.
4. Trace mode = max hold.
5. Sweep = auto couple.
6. Allow the trace to stabilize.
7. Measure the maximum width of the emission that is constrained by the frequencies associated with the two outermost amplitude points (upper and lower frequencies) that are attenuated by 6 dB relative to the maximum level measured in the fundamental emission.

10.4 Test Result



Condition	Mode	Frequency (MHz)	-20 dB Bandwidth (MHz)	Verdict
NVNT	1-DH1	2402	0.902	Pass
NVNT	1-DH1	2441	0.915	Pass
NVNT	1-DH1	2480	0.912	Pass
NVNT	2-DH1	2402	1.264	Pass
NVNT	2-DH1	2441	1.255	Pass
NVNT	2-DH1	2480	1.255	Pass
NVNT	3-DH1	2402	1.248	Pass
NVNT	3-DH1	2441	1.25	Pass
NVNT	3-DH1	2480	1.239	Pass









CO. LTD.





11. Maximum Peak Output Power

11.1 Block Diagram Of Test Setup



11.2 Limit


FCC Part15 (15.247) , Subpart C				
Section	Test Item	Limit	Frequency Range (MHz)	Result
15.247(b)(1)	Peak Output Power	0.125 watt or 21dBm	2400-2483.5	PASS


11.3 Test procedure

1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum.
2. Set the spectrum analyzer: RBW = 2MHz. VBW = 6MHz. Sweep = auto; Detector Function = Peak.
3. Keep the EUT in transmitting at lowest, medium and highest channel individually. Record the max value.


11.4 Test Result

Condition	Mode	Frequency (MHz)	Conducted Power (dBm)	Limit (dBm)	Verdict
NVNT	1-DH1	2402	-1.98	21	Pass
NVNT	1-DH1	2441	-2.41	21	Pass
NVNT	1-DH1	2480	-2.79	21	Pass
NVNT	2-DH1	2402	1.12	21	Pass
NVNT	2-DH1	2441	0.6	21	Pass
NVNT	2-DH1	2480	-0.41	21	Pass
NVNT	3-DH1	2402	1.61	21	Pass
NVNT	3-DH1	2441	1.18	21	Pass
NVNT	3-DH1	2480	0.11	21	Pass








STING
C
ED
A



CO., LTD.



SHENZHEN



12. Hopping Channel Separation

12.1 Block Diagram Of Test Setup



12.2 Limit


Frequency hopping systems shall have hopping channel carrier frequencies separated by a minimum of 25 kHz or the 20 dB bandwidth of the hopping channel, whichever is greater. Alternatively, frequency hopping systems operating in the 2400-2483.5 MHz band may have hopping channel carrier frequencies that are separated by 25 kHz or two-thirds of the 20 dB bandwidth of the hopping channel, whichever is greater, provided the systems operate with an output power no greater than 0.125W.



12.3 Test procedure



1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum.
2. Set the spectrum analyzer: RBW = 30kHz. VBW = 100kHz , Span = 2.0MHz. Sweep = auto; Detector Function = Peak. Trace = Max hold.
3. Allow the trace to stabilize. Use the marker-delta function to determine the separation between the peaks of the adjacent channels. The limit is specified in one of the subparagraphs of this Section Submit this plot.



12.4 Test Result

Condition	Mode	Hopping Freq1 (MHz)	Hopping Freq2 (MHz)	HFS (MHz)	Limit (MHz)	Verdict
NVNT	1-DH1	2401.852	2402.85	0.998	0.601	Pass
NVNT	1-DH1	2440.85	2441.85	1	0.61	Pass
NVNT	1-DH1	2478.85	2479.85	1	0.608	Pass
NVNT	2-DH1	2401.85	2402.85	1	0.843	Pass
NVNT	2-DH1	2440.85	2441.852	1.002	0.837	Pass
NVNT	2-DH1	2478.85	2479.848	0.998	0.837	Pass
NVNT	3-DH1	2402.038	2403.036	0.998	0.832	Pass
NVNT	3-DH1	2441.036	2442.036	1	0.833	Pass
NVNT	3-DH1	2479.036	2480.04	1.004	0.826	Pass










SHENZHEN



13. Number Of Hopping Frequency

13.1 Block Diagram Of Test Setup



13.2 Limit


Frequency hopping systems in the 2400-2483.5 MHz band shall use at least 15 channels.


13.3 Test procedure

1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum.
2. Set the spectrum analyzer: RBW = 100kHz. VBW = 300kHz. Sweep = auto; Detector Function = Peak. Trace = Max hold.
3. Allow the trace to stabilize. It may prove necessary to break the span up to sections. in order to clearly show all of the hopping frequencies. The limit is specified in one of the subparagraphs of this Section.
4. Set the spectrum analyzer: Start Frequency = 2.4GHz, Stop Frequency = 2.4835GHz. Sweep=auto;

13.4 Test Result

Condition	Mode	Hopping Number	Limit	Verdict
NVNT	1-DH1	79	15	Pass
NVNT	2-DH1	79	15	Pass
NVNT	3-DH1	79	15	Pass





14. Dwell Time

14.1 Block Diagram Of Test Setup



14.2 Limit

≤0.4 Second


14.3 Test procedure



1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum.
2. Set spectrum analyzer span = 0. Centred on a hopping channel;
3. Set RBW = 1MHz and VBW = 3MHz. Sweep = as necessary to capture the entire dwell time per hopping channel. Set the EUT for DH5, DH3 and DH1 packet transmitting.
4. Use the marker-delta function to determine the dwell time. If this value varies with different modes of operation (e.g.. data rate. modulation format. etc.). repeat this test for each variation. The limit is specified in one of the subparagraphs of this Section. Submit this plot(s).



14.4 Test Result



Condition	Mode	Frequency (MHz)	Pulse Time (ms)	Total Dwell Time (ms)	Burst Count	Period Time (ms)	Limit (ms)	Verdict
NVNT	1-DH1	2441	0.39	123.24	316	31600	400	Pass
NVNT	1-DH3	2441	1.643	266.166	162	31600	400	Pass
NVNT	1-DH5	2441	2.892	297.876	103	31600	400	Pass
NVNT	2-DH1	2441	0.398	126.166	317	31600	400	Pass
NVNT	2-DH3	2441	1.651	270.764	164	31600	400	Pass
NVNT	2-DH5	2441	2.895	289.5	100	31600	400	Pass
NVNT	3-DH1	2441	0.396	126.324	319	31600	400	Pass
NVNT	3-DH3	2441	1.65	265.65	161	31600	400	Pass
NVNT	3-DH5	2441	2.898	289.8	100	31600	400	Pass



Note: Total Dwell Time (ms)= Pulse Time (ms)* Burst Count





















CO., LTD.







15. Antenna Requirement

15.1 Limit

15.203 requirement: For intentional device, according to 15.203: an intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device.

15.2 Test Result

The EUT antenna is Internal antenna, fulfill the requirement of this section.

16. EUT Photographs

EUT Photo 1



NOTE: Appendix-Photographs Of EUT Constructional Details.


17. EUT Test Setup Photographs

Conducted Measurement Photo



Radiated Measurement Photos





STATEMENT

1. The equipment lists are traceable to the national reference standards.
2. The test report can not be partially copied unless prior written approval is issued from our lab.
3. The test report is invalid without the "special seal for inspection and testing".
4. The test report is invalid without the signature of the approver.
5. The test process and test result is only related to the Unit Under Test.
6. Sample information is provided by the client and the laboratory is not responsible for its authenticity.
7. The quality system of our laboratory is in accordance with ISO/IEC17025.
8. If there is any objection to this test report, the client should inform issuing laboratory within 15 days from the date of receiving test report.

Address:

1-2/F., Building B, Pengzhou Industrial Park, No.158, Fuyuan 1st Road, Zhancheng, Fuhai Subdistrict, Bao'an District, Shenzhen, Guangdong, China

TEL: 400-788-9558

P.C.: 518103

FAX: 0755-33229357

Website: <http://www.chnbctc.com>

Consultation E-mail: bctc@bctc-lab.com.cn

Complaint/Advice E-mail: advice@bctc-lab.com.cn

***** END *****

2017