



SAR TEST REPORT

For

Wishtel Pvt Ltd

Tablet PC

Test Model: IRA T1015

Prepared for : Wishtel Pvt Ltd
Address : 4, Champaklal Industrail Estate, Sion East, Mumbai, MH - 400022, Mumbai, India
Prepared by : Shenzhen LCS Compliance Testing Laboratory Ltd.
Address : 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park
Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel : (+86)755-82591330
Fax : (+86)755-82591332
Web : www.LCS-cert.com
Mail : webmaster@LCS-cert.com

Date of receipt of test sample : December 10, 2024
Number of tested samples : 1
Sample number : A12024283-1
Serial number : Prototype
Date of Test : December 10, 2024 ~ December 16, 2024
Date of Report : December 17, 2024



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: (+86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity

**SAR TEST REPORT**

Report Reference No.....: LCSA12024283EB

Date Of Issue.....: December 17, 2024

Testing Laboratory Name.....: Shenzhen LCS Compliance Testing Laboratory Ltd.

Address.....: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Testing Location/ Procedure.....: Full application of Harmonised standards ☒
Partial application of Harmonised standards ☐
Other standard testing method ☐**Applicant's Name.....: Wishtel Pvt Ltd**

Address.....: 4, Champaklal Industrail Estate, Sion East, Mumbai, MH - 400022, Mumbai, India

Test Specification:

Standard.....: FCC 47CFR §2.1093, ANSI/IEEE C95.1-2019, IEEE 1528-2013

Test Report Form No.....: TRF-4-E-102 A/0

TRF Originator.....: Shenzhen LCS Compliance Testing Laboratory Ltd.

Master TRF.....: Dated 2014-09

Shenzhen LCS Compliance Testing Laboratory Ltd. All rights reserved.

This publication may be reproduced in whole or in part for non-commercial purposes as long as the Shenzhen LCS Compliance Testing Laboratory Ltd. is acknowledged as copyright owner and source of the material. Shenzhen LCS Compliance Testing Laboratory Ltd. takes noresponsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.

Test Item Description.....: Tablet PC

Trade Mark.....: Wishtel

Model/Type Reference.....: IRA T1015

Ratings.....: Input: 5V=2000mA
For AC Adapter Input: 100-240V~, 50/60Hz, 0.35A MAX
Adapter Output: 5V=2000mA
DC 3.8V by Rechargeable Li-ion Battery, 7000mAh**Result: Positive****Compiled by:**

Jay Zhan

Jay Zhan/ File administrators

Supervised by:

Cary Luo

Cary Luo / Technique principal

Approved by:

Gavin Liang

Gavin Liang/ Manager





SAR -- TEST REPORT

Test Report No. : LCSA12024283EB		December 17, 2024 Date of issue
EUT.....	: Tablet PC	
Type/Model	: IRA T1015	
Applicant..... : Wishtel Pvt Ltd		
Address..... : 4, Champaklal Industrail Estate, Sion East, Mumbai, MH - 400022, Mumbai, India		
Telephone..... : /		
Fax..... : /		
Manufacturer..... : Wishtel Pvt Ltd		
Address..... : 4, Champaklal Industrail Estate, Sion East, Mumbai, MH - 400022, Mumbai, India		
Telephone..... :		
Fax..... : /		
Factory..... : /		
Address..... : /		
Telephone..... : /		
Fax..... : /		

Test Result	Positive
-------------	----------

The test report merely corresponds to the test sample.
It is not permitted to copy extracts of these test result without the written permission of the test laboratory.





Revision History

Revision	Issue Date	Revision Content	Revised By
000	December 17, 2024	Initial Issue	---





TABLE OF CONTENTS

1. TEST STANDARDS AND TEST DESCRIPTION	6
1.1. STATEMENT OF COMPLIANCE	6
1.2. TEST LOCATION	7
1.3. TEST FACILITY	8
1.4. TEST LABORATORY ENVIRONMENT	9
1.5. PRODUCT DESCRIPTION	10
1.6. DUT ANTENNA LOCATIONS	13
1.7. TEST SPECIFICATION	14
1.8. RF EXPOSURE LIMITS	15
1.9. EQUIPMENT LIST	16
2. SAR MEASUREMENTS SYSTEM CONFIGURATION	17
2.1. SAR MEASUREMENT SYSTEM	17
2.2. ISOTROPIC E-FIELD PROBE EX3DV4	19
2.3. DATA ACQUISITION ELECTRONICS (DAE)	20
2.4. SAM TWIN PHANTOM	20
2.5. ELI PHANTOM	21
2.6. DEVICE HOLDER FOR TRANSMITTERS	22
2.7. MEASUREMENT PROCEDURE	23
3. SAR MEASUREMENT VARIABILITY AND UNCERTAINTY	27
3.1. SAR MEASUREMENT VARIABILITY	27
3.2. SAR MEASUREMENT UNCERTAINTY	27
4. DESCRIPTION OF TEST POSITION	28
4.1. TEST POSITIONS CONFIGURATION	28
5. SAR SYSTEM VERIFICATION PROCEDURE	29
5.1. TISSUE SIMULATE LIQUID	29
5.2. SAR SYSTEM CHECK	31
6. SAR MEASUREMENT PROCEDURE	34
6.1. CONDUCTED POWER MEASUREMENT	34
6.2. GSM TEST CONFIGURATION	34
6.3. UMTS TEST CONFIGURATION	34
6.4. LTE TEST CONFIGURATION	36
6.5. WIFI TEST CONFIGURATION	36
6.6. POWER REDUCTION	39
6.7. POWER DRIFT	39
7. TEST CONDITIONS AND RESULTS	40
7.1. CONDUCTED POWER RESULTS	40
7.2. STAND-ALONE SAR TEST EVALUATION	62
7.3. SAR MEASUREMENT RESULTS	66
7.4. MULTIPLE TRANSMITTER EVALUATION	76
7.5. MEASUREMENT UNCERTAINTY	79





1. TEST STANDARDS AND TEST DESCRIPTION

1.1. Statement of Compliance

The maximum of results of SAR found during testing for IRA T1015 are follows:

<Highest Reported standalone SAR Summary>

Classment Class	Frequency Band	Body (Report SAR1-g (W/kg))
		(Separation Distance 0mm)
PCB	GSM 850	0.490
	GSM1900	0.697
	WCDMA Band II	0.701
	WCDMA Band V	0.500
	LTE Band 5	0.609
	LTE Band 7	0.782
	LTE Band 38	0.774
	LTE Band 41	0.758
DTS	WIFI2.4G	0.496
NII	WIFI5.2G	0.289
	WIFI5.3G	0.243
	WIFI5.5G	0.396
	WIFI5.8G	0.278

Note

1) This device is in compliance with Specific Absorption Rate (SAR) for general population/uncontrolled exposure Limb limits(4 W/kg) specified in FCC 47 CFR part 2 (2.1093) and ANSI/IEEE C95.1-2005, and had been tested in accordance with the measurement methods and procedures specified in IEEE 1528-2013.

<Highest Reported simultaneous SAR Summary>

Exposure Position	Classment Class	Report SAR1-g (W/kg)	Highest Reported Simultaneous Transmission SAR1-g (W/kg)
Body	PCB	0.782	1.278
	DTS	0.496	





1.2. Test Location

Company: Shenzhen LCS Compliance Testing Laboratory Ltd.
Address: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Telephone: (+86)755-82591330
Fax: (+86)755-82591330
Web: www.LCS-cert.com
E-mail: webmaster@LCS-cert.com



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: (+86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity



1.3. Test Facility

The test facility is recognized, certified, or accredited by the following organizations:

Site Description
SAR Lab.

:	NVLAP	Accreditation	Code	is	600167-0.
	FCC	Designation	Number	is	CN5024.
	CAB	identifier	is		CN0071.
	CNAS Registration Number is L4595.				
	Test Firm Registration Number: 254912.				





1.4. Test Laboratory Environment

Temperature	Min. = 18°C, Max. = 25 °C
Relative humidity	Min. = 30%, Max. = 70%
Ground system resistance	< 0.5
Atmospheric pressure:	950-1050mbar
Ambient noise is checked and found very low and in compliance with requirement of standards. Reflection of surrounding objects is minimized and in compliance with requirement of standards.	





1.5. Product Description

The **Wishtel Pvt Ltd's** Model: IRA T1015 or the "EUT" as referred to in this report; more general information as follows, for more details, refer to the user's manual of the EUT.

EUT	: Tablet PC
Test Model	: IRA T1015
Ratings	: Input: 5V $\overline{\text{---}}$ 2000mA For AC Adapter Input: 100-240V~, 50/60Hz, 0.35A MAX Adapter Output: 5V $\overline{\text{---}}$ 2000mA DC 3.8V by Rechargeable Li-ion Battery, 7000mAh
Hardware Version	: S866T-T310-V1.0
Software Version	: T1015_V1.1_20241108
Bluetooth	:
Frequency Range	: 2402MHz~2480MHz
Channel Number	: 79 channels for Bluetooth V5.0 (DSS) 40 channels for Bluetooth V5.0 (DTS)
Channel Spacing	: 1MHz for Bluetooth V5.0 (DSS) 2MHz for Bluetooth V5.0 (DTS)
Modulation Type	: GFSK, $\pi/4$ -DQPSK, 8-DPSK for Bluetooth V5.0 (DSS) GFSK for Bluetooth V5.0 (DTS)
Bluetooth Version	: V5.0
Antenna Description	: FPC Antenna, 2.0dBi(Max.)
WIFI(2.4G Band)	:
Frequency Range	: 2412MHz~2462MHz
Channel Spacing	: 5MHz
Channel Number	: 11 Channels for 20MHz bandwidth (2412~2462MHz) 7 Channels for 40MHz bandwidth (2422~2452MHz)
Modulation Type	: IEEE 802.11b: DSSS (CCK, DQPSK, DBPSK) IEEE 802.11g: OFDM (64QAM, 16QAM, QPSK, BPSK) IEEE 802.11n: OFDM (64QAM, 16QAM, QPSK, BPSK)
Antenna Description	: FPC Antenna, 2.0dBi(Max.)
WIFI(5.2G Band)	:
Frequency Range	: 5180MHz~5240MHz
Channel Number	: 4 Channels for 20MHz bandwidth(5180MHz~5240MHz) 2 channels for 40MHz bandwidth(5190MHz~5230MHz) 1 channels for 80MHz bandwidth(5210MHz)
Modulation Type	: IEEE 802.11a/n: OFDM (64QAM, 16QAM, QPSK, BPSK) IEEE 802.11ac: OFDM (256QAM, 64QAM, 16QAM, QPSK, BPSK)
Antenna Description	: FPC Antenna, 3.28dBi(Max.)
WIFI(5.3G Band)	:
Frequency Range	: 5260MHz~5320MHz
Channel Number	: 4 Channels for 20MHz bandwidth(5260MHz~5320MHz) 2 channels for 40MHz bandwidth(5270MHz~5310MHz) 1 channels for 80MHz bandwidth(5290MHz)
Modulation Type	: IEEE 802.11a/n: OFDM (64QAM, 16QAM, QPSK, BPSK) IEEE 802.11ac: OFDM (256QAM, 64QAM, 16QAM, QPSK, BPSK)





Antenna Description : FPC Antenna, 3.28dBi(Max.)

WIFI(5.5G Band) :

Frequency Range : 5500MHz~5700MHz

Channel Number : 11 Channels for 20MHz bandwidth(5500MHz~5700MHz)
5 Channels for 40MHz bandwidth(5510MHz~5670MHz)
2 Channels for 80MHz bandwidth(5530MHz, 5610MHz)

Modulation Type : IEEE 802.11a/n: OFDM (64QAM, 16QAM, QPSK, BPSK)
IEEE 802.11ac: OFDM (256QAM, 64QAM, 16QAM, QPSK, BPSK)

Antenna Description : FPC Antenna, 3.28dBi(Max.)

WIFI(5.8G Band) :

Frequency Range : 5745MHz~5825MHz

Channel Number : 5 channels for 20MHz bandwidth(5745MHz~5825MHz)
2 channels for 40MHz bandwidth(5755MHz~5795MHz)
1 channels for 80MHz bandwidth(5775MHz)

Modulation Type : IEEE 802.11a/n: OFDM (64QAM, 16QAM, QPSK, BPSK)
IEEE 802.11ac: OFDM (256QAM, 64QAM, 16QAM, QPSK, BPSK)

Antenna Description : FPC Antenna, 3.28dBi(Max.)

2G :

Support Band : ☒ GSM 900 (EU-Band) ☒ DCS 1800 (EU-Band)
☒ GSM 850 (U.S.-Band) ☒ PCS 1900 (U.S.-Band)

Release Version : R99

GPRS Class : Class 12

EGPRS Class : Class 12

Type Of Modulation : GMSK for GSM/GPRS; GMSK/8PSK for EGPRS

Antenna Description : FPC Antenna
-2.88dBi (max.) For GSM 850
-4.12dBi (max.) For PCS 1900

3G :

Support Band : ☒ WCDMA Band I (EU-Band)
☒ WCDMA Band II (U.S.-Band)
☒ WCDMA Band V (U.S.-Band)
☒ WCDMA Band VIII (EU-Band)

Release Version : R10

Type Of Modulation : QPSK,16QAM

Antenna Description : FPC Antenna
-4.12dBi (max.) For WCDMA Band II
-2.88dBi (max.) For WCDMA Band V

LTE :

Support Band : ☒ E-UTRA Band 5(U.S.-Band)
☒ E-UTRA Band 7(U.S.-Band)
☒ E-UTRA Band 38(U.S.-Band)
☒ E-UTRA Band 41(U.S.-Band)

LTE Release Version : R10

Type Of Modulation : QPSK/16QAM

Antenna Description : FPC Antenna
-2.88dBi (max.) For E-UTRA Band 5
-3.41dBi (max.) For E-UTRA Band 7





-3.43dBi (max.) For E-UTRA Band 38

-3.41dBi (max.) For E-UTRA Band 41

Power Class : Class 3

GPS Function : Support and only RX




Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity

1.6. DUT Antenna Locations



Note:

- 1) Main Antenna: GSM850/1900, WCDMA Band II/V, LTE Band 5/7/38/41, the Div ant only for Rx.
- 2) WIFI&BT Antenna: WIFI 2.4G/5.2G/5.3G/5.5G/5.8G, Bluetooth

Per KDB 616217, the diagonal length is > 200mm, the device is considered a "tablet" device and needed to test 0mm 1-g body SAR.

Distance from the antenna to the EUT edge(mm)						
ANT	Front	Back	Left	Right	Top	Bottom
MAIN	5	5	128	55	5	152
WIFI&BT	5	5	64	152	5	152

When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.





1.7. Test Specification

Identity	Document Title
FCC 47CFR §2.1093	Radiofrequency Radiation Exposure Evaluation: Portable Devices
ANSI/IEEE C95.1-1992	IEEE Standard for Safety Levels with Respect to Human Exposure to Radio Frequency Electromagnetic Fields, 3 kHz – 300 GHz.
IEEE 1528-2013	Recommended Practice for Determining the Peak Spatial-Average Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques
KDB 941225 D01	3G SAR Measurement Procedures v03r01
KDB 941225 D05	SAR for LTE Devices v02r05
KDB 941225 D06	Hotspot Mode SAR v02r01
KDB 248227 D01	SAR Guidance for IEEE 802.11 Wi-Fi SAR v02r02
KDB 648474 D04	Handset SAR v01r03
KDB 447498 D01	General RF Exposure Guidance v06
KDB 865664 D01	SAR Measurement 100 MHz to 6 GHz v01r04
KDB 865664 D02	RF Exposure Reporting v01r02
KDB 690783 D01	SAR Listings on Grants v01r03





1.8. RF exposure limits

Human Exposure	Uncontrolled Environment General Population	Controlled Environment Occupational
Spatial Peak SAR* (Brain*Trunk)	1.60 mW/g	8.00 mW/g
Spatial Average SAR** (Whole Body)	0.08 mW/g	0.40 mW/g
Spatial Peak SAR*** (Hands/Feet/Ankle/Wrist)	4.00 mW/g	20.00 mW/g

Notes:

* The Spatial Peak value of the SAR averaged over any 1 gram of tissue (defined as a tissue volume in the shape of a cube) and over the appropriate averaging time

** The Spatial Average value of the SAR averaged over the whole body.

*** The Spatial Peak value of the SAR averaged over any 10 grams of tissue (defined as a tissue volume in the shape of a cube) and over the appropriate averaging time.

Uncontrolled Environments are defined as locations where there is the exposure of individuals who have no knowledge or control of their exposure.

Controlled Environments are defined as locations where there is exposure that may be incurred by persons who are aware of the potential for exposure, (i.e. as a result of employment or occupation.)





1.9. Equipment list

Test Platform		SPEAG DASY5 Professional				
Description		SAR Test System (Frequency range 300MHz-6GHz)				
Software Reference		DASY52; SEMCAD X				
Hardware Reference						
Equipment		Manufacturer	Model	Serial Number	Calibration Date	Due date of calibration
☒	PC	Lenovo	NA	NA	NA ¹	NA ¹
☒	Twin Phantom	SPEAG	SAM V5.0	1850	NA ¹	NA ¹
☒	ELI Phantom	SPEAG	ELI V6.0	2010	NA ¹	NA ¹
☒	DAE	SPEAG	DAE3	373	2024/1/3	2025/1/2
☒	E-Field Probe	SPEAG	EX3DV4	3805	2024/11/23	2025/11/22
☒	Validation Kits	SPEAG	D835V2	4d124	2023/10/24	2026/10/23
☒	Validation Kits	SPEAG	D1900V2	5d055	2023/10/20	2026/10/19
☒	Validation Kits	SPEAG	D2450V2	808	2023/10/23	2026/10/22
☒	Validation Kits	SPEAG	D2600V2	1071	2023/6/20	2026/6/19
☒	Validation Kits	SPEAG	D5GHzV2	1046	2023/10/23	2026/10/22
☒	Agilent Network Analyzer	Agilent	8753E	SU38432944	2024/6/6	2025/6/5
☒	Dielectric Probe Kit	SPEAG	DAK3.5	1425	2024/6/6	2025/6/5
☒	Universal Radio Communication Tester	R&S	CMW500	42115	2024/10/08	2025/10/07
☒	Directional Coupler	MCLI/USA	4426-20	03746	2024/6/6	2025/6/5
☒	Power meter	Agilent	E4419B	MY45104493	2024/10/08	2025/10/07
☒	Power meter	Agilent	E4419B	MY45100308	2024/10/08	2025/10/07
☒	Power sensor	Agilent	E9301H	MY41495616	2024/10/08	2025/10/07
☒	Power sensor	Agilent	E9301H	MY41495234	2024/10/08	2025/10/07
☒	Signal Generator	Agilent	E4438C	MY49072627	2024/6/6	2025/6/5
☒	Broadband Preamplifier	/	BP-01M18G	P190501	2024/6/6	2025/6/5
☒	DC POWER SUPPLY	I-SHENG	SP-504	NA	2024/6/6	2025/6/5
☒	Speed reading thermometer	HTC-1	NA	LCS-E-138	2024/6/6	2025/6/5

Note: All the equipments are within the valid period when the tests are performed.

“1” : NA as this is not measurement equipment.



2. SAR MEASUREMENTS SYSTEM CONFIGURATION

2.1. SAR Measurement System

This SAR Measurement System uses a Computer-controlled 3-D stepper motor system (SPEAG DASY5 professional system). A E-field probe is used to determine the internal electric fields. The SAR can be obtained from the equation $SAR = \sigma (|E|^2) / \rho$ where σ and ρ are the conductivity and mass density of the tissue-Simulate.


The DASY5 system for performing compliance tests consists of the following items:

A standard high precision 6-axis robot (Stabile RX family) with controller, teach pendant and software .An arm extension for accommodation the data acquisition electronics (DAE).

A dosimetric probe, i.e., an isotropic E-field probe optimized and calibrated for usage in tissue simulating liquid. The probe is equipped with an optical surface detector system.

A data acquisition electronics (DAE) which performs the signal amplification, signal multiplexing, AD-conversion, offset measurements, mechanical surface detection, collision detection, etc. The unit is battery powered with standard or rechargeable batteries. The signal is optically transmitted to the EOC.

The Electro-optical converter (EOC) performs the conversion between optical and electrical of the signals for the digital communication to DAE and for the analog signal from the optical surface detection. The EOC is connected to the measurement server.



F-1. SAR Measurement System Configuration





- The function of the measurement server is to perform the time critical tasks such as signal filtering, control of the robot operation and fast movement interrupts.
- A probe alignment unit which improves the (absolute) accuracy of the probe positioning.
- A computer operating Windows 7.
- DASY5 software.
- Remote control with teach pendant and additional circuitry for robot safety such as warning lamps, etc.
- The SAM twin phantom enabling testing left-hand, right-hand and Body Worn usage.
- The device holder for handheld mobile phones.
- Tissue simulating liquid mixed according to the given recipes.
- Validation dipole kits allowing to validating the proper functioning of the system.






2.2. Isotropic E-field Probe EX3DV4


	Symmetrical design with triangular core Built-in shielding against static charges PEEK enclosure material (resistant to organic solvents, e.g., DGBE)
Calibration	ISO/IEC 17025 calibration service available.
Frequency	10 MHz to > 6 GHz Linearity: ± 0.2 dB (30 MHz to 6 GHz)
Directivity	± 0.3 dB in TSL (rotation around probe axis) ± 0.5 dB in TSL (rotation normal to probe axis)
Dynamic Range	10 μ W/g to > 100 mW/g Linearity: ± 0.2 dB (noise: typically < 1 μ W/g)
Dimensions	Overall length: 337 mm (Tip: 20 mm) Tip diameter: 2.5 mm (Body: 12 mm) Typical distance from probe tip to dipole centers: 1 mm
Application	High precision dosimetric measurements in any exposure scenario (e.g., very strong gradient fields); the only probe that enables compliance testing for frequencies up to 6 GHz with precision of better 30%.
Compatibility	DASY3, DASY4, DASY52 SAR and higher, EASY4/MRI



2.3. Data Acquisition Electronics (DAE)

Model	DAE	
Construction	Signal amplifier, multiplexer, A/D converter and control logic. Serial optical link for communication with DASY4/5 embedded system (fully remote controlled). Two step probe touch detector for mechanical surface detection and emergency robot stop.	
Measurement Range	-100 to +300 mV (16 bit resolution and two range settings: 4mV,400mV)	
Input Offset Voltage	< 5μV (with auto zero)	
Input Bias Current	< 50 f A	
Dimensions	60 x 60 x 68 mm	

2.4. SAM Twin Phantom


Material	Vinylester, glass fiber reinforced (VE-GF)	
Liquid Compatibility	Compatible with all SPEAG tissue simulating liquids (incl. DGBE type)	
Shell Thickness	2 ± 0.2 mm (6 ± 0.2 mm at ear point)	
Dimensions (incl. Wooden Support)	Length: 1000 mm Width: 500 mm Height: adjustable feet	
Filling Volume	approx. 25 liters	
Wooden Support	SPEAG standard phantom table	

The shell corresponds to the specifications of the Specific Anthropomorphic Mannequin (SAM) phantom defined in IEEE 1528 and IEC 62209-1. It enables the dosimetric evaluation of left and right hand phone usage as well as body mounted usage at the flat phantom region. A cover prevents evaporation of the liquid. Reference markings on the phantom allow the complete setup of all predefined phantom positions and measurement grids by teaching three points with the robot.

Twin SAM V5.0 has the same shell geometry and is manufactured from the same material as Twin SAM V4.0, but has reinforced top structure.



2.5. ELI Phantom

Material	Vinylester, glass fiber reinforced (VE-GF)	
Liquid Compatibility	Compatible with all SPEAG tissue simulating liquids (incl. DGBE type)	
Shell Thickness	2.0 ± 0.2 mm (bottom plate)	
Dimensions	Major axis: 600 mm Minor axis: 400 mm	
Filling Volume	approx. 30 liters	
Wooden Support	SPEAG standard phantom table	

Phantom for compliance testing of handheld and body-mounted wireless devices in the frequency range of 30 MHz to 6 GHz. ELI is fully compatible with the IEC 62209-2 standard and all known tissue simulating liquids. ELI has been optimized regarding its performance and can be integrated into our standard phantom tables. A cover prevents evaporation of the liquid. Reference markings on the phantom allow installation of the complete setup, including all predefined phantom positions and measurement grids, by teaching three points. The phantom is compatible with all SPEAG dosimetric probes and dipoles.

ELI V5.0 has the same shell geometry and is manufactured from the same material as ELI4, but has reinforced top structure.



2.6. Device Holder for Transmitters



F-2. Device Holder for Transmitters

- The DASY device holder is designed to cope with different positions given in the standard. It has two scales for the device rotation (with respect to the body axis) and the device inclination (with respect to the line between the ear reference points). The rotation centres for both scales are the ear reference point (ERP). Thus the device needs no repositioning when changing the angles.
- The DASY device holder has been made out of low-loss POM material having the following dielectric parameters: relative permittivity $\epsilon=3$ and loss tangent $\delta=0.02$. The amount of dielectric material has been reduced in the closest vicinity of the device, since measurements have suggested that the influence of the clamp on the test results could thus be lowered.





2.7. Measurement procedure

2.7.1. Scanning procedure

Step 1: Power reference measurement

The “reference” and “drift” measurements are located at the beginning and end of the batch process. They measure the field drift at one single point in the liquid over the complete procedure.

Step 2: Area scan

The SAR distribution at the exposed side of the head was measured at a distance of 4mm from the inner surface of the shell. The area covered the entire dimension of the head and the horizontal grid spacing was 15mm*15mm or 12mm*12mm or 10mm*10mm. Based on the area scan data, the area of the maximum absorption was determined by spline interpolation.

Step 3: Zoom scan

Around this point, a volume of 32mm*32mm*30mm ($f \leq 2\text{GHz}$), 30mm*30mm*30mm (f for 2-3GHz) and 24mm*24mm*22mm (f for 5-6GHz) was assessed by measuring 5x5x7 points ($f \leq 2\text{GHz}$), 7x7x7 points (f for 2-3GHz) and 7x7x12 points (f for 5-6GHz). On this basis of this data set, the spatial peak SAR value was evaluated with the following procedure:

The data at the surface was extrapolated, since the centre of the dipoles is 2.0mm away from the tip of the probe and the distance between the surface and the lowest measuring point is 1.2mm. (This can be variable. Refer to the probe specification). The extrapolation was based on a least square algorithm. A polynomial of the fourth order was calculated through the points in z-axes. This polynomial was then used to evaluate the points between the surface and the probe tip. The maximum interpolated value was searched with a straight-forward algorithm. Around this maximum the SAR values averaged over the spatial volumes (1g or 10g) were computed using the 3D-Spline interpolation algorithm. The volume was integrated with the trapezoidal algorithm. One thousand points were interpolated to calculate the average. All neighbouring volumes were evaluated until no neighboring volume with a higher average value was found.

The area and zoom scan resolutions specified in the table below must be applied to the SAR measurements. Probe boundary effect error compensation is required for measurements with the probe tip closer than half a probe tip diameter to the phantom surface. Both the probe tip diameter and sensor offset distance must satisfy measurement protocols; to ensure probe boundary effect errors are minimized and the higher fields closest to the phantom surface can be correctly measured and extrapolated to the phantom surface for computing 1-g SAR. Tolerances of the post-processing algorithms must be verified by the test laboratory for the scan resolutions used in the SAR measurements, according to the reference distribution functions specified in IEEE Std. 1528-2013.





		≤ 3 GHz	> 3 GHz
Maximum distance from closest measurement point (geometric center of probe sensors) to phantom surface		5 ± 1 mm	$\frac{1}{2} \cdot \delta \cdot \ln(2) \pm 0.5$ mm
Maximum probe angle from probe axis to phantom surface normal at the measurement location		$30^\circ \pm 1^\circ$	$20^\circ \pm 1^\circ$
Maximum area scan spatial resolution: Δx_{Area} , Δy_{Area}		≤ 2 GHz: ≤ 15 mm $2 - 3$ GHz: ≤ 12 mm	$3 - 4$ GHz: ≤ 12 mm $4 - 6$ GHz: ≤ 10 mm
		When the x or y dimension of the test device, in the measurement plane orientation, is smaller than the above, the measurement resolution must be $\leq$ the corresponding x or y dimension of the test device with at least one measurement point on the test device.	
Maximum zoom scan spatial resolution: Δx_{Zoom} , Δy_{Zoom}		≤ 2 GHz: ≤ 8 mm $2 - 3$ GHz: ≤ 5 mm*	$3 - 4$ GHz: ≤ 5 mm* $4 - 6$ GHz: ≤ 4 mm*
Maximum zoom scan spatial resolution, normal to phantom surface	uniform grid: $\Delta z_{Zoom}(n)$	≤ 5 mm	$3 - 4$ GHz: ≤ 4 mm $4 - 5$ GHz: ≤ 3 mm $5 - 6$ GHz: ≤ 2 mm
	graded grid $\Delta z_{Zoom}(1)$: between 1 st two points closest to phantom surface	≤ 4 mm	$3 - 4$ GHz: ≤ 3 mm $4 - 5$ GHz: ≤ 2.5 mm $5 - 6$ GHz: ≤ 2 mm
	$\Delta z_{Zoom}(n>1)$: between subsequent points	$\leq 1.5 \cdot \Delta z_{Zoom}(n-1)$	
Minimum zoom scan volume	x, y, z	≥ 30 mm	$3 - 4$ GHz: ≥ 28 mm $4 - 5$ GHz: ≥ 25 mm $5 - 6$ GHz: ≥ 22 mm

Step 4: Power reference measurement (drift)

The Power Drift Measurement job measures the field at the same location as the most recent power reference measurement job within the same procedure, and with the same settings. The indicated drift is mainly the variation of the DUT's output power and should vary max. $\pm 5\%$

2.7.2. Data Storage

The DASY software stores the acquired data from the data acquisition electronics as raw data (in microvolt readings from the probe sensors), together with all necessary software parameters for the data evaluation (probe calibration data, liquid parameters and device frequency and modulation data) in measurement files with the extension ".DAE4". The software evaluates the desired unit and format for output each time the data is visualized or exported. This allows verification of the complete software setup even after the measurement and allows correction of incorrect parameter settings. For example, if a measurement has been performed with a wrong crest factor parameter in the device setup, the parameter can be corrected afterwards and the data can be re-evaluated. The measured data can be visualized or exported in different units or formats, depending on the selected probe type ([V/m], [A/m], [°C], [m W/g], [m W/cm²], [dBrel], etc.). Some of these units are not available in certain situations or show meaningless results, e.g., a SAR output in a lossless media will always be zero. Raw data can also be exported to perform the evaluation with other software packages.





2.7.3. Data Evaluation by SEMCAD

The SEMCAD software automatically executes the following procedures to calculate the field units from the microvolt readings at the probe connector. The parameters used in the evaluation are stored in the configuration modules of the software:

Probe parameters:	- Sensitivity	Normi, ai0, ai1, ai2
- Conversion factor	ConvFi	
- Diode compression point	Dcpi	
Device parameters:	- Frequency	f
- Crest factor	cf	
Media parameters:	- Conductivity	ϵ
- Density	ρ	

These parameters must be set correctly in the software. They can be found in the component documents or they can be imported into the software from the configuration files issued for the DASY components. In the direct measuring mode of the multimeter option, the parameters of the actual system setup are used. In the scan visualization and export modes, the parameters stored in the corresponding document files are used.

The first step of the evaluation is a linearization of the filtered input signal to account for the compression characteristics of the detector diode. The compensation depends on the input signal, the diode type and the DC-transmission factor from the diode to the evaluation electronics.

If the exciting field is pulsed, the crest factor of the signal must be known to correctly compensate for peak power. The formula for each channel can be given as:

$$V_i = U_i + U_i^2 \cdot cf / dcp_i$$

With V_i = compensated signal of channel i (i = x, y, z)

U_i = input signal of channel i (i = x, y, z)

cf = crest factor of exciting field (DASY parameter)

dcp i = diode compression point (DASY parameter)

From the compensated input signals the primary field data for each channel can be evaluated:

E-field probes:

$$E_i = (V_i / Norm_i \cdot ConvF)^{1/2}$$





H-field probes:

$$H_i = (V_i)^{1/2} \cdot (a_{i0} + a_{i1}f + a_{i2}f^2) / f$$

With V_i = compensated signal of channel i ($i = x, y, z$)

Normi = sensor sensitivity of channel i ($i = x, y, z$)

[mV/(V/m)²] for E-field Probes

ConvF = sensitivity enhancement in solution

a_{ij} = sensor sensitivity factors for H-field probes

f = carrier frequency [GHz]

E_i = electric field strength of channel i in V/m

H_i = magnetic field strength of channel i in A/m

The RSS value of the field components gives the total field strength (Hermitian magnitude):

$$E_{tot} = (E_x^2 + E_y^2 + E_z^2)^{1/2}$$

The primary field data are used to calculate the derived field units.

$$SAR = (E_{tot}^2 \cdot \sigma) / (\epsilon \cdot 1000)$$

with SAR = local specific absorption rate in mW/g

E_{tot} = total field strength in V/m

σ = conductivity in [mho/m] or [Siemens/m]

ϵ = equivalent tissue density in g/cm³

Note that the density is normally set to 1 (or 1.06), to account for actual brain density rather than the density of the simulation liquid. The power flow density is calculated assuming the excitation field to be a free space field.

$$P_{pwe} = E_{tot}^2 / 3770 \text{ or } P_{pwe} = H_{tot}^2 \cdot 37.7$$

with P_{pwe} = equivalent power density of a plane wave in mW/cm²

E_{tot} = total electric field strength in V/m

H_{tot} = total magnetic field strength in A/m



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



3. SAR measurement variability and uncertainty

3.1. SAR measurement variability

Per KDB865664 D01 SAR measurement 100 MHz to 6 GHz v01r04, SAR measurement variability must be assessed for each frequency band, which is determined by the SAR probe calibration point and tissue-equivalent medium used for the device measurements. The additional measurements are repeated after the completion of all measurements requiring the same head or body tissue-equivalent medium in a frequency band. The test device should be returned to ambient conditions (normal room temperature) with the battery fully charged before it is re-mounted on the device holder for the repeated measurement(s) to minimize any unexpected variations in the repeated results.

1) Repeated measurement is not required when the original highest measured SAR is < 0.80 W/kg; steps 2) through 4) do not apply.

2) When the original highest measured SAR is ≥ 0.80 W/kg, repeat that measurement once.

3) Perform a second repeated measurement only if the ratio of largest to smallest SAR for the original and first repeated measurements is > 1.20 or when the original or repeated measurement is ≥ 1.45 W/kg ($\sim 10\%$ from the 1-g SAR limit).

4) Perform a third repeated measurement only if the original, first or second repeated measurement is ≥ 1.5 W/kg and the ratio of largest to smallest SAR for the original, first and second repeated measurements is > 1.20 .

The same procedures should be adapted for measurements according to extremity and occupational exposure limits by applying a factor of 2.5 for extremity exposure and a factor of 5 for occupational exposure to the corresponding SAR thresholds.

3.2. SAR measurement uncertainty

Per KDB865664 D01 SAR Measurement 100 MHz to 6 GHz, when the highest measured 1-g SAR within a frequency band is < 1.5 W/kg, the extensive SAR measurement uncertainty analysis described in IEEE Std 1528-2013 is not required in SAR reports submitted for equipment approval. The equivalent ratio (1.5/1.6) is applied to extremity and occupational exposure conditions.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



4. Description of Test Position

4.1. Test Positions Configuration

Per FCC KDB616217 D04, The required minimum test separation distance for incorporating transmitters and antennas into laptop, notebook and netbook computer displays is determined with the display screen opened at an angle of 90° to the keyboard compartment. If a computer has other operating configurations that require a different or more conservative display to keyboard angle for normal use, a KDB inquiry should be submitted to determine the test requirements. When antennas are incorporated in the keyboard section of a laptop computer, SAR is required for the bottom surface of the keyboard.

Provided tablet use conditions are not supported by the laptop computer, SAR tests for bystander exposure from the edges of the keyboard and display screen of laptop computers are generally not required. However, when edge testing is necessary, the similar concerns for simultaneous transmission on adjacent or multiple edges described for tablets also apply.

For this device, the transmit antenna are located at the screen section.

Body operating configurations are tested with the device bottom side positioned against a flat phantom with test separation distance of 0mm in a normal use configuration.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



5. SAR System Verification Procedure

5.1. Tissue Simulate Liquid

5.1.1. Recipes for Tissue Simulate Liquid

The following tables give the recipes for tissue simulating liquids to be used in different frequency bands:

Ingredients (% by weight)	Frequency (MHz)				
	450	700-900	1750-2000	2300-2500	2500-2700
Water	38.56	40.30	55.24	55.00	54.92
Salt (NaCl)	3.95	1.38	0.31	0.2	0.23
Sucrose	56.32	57.90	0	0	0
HEC	0.98	0.24	0	0	0
Bactericide	0.19	0.18	0	0	0
Tween	0	0	44.45	44.80	44.85
Salt: 99+% Pure Sodium Chloride			Sucrose: 98+% Pure Sucrose		
Water: De-ionized, 16 MΩ ⁺ resistivity			HEC: Hydroxyethyl Cellulose		
Tween: Polyoxyethylene (20) sorbitan monolaurate					
HSL5GHz is composed of the following ingredients:					
Water: 50-65%					
Mineral oil: 10-30%					
Emulsifiers: 8-25%					
Sodium salt: 0-1.5%					

Table 1: Recipe of Tissue Simulate Liquid





5.1.2. Measurement for Tissue Simulate Liquid

The dielectric properties for this Tissue Simulate Liquids were measured by using the DAKS. The Conductivity (σ) and Permittivity (ρ) are listed in bellow table. For the SAR measurement given in this report. The temperature variation of the Tissue Simulate Liquids was $22\pm2^{\circ}\text{C}$.


Tissue Type	Measured Frequency (MHz)	Target Tissue ($\pm 5\%$)		Measured Tissue		Liquid Temp. ($^{\circ}\text{C}$)	Measured Date
		ϵ_r	$\sigma(\text{S/m})$	ϵ_r	$\sigma(\text{S/m})$		
835 Head	835	41.5 (39.43~43.58)	0.9 (0.86~0.95)	42.524	0.925	22.4	December 10, 2024
1900 Head	1900	40 (38.00~42.00)	1.4 (1.33~1.47)	39.458	1.422	22.5	December 11, 2024
2450 Head	2450	39.2 (37.24~41.16)	1.8 (1.71~1.89)	38.451	1.826	22.3	December 12, 2024
2600 Head	2600	39 (37.05~40.95)	1.96 (1.86~2.06)	38.471	2.015	22.2	December 14, 2024
5250 Head	5250	36.0 (34.20~37.80)	4.66 (4.43~4.89)	35.985	4.766	23.3	December 16, 2024
5600 Head	5600	35.5 (33.73~37.28)	5.07 (4.82~5.32)	34.447	4.996	23.3	December 16, 2024
5750 Head	5750	35.3 (33.54~37.07)	5.27 (5.01~5.53)	34.655	5.165	23.3	December 16, 2024

Table 2: Measurement result of Tissue electric parameters



5.2. SAR System Check

The microwave circuit arrangement for system Check is sketched in F-1. The daily system accuracy verification occurs within the flat section of the SAM phantom. A SAR measurement was performed to see if the measured SAR was within $\pm 10\%$ from the target SAR values. The tests were conducted on the same days as the measurement of the EUT. The obtained results from the system accuracy verification are displayed in the following table (A power level of 250mW (below 3GHz) or 100mW (3-6GHz) was input to the dipole antenna). During the tests, the ambient temperature of the laboratory was in the range $22\pm 2^{\circ}\text{C}$, the relative humidity was in the range 60% and the liquid depth above the ear reference points was above $15\pm 0.5\text{ cm}$ in all the cases. It is seen that the system is operating within its specification, as the results are within acceptable tolerance of the reference values.



F-1. the microwave circuit arrangement used for SAR system check

5.2.1. Justification for Extended SAR Dipole Calibrations

1) Referring to KDB865664 D01 requirements for dipole calibration, instead of the typical annual calibration recommended by measurement standards, longer calibration intervals of up to three years may be considered when it is demonstrated that the SAR target, impedance and return loss of a dipole have remain stable according to the following requirements. Each measured dipole is expected to evaluate with the following criteria at least on annual interval in Appendix C.

- There is no physical damage on the dipole;
- System check with specific dipole is within 10% of calibrated value;
- Return-loss is within 20% of calibrated measurement;
- Impedance is within 5Ω from the previous measurement.

2) Network analyzer probe calibration against air, distilled water and a shorting block performed before measuring liquid parameters.

D835V2 SN 4d124 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2023-10-24	-35.6		50.2		1.65	
2023-10-23	-35.56	-0.11	49.8	-0.4	1.64	0.01

D1900V2 SN 5d055 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)



Shenzhen LCS Compliance Testing Laboratory Ltd.
 Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
 Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
 Scan code to check authenticity



2023-10-20	-26.1		51.3		4.84	
2024-10-19	-26.0	-0.38	51.5	0.2	4.85	0.01

D2450V2 SN 808 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2023-10-23	-26.3		51.4		4.73	
2024-10-22	-26.27	-0.11	51.2	-0.2	4.70	-0.03

D2600V2 SN 1071 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2023-06-20	-23.7		48.6		-6.32	
2024-06-19	-23.68	-0.08	48.5	-0.1	-6.30	0.02

D5GHzV2 SN 1046 Extend Dipole Calibrations(5250MHz)

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2023-10-23	-28.6		49.9		-3.71	
2024-10-22	-28.5	-0.35	49.6	-0.3	-3.70	0.01

D5GHzV2 SN 1046 Extend Dipole Calibrations(5600MHz)

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2023-10-23	-25.9		55.3		0.26	
2024-10-22	-25.6	-1.16	55.1	-0.2	0.24	-0.02

D5GHzV2 SN 1046 Extend Dipole Calibrations(5750MHz)

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2023-10-23	-26.8		54.6		1.18	
2024-10-22	-26.74	-0.22	54.9	0.3	1.20	0.02



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



5.2.2. Summary System Check Result(s)

Validation Kit		Measured SAR 100mW	Measured SAR100mW	Measured SAR (normalized to 1W)	Measured SAR (normalized to 1W)	Target SAR (normalized to 1W) (±10%)	Target SAR (normalized to 1W) (±10%)	Liquid Temp. (°C)	Measured Date
		1g (W/kg)	10g (W/kg)	1g (W/kg)	10g (W/kg)	1-g(W/kg)	10-g(W/kg)		
D835V2	Head	0.88	0.63	8.80	6.30	9.59 (8.63~10.55)	6.37 (5.73~7.01)	22.4	December 10, 2024
D1900V2	Head	3.78	1.99	37.80	19.90	40.2 (36.18~44.22)	20.9 (18.81~22.99)	22.5	December 11, 2024
D2450V2	Head	5.03	2.35	50.30	23.50	53.5 (48.15~58.85)	24.8 (22.32~27.28)	22.3	December 12, 2024
D2600V2	Head	5.27	2.45	52.70	24.50	56.8 (51.12~62.48)	25.5 (22.95~28.05)	22.2	December 14, 2024
Validation Kit		Measured SAR 100mW	Measured SAR 100mW	Measured SAR (normalized to 1W)	Measured SAR (normalized to 1W)	Target SAR (normalized to 1W) (±10%)	Target SAR (normalized to 1W) (±10%)	Liquid Temp. (°C)	Measured Date
		1g (W/kg)	10g (W/kg)	1g (W/kg)	10g (W/kg)	1-g(W/kg)	10-g(W/kg)		
D5GHzV2	Head (5.25GHz)	7.66	2.15	76.60	21.50	78.1 (70.29~85.91)	22.2 (19.98~24.42)	23.3	December 16, 2024
	Head (5.6GHz)	7.53	2.28	75.30	22.80	81.9 (73.71~90.09)	23.1 (20.79~25.41)	23.3	December 16, 2024
	Head (5.75GHz)	7.43	2.11	74.30	21.10	77.4 (69.66~85.14)	21.6 (19.44~23.76)	23.3	December 16, 2024

Table 3: Please see the Appendix A





6. SAR measurement procedure

The measurement procedures are as follows:

6.1. Conducted power measurement

- For WWAN power measurement, use base station simulator connection with RF cable, at maximum power in each supported wireless interface and frequency band.
- Read the WWAN RF power level from the base station simulator.
- For WLAN power measurement, use engineering software to configure EUT WLAN continuously Transmission, at maximum RF power in each supported wireless interface and frequency band.
- Connect EUT RF port through RF cable to the power meter, and measure WLAN output power.

6.2. GSM Test Configuration

SAR tests for GSM 850 and GSM 1900, a communication link is set up with a System Simulator (SS) by air link. Using CMU200 the power level is set to "5" for GSM 850, set to "0" for GSM 1900. Since the GPRS class is 12 for this EUT, it has at most 4 timeslots in uplink and at most 4 timeslots in downlink, the maximum total timeslots is 4. the EGPRS class is 12 for this EUT, it has at most 4 timeslots in uplink and at most 4 timeslots in downlink, the maximum total timeslots is 4.

SAR test reduction for GPRS and EDGE modes is determined by the source-based time-averaged output power specified for production units, including tune-up tolerance. The data mode with highest specified time-averaged output power should be tested for SAR compliance in the applicable exposure conditions. For modes with the same specified maximum output power and tolerance, the higher number time-slot configuration should be tested. GSM voice and GPRS data use GMSK, which is a constant amplitude modulation with minimal peak to average power difference within the time-slot burst. For EDGE, GMSK is used for MCS 1 – MCS 4 and 8-PSK is used for MCS 5 – MCS 9; where 8-PSK has an inherently higher peak-to-average power ratio. The GMSK and 8-PSK EDGE configurations are considered separately for SAR compliance. The GMSK EDGE configurations are grouped with GPRS and considered with respect to time-averaged maximum output power to determine compliance. The 3G SAR test reduction procedure is applied to 8-PSK EDGE with GMSK GPRS/EDGE as the primary mode.

6.3. UMTS Test Configuration

3G SAR Test Reduction Procedure

In the following procedures, the mode tested for SAR is referred to as the primary mode. The equivalent modes considered for SAR test reduction are denoted as secondary modes. Both primary and secondary modes must be in the same frequency band. When the maximum output power and tune-up tolerance specified for production units in a secondary mode is $\leq \frac{1}{4}$ dB higher than the primary mode or when the highest reported SAR of the primary mode is scaled by the ratio of specified maximum output power and tune-up tolerance of secondary to primary mode and the adjusted SAR is ≤ 1.2 W/kg, SAR measurement is not required for the secondary mode.³ This is referred to as the 3G SAR test reduction procedure in the following SAR test guidance, where the primary mode is identified in the applicable wireless mode test procedures and the secondary mode is wireless mode being considered for SAR test reduction by that procedure. When the 3G SAR test reduction procedure is not satisfied, it is identified as "otherwise" in the applicable procedures; SAR measurement is required for the secondary mode.

Output power Verification

Maximum output power is verified on the high, middle and low channels according to procedures described in section 5.2 of 3GPP TS 34.121, using the appropriate RMC or AMR with TPC (transmit power control) set to all "1's" for WCDMA/HSDPA or by applying the required inner loop power control procedures to maintain maximum output power while HSUPA is active. Results for all applicable physical channel configurations (DPCCH, DPDCHn and spreading codes, HSDPA, HSPA) are required in the SAR report. All configurations that are not supported by the handset or cannot be measured due to technical or equipment limitations must be clearly identified.

Head SAR

SAR for next to the ear head exposure is measured using a 12.2 kbps RMC with TPC bits configured to all "1's". The 3G SAR test reduction procedure is applied to AMR configurations with 12.2 kbps RMC as the primary mode.





Otherwise, SAR is measured for 12.2 kbps AMR in 3.4 kbps SRB (signaling radio bearer) using the highest reported SAR configuration in 12.2 kbps RMC for head exposure.

1) Body-Worn Accessory SAR

SAR for body-worn accessory configurations is measured using a 12.2 kbps RMC with TPC bits configured to all "1's". The 3G SAR test reduction procedure is applied to other spreading codes and multiple DPDCHn configurations supported by the handset with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured using an applicable RMC configuration with the corresponding spreading code or DPDCHn, for the highest reported body-worn accessory exposure SAR configuration in 12.2 kbps RMC. When more than 2 DPDCHn are supported by the handset, it may be necessary to configure additional DPDCHn using FTM (Factory Test Mode) or other chipset based test approaches with parameters similar to those used in 384 kbps and 768 kbps RMC.

2) Handsets with Release 5 HSDPA

The 3G SAR test reduction procedure is applied to HSDPA body-worn accessory configurations with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured for HSDPA using the HSDPA body SAR procedures in the "Release 5 HSDPA Data Devices" section of this document, for the highest reported SAR body-worn accessory exposure configuration in 12.2 kbps RMC. Handsets with both HSDPA and HSUPA are tested according to Release 6 HSPA test procedures.

HSDPA should be configured according to the UE category of a test device. The number of HSDSCH/ HS-PDSCHs, HARQ processes, minimum inter-TTI interval, transport block sizes and RV coding sequence are defined by the H-set. To maintain a consistent test configuration and stable transmission conditions, QPSK is used in the H-set for SAR testing. HS-DPCCH should be configured with a CQI feedback cycle of 4 ms with a CQI repetition factor of 2 to maintain a constant rate of active CQI slots. DPCCH and DPDCH gain factors (β_c , β_d), and HS-DPCCH power offset parameters (Δ_{ACK} , Δ_{NACK} , Δ_{CQI}) should be set according to values indicated in the Table below. The CQI value is determined by the UE category, transport block size, number of HS-PDSCHs and modulation used in the H-set

Table 2: Subtests for UMTS Release 5 HSDPA

Sub-set	β_c	β_d	β_d (SF)	β_c/β_d	β_{hs} (note 1, note 2)	CM(dB) (note 3)	MPR(dB)
1	2/15	15/15	64	2/15	4/15	0.0	0.0
2	12/15 (note 4)	15/15 (note 4)	64	12/15 (note 4)	24/15	1.0	0.0
3	15/15	8/15	64	15/8	30/15	1.5	0.5
4	15/15	4/15	64	15/4	30/15	1.5	0.5
Note1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 8 \left(\frac{A_{hs}}{\beta_{hs}/\beta_c} \right)$ $A_{hs} = \beta_{hs}/\beta_c = 30/15$ $\beta_{hs} = 30/15 * \beta_c$							
Note2: CM=1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$.							
Note3: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period(TF1,TF0) is achieved by setting the signaled gain factors for the reference TFC (TFC1,TF1) to $\beta_c=11/15$ and $\beta_d=15/15$.							

HSUPA Test Configuration

The 3G SAR test reduction procedure is applied to HSPA (HSUPA/HSDPA with RMC) body-worn accessory configurations with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured for HSPA using the HSPA body SAR procedures in the "Release 6 HSPA Data Devices" section of this document, for the highest reported body-worn accessory exposure SAR configuration in 12.2 kbps RMC. When VOIP is applicable for next to the ear head exposure in HSPA, the 3G SAR test reduction procedure is applied to HSPA with 12.2 kbps RMC as the primary mode; otherwise, the same HSPA configuration used for body-worn accessory measurements is tested for next to the ear head exposure.

Due to inner loop power control requirements in HSPA, a communication test set is required for output power and SAR tests. The 12.2 kbps RMC, FRC H-set 1 and E-DCH configurations for HSPA are configured according to the β values indicated in Table 2 and other applicable procedures described in the 'WCDMA Handset' and 'Release 5 HSDPA Data Devices' sections of this document

Table 3: Sub-Test 5 Setup for Release 6 HSUPA



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity



Sub-set	β_c	β_d	β_d (SF)	β_c/β_d	$\beta_{hs}^{(1)}$	β_{ec}	β_{ed}	β_{ed} (SF)	β_{ed} (codes)	CM ⁽²⁾ (dB)	MPR (dB)	AG ⁽⁴⁾ Index	E-TFCI
1	11/15 ⁽³⁾	15/15 ⁽³⁾	64	11/15 ⁽³⁾	22/15	209/225	1039/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	β_{ed1} : 47/15 β_{ed2} : 47/15	4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 ⁽⁴⁾	15/15 ⁽⁴⁾	64	15/15 ⁽⁴⁾	30/15	24/15	134/15	4	1	1.0	0.0	21	81

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.

Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$.

Note 4: For subtest 5 the β_c/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$.

Note 5: Testing UE using E-DPDCH Physical Layer category 1 Sub-test 3 is not required according to TS 25.306

Figure 5.1g.

Note 6: β_{ed} can not be set directly; it is set by Absolute Grant Value.

6.4. LTE Test Configuration

QPSK with 1 RB allocation

Start with the largest channel bandwidth and measure SAR for QPSK with 1 RB allocation, using the RB offset and required test channel combination with the highest maximum output power among RB offsets at the upper edge, middle and lower edge of each required test channel. When the reported SAR is ≤ 0.8 W/kg, testing of the remaining RB offset configurations and required test channels is not required for 1 RB allocation; otherwise, SAR is required for the remaining required test channels and only for the RB offset configuration with the highest output power for that channel. When the reported SAR of a required test channel is > 1.45 W/kg, SAR is required for all three RB offset configurations for that required test channel.

QPSK with 50% RB allocation

The procedures required for 1 RB allocation in section 4.2.1 are applied to measure the SAR for QPSK with 50% RB allocation.

QPSK with 100% RB allocation

For QPSK with 100% RB allocation, SAR is not required when the highest maximum output power for 100 % RB allocation is less than the highest maximum output power in 50% and 1 RB allocations and the highest reported SAR for 1 RB and 50% RB allocation in sections 4.2.1 and 4.2.2 are ≤ 0.8 W/kg. Otherwise, SAR is measured for the highest output power channel; and if the reported SAR is > 1.45 W/kg, the remaining required test channels must also be tested.

6.5. WIFI Test Configuration

The SAR measurement and test reduction procedures are structured according to either the DSSS or OFDM transmission mode configurations used in each standalone frequency band and aggregated band. For devices that operate in exposure configurations that require multiple test positions, additional SAR test reduction may be applied. The maximum output power specified for production units, including tune-up tolerance, are used to determine initial SAR test requirements for the 802.11 transmission modes in a frequency band. SAR is measured using the highest measured maximum output power channel for the initial test configuration. SAR measurement and test reduction for the remaining 802.11 modes and test channels are determined according to measured or specified maximum output power and reported SAR of the initial measurements. The general test reduction and SAR measurement approaches are summarized in the following:

1. The maximum output power specified for production units are determined for all applicable 802.11 transmission modes in each standalone and aggregated frequency band. Maximum output power is measured for the highest maximum output power configuration(s) in each frequency band according to the default power measurement procedures.
2. For OFDM transmission configurations in the 2.4 GHz and 5 GHz bands, an "initial test configuration" is first determined for each standalone and aggregated frequency band according to the maximum output power and tune-up tolerance specified for production units.
 - a. When the same maximum power is specified for multiple transmission modes in a frequency band, the largest channel bandwidth, lowest order modulation, lowest data rate and lowest order 802.11 a/g/n/ac mode is used for



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



SAR measurement, on the highest measured output power channel in the initial test configuration, for each frequency band.

b. SAR is measured for OFDM configurations using the initial test configuration procedures. Additional frequency band specific SAR test reduction may be considered for individual frequency bands

c. Depending on the reported SAR of the highest maximum output power channel tested in the initial test configuration, SAR test reduction may apply to subsequent highest output channels in the initial test configuration to reduce the number of SAR measurements.

3. The Initial test configuration does not apply to DSSS. The 2.4 GHz band SAR test requirements and 802.11b DSSS procedures are used to establish the transmission configurations required for SAR measurement.

4. An "initial test position" is applied to further reduce the number of SAR tests for devices operating in next to the ear, UMPC mini-tablet or hotspot mode exposure configurations that require multiple test positions.

a. SAR is measured for 802.11b according to the 2.4 GHz DSSS procedure using the exposure condition established by the initial test position.

b. SAR is measured for 2.4 GHz and 5 GHz OFDM configurations using the initial test configuration.

802.11b/g/n operating modes are tested independently according to the service requirements in each frequency band. 802.11b/g/n modes are tested on the maximum average output channel.

5. The Initial test position does not apply to devices that require a fixed exposure test position. SAR is measured in a fixed exposure test position for these devices in 802.11b according to the 2.4 GHz DSSS procedure or in 2.4 GHz and 5 GHz OFDM configurations using the initial test configuration procedures.

6. The "subsequent test configuration" procedures are applied to determine if additional SAR measurements are required for the remaining OFDM transmission modes that have not been tested in the initial test configuration. SAR test exclusion is determined according to reported SAR in the initial test configuration and maximum output power specified or measured for these other OFDM configurations.

2.4 GHz and 5GHz SAR Procedures

Separate SAR procedures are applied to DSSS and OFDM configurations in the 2.4 GHz band to simplify DSSS test requirements. For 802.11b DSSS SAR measurements, DSSS SAR procedure applies to fixed exposure test position and initial test position procedure applies to multiple exposure test positions. When SAR measurement is required for an OFDM configuration, the initial test configuration, subsequent test configuration and initial test position procedures are applied. The SAR test exclusion requirements for 802.11g/n OFDM configurations are described in section 5.2.2.

1. 802.11b DSSS SAR Test Requirements

SAR is measured for 2.4 GHz 802.11b DSSS using either a fixed test position or, when applicable, the initial test position procedure. SAR test reduction is determined according to the following:

- When the reported SAR of the highest measured maximum output power channel (section 3.1) for the exposure configuration is ≤ 0.8 W/kg, no further SAR testing is required for 802.11b DSSS in that exposure configuration.
- When the reported SAR is > 0.8 W/kg, SAR is required for that exposure configuration using the next highest measured output power channel. When any reported SAR is > 1.2 W/kg, SAR is required for the third channel; i.e., all channels require testing.

1. 2.4 GHz 802.11g/n OFDM SAR Test Exclusion Requirements

When SAR measurement is required for 2.4 GHz 802.11g/n OFDM configurations, the measurement and test reduction procedures for OFDM are applied (section 5.3). SAR is not required for the following 2.4 GHz OFDM conditions.

- When KDB Publication 447498 SAR test exclusion applies to the OFDM configuration
- When the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg.

2. SAR Test Requirements for OFDM Configurations

When SAR measurement is required for 802.11 a/g/n/ac OFDM configurations, each standalone and frequency aggregated band is considered separately for SAR test reduction. When the same transmitter and antenna(s) are used for U-NII-1 and U-NII-2A bands, additional SAR test reduction applies. When band gap channels between U-NII-2C band and 5.8 GHz U-NII-3 or §15.247 band are supported, the highest maximum output power transmission mode configuration and maximum output power channel across the bands must be used to determine SAR test reduction, according to the initial test configuration and subsequent test configuration requirements.²⁰ In applying the initial test configuration and subsequent test configuration procedures, the 802.11 transmission configuration with the highest specified maximum output power and the channel within a test configuration with the highest measured maximum output power should be clearly distinguished to apply the procedures.

3. OFDM Transmission Mode SAR Test Configuration and Channel Selection Requirements

The initial test configuration for 2.4 GHz and 5 GHz OFDM transmission modes is determined by the 802.11 configuration with the highest maximum output power specified for production units, including tune-up tolerance, in each standalone and aggregated frequency band. SAR for the initial test configuration is measured using the





highest maximum output power channel determined by the default power measurement procedures (section 4). When multiple configurations in a frequency band have the same specified maximum output power, the initial test configuration is determined according to the following steps applied sequentially.

- The largest channel bandwidth configuration is selected among the multiple configurations with the same specified maximum output power.
- If multiple configurations have the same specified maximum output power and largest channel bandwidth, the lowest order modulation among the largest channel bandwidth configurations is selected.
- If multiple configurations have the same specified maximum output power, largest channel bandwidth and lowest order modulation, the lowest data rate configuration among these configurations is selected.
- When multiple transmission modes (802.11a/g/n/ac) have the same specified maximum output power, largest channel bandwidth, lowest order modulation and lowest data rate, the lowest order 802.11 mode is selected; i.e., 802.11a is chosen over 802.11n then 802.11ac or 802.11g is chosen over 802.11n.

After an initial test configuration is determined, if multiple test channels have the same measured maximum output power, the channel chosen for SAR measurement is determined according to the following. These channel selection procedures apply to both the initial test configuration and subsequent test configuration(s), with respect to the default power measurement procedures or additional power measurements required for further SAR test reduction. The same procedures also apply to subsequent highest output power channel(s) selection.

- Channels with measured maximum output power within $\frac{1}{4}$ dB of each other are considered to have the same maximum output.
- When there are multiple test channels with the same measured maximum output power, the channel closest to mid-band frequency is selected for SAR measurement.
- When there are multiple test channels with the same measured maximum output power and equal separation from mid-band frequency; for example, high and low channels or two mid-band channels, the higher frequency (number) channel is selected for SAR measurement.

Initial Test Configuration Procedures

An initial test configuration is determined for OFDM transmission modes according to the channel bandwidth, modulation and data rate combination(s) with the highest maximum output power specified for production units in each standalone and aggregated frequency band. SAR is measured using the highest measured maximum output power channel. For configurations with the same specified or measured maximum output power, additional transmission mode and test channel selection procedures are required (see section 5.3.2). SAR test reduction of subsequent highest output test channels is based on the reported SAR of the initial test configuration. For next to the ear, hotspot mode and UMC mini-tablet exposure configurations where multiple test positions are required, the initial test position procedure is applied to minimize the number of test positions required for SAR measurement using the initial test configuration transmission mode.²³ For fixed exposure conditions that do not have multiple SAR test positions, SAR is measured in the transmission mode determined by the initial test configuration. When the reported SAR of the initial test configuration is > 0.8 W/kg, SAR measurement is required for the subsequent next highest measured output power channel(s) in the initial test configuration until the reported SAR is ≤ 1.2 W/kg or all required channels are tested.

4. Subsequent Test Configuration Procedures

SAR measurement requirements for the remaining 802.11 transmission mode configurations that have not been tested in the initial test configuration are determined separately for each standalone and aggregated frequency band, in each exposure condition, according to the maximum output power specified for production units. The initial test position procedure is applied to next to the ear, UMPC mini-tablet and hotspot mode configurations. When the same maximum output power is specified for multiple transmission modes, the procedures in section 5.3.2 are applied to determine the test configuration. Additional power measurements may be required to determine if SAR measurements are required for subsequent highest output power channels in a subsequent test configuration. The subsequent test configuration and SAR measurement procedures are described in the following.

- When SAR test exclusion provisions of KDB Publication 447498 are applicable and SAR measurement is not required for the initial test configuration, SAR is also not required for the next highest maximum output power transmission mode subsequent test configuration(s) in that frequency band or aggregated band and exposure configuration.
- When the highest reported SAR for the initial test configuration (when applicable, include subsequent highest output channels), according to the initial test position or fixed exposure position requirements, is adjusted by the ratio of the subsequent test configuration to initial test configuration specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg, SAR is not required for that subsequent test configuration.
- The number of channels in the initial test configuration and subsequent test configuration can be different due to differences in channel bandwidth. When SAR measurement is required for a subsequent test configuration and the channel bandwidth is smaller than that in the initial test configuration, all channels in the subsequent test configuration that overlap with the larger bandwidth channel tested in the initial test configuration should be used to determine the highest maximum output power channel. This step requires additional power





measurement to identify the highest maximum output power channel in the subsequent test configuration to determine SAR test reduction.

- 1). SAR should first be measured for the channel with highest measured output power in the subsequent test configuration.
- 2). SAR for subsequent highest measured maximum output power channels in the subsequent test configuration is required only when the reported SAR of the preceding higher maximum output power channel(s) in the subsequent test configuration is > 1.2 W/kg or until all required channels are tested.
 - a) For channels with the same measured maximum output power, SAR should be measured using the channel closest to the center frequency of the larger channel bandwidth channel in the initial test configuration.
 - d. SAR measurements for the remaining highest specified maximum output power OFDM transmission mode configurations that have not been tested in the initial test configuration (highest maximum output) or subsequent test configuration(s) (subsequent next highest maximum output power) is determined by applying the subsequent test configuration procedures in this section to the remaining configurations according to the following:
 - 1) replace “subsequent test configuration” with “next subsequent test configuration” (i.e., subsequent next highest specified maximum output power configuration)
 - 2) replace “initial test configuration” with “all tested higher output power configurations.”

6.6. Power Reduction

The product without any power reduction.

6.7. Power Drift

To control the output power stability during the SAR test, SAR system calculates the power drift by measuring the E-field at the same location at the beginning and at the end of the measurement for each test position. This ensures that the power drift during one measurement is within ± 0.2 dB.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



7. TEST CONDITIONS AND RESULTS

7.1. Conducted Power Results

According KDB 447498 D01 General RF Exposure Guidance v06 Section 4.1 2) states that “Unless it is specified differently in the published RF exposure KDB procedures, these requirements also apply to test reduction and test exclusion considerations. Time-averaged maximum conducted output power applies to SAR and, as required by § 2.1091(c), time-averaged ERP applies to MPE. When an antenna port is not available on the device to support conducted power measurement, such as FRS and certain Part 15 transmitters with built-in integral antennas, the maximum output power allowed for production units should be used to determine RF exposure test exclusion and compliance.”

<GSM Conducted Power>

General Note:

1. Per KDB 447498 D01v06, the maximum output power channel is used for SAR testing and for further SAR test reduction.
2. According to October 2013TCB Workshop, for GSM / GPRS / EGPRS, the number of time slots to test for SAR should correspond to the highest frame-average maximum output power configuration, considering the possibility of e.g. 3rd party VoIP operation for head and body-worn SAR testing, the EUT was set in GPRS (4Tx slot) for GSM850/GSM1900 band due to their highest frame-average power.
3. For hotspot mode SAR testing, GPRS should be evaluated, therefore the EUT was set in GPRS (4 Tx slots) for GSM850/GSM1900 band due to its highest frame-average power.

7.1.1. Conducted power measurement results for GSM850

GSM 850										
Burst Output Power(dBm)					Tune up	Division Factors	Frame-Average Output Power(dBm)			Tune up
Channel		128	190	251			128	190	251	
GSM(GMSK)	GSM	32.7	32.72	32.69	33.00	-9.19	23.51	23.53	23.50	23.81
GPRS(GMSK)	1 TX Slot	32.55	32.53	32.49	33.00	-9.19	23.36	23.34	23.30	23.81
	2 TX Slots	30.96	30.99	30.95	31.00	-6.18	24.78	24.81	24.77	24.82
	3 TX Slots	29.48	29.48	29.48	30.00	-4.42	25.06	25.06	25.06	25.58
	4 TX Slots	28	28.01	27.97	28.50	-3.17	24.83	24.84	24.80	25.33
EGPRS(8PSK)	1 TX Slot	25.99	26.03	25.94	26.50	-9.19	16.80	16.84	16.75	17.31
	2 TX Slots	24.46	24.48	24.44	25.00	-6.18	18.28	18.30	18.26	18.82
	3 TX Slots	22.95	23.02	22.96	23.50	-4.42	18.53	18.60	18.54	19.08
	4 TX Slots	21.46	21.52	21.47	22.00	-3.17	18.29	18.35	18.30	18.83

7.1.2. Conducted power measurement results for PCS1900

GSM 1900										
Burst Output Power(dBm)					Tune up	Division Factors	Frame-Average Output Power(dBm)			Tune up
Channel		512	661	810			512	661	810	
GSM(GMSK)	GSM	29.69	29.68	29.63	30.00	-9.19	20.50	20.49	20.44	20.81
GPRS(GMSK)	1 TX Slot	29.55	29.57	29.48	30.00	-9.19	20.36	20.38	20.29	20.81
	2 TX Slots	27.96	28.03	27.95	28.50	-6.18	21.78	21.85	21.77	22.32
	3 TX Slots	26.49	26.52	26.45	27.00	-4.42	22.07	22.10	22.03	22.58
	4 TX Slots	24.95	25.02	24.94	25.50	-3.17	21.78	21.85	21.77	22.33
EGPRS(8PSK)	1 TX Slot	25.49	25.52	25.43	26.00	-9.19	16.30	16.33	16.24	16.81
	2 TX Slots	24	24.02	23.97	24.50	-6.18	17.82	17.84	17.79	18.32
	3 TX Slots	21.98	22.03	21.92	22.50	-4.42	17.56	17.61	17.50	18.08
	4 TX Slots	20.48	20.47	20.47	20.50	-3.17	17.31	17.30	17.30	17.33

Note:



Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity



1) CMW500 measures GSM peak and average output power for active timeslots. For SAR the time based average power is relevant. The difference in between depends on the duty cycle of the TDMA signal:

No. of timeslots	1	2	3	4
Duty Cycle	1:8.3	1:4.15	1:2.77	1:2.075
Time based avg. power compared to slotted avg. power	-9.19	-6.18	-4.42	-3.17

2) The frame-averaged power is linearly proportion to the slot number configured and it is linearly scaled the maximum burst-averaged power based on time slots. The calculated method is shown as below:

3) Frame-averaged power = $10 \times \log(\text{Burst-averaged power mW} \times \text{Slot used} / 8)$

When the maximum output power variation across the required test channels is $> \frac{1}{2}$ dB, instead of the middle channel, the highest output power channel must be used

When multiple slots can be used, SAR should be tested to account for the maximum source-based time-averaged output power.

<UMTS Conducted Power>

The following tests were conducted according to the test requirements outlines in 3GPP TS 34.121 specification. A summary of these settings are illustrated below:

HSDPA Setup Configuration:

- The EUT was connected to Base Station CMW500 referred to the Setup Configuration.
- The RF path losses were compensated into the measurements.
- A call was established between EUT and Base Station with following setting:
 - Set Gain Factors (β_c and β_d) and parameters were set according to each
 - Specific sub-test in the following table, C10.1.4, quoted from the TS 34.121
 - Set RMC 12.2Kbps + HSDPA mode.
 - Set Cell Power = -86 dBm
 - Set HS-DSCH Configuration Type to FRC (H-set 1, QPSK)
 - Select HSDPA Uplink Parameters
 - Set Delta ACK, Delta NACK and Delta CQI = 8
 - Set Ack-Nack Repetition Factor to 3
 - Set CQI Feedback Cycle (k) to 4 ms
 - Set CQI Repetition Factor to 2
 - Power Ctrl Mode = All Up bits
- The transmitted maximum output power was recorded.

Table C.10.1.4: β values for transmitter characteristics tests with HS-DPCCH

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	β_{HS} (Note 1, Note 2)	CM (dB) (Note 3)	MPR (dB) (Note 3)
1	2/15	15/15	64	2/15	4/15	0.0	0.0
2	12/15 (Note 4)	15/15 (Note 4)	64	12/15 (Note 4)	24/15	1.0	0.0
3	15/15	8/15	64	15/8	30/15	1.5	0.5
4	15/15	4/15	64	15/4	30/15	1.5	0.5

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 30/15$ with $\beta_{HS} = 30/15 * \beta_c$.

Note 2: For the HS-DPCCH power mask requirement test in clause 5.2C, 5.7A, and the Error Vector Magnitude (EVM) with HS-DPCCH test in clause 5.13.1A, and HSDPA EVM with phase discontinuity in clause 5.13.1AA, Δ_{ACK} and $\Delta_{NACK} = 30/15$ with $\beta_{HS} = 30/15 * \beta_c$, and $\Delta_{CQI} = 24/15$ with $\beta_{HS} = 24/15 * \beta_c$.

Note 3: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{HS}/\beta_c = 24/15$. For all other combinations of DPDCCH, DPCCH and HS-DPCCH the MPR is based on the relative CM difference. This is applicable for only UEs that support HSDPA in release 6 and later releases.

Note 4: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$.

Setup Configuration



**HSUPA Setup Configuration:**

- a. The EUT was connected to Base Station R&S CMW500 referred to the Setup Configuration.
- b. The RF path losses were compensated into the measurements.
- c. A call was established between EUT and Base Station with following setting * :
 - i. Call Configs = 5.2B, 5.9B, 5.10B, and 5.13.2B with QPSK
 - ii. Set the Gain Factors (β_c and β_d) and parameters (AG Index) were set according to each specific sub-test in the following table, C11.1.3, quoted from the TS 34.121
 - iii. Set Cell Power = -86 dBm
 - iv. Set Channel Type = 12.2k + HSPA
 - v. Set UE Target Power
 - vi. Power Ctrl Mode= Alternating bits
 - vii. Set and observe the E-TFCI
 - viii. Confirm that E-TFCI is equal to the target E-TFCI of 75 for sub-test 1, and other subtest's E-TFCI
- d. The transmitted maximum output power was recorded.

Table C.11.1.3: β values for transmitter characteristics tests with HS-DPCCH and E-DCH

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	β_{HS} (Note 1)	β_{ec}	β_{ed} (Note 5) (Note 6)	β_{ed} (SF)	β_{ed} (Codes)	CM (dB) (Note 2)	MPR (dB) (Note 2)	AG Index (Note 6)	E-TFCI
1	11/15 (Note 3)	15/15 (Note 3)	64	11/15 (Note 3)	22/15	209/25	1309/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	β_{ed1} : 47/15 β_{ed2} : 47/15	4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 (Note 4)	15/15 (Note 4)	64	15/15 (Note 4)	30/15	24/15	134/15	4	1	1.0	0.0	21	81

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 30/15$ with $\beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.

Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$.

Note 4: For subtest 5 the β_c/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$.

Note 5: In case of testing by UE using E-DPDCH Physical Layer category 1, Sub-test 3 is omitted according to TS25.306 Table 5.1g.

Note 6: β_{ed} can not be set directly, it is set by Absolute Grant Value.

General Note

1. Per KDB 941225 D01, RMC 12.2kbps setting is used to evaluate SAR. If AMR 12.2kbps power is < 0.25dB higher than RMC 12.2kbps, SAR tests with AMR 12.2kbps can be excluded.
2. By design, AMR and HSDPA/HSUPA RF power will not be larger than RMC 12.2kbps, detailed information is included in Tune-up Procure exhibit.
3. It is expected by the manufacturer that MPR for some HSDPA/HSUPA subtests may differ from the specification of 3GPP, according to the chipset implementation in this model. The implementation and expected deviation are detailed in tune-up procedure exhibit.





7.1.3. Conducted Power Measurement Results(WCDMA Band II)

Item	Band	WCDMA Band II result (dBm)			
		Channel/Frequency(MHz)			
	sub-test	9262/1852.4	9400/1880	9538/1907.6	Tune up
RMC	12.2kbps RMC	23.59	23.61	23.61	24.00
HSDPA	Sub –Test 1	22.99	22.94	22.88	23.00
	Sub –Test 2	22.81	22.87	22.90	23.00
	Sub –Test 3	22.85	22.77	22.76	23.00
	Sub –Test 4	22.74	22.80	22.74	23.00
HSUPA	Sub –Test 1	22.77	22.83	22.88	23.00
	Sub –Test 2	22.84	22.78	22.74	23.00
	Sub –Test 3	22.73	22.81	22.76	23.00
	Sub –Test 4	22.78	22.77	22.78	23.00
	Sub –Test 5	22.80	22.89	22.90	23.00

Note:

- 1) when the maximum output power variation across the required test channels is $> \frac{1}{2}$ dB, instead of the middle channel, the highest output power channel must be used.

7.1.4. Conducted Power Measurement Results(WCDMA Band V)

Item	Band	WCDMA Band V result (dBm)			
		Channel/Frequency(MHz)			
	sub-test	4132/826.4	4182/836.4	4233/846.6	Tune up
RMC	12.2kbps RMC	23.44	23.45	23.56	24.00
HSDPA	Sub –Test 1	22.81	22.70	22.85	23.00
	Sub –Test 2	22.89	22.71	22.72	23.00
	Sub –Test 3	22.87	22.82	22.75	23.00
	Sub –Test 4	22.81	22.79	22.76	23.00
HSUPA	Sub –Test 1	22.86	22.80	22.80	23.00
	Sub –Test 2	22.81	22.75	22.72	23.00
	Sub –Test 3	22.74	22.77	22.79	23.00
	Sub –Test 4	22.88	22.76	22.77	23.00
	Sub –Test 5	22.90	22.83	22.74	23.00

Note:

- 1) when the maximum output power variation across the required test channels is $> \frac{1}{2}$ dB, instead of the middle channel, the highest output power channel must be used.



**7.1.5. Conducted Power Measurement Results(LTE Band 5)**

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Tune up(dBm)
Band5	1.4MHz	QPSK	20407	1RB#0	24.21	25.00
Band5	1.4MHz	16QAM	20407	1RB#0	23.50	24.00
Band5	1.4MHz	QPSK	20407	1RB#2	24.13	25.00
Band5	1.4MHz	16QAM	20407	1RB#2	23.39	24.00
Band5	1.4MHz	QPSK	20407	1RB#5	24.26	25.00
Band5	1.4MHz	16QAM	20407	1RB#5	23.46	24.00
Band5	1.4MHz	QPSK	20407	3RB#0	23.96	24.00
Band5	1.4MHz	16QAM	20407	3RB#0	23.78	24.00
Band5	1.4MHz	QPSK	20407	3RB#1	23.77	24.00
Band5	1.4MHz	16QAM	20407	3RB#1	23.98	24.00
Band5	1.4MHz	QPSK	20407	3RB#3	23.78	24.00
Band5	1.4MHz	16QAM	20407	3RB#3	24.04	25.00
Band5	1.4MHz	QPSK	20407	6RB#0	23.20	24.00
Band5	1.4MHz	16QAM	20407	6RB#0	22.84	23.00
Band5	1.4MHz	QPSK	20525	1RB#0	23.98	24.00
Band5	1.4MHz	16QAM	20525	1RB#0	23.71	24.00
Band5	1.4MHz	QPSK	20525	1RB#2	24.07	25.00
Band5	1.4MHz	16QAM	20525	1RB#2	23.68	24.00
Band5	1.4MHz	QPSK	20525	1RB#5	24.04	25.00
Band5	1.4MHz	16QAM	20525	1RB#5	23.75	24.00
Band5	1.4MHz	QPSK	20525	3RB#0	23.97	24.00
Band5	1.4MHz	16QAM	20525	3RB#0	23.96	24.00
Band5	1.4MHz	QPSK	20525	3RB#1	23.96	24.00
Band5	1.4MHz	16QAM	20525	3RB#1	23.95	24.00
Band5	1.4MHz	QPSK	20525	3RB#3	23.96	24.00
Band5	1.4MHz	16QAM	20525	3RB#3	24.07	25.00
Band5	1.4MHz	QPSK	20525	6RB#0	23.18	24.00
Band5	1.4MHz	16QAM	20525	6RB#0	22.84	23.00
Band5	1.4MHz	QPSK	20643	1RB#0	23.81	24.00
Band5	1.4MHz	16QAM	20643	1RB#0	23.78	24.00
Band5	1.4MHz	QPSK	20643	1RB#2	23.54	24.00
Band5	1.4MHz	16QAM	20643	1RB#2	23.66	24.00
Band5	1.4MHz	QPSK	20643	1RB#5	23.33	24.00
Band5	1.4MHz	16QAM	20643	1RB#5	23.51	24.00
Band5	1.4MHz	QPSK	20643	3RB#0	23.83	24.00
Band5	1.4MHz	16QAM	20643	3RB#0	24.00	25.00
Band5	1.4MHz	QPSK	20643	3RB#1	23.57	24.00
Band5	1.4MHz	16QAM	20643	3RB#1	23.87	24.00
Band5	1.4MHz	QPSK	20643	3RB#3	23.76	24.00
Band5	1.4MHz	16QAM	20643	3RB#3	23.73	24.00
Band5	1.4MHz	QPSK	20643	6RB#0	23.13	24.00
Band5	1.4MHz	16QAM	20643	6RB#0	22.52	23.00
Band5	3MHz	QPSK	20415	1RB#0	23.88	24.00
Band5	3MHz	16QAM	20415	1RB#0	23.24	24.00
Band5	3MHz	QPSK	20415	1RB#8	23.87	24.00
Band5	3MHz	16QAM	20415	1RB#8	23.05	24.00
Band5	3MHz	QPSK	20415	1RB#14	23.69	24.00
Band5	3MHz	16QAM	20415	1RB#14	23.08	24.00
Band5	3MHz	QPSK	20415	8RB#0	22.98	23.00
Band5	3MHz	16QAM	20415	8RB#0	22.94	23.00
Band5	3MHz	QPSK	20415	8RB#4	22.94	23.00
Band5	3MHz	16QAM	20415	8RB#4	22.88	23.00
Band5	3MHz	QPSK	20415	8RB#7	22.88	23.00
Band5	3MHz	16QAM	20415	8RB#7	22.88	23.00
Band5	3MHz	QPSK	20415	15RB#0	22.88	23.00
Band5	3MHz	16QAM	20415	15RB#0	22.35	23.00
Band5	3MHz	QPSK	20525	1RB#0	23.83	24.00
Band5	3MHz	16QAM	20525	1RB#0	22.56	23.00
Band5	3MHz	QPSK	20525	1RB#8	23.93	24.00
Band5	3MHz	16QAM	20525	1RB#8	23.52	24.00
Band5	3MHz	QPSK	20525	1RB#14	24.11	25.00
Band5	3MHz	16QAM	20525	1RB#14	23.53	24.00
Band5	3MHz	QPSK	20525	8RB#0	22.87	23.00



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band5	3MHz	16QAM	20525	8RB#0	22.97	23.00
Band5	3MHz	QPSK	20525	8RB#4	23.14	24.00
Band5	3MHz	16QAM	20525	8RB#4	23.11	24.00
Band5	3MHz	QPSK	20525	8RB#7	23.14	24.00
Band5	3MHz	16QAM	20525	8RB#7	23.18	24.00
Band5	3MHz	QPSK	20525	15RB#0	22.98	23.00
Band5	3MHz	16QAM	20525	15RB#0	22.27	23.00
Band5	3MHz	QPSK	20635	1RB#0	23.85	24.00
Band5	3MHz	16QAM	20635	1RB#0	23.93	24.00
Band5	3MHz	QPSK	20635	1RB#8	23.76	24.00
Band5	3MHz	16QAM	20635	1RB#8	23.97	24.00
Band5	3MHz	QPSK	20635	1RB#14	23.27	24.00
Band5	3MHz	16QAM	20635	1RB#14	23.01	24.00
Band5	3MHz	QPSK	20635	8RB#0	23.07	24.00
Band5	3MHz	16QAM	20635	8RB#0	23.02	24.00
Band5	3MHz	QPSK	20635	8RB#4	23.04	24.00
Band5	3MHz	16QAM	20635	8RB#4	22.89	23.00
Band5	3MHz	QPSK	20635	8RB#7	22.94	23.00
Band5	3MHz	16QAM	20635	8RB#7	23.08	24.00
Band5	3MHz	QPSK	20635	15RB#0	22.96	23.00
Band5	3MHz	16QAM	20635	15RB#0	22.52	23.00
Band5	5MHz	QPSK	20425	1RB#0	23.89	24.00
Band5	5MHz	16QAM	20425	1RB#0	22.71	23.00
Band5	5MHz	QPSK	20425	1RB#12	23.91	24.00
Band5	5MHz	16QAM	20425	1RB#12	22.71	23.00
Band5	5MHz	QPSK	20425	1RB#24	23.95	24.00
Band5	5MHz	16QAM	20425	1RB#24	22.75	23.00
Band5	5MHz	QPSK	20425	12RB#0	23.01	24.00
Band5	5MHz	16QAM	20425	12RB#0	22.96	23.00
Band5	5MHz	QPSK	20425	12RB#6	22.92	23.00
Band5	5MHz	16QAM	20425	12RB#6	23.02	24.00
Band5	5MHz	QPSK	20425	12RB#13	22.98	23.00
Band5	5MHz	16QAM	20425	12RB#13	22.99	23.00
Band5	5MHz	QPSK	20425	25RB#0	22.97	23.00
Band5	5MHz	16QAM	20425	25RB#0	22.64	23.00
Band5	5MHz	QPSK	20525	1RB#0	23.86	24.00
Band5	5MHz	16QAM	20525	1RB#0	23.67	24.00
Band5	5MHz	QPSK	20525	1RB#12	23.75	24.00
Band5	5MHz	16QAM	20525	1RB#12	23.85	24.00
Band5	5MHz	QPSK	20525	1RB#24	23.77	24.00
Band5	5MHz	16QAM	20525	1RB#24	23.84	24.00
Band5	5MHz	QPSK	20525	12RB#0	23.02	24.00
Band5	5MHz	16QAM	20525	12RB#0	23.07	24.00
Band5	5MHz	QPSK	20525	12RB#6	22.87	23.00
Band5	5MHz	16QAM	20525	12RB#6	23.01	24.00
Band5	5MHz	QPSK	20525	12RB#13	22.99	23.00
Band5	5MHz	16QAM	20525	12RB#13	22.99	23.00
Band5	5MHz	QPSK	20525	25RB#0	22.99	23.00
Band5	5MHz	16QAM	20525	25RB#0	22.31	23.00
Band5	5MHz	QPSK	20625	1RB#0	23.88	24.00
Band5	5MHz	16QAM	20625	1RB#0	23.33	24.00
Band5	5MHz	QPSK	20625	1RB#12	23.76	24.00
Band5	5MHz	16QAM	20625	1RB#12	23.23	24.00
Band5	5MHz	QPSK	20625	1RB#24	23.40	24.00
Band5	5MHz	16QAM	20625	1RB#24	22.88	23.00
Band5	5MHz	QPSK	20625	12RB#0	23.16	24.00
Band5	5MHz	16QAM	20625	12RB#0	23.11	24.00
Band5	5MHz	QPSK	20625	12RB#6	23.11	24.00
Band5	5MHz	16QAM	20625	12RB#6	23.12	24.00
Band5	5MHz	QPSK	20625	12RB#13	23.00	24.00
Band5	5MHz	16QAM	20625	12RB#13	23.19	24.00
Band5	5MHz	QPSK	20625	25RB#0	23.18	24.00
Band5	5MHz	16QAM	20625	25RB#0	22.53	23.00
Band5	10MHz	QPSK	20450	1RB#0	23.80	24.00
Band5	10MHz	16QAM	20450	1RB#0	23.34	24.00
Band5	10MHz	QPSK	20450	1RB#24	23.86	24.00



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band5	10MHz	16QAM	20450	1RB#24	23.32	24.00
Band5	10MHz	QPSK	20450	1RB#49	23.89	24.00
Band5	10MHz	16QAM	20450	1RB#49	23.39	24.00
Band5	10MHz	QPSK	20450	25RB#0	23.04	24.00
Band5	10MHz	16QAM	20450	25RB#0	23.02	24.00
Band5	10MHz	QPSK	20450	25RB#12	23.02	24.00
Band5	10MHz	16QAM	20450	25RB#12	23.02	24.00
Band5	10MHz	QPSK	20450	25RB#25	22.97	23.00
Band5	10MHz	16QAM	20450	25RB#25	22.94	23.00
Band5	10MHz	QPSK	20450	50RB#0	22.87	23.00
Band5	10MHz	16QAM	20450	50RB#0	22.41	23.00
Band5	10MHz	QPSK	20525	1RB#0	23.81	24.00
Band5	10MHz	16QAM	20525	1RB#0	23.45	24.00
Band5	10MHz	QPSK	20525	1RB#24	23.89	24.00
Band5	10MHz	16QAM	20525	1RB#24	23.57	24.00
Band5	10MHz	QPSK	20525	1RB#49	23.93	24.00
Band5	10MHz	16QAM	20525	1RB#49	22.69	23.00
Band5	10MHz	QPSK	20525	25RB#0	23.07	24.00
Band5	10MHz	16QAM	20525	25RB#0	23.10	24.00
Band5	10MHz	QPSK	20525	25RB#12	22.97	23.00
Band5	10MHz	16QAM	20525	25RB#12	22.93	23.00
Band5	10MHz	QPSK	20525	25RB#25	23.08	24.00
Band5	10MHz	16QAM	20525	25RB#25	23.04	24.00
Band5	10MHz	QPSK	20525	50RB#0	23.19	24.00
Band5	10MHz	16QAM	20525	50RB#0	22.58	23.00
Band5	10MHz	QPSK	20600	1RB#0	23.90	24.00
Band5	10MHz	16QAM	20600	1RB#0	23.98	24.00
Band5	10MHz	QPSK	20600	1RB#24	23.92	24.00
Band5	10MHz	16QAM	20600	1RB#24	23.93	24.00
Band5	10MHz	QPSK	20600	1RB#49	23.83	24.00
Band5	10MHz	16QAM	20600	1RB#49	23.23	24.00
Band5	10MHz	QPSK	20600	25RB#0	23.05	24.00
Band5	10MHz	16QAM	20600	25RB#0	23.06	24.00
Band5	10MHz	QPSK	20600	25RB#12	23.03	24.00
Band5	10MHz	16QAM	20600	25RB#12	23.09	24.00
Band5	10MHz	QPSK	20600	25RB#25	23.18	24.00
Band5	10MHz	16QAM	20600	25RB#25	23.15	24.00
Band5	10MHz	QPSK	20600	50RB#0	23.12	24.00
Band5	10MHz	16QAM	20600	50RB#0	22.64	23.00



**7.1.6. Conducted Power Measurement Results(LTE Band 7)**

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Tune up(dBm)
Band7	5MHz	QPSK	20775	1RB#0	22.51	23.00
Band7	5MHz	16QAM	20775	1RB#0	21.07	22.00
Band7	5MHz	QPSK	20775	1RB#12	22.55	23.00
Band7	5MHz	16QAM	20775	1RB#12	21.11	22.00
Band7	5MHz	QPSK	20775	1RB#24	21.90	22.00
Band7	5MHz	16QAM	20775	1RB#24	21.09	22.00
Band7	5MHz	QPSK	20775	12RB#0	21.63	22.00
Band7	5MHz	16QAM	20775	12RB#0	21.71	22.00
Band7	5MHz	QPSK	20775	12RB#6	21.69	22.00
Band7	5MHz	16QAM	20775	12RB#6	21.68	22.00
Band7	5MHz	QPSK	20775	12RB#13	21.63	22.00
Band7	5MHz	16QAM	20775	12RB#13	21.60	22.00
Band7	5MHz	QPSK	20775	25RB#0	21.71	22.00
Band7	5MHz	16QAM	20775	25RB#0	20.88	21.00
Band7	5MHz	QPSK	21100	1RB#0	21.93	22.00
Band7	5MHz	16QAM	21100	1RB#0	21.51	22.00
Band7	5MHz	QPSK	21100	1RB#12	22.17	23.00
Band7	5MHz	16QAM	21100	1RB#12	21.49	22.00
Band7	5MHz	QPSK	21100	1RB#24	22.05	23.00
Band7	5MHz	16QAM	21100	1RB#24	21.66	22.00
Band7	5MHz	QPSK	21100	12RB#0	21.26	22.00
Band7	5MHz	16QAM	21100	12RB#0	21.38	22.00
Band7	5MHz	QPSK	21100	12RB#6	21.38	22.00
Band7	5MHz	16QAM	21100	12RB#6	21.38	22.00
Band7	5MHz	QPSK	21100	12RB#13	21.39	22.00
Band7	5MHz	16QAM	21100	12RB#13	21.39	22.00
Band7	5MHz	QPSK	21100	25RB#0	21.38	22.00
Band7	5MHz	16QAM	21100	25RB#0	20.52	21.00
Band7	5MHz	QPSK	21425	1RB#0	22.07	23.00
Band7	5MHz	16QAM	21425	1RB#0	20.80	21.00
Band7	5MHz	QPSK	21425	1RB#12	22.16	23.00
Band7	5MHz	16QAM	21425	1RB#12	20.90	21.00
Band7	5MHz	QPSK	21425	1RB#24	22.18	23.00
Band7	5MHz	16QAM	21425	1RB#24	20.90	21.00
Band7	5MHz	QPSK	21425	12RB#0	21.34	22.00
Band7	5MHz	16QAM	21425	12RB#0	21.32	22.00
Band7	5MHz	QPSK	21425	12RB#6	21.32	22.00
Band7	5MHz	16QAM	21425	12RB#6	21.31	22.00
Band7	5MHz	QPSK	21425	12RB#13	21.28	22.00
Band7	5MHz	16QAM	21425	12RB#13	21.38	22.00
Band7	5MHz	QPSK	21425	25RB#0	21.31	22.00
Band7	5MHz	16QAM	21425	25RB#0	20.37	21.00
Band7	10MHz	QPSK	20800	1RB#0	22.08	23.00
Band7	10MHz	16QAM	20800	1RB#0	21.52	22.00
Band7	10MHz	QPSK	20800	1RB#24	21.82	22.00
Band7	10MHz	16QAM	20800	1RB#24	21.46	22.00
Band7	10MHz	QPSK	20800	1RB#49	21.74	22.00
Band7	10MHz	16QAM	20800	1RB#49	21.29	22.00
Band7	10MHz	QPSK	20800	25RB#0	21.70	22.00
Band7	10MHz	16QAM	20800	25RB#0	21.70	22.00
Band7	10MHz	QPSK	20800	25RB#12	21.70	22.00
Band7	10MHz	16QAM	20800	25RB#12	21.70	22.00
Band7	10MHz	QPSK	20800	25RB#25	21.54	22.00
Band7	10MHz	16QAM	20800	25RB#25	21.52	22.00
Band7	10MHz	QPSK	20800	50RB#0	21.70	22.00
Band7	10MHz	16QAM	20800	50RB#0	20.88	21.00
Band7	10MHz	QPSK	21100	1RB#0	22.24	23.00
Band7	10MHz	16QAM	21100	1RB#0	21.22	22.00
Band7	10MHz	QPSK	21100	1RB#24	22.32	23.00
Band7	10MHz	16QAM	21100	1RB#24	21.41	22.00
Band7	10MHz	QPSK	21100	1RB#49	22.36	23.00
Band7	10MHz	16QAM	21100	1RB#49	21.39	22.00



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band7	10MHz	QPSK	21100	25RB#0	21.30	22.00
Band7	10MHz	16QAM	21100	25RB#0	21.31	22.00
Band7	10MHz	QPSK	21100	25RB#12	21.31	22.00
Band7	10MHz	16QAM	21100	25RB#12	21.31	22.00
Band7	10MHz	QPSK	21100	25RB#25	21.47	22.00
Band7	10MHz	16QAM	21100	25RB#25	21.48	22.00
Band7	10MHz	QPSK	21100	50RB#0	21.44	22.00
Band7	10MHz	16QAM	21100	50RB#0	20.53	21.00
Band7	10MHz	QPSK	21400	1RB#0	21.94	22.00
Band7	10MHz	16QAM	21400	1RB#0	21.62	22.00
Band7	10MHz	QPSK	21400	1RB#24	22.19	23.00
Band7	10MHz	16QAM	21400	1RB#24	21.86	22.00
Band7	10MHz	QPSK	21400	1RB#49	22.18	23.00
Band7	10MHz	16QAM	21400	1RB#49	21.95	22.00
Band7	10MHz	QPSK	21400	25RB#0	21.39	22.00
Band7	10MHz	16QAM	21400	25RB#0	21.37	22.00
Band7	10MHz	QPSK	21400	25RB#12	21.37	22.00
Band7	10MHz	16QAM	21400	25RB#12	21.27	22.00
Band7	10MHz	QPSK	21400	25RB#25	21.30	22.00
Band7	10MHz	16QAM	21400	25RB#25	21.31	22.00
Band7	10MHz	QPSK	21400	50RB#0	21.41	22.00
Band7	10MHz	16QAM	21400	50RB#0	20.54	21.00
Band7	15MHz	QPSK	20825	1RB#0	22.00	23.00
Band7	15MHz	16QAM	20825	1RB#0	21.95	22.00
Band7	15MHz	QPSK	20825	1RB#38	21.44	22.00
Band7	15MHz	16QAM	20825	1RB#38	21.44	22.00
Band7	15MHz	QPSK	20825	1RB#74	21.47	22.00
Band7	15MHz	16QAM	20825	1RB#74	21.49	22.00
Band7	15MHz	QPSK	20825	38RB#0	21.59	22.00
Band7	15MHz	16QAM	20825	38RB#0	21.58	22.00
Band7	15MHz	QPSK	20825	38RB#18	21.58	22.00
Band7	15MHz	16QAM	20825	38RB#18	21.57	22.00
Band7	15MHz	QPSK	20825	38RB#37	21.57	22.00
Band7	15MHz	16QAM	20825	38RB#37	21.56	22.00
Band7	15MHz	QPSK	20825	75RB#0	21.56	22.00
Band7	15MHz	16QAM	20825	75RB#0	21.38	22.00
Band7	15MHz	QPSK	21100	1RB#0	22.71	23.00
Band7	15MHz	16QAM	21100	1RB#0	22.32	23.00
Band7	15MHz	QPSK	21100	1RB#38	22.88	23.00
Band7	15MHz	16QAM	21100	1RB#38	22.47	23.00
Band7	15MHz	QPSK	21100	1RB#74	22.96	23.00
Band7	15MHz	16QAM	21100	1RB#74	22.60	23.00
Band7	15MHz	QPSK	21100	38RB#0	22.24	23.00
Band7	15MHz	16QAM	21100	38RB#0	22.25	23.00
Band7	15MHz	QPSK	21100	38RB#18	22.25	23.00
Band7	15MHz	16QAM	21100	38RB#18	22.25	23.00
Band7	15MHz	QPSK	21100	38RB#37	22.26	23.00
Band7	15MHz	16QAM	21100	38RB#37	22.25	23.00
Band7	15MHz	QPSK	21100	75RB#0	22.25	23.00
Band7	15MHz	16QAM	21100	75RB#0	21.54	22.00
Band7	15MHz	QPSK	21375	1RB#0	21.94	22.00
Band7	15MHz	16QAM	21375	1RB#0	21.62	22.00
Band7	15MHz	QPSK	21375	1RB#38	22.15	23.00
Band7	15MHz	16QAM	21375	1RB#38	21.94	22.00
Band7	15MHz	QPSK	21375	1RB#74	22.50	23.00
Band7	15MHz	16QAM	21375	1RB#74	22.30	23.00
Band7	15MHz	QPSK	21375	38RB#0	22.20	23.00
Band7	15MHz	16QAM	21375	38RB#0	22.19	23.00
Band7	15MHz	QPSK	21375	38RB#18	22.18	23.00
Band7	15MHz	16QAM	21375	38RB#18	22.18	23.00
Band7	15MHz	QPSK	21375	38RB#37	22.17	23.00
Band7	15MHz	16QAM	21375	38RB#37	22.17	23.00
Band7	15MHz	QPSK	21375	75RB#0	22.17	23.00
Band7	15MHz	16QAM	21375	75RB#0	21.63	22.00
Band7	20MHz	QPSK	20850	1RB#0	21.97	22.00
Band7	20MHz	16QAM	20850	1RB#0	21.80	22.00



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band7	20MHz	QPSK	20850	1RB#49	21.35	22.00
Band7	20MHz	16QAM	20850	1RB#49	21.22	22.00
Band7	20MHz	QPSK	20850	1RB#99	22.62	23.00
Band7	20MHz	16QAM	20850	1RB#99	21.86	22.00
Band7	20MHz	QPSK	20850	50RB#0	21.43	22.00
Band7	20MHz	16QAM	20850	50RB#0	21.44	22.00
Band7	20MHz	QPSK	20850	50RB#25	21.43	22.00
Band7	20MHz	16QAM	20850	50RB#25	21.43	22.00
Band7	20MHz	QPSK	20850	50RB#50	21.83	22.00
Band7	20MHz	16QAM	20850	50RB#50	21.81	22.00
Band7	20MHz	QPSK	20850	100RB#0	21.61	22.00
Band7	20MHz	16QAM	20850	100RB#0	21.36	22.00
Band7	20MHz	QPSK	21100	1RB#0	23.15	24.00
Band7	20MHz	16QAM	21100	1RB#0	22.61	23.00
Band7	20MHz	QPSK	21100	1RB#49	23.36	24.00
Band7	20MHz	16QAM	21100	1RB#49	22.81	23.00
Band7	20MHz	QPSK	21100	1RB#99	23.36	24.00
Band7	20MHz	16QAM	21100	1RB#99	22.98	23.00
Band7	20MHz	QPSK	21100	50RB#0	22.27	23.00
Band7	20MHz	16QAM	21100	50RB#0	22.28	23.00
Band7	20MHz	QPSK	21100	50RB#25	22.29	23.00
Band7	20MHz	16QAM	21100	50RB#25	22.29	23.00
Band7	20MHz	QPSK	21100	50RB#50	22.49	23.00
Band7	20MHz	16QAM	21100	50RB#50	22.49	23.00
Band7	20MHz	QPSK	21100	100RB#0	22.39	23.00
Band7	20MHz	16QAM	21100	100RB#0	21.63	22.00
Band7	20MHz	QPSK	21350	1RB#0	22.29	23.00
Band7	20MHz	16QAM	21350	1RB#0	22.06	23.00
Band7	20MHz	QPSK	21350	1RB#49	21.93	22.00
Band7	20MHz	16QAM	21350	1RB#49	21.80	22.00
Band7	20MHz	QPSK	21350	1RB#99	22.92	23.00
Band7	20MHz	16QAM	21350	1RB#99	22.43	23.00
Band7	20MHz	QPSK	21350	50RB#0	21.92	22.00
Band7	20MHz	16QAM	21350	50RB#0	21.89	22.00
Band7	20MHz	QPSK	21350	50RB#25	21.89	22.00
Band7	20MHz	16QAM	21350	50RB#25	21.88	22.00
Band7	20MHz	QPSK	21350	50RB#50	22.43	23.00
Band7	20MHz	16QAM	21350	50RB#50	22.43	23.00
Band7	20MHz	QPSK	21350	100RB#0	22.16	23.00
Band7	20MHz	16QAM	21350	100RB#0	21.71	22.00



**7.1.7. Conducted Power Measurement Results(LTE Band 38)**

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Tune up(dBm)
Band38	5MHz	QPSK	37775	25RB#0	23.01	24.00
Band38	5MHz	16QAM	37775	25RB#0	22.17	23.00
Band38	5MHz	QPSK	38000	25RB#0	22.89	23.00
Band38	5MHz	16QAM	38000	25RB#0	22.28	23.00
Band38	5MHz	QPSK	38225	25RB#0	22.63	23.00
Band38	5MHz	16QAM	38225	25RB#0	21.91	22.00
Band38	10MHz	QPSK	37800	50RB#0	22.84	23.00
Band38	10MHz	16QAM	37800	50RB#0	22.13	23.00
Band38	10MHz	QPSK	38000	50RB#0	23.03	24.00
Band38	10MHz	16QAM	38000	50RB#0	22.05	23.00
Band38	10MHz	QPSK	38200	50RB#0	22.69	23.00
Band38	10MHz	16QAM	38200	50RB#0	21.84	22.00
Band38	15MHz	QPSK	37825	75RB#0	22.97	23.00
Band38	15MHz	16QAM	37825	75RB#0	22.12	23.00
Band38	15MHz	QPSK	38000	75RB#0	22.98	23.00
Band38	15MHz	16QAM	38000	75RB#0	22.11	23.00
Band38	15MHz	QPSK	38175	75RB#0	22.75	23.00
Band38	15MHz	16QAM	38175	75RB#0	21.87	22.00
Band38	20MHz	QPSK	37850	100RB#0	23.01	24.00
Band38	5MHz	QPSK	37775	1RB#0	23.85	24.00
Band38	5MHz	16QAM	37775	1RB#0	27.93	28.00
Band38	5MHz	QPSK	37775	1RB#12	23.90	24.00
Band38	5MHz	16QAM	37775	1RB#12	23.29	24.00
Band38	5MHz	QPSK	37775	1RB#24	24.00	25.00
Band38	20MHz	16QAM	37850	100RB#0	22.29	23.00
Band38	20MHz	QPSK	38000	100RB#0	23.02	24.00
Band38	20MHz	16QAM	38000	100RB#0	22.13	23.00
Band38	20MHz	QPSK	38150	100RB#0	22.79	23.00
Band38	20MHz	16QAM	38150	100RB#0	21.82	22.00
Band38	5MHz	16QAM	37775	1RB#24	23.43	24.00
Band38	5MHz	QPSK	37775	12RB#0	22.83	23.00
Band38	5MHz	16QAM	37775	12RB#0	21.93	22.00
Band38	5MHz	QPSK	37775	12RB#6	22.81	23.00
Band38	5MHz	16QAM	37775	12RB#6	21.98	22.00
Band38	5MHz	QPSK	37775	12RB#13	22.78	23.00
Band38	5MHz	16QAM	37775	12RB#13	21.92	22.00
Band38	5MHz	QPSK	38000	1RB#0	24.03	25.00
Band38	5MHz	16QAM	38000	1RB#0	23.20	24.00
Band38	5MHz	QPSK	38000	1RB#12	24.03	25.00
Band38	5MHz	16QAM	38000	1RB#12	23.24	24.00
Band38	5MHz	QPSK	38000	1RB#24	23.95	24.00
Band38	5MHz	16QAM	38000	1RB#24	23.38	24.00
Band38	5MHz	QPSK	38000	12RB#0	23.08	24.00
Band38	5MHz	16QAM	38000	12RB#0	22.14	23.00
Band38	5MHz	QPSK	38000	12RB#6	23.07	24.00
Band38	5MHz	16QAM	38000	12RB#6	22.13	23.00
Band38	5MHz	QPSK	38000	12RB#13	23.03	24.00
Band38	5MHz	16QAM	38000	12RB#13	22.05	23.00
Band38	5MHz	QPSK	38225	1RB#0	23.56	24.00
Band38	5MHz	16QAM	38225	1RB#0	23.18	24.00
Band38	5MHz	QPSK	38225	1RB#12	23.66	24.00
Band38	5MHz	16QAM	38225	1RB#12	23.15	24.00
Band38	5MHz	QPSK	38225	1RB#24	23.58	24.00
Band38	5MHz	16QAM	38225	1RB#24	23.07	24.00
Band38	5MHz	QPSK	38225	12RB#0	22.64	23.00
Band38	5MHz	16QAM	38225	12RB#0	21.74	22.00
Band38	5MHz	QPSK	38225	12RB#6	22.65	23.00
Band38	5MHz	16QAM	38225	12RB#6	21.73	22.00
Band38	5MHz	QPSK	38225	12RB#13	22.61	23.00
Band38	5MHz	16QAM	38225	12RB#13	21.67	22.00
Band38	10MHz	QPSK	37800	1RB#0	23.96	24.00
Band38	10MHz	16QAM	37800	1RB#0	23.25	24.00



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band38	10MHz	QPSK	37800	1RB#24	24.03	25.00
Band38	10MHz	16QAM	37800	1RB#24	23.17	24.00
Band38	10MHz	QPSK	37800	1RB#49	24.08	25.00
Band38	10MHz	16QAM	37800	1RB#49	23.18	24.00
Band38	10MHz	QPSK	37800	25RB#0	22.93	23.00
Band38	10MHz	16QAM	37800	25RB#0	22.14	23.00
Band38	10MHz	QPSK	37800	25RB#12	22.93	23.00
Band38	10MHz	16QAM	37800	25RB#12	22.13	23.00
Band38	10MHz	QPSK	37800	25RB#25	22.95	23.00
Band38	10MHz	16QAM	37800	25RB#25	22.07	23.00
Band38	10MHz	QPSK	38000	1RB#0	23.93	24.00
Band38	10MHz	16QAM	38000	1RB#0	22.94	23.00
Band38	10MHz	QPSK	38000	1RB#24	23.99	24.00
Band38	10MHz	16QAM	38000	1RB#24	22.92	23.00
Band38	10MHz	QPSK	38000	1RB#49	23.95	24.00
Band38	10MHz	16QAM	38000	1RB#49	22.83	23.00
Band38	10MHz	QPSK	38000	25RB#0	23.09	24.00
Band38	10MHz	16QAM	38000	25RB#0	22.35	23.00
Band38	10MHz	QPSK	38000	25RB#12	22.93	23.00
Band38	10MHz	16QAM	38000	25RB#12	22.34	23.00
Band38	10MHz	QPSK	38000	25RB#25	22.94	23.00
Band38	10MHz	16QAM	38000	25RB#25	22.31	23.00
Band38	10MHz	QPSK	38200	1RB#0	23.83	24.00
Band38	10MHz	16QAM	38200	1RB#0	23.29	24.00
Band38	10MHz	QPSK	38200	1RB#24	23.77	24.00
Band38	10MHz	16QAM	38200	1RB#24	23.35	24.00
Band38	10MHz	QPSK	38200	1RB#49	23.76	24.00
Band38	10MHz	16QAM	38200	1RB#49	23.25	24.00
Band38	10MHz	QPSK	38200	25RB#0	22.60	23.00
Band38	10MHz	16QAM	38200	25RB#0	21.82	22.00
Band38	10MHz	QPSK	38200	25RB#12	22.62	23.00
Band38	10MHz	16QAM	38200	25RB#12	21.83	22.00
Band38	10MHz	QPSK	38200	25RB#25	22.61	23.00
Band38	10MHz	16QAM	38200	25RB#25	21.78	22.00
Band38	15MHz	QPSK	37825	1RB#0	24.18	25.00
Band38	15MHz	16QAM	37825	1RB#0	23.37	24.00
Band38	15MHz	QPSK	37825	1RB#38	24.15	25.00
Band38	15MHz	16QAM	37825	1RB#38	23.29	24.00
Band38	15MHz	QPSK	37825	1RB#74	24.20	25.00
Band38	15MHz	16QAM	37825	1RB#74	23.42	24.00
Band38	15MHz	QPSK	37825	38RB#0	22.97	23.00
Band38	15MHz	16QAM	37825	38RB#0	22.97	23.00
Band38	15MHz	QPSK	37825	38RB#18	22.96	23.00
Band38	15MHz	16QAM	37825	38RB#18	22.96	23.00
Band38	15MHz	QPSK	37825	38RB#37	22.97	23.00
Band38	15MHz	16QAM	37825	38RB#37	22.97	23.00
Band38	15MHz	QPSK	38000	1RB#0	24.16	25.00
Band38	15MHz	16QAM	38000	1RB#0	22.66	23.00
Band38	15MHz	QPSK	38000	1RB#38	24.08	25.00
Band38	15MHz	16QAM	38000	1RB#38	22.77	23.00
Band38	15MHz	QPSK	38000	1RB#74	24.00	25.00
Band38	15MHz	16QAM	38000	1RB#74	22.03	23.00
Band38	15MHz	QPSK	38000	38RB#0	22.98	23.00
Band38	15MHz	16QAM	38000	38RB#0	22.97	23.00
Band38	15MHz	QPSK	38000	38RB#18	22.98	23.00
Band38	15MHz	16QAM	38000	38RB#18	22.98	23.00
Band38	15MHz	QPSK	38000	38RB#37	22.98	23.00
Band38	15MHz	16QAM	38000	38RB#37	22.98	23.00
Band38	15MHz	QPSK	38175	1RB#0	23.89	24.00
Band38	15MHz	16QAM	38175	1RB#0	23.51	24.00
Band38	15MHz	QPSK	38175	1RB#38	23.85	24.00
Band38	15MHz	16QAM	38175	1RB#38	23.27	24.00
Band38	15MHz	QPSK	38175	1RB#74	23.78	24.00
Band38	15MHz	16QAM	38175	1RB#74	23.27	24.00
Band38	15MHz	QPSK	38175	38RB#0	22.62	23.00
Band38	15MHz	16QAM	38175	38RB#0	22.61	23.00



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band38	15MHz	QPSK	38175	38RB#18	22.77	23.00
Band38	15MHz	16QAM	38175	38RB#18	22.77	23.00
Band38	15MHz	QPSK	38175	38RB#37	22.77	23.00
Band38	15MHz	16QAM	38175	38RB#37	22.75	23.00
Band38	20MHz	QPSK	37850	1RB#0	23.82	24.00
Band38	20MHz	16QAM	37850	1RB#0	23.28	24.00
Band38	20MHz	QPSK	37850	1RB#49	23.95	24.00
Band38	20MHz	16QAM	37850	1RB#49	23.39	24.00
Band38	20MHz	QPSK	37850	1RB#99	23.92	24.00
Band38	20MHz	16QAM	37850	1RB#99	23.15	24.00
Band38	20MHz	QPSK	37850	50RB#0	23.03	24.00
Band38	20MHz	16QAM	37850	50RB#0	22.37	23.00
Band38	20MHz	QPSK	37850	50RB#25	23.05	24.00
Band38	20MHz	16QAM	37850	50RB#25	22.31	23.00
Band38	20MHz	QPSK	37850	50RB#50	22.98	23.00
Band38	20MHz	16QAM	37850	50RB#50	22.31	23.00
Band38	20MHz	QPSK	38000	1RB#0	24.19	25.00
Band38	20MHz	16QAM	38000	1RB#0	23.56	24.00
Band38	20MHz	QPSK	38000	1RB#49	24.13	25.00
Band38	20MHz	16QAM	38000	1RB#49	23.49	24.00
Band38	20MHz	QPSK	38000	1RB#99	23.91	24.00
Band38	20MHz	16QAM	38000	1RB#99	23.32	24.00
Band38	20MHz	QPSK	38000	50RB#0	23.08	24.00
Band38	20MHz	16QAM	38000	50RB#0	22.23	23.00
Band38	20MHz	QPSK	38000	50RB#25	22.93	23.00
Band38	20MHz	16QAM	38000	50RB#25	22.20	23.00
Band38	20MHz	QPSK	38000	50RB#50	22.96	23.00
Band38	20MHz	16QAM	38000	50RB#50	22.11	23.00
Band38	20MHz	QPSK	38150	1RB#0	23.91	24.00
Band38	20MHz	16QAM	38150	1RB#0	23.37	24.00
Band38	20MHz	QPSK	38150	1RB#49	23.88	24.00
Band38	20MHz	16QAM	38150	1RB#49	23.14	24.00
Band38	20MHz	QPSK	38150	1RB#99	23.82	24.00
Band38	20MHz	16QAM	38150	1RB#99	23.06	24.00
Band38	20MHz	QPSK	38150	50RB#0	22.93	23.00
Band38	20MHz	16QAM	38150	50RB#0	21.92	22.00
Band38	20MHz	QPSK	38150	50RB#25	22.79	23.00
Band38	20MHz	16QAM	38150	50RB#25	21.89	22.00
Band38	20MHz	QPSK	38150	50RB#50	22.65	23.00
Band38	20MHz	16QAM	38150	50RB#50	21.88	22.00



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity

**7.1.8. Conducted Power Measurement Results(LTE Band 41)**

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Tune up(dBm)
Band41	5MHz	QPSK	39675	1RB#0	22.86	23.00
Band41	5MHz	16QAM	39675	1RB#0	22.82	23.00
Band41	5MHz	QPSK	39675	1RB#12	22.85	23.00
Band41	5MHz	16QAM	39675	1RB#12	22.75	23.00
Band41	5MHz	QPSK	39675	1RB#24	22.79	23.00
Band41	5MHz	16QAM	39675	1RB#24	22.92	23.00
Band41	5MHz	QPSK	39675	12RB#0	21.92	22.00
Band41	5MHz	16QAM	39675	12RB#0	21.93	22.00
Band41	5MHz	QPSK	39675	12RB#6	21.93	22.00
Band41	5MHz	16QAM	39675	12RB#6	21.93	22.00
Band41	5MHz	QPSK	39675	12RB#13	21.93	22.00
Band41	5MHz	16QAM	39675	12RB#13	21.94	22.00
Band41	5MHz	QPSK	39675	25RB#0	21.93	22.00
Band41	5MHz	16QAM	39675	25RB#0	21.33	22.00
Band41	5MHz	QPSK	40620	1RB#0	21.87	22.00
Band41	5MHz	16QAM	40620	1RB#0	21.54	22.00
Band41	5MHz	QPSK	40620	1RB#12	21.78	22.00
Band41	5MHz	16QAM	40620	1RB#12	21.46	22.00
Band41	5MHz	QPSK	40620	1RB#24	21.73	22.00
Band41	5MHz	16QAM	40620	1RB#24	21.42	22.00
Band41	5MHz	QPSK	40620	12RB#0	20.84	21.00
Band41	5MHz	16QAM	40620	12RB#0	20.82	21.00
Band41	5MHz	QPSK	40620	12RB#6	20.85	21.00
Band41	5MHz	16QAM	40620	12RB#6	20.86	21.00
Band41	5MHz	QPSK	40620	12RB#13	20.86	21.00
Band41	5MHz	16QAM	40620	12RB#13	20.87	21.00
Band41	5MHz	QPSK	40620	25RB#0	20.87	21.00
Band41	5MHz	16QAM	40620	25RB#0	20.10	21.00
Band41	5MHz	QPSK	41565	1RB#0	22.92	23.00
Band41	5MHz	16QAM	41565	1RB#0	22.77	23.00
Band41	5MHz	QPSK	41565	1RB#12	23.01	24.00
Band41	5MHz	16QAM	41565	1RB#12	22.78	23.00
Band41	5MHz	QPSK	41565	1RB#24	23.07	24.00
Band41	5MHz	16QAM	41565	1RB#24	22.74	23.00
Band41	5MHz	QPSK	41565	12RB#0	22.26	23.00
Band41	5MHz	16QAM	41565	12RB#0	22.26	23.00
Band41	5MHz	QPSK	41565	12RB#6	22.26	23.00
Band41	5MHz	16QAM	41565	12RB#6	22.26	23.00
Band41	5MHz	QPSK	41565	12RB#13	22.27	23.00
Band41	5MHz	16QAM	41565	12RB#13	22.27	23.00
Band41	5MHz	QPSK	41565	25RB#0	22.27	23.00
Band41	5MHz	16QAM	41565	25RB#0	21.55	22.00
Band41	10MHz	QPSK	39700	1RB#0	23.68	24.00
Band41	10MHz	16QAM	39700	1RB#0	23.29	24.00
Band41	10MHz	QPSK	39700	1RB#24	23.57	24.00
Band41	10MHz	16QAM	39700	1RB#24	23.27	24.00
Band41	10MHz	QPSK	39700	1RB#49	23.56	24.00
Band41	10MHz	16QAM	39700	1RB#49	23.29	24.00
Band41	10MHz	QPSK	39700	25RB#0	22.58	23.00
Band41	10MHz	16QAM	39700	25RB#0	22.58	23.00
Band41	10MHz	QPSK	39700	25RB#12	22.58	23.00
Band41	10MHz	16QAM	39700	25RB#12	22.58	23.00
Band41	10MHz	QPSK	39700	25RB#25	22.49	23.00
Band41	10MHz	16QAM	39700	25RB#25	22.48	23.00
Band41	10MHz	QPSK	39700	50RB#0	22.61	23.00
Band41	10MHz	16QAM	39700	50RB#0	21.82	22.00
Band41	10MHz	QPSK	40620	1RB#0	23.02	24.00
Band41	10MHz	16QAM	40620	1RB#0	22.37	23.00
Band41	10MHz	QPSK	40620	1RB#24	22.92	23.00
Band41	10MHz	16QAM	40620	1RB#24	22.28	23.00
Band41	10MHz	QPSK	40620	1RB#49	22.88	23.00



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band41	10MHz	16QAM	40620	1RB#49	21.66	22.00
Band41	10MHz	QPSK	40620	25RB#0	21.92	22.00
Band41	10MHz	16QAM	40620	25RB#0	21.92	22.00
Band41	10MHz	QPSK	40620	25RB#12	21.96	22.00
Band41	10MHz	16QAM	40620	25RB#12	22.08	23.00
Band41	10MHz	QPSK	40620	25RB#25	21.88	22.00
Band41	10MHz	16QAM	40620	25RB#25	21.92	22.00
Band41	10MHz	QPSK	40620	50RB#0	21.82	22.00
Band41	10MHz	16QAM	40620	50RB#0	21.13	22.00
Band41	10MHz	QPSK	41540	1RB#0	22.93	23.00
Band41	10MHz	16QAM	41540	1RB#0	22.81	23.00
Band41	10MHz	QPSK	41540	1RB#24	22.94	23.00
Band41	10MHz	16QAM	41540	1RB#24	22.73	23.00
Band41	10MHz	QPSK	41540	1RB#49	23.05	24.00
Band41	10MHz	16QAM	41540	1RB#49	22.77	23.00
Band41	10MHz	QPSK	41540	25RB#0	22.07	23.00
Band41	10MHz	16QAM	41540	25RB#0	22.03	23.00
Band41	10MHz	QPSK	41540	25RB#12	22.04	23.00
Band41	10MHz	16QAM	41540	25RB#12	22.04	23.00
Band41	10MHz	QPSK	41540	25RB#25	22.04	23.00
Band41	10MHz	16QAM	41540	25RB#25	22.04	23.00
Band41	10MHz	QPSK	41540	50RB#0	21.90	22.00
Band41	10MHz	16QAM	41540	50RB#0	21.10	22.00
Band41	15MHz	QPSK	39725	1RB#0	23.57	24.00
Band41	15MHz	16QAM	39725	1RB#0	23.27	24.00
Band41	15MHz	QPSK	39725	1RB#38	23.49	24.00
Band41	15MHz	16QAM	39725	1RB#38	22.39	23.00
Band41	15MHz	QPSK	39725	1RB#74	22.85	23.00
Band41	15MHz	16QAM	39725	1RB#74	22.35	23.00
Band41	15MHz	QPSK	39725	38RB#0	22.13	23.00
Band41	15MHz	16QAM	39725	38RB#0	22.10	23.00
Band41	15MHz	QPSK	39725	38RB#18	22.10	23.00
Band41	15MHz	16QAM	39725	38RB#18	22.09	23.00
Band41	15MHz	QPSK	39725	38RB#37	22.09	23.00
Band41	15MHz	16QAM	39725	38RB#37	22.09	23.00
Band41	15MHz	QPSK	39725	75RB#0	22.09	23.00
Band41	15MHz	16QAM	39725	75RB#0	21.45	22.00
Band41	15MHz	QPSK	40620	1RB#0	23.46	24.00
Band41	15MHz	16QAM	40620	1RB#0	21.98	22.00
Band41	15MHz	QPSK	40620	1RB#38	23.34	24.00
Band41	15MHz	16QAM	40620	1RB#38	21.70	22.00
Band41	15MHz	QPSK	40620	1RB#74	23.17	24.00
Band41	15MHz	16QAM	40620	1RB#74	21.74	22.00
Band41	15MHz	QPSK	40620	38RB#0	22.17	23.00
Band41	15MHz	16QAM	40620	38RB#0	22.15	23.00
Band41	15MHz	QPSK	40620	38RB#18	22.15	23.00
Band41	15MHz	16QAM	40620	38RB#18	22.15	23.00
Band41	15MHz	QPSK	40620	38RB#37	22.15	23.00
Band41	15MHz	16QAM	40620	38RB#37	22.15	23.00
Band41	15MHz	QPSK	40620	75RB#0	22.15	23.00
Band41	15MHz	16QAM	40620	75RB#0	21.10	22.00
Band41	15MHz	QPSK	41515	1RB#0	22.91	23.00
Band41	15MHz	16QAM	41515	1RB#0	22.79	23.00
Band41	15MHz	QPSK	41515	1RB#38	22.91	23.00
Band41	15MHz	16QAM	41515	1RB#38	22.90	23.00
Band41	15MHz	QPSK	41515	1RB#74	22.98	23.00
Band41	15MHz	16QAM	41515	1RB#74	22.79	23.00
Band41	15MHz	QPSK	41515	38RB#0	21.89	22.00
Band41	15MHz	16QAM	41515	38RB#0	21.85	22.00
Band41	15MHz	QPSK	41515	38RB#18	21.85	22.00
Band41	15MHz	16QAM	41515	38RB#18	21.85	22.00
Band41	15MHz	QPSK	41515	38RB#37	21.85	22.00
Band41	15MHz	16QAM	41515	38RB#37	21.85	22.00
Band41	15MHz	QPSK	41515	75RB#0	21.85	22.00
Band41	15MHz	16QAM	41515	75RB#0	21.06	22.00
Band41	20MHz	QPSK	39750	1RB#0	23.23	24.00



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band41	20MHz	16QAM	39750	1RB#0	22.70	23.00
Band41	20MHz	QPSK	39750	1RB#49	23.04	24.00
Band41	20MHz	16QAM	39750	1RB#49	22.58	23.00
Band41	20MHz	QPSK	39750	1RB#99	22.92	23.00
Band41	20MHz	16QAM	39750	1RB#99	22.60	23.00
Band41	20MHz	QPSK	39750	50RB#0	22.16	23.00
Band41	20MHz	16QAM	39750	50RB#0	21.54	22.00
Band41	20MHz	QPSK	39750	50RB#25	22.17	23.00
Band41	20MHz	16QAM	39750	50RB#25	21.54	22.00
Band41	20MHz	QPSK	39750	50RB#50	22.01	23.00
Band41	20MHz	16QAM	39750	50RB#50	21.40	22.00
Band41	20MHz	QPSK	39750	100RB#0	22.01	23.00
Band41	20MHz	16QAM	39750	100RB#0	21.44	22.00
Band41	20MHz	QPSK	40620	1RB#0	23.32	24.00
Band41	20MHz	16QAM	40620	1RB#0	22.55	23.00
Band41	20MHz	QPSK	40620	1RB#49	23.19	24.00
Band41	20MHz	16QAM	40620	1RB#49	22.35	23.00
Band41	20MHz	QPSK	40620	1RB#99	23.10	24.00
Band41	20MHz	16QAM	40620	1RB#99	22.12	23.00
Band41	20MHz	QPSK	40620	50RB#0	22.15	23.00
Band41	20MHz	16QAM	40620	50RB#0	21.48	22.00
Band41	20MHz	QPSK	40620	50RB#25	22.16	23.00
Band41	20MHz	16QAM	40620	50RB#25	21.48	22.00
Band41	20MHz	QPSK	40620	50RB#50	22.09	23.00
Band41	20MHz	16QAM	40620	50RB#50	21.24	22.00
Band41	20MHz	QPSK	40620	100RB#0	22.02	23.00
Band41	20MHz	16QAM	40620	100RB#0	21.36	22.00
Band41	20MHz	QPSK	41490	1RB#0	22.89	23.00
Band41	20MHz	16QAM	41490	1RB#0	21.99	22.00
Band41	20MHz	QPSK	41490	1RB#49	22.91	23.00
Band41	20MHz	16QAM	41490	1RB#49	21.84	22.00
Band41	20MHz	QPSK	41490	1RB#99	23.06	24.00
Band41	20MHz	16QAM	41490	1RB#99	22.00	23.00
Band41	20MHz	QPSK	41490	50RB#0	22.01	23.00
Band41	20MHz	16QAM	41490	50RB#0	21.19	22.00
Band41	20MHz	QPSK	41490	50RB#25	22.02	23.00
Band41	20MHz	16QAM	41490	50RB#25	21.14	22.00
Band41	20MHz	QPSK	41490	50RB#50	22.06	23.00
Band41	20MHz	16QAM	41490	50RB#50	21.18	22.00
Band41	20MHz	QPSK	41490	100RB#0	21.96	22.00
Band41	20MHz	16QAM	41490	100RB#0	21.17	22.00





7.1.9. Conducted Power Measurement Results(WIFI 2.4G)

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Duty Factor (dB)	Total Power (dBm)	Tune Up (dBm)
NVNT	b	2412	Ant1	15.01	0	15.01	16.00
NVNT	b	2437	Ant1	15.35	0	15.35	16.00
NVNT	b	2462	Ant1	15.66	0	15.66	16.00
NVNT	g	2412	Ant1	14.73	0	14.73	15.00
NVNT	g	2437	Ant1	14.65	0	14.65	15.00
NVNT	g	2462	Ant1	14.33	0	14.33	15.00
NVNT	n20	2412	Ant1	13.07	0	13.07	14.00
NVNT	n20	2437	Ant1	12.81	0	12.81	14.00
NVNT	n20	2462	Ant1	13.78	0	13.78	14.00
NVNT	n40	2422	Ant1	12.63	0	12.63	13.00
NVNT	n40	2437	Ant1	11.88	0	11.88	13.00
NVNT	n40	2452	Ant1	12.54	0	12.54	13.00

Note:

a) Power must be measured at each transmit antenna port according to the DSSS and OFDM transmission configurations in each standalone and aggregated frequency band.

b) Power measurement is required for the transmission mode configuration with the highest maximum output power specified for production units.


1) When the same highest maximum output power specification applies to multiple transmission modes, the largest channel bandwidth configuration with the lowest order modulation and lowest data rate is measured.

2) When the same highest maximum output power is specified for multiple largest channel bandwidth configurations with the same lowest order modulation or lowest order modulation and lowest data rate, power measurement is required for all equivalent 802.11 configurations with the same maximum output power.

c) For each transmission mode configuration, power must be measured for the highest and lowest channels; and at the mid-band channel(s) when there are at least 3 channels. For configurations with multiple mid-band channels, due to an even number of channels, both channels should be measured.

WIFI 2.4G (802.11b):

Duty cycle=99.16%



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



7.1.11. Conducted Power Measurement Results(WIFI 5.3G)

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Duty Factor (dB)	Total Power (dBm)	Tune Up (dBm)
NVNT	a	5260	Ant1	12.24	0.24	12.48	12.50
NVNT	a	5300	Ant1	11.95	0.24	12.19	12.50
NVNT	a	5320	Ant1	12.11	0.24	12.35	12.50
NVNT	n20	5260	Ant1	11.85	0.12	11.97	12.00
NVNT	n20	5300	Ant1	11.41	0.12	11.53	12.00
NVNT	n20	5320	Ant1	11.31	0.12	11.43	12.00
NVNT	n40	5270	Ant1	10.87	0.23	11.1	11.50
NVNT	n40	5310	Ant1	10.07	0.24	10.31	11.50
NVNT	ac20	5260	Ant1	11.32	0.12	11.44	12.50
NVNT	ac20	5300	Ant1	11.84	0.12	11.96	12.50
NVNT	ac20	5320	Ant1	11.97	0.12	12.09	12.50
NVNT	ac40	5270	Ant1	10.88	0.24	11.12	11.50
NVNT	ac40	5310	Ant1	10.02	0.24	10.26	11.50
NVNT	ac80	5290	Ant1	8.93	0.25	9.18	9.50

Note:

a) Power must be measured at each transmit antenna port according to the DSSS and OFDM transmission configurations in each standalone and aggregated frequency band.

b) Power measurement is required for the transmission mode configuration with the highest maximum output power specified for production units.


1) When the same highest maximum output power specification applies to multiple transmission modes, the largest channel bandwidth configuration with the lowest order modulation and lowest data rate is measured.

2) When the same highest maximum output power is specified for multiple largest channel bandwidth configurations with the same lowest order modulation or lowest order modulation and lowest data rate, power measurement is required for all equivalent 802.11 configurations with the same maximum output power.

c) For each transmission mode configuration, power must be measured for the highest and lowest channels; and at the mid-band channel(s) when there are at least 3 channels. For configurations with multiple mid-band channels, due to an even number of channels, both channels should be measured.

WIFI 5.3G (802.11a):

Duty cycle=94.56%





7.1.12. Conducted Power Measurement Results(WIFI 5.5G)

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Duty Factor (dB)	Total Power (dBm)	Tune Up (dBm)
NVNT	a	5500	Ant1	12.82	0.24	13.06	14.00
NVNT	a	5580	Ant1	12.2	0.24	12.44	13.00
NVNT	a	5700	Ant1	11.81	0.24	12.05	13.00
NVNT	n20	5500	Ant1	10.92	0.12	11.04	12.00
NVNT	n20	5580	Ant1	11.24	0.12	11.36	12.00
NVNT	n20	5700	Ant1	11.23	0.12	11.35	12.00
NVNT	n40	5510	Ant1	10.99	0.24	11.23	12.00
NVNT	n40	5550	Ant1	11.08	0.24	11.32	12.00
NVNT	n40	5670	Ant1	10.77	0.24	11.01	12.00
NVNT	ac20	5500	Ant1	11.44	0.12	11.56	12.00
NVNT	ac20	5580	Ant1	11.71	0.12	11.83	12.00
NVNT	ac20	5700	Ant1	11.23	0.12	11.35	12.00
NVNT	ac40	5510	Ant1	10.59	0.24	10.83	11.00
NVNT	ac40	5550	Ant1	10.67	0.24	10.91	11.00
NVNT	ac40	5670	Ant1	9.74	0.24	9.98	10.00
NVNT	ac80	5530	Ant1	9.43	0.25	9.68	10.00
NVNT	ac80	5610	Ant1	9.67	0.25	9.92	10.00

Note:

a) Power must be measured at each transmit antenna port according to the DSSS and OFDM transmission configurations in each standalone and aggregated frequency band.

b) Power measurement is required for the transmission mode configuration with the highest maximum output power specified for production units.


1) When the same highest maximum output power specification applies to multiple transmission modes, the largest channel bandwidth configuration with the lowest order modulation and lowest data rate is measured.

2) When the same highest maximum output power is specified for multiple largest channel bandwidth configurations with the same lowest order modulation or lowest order modulation and lowest data rate, power measurement is required for all equivalent 802.11 configurations with the same maximum output power.

c) For each transmission mode configuration, power must be measured for the highest and lowest channels; and at the mid-band channel(s) when there are at least 3 channels. For configurations with multiple mid-band channels, due to an even number of channels, both channels should be measured.

WIFI 5.5G (802.11a):

Duty cycle=94.65%



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity

**7.1.13. Conducted Power Measurement Results(WIFI 5.8G)**

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Duty Factor (dB)	Total Power (dBm)	Tune Up (dBm)
NVNT	a	5745	Ant1	11.95	0.24	12.19	13.00
NVNT	a	5785	Ant1	12.38	0.24	12.62	13.00
NVNT	a	5825	Ant1	12.63	0.24	12.87	13.00
NVNT	n20	5745	Ant1	11.3	0.12	11.42	12.00
NVNT	n20	5785	Ant1	11.66	0.12	11.78	12.00
NVNT	n20	5825	Ant1	11.54	0.12	11.66	12.00
NVNT	n40	5755	Ant1	10.17	0.24	10.41	11.50
NVNT	n40	5795	Ant1	10.88	0.23	11.11	11.50
NVNT	ac20	5745	Ant1	11.72	0.12	11.84	12.00
NVNT	ac20	5785	Ant1	11.2	0.12	11.32	12.00
NVNT	ac20	5825	Ant1	11.52	0.12	11.64	12.00
NVNT	ac40	5755	Ant1	10.34	0.24	10.58	11.50
NVNT	ac40	5795	Ant1	10.86	0.24	11.1	11.50
NVNT	ac80	5775	Ant1	9.52	0.47	9.99	10.00

Note:

a) Power must be measured at each transmit antenna port according to the DSSS and OFDM transmission configurations in each standalone and aggregated frequency band.

b) Power measurement is required for the transmission mode configuration with the highest maximum output power specified for production units.


1) When the same highest maximum output power specification applies to multiple transmission modes, the largest channel bandwidth configuration with the lowest order modulation and lowest data rate is measured.

2) When the same highest maximum output power is specified for multiple largest channel bandwidth configurations with the same lowest order modulation or lowest order modulation and lowest data rate, power measurement is required for all equivalent 802.11 configurations with the same maximum output power.

c) For each transmission mode configuration, power must be measured for the highest and lowest channels; and at the mid-band channel(s) when there are at least 3 channels. For configurations with multiple mid-band channels, due to an even number of channels, both channels should be measured.

WIFI 5.8G (802.11a):

Duty cycle=94.56%



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



7.1.14. Conducted Power Measurement Results(Bluetooth)

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Tune Up (dBm)
NVNT	1-DH5	2402	Ant1	-0.22	0.00
NVNT	1-DH5	2441	Ant1	0.01	1.00
NVNT	1-DH5	2480	Ant1	-1.09	-1.00
NVNT	2-DH5	2402	Ant1	1.53	2.00
NVNT	2-DH5	2441	Ant1	1.78	2.00
NVNT	2-DH5	2480	Ant1	0.62	1.00
NVNT	3-DH5	2402	Ant1	-0.56	0.00
NVNT	3-DH5	2441	Ant1	-0.25	0.00
NVNT	3-DH5	2480	Ant1	0.96	1.00

BLE

TestMode	Antenna	Frequency (MHz)	Antenna	Conducted Power (dBm)	Tune Up (dBm)
BLE 1M	Ant1	2402	Ant1	0.68	1.00
		2440	Ant1	0.36	1.00
		2480	Ant1	-0.75	0.00
BLE 2M	Ant1	2402	Ant1	0.59	1.00
		2440	Ant1	0.17	1.00
		2480	Ant1	-0.92	0.00





7.2. Stand-alone SAR test evaluation

Unless specifically required by the published RF exposure KDB procedures, standalone 1-g head or body and Product specific 10g SAR evaluation for general population exposure conditions, by measurement or numerical simulation, is not required when the corresponding SAR Test Exclusion Threshold condition is satisfied. These test exclusion conditions are based on source-based time-averaged maximum conducted output power of the RF channel requiring evaluation, adjusted for tune-up tolerance, and the minimum test separation distance required for the exposure conditions.

SAR Test Exclusion Thresholds for 100 MHz – 6 GHz and ≤ 50 mm

MHz	5	10	15	20	25	mm
150	39	77	116	155	194	SAR Test Exclusion Threshold (mW)
300	27	55	82	110	137	
450	22	45	67	89	112	
835	16	33	49	66	82	
900	16	32	47	63	79	
1500	12	24	37	49	61	
1900	11	22	33	44	54	
2450	10	19	29	38	48	
3600	8	16	24	32	40	
5200	7	13	20	26	33	
5400	6	13	19	26	32	
5800	6	12	19	25	31	
MHz	30	35	40	45	50	mm
150	232	271	310	349	387	SAR Test Exclusion Threshold (mW)
300	164	192	219	246	274	
450	134	157	179	201	224	
835	98	115	131	148	164	
900	95	111	126	142	158	
1500	73	86	98	110	122	
1900	65	76	87	98	109	
2450	57	67	77	86	96	
3600	47	55	63	71	79	
5200	39	46	53	59	66	
5400	39	45	52	58	65	
5800	37	44	50	56	62	

When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.





The test exclusions are applicable only when the minimum test separation distance is > 50 mm and for transmission frequencies between 100 MHz and 6 GHz.

SAR Test Exclusion Thresholds for 100 MHz – 6 GHz and > 50 mm

MHz	50	60	70	80	90	100	110	120	130	140	150	160	170	180	190	mm
100	474	481	487	494	501	507	514	521	527	534	541	547	554	561	567	mW
150	387	397	407	417	427	437	447	457	467	477	487	497	507	517	527	
300	274	294	314	334	354	374	394	414	434	454	474	494	514	534	554	
450	224	254	284	314	344	374	404	434	464	494	524	554	584	614	644	
835	164	220	275	331	387	442	498	554	609	665	721	776	832	888	943	
900	158	218	278	338	398	458	518	578	638	698	758	818	878	938	998	
1500	122	222	322	422	522	622	722	822	922	1022	1122	1222	1322	1422	1522	
1900	109	209	309	409	509	609	709	809	909	1009	1109	1209	1309	1409	1509	
2450	96	196	296	396	496	596	696	796	896	996	1096	1196	1296	1396	1496	
3600	79	179	279	379	479	579	679	779	879	979	1079	1179	1279	1379	1479	
5200	66	166	266	366	466	566	666	766	866	966	1066	1166	1266	1366	1466	
5400	65	165	265	365	465	565	665	765	865	965	1065	1165	1265	1365	1465	
5800	62	162	262	362	462	562	662	762	862	962	1062	1162	1262	1362	1462	

According to the table above, Standalone SAR exclusion calculation for this device are as below:

Freq. Band	Frequency (MHz)	Position	Test Separation (mm)	Max Power (dBm)	Max Power (mW)	Exclusion Threshold (mW)	Exclusion (Yes/No)
BT	2441	Rear side	5	2.00	1.58	10	Yes
	2441	Left side	64	2.00	1.58	236	Yes
	2441	Right side	152	2.00	1.58	1116	Yes
	2441	Top side	5	2.00	1.58	10	Yes
	2441	Bottom side	152	2.00	1.58	1116	Yes
Wi-Fi 2.4G	2462	Rear side	5	16.00	39.81	10	No
	2462	Left side	64	16.00	39.81	236	Yes
	2462	Right side	152	16.00	39.81	1116	Yes
	2462	Top side	5	16.00	39.81	10	No
	2462	Bottom side	152	16.00	39.81	1116	Yes
Wi-Fi 5.2G	5240	Rear side	5	13.00	19.95	7	No
	5240	Left side	64	13.00	19.95	206	Yes
	5240	Right side	152	13.00	19.95	1086	Yes
	5240	Top side	5	13.00	19.95	7	No
	5240	Bottom side	152	13.00	19.95	1086	Yes
Wi-Fi 5.3G	5260	Rear side	5	12.50	17.78	6	No
	5260	Left side	64	12.50	17.78	205	Yes
	5260	Right side	152	12.50	17.78	1085	Yes
	5260	Top side	5	12.50	17.78	6	No
	5260	Bottom side	152	12.50	17.78	1085	Yes
Wi-Fi 5.5G	5500	Rear side	5	14.00	25.12	6	No
	5500	Left side	64	14.00	25.12	202	Yes



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Wi-Fi 5.8G	5500	Right side	152	14.00	25.12	1082	Yes
	5500	Top side	5	14.00	25.12	6	No
	5500	Bottom side	152	14.00	25.12	1082	Yes
	5825	Rear side	5	13.00	19.95	6	No
	5825	Left side	64	13.00	19.95	202	Yes
	5825	Right side	152	13.00	19.95	1082	Yes
	5825	Top side	5	13.00	19.95	6	No
	5825	Bottom side	152	13.00	19.95	1082	Yes

Freq. Band	Frequency (MHz)	Position	Test Separation (mm)	Max Power (dBm)	Max Power (mW)	Exclusion Threshold (mW)	Exclusion (Yes/No)
GSM 850	824.2	Rear side	5	25.58	361.41	16	No
	824.2	Left side	128	25.58	361.41	598	Yes
	824.2	Right side	55	25.58	361.41	192	No
	824.2	Top side	5	25.58	361.41	16	No
	824.2	Bottom side	152	25.58	361.41	732	Yes
PCS 1900	1880	Rear side	5	22.58	181.13	11	No
	1880	Left side	128	22.58	181.13	889	Yes
	1880	Right side	55	22.58	181.13	159	No
	1880	Top side	5	22.58	181.13	11	No
	1880	Bottom side	152	22.58	181.13	1129	Yes
WCDMA Band II	1907.6	Rear side	5	24.00	251.19	11	No
	1907.6	Left side	128	24.00	251.19	889	Yes
	1907.6	Right side	55	24.00	251.19	159	No
	1907.6	Top side	5	24.00	251.19	11	No
	1907.6	Bottom side	152	24.00	251.19	1129	Yes
WCDMA Band V	846.6	Rear side	5	24.00	251.19	16	No
	846.6	Left side	128	24.00	251.19	598	Yes
	846.6	Right side	55	24.00	251.19	192	No
	846.6	Top side	5	24.00	251.19	16	No
	846.6	Bottom side	152	24.00	251.19	732	Yes
LTE Band 5	836.5	Rear side	5	24.00	251.19	16	No
	836.5	Left side	128	24.00	251.19	598	Yes
	836.5	Right side	55	24.00	251.19	192	No
	836.5	Top side	5	24.00	251.19	16	No
	836.5	Bottom side	152	24.00	251.19	732	Yes
LTE Band 7	2535.0	Rear side	5	24.00	251.19	10	No
	2535.0	Left side	128	24.00	251.19	876	Yes
	2535.0	Right side	55	24.00	251.19	146	No
	2535.0	Top side	5	24.00	251.19	10	No
	2535.0	Bottom side	152	24.00	251.19	1116	Yes
LTE Band 38	2595.0	Rear side	5	25.00	316.23	10	No
	2595.0	Left side	128	25.00	316.23	876	Yes
	2595.0	Right side	55	25.00	316.23	146	No
	2595.0	Top side	5	25.00	316.23	10	No
	2595.0	Bottom side	152	25.00	316.23	1116	Yes
LTE Band 41	2593.0	Rear side	5	24.00	251.19	10	No
	2593.0	Left side	128	24.00	251.19	876	Yes



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



2593.0	Right side	55	24.00	251.19	146	No
2593.0	Top side	5	24.00	251.19	10	No
2593.0	Bottom side	152	24.00	251.19	1116	Yes

From what is shown in the table above, we can draw the conclusion that:

EUT Sides for SAR Testing							
Mode	Exposure Condition	Front	Back	Left	Right	Top	Bottom
BT	Body	N/A	No	No	No	No	No
WIFI 2.4G	Body	N/A	Yes	No	No	Yes	No
WIFI 5.2G	Body	N/A	Yes	No	No	Yes	No
WIFI 5.3G	Body	N/A	Yes	No	No	Yes	No
WIFI 5.5G	Body	N/A	Yes	No	No	Yes	No
WIFI 5.8G	Body	N/A	Yes	No	No	Yes	No

EUT Sides for SAR Testing							
Mode	Exposure Condition	Front	Back	Left	Right	Top	Bottom
GSM 850	Body	N/A	Yes	No	Yes	Yes	No
PCS 1900	Body	N/A	Yes	No	Yes	Yes	No
WCDMA Band II	Body	N/A	Yes	No	Yes	Yes	No
WCDMA Band V	Body	N/A	Yes	No	Yes	Yes	No
LTE Band 5	Body	N/A	Yes	No	Yes	Yes	No
LTE Band 7	Body	N/A	Yes	No	Yes	Yes	No
LTE Band 38	Body	N/A	Yes	No	Yes	Yes	No
LTE Band 41	Body	N/A	Yes	No	Yes	Yes	No

EUT Sides for SAR Testing.

Note:

According to KDB616217, exposures to hands for typical consumer transmitters used in tablets are not expected to exceed the extremity SAR limit; therefore, SAR evaluation for the front surface of tablet display screens are generally not necessary.





7.3. SAR Measurement Results

The calculated SAR is obtained by the following formula:

Reported SAR=Measured SAR* $10^{(P_{\text{target}}-P_{\text{measured}})/10}$ * DutyCycle Factor

Scaling factor= $10^{(P_{\text{target}}-P_{\text{measured}})/10}$

DutyCycle Factor=1/Dutycycle%

Reported SAR= Measured SAR* Scaling factor* DutyCycle Factor

Where

P_{target} is the power of manufacturing upper limit;

P_{measured} is the measured power;

Measured SAR is measured SAR at measured power which including power drift)

Reported SAR which including Power Drift and Scaling factor

7.3.1. SAR Results[GSM 850]

SAR Values [GSM850]								
Ch/ Freq. (MHz)	Channel Type	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
							Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)								
128/824.2	GPRS 3TS	Rear side	29.48	30.00	0.08	1.127	0.435	0.490
128/824.2	GPRS 3TS	Right side	29.48	30.00	-0.15	1.127	0.352	0.397
128/824.2	GPRS 3TS	Top side	29.48	30.00	-0.03	1.127	0.387	0.436

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB447498 D01, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - $\leq 0.8\text{W/kg}$ for 1-g or 2.0W/kg for 10-g respectively, when the transmission band is $\leq 100\text{MHz}$.
 - $\leq 0.6\text{ W/kg}$ or 1.5 W/kg , for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz.
 - $\leq 0.4\text{ W/kg}$ or 1.0 W/kg , for 1-g or 10-g respectively, when the transmission band is $\geq 200\text{ MHz}$.





7.3.2. SAR Results[PCS 1900]

SAR Values [GSM1900]								
Ch/ Freq. (MHz)	Channel Type	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
							Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)								
661/1880	GPRS 3TS	Rear side	26.52	27.00	0.02	1.117	0.624	0.697
661/1880	GPRS 3TS	Right side	26.52	27.00	0.14	1.117	0.521	0.582
661/1880	GPRS 3TS	Top side	26.52	27.00	-0.12	1.117	0.578	0.646

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB447498 D01, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - $\leq 0.8\text{W/kg}$ for 1-g or 2.0W/kg for 10-g respectively, when the transmission band is $\leq 100\text{MHz}$.
 - $\leq 0.6\text{ W/kg}$ or 1.5 W/kg , for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz.
 - $\leq 0.4\text{ W/kg}$ or 1.0 W/kg , for 1-g or 10-g respectively, when the transmission band is $\geq 200\text{ MHz}$.





7.3.3. SAR Results [WCDMA Band II]

SAR Values [WCDMA Band II]								
Ch/ Freq. (MHz)	Channel Type	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
							Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)								
9400/1880	RMC	Rear side	23.61	24.00	0.06	1.094	0.641	0.701
9400/1880	RMC	Right side	23.61	24.00	-0.17	1.094	0.556	0.608
9400/1880	RMC	Top side	23.61	24.00	-0.15	1.094	0.595	0.651

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB447498 D01, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - $\leq 0.8\text{W/kg}$ for 1-g or 2.0W/kg for 10-g respectively, when the transmission band is $\leq 100\text{MHz}$.
 - $\leq 0.6\text{ W/kg}$ or 1.5 W/kg , for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz.
 - $\leq 0.4\text{ W/kg}$ or 1.0 W/kg , for 1-g or 10-g respectively, when the transmission band is $\geq 200\text{ MHz}$.
3. RMC* - RMC 12.2kbps mode;





7.3.4. SAR Results [WCDMA Band V]

SAR Values [WCDMA Band V]								
Ch/ Freq. (MHz)	Channel Type	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
							Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)								
4233/846.6	RMC	Rear side	23.56	24.00	0.07	1.107	0.452	0.500
4233/846.6	RMC	Right side	23.56	24.00	-0.12	1.107	0.365	0.404
4233/846.6	RMC	Top side	23.56	24.00	-0.14	1.107	0.400	0.443

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB447498 D01, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - $\leq 0.8\text{W/kg}$ for 1-g or 2.0W/kg for 10-g respectively, when the transmission band is $\leq 100\text{MHz}$.
 - $\leq 0.6\text{ W/kg}$ or 1.5 W/kg , for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz.
 - $\leq 0.4\text{ W/kg}$ or 1.0 W/kg , for 1-g or 10-g respectively, when the transmission band is $\geq 200\text{ MHz}$.
- 3) RMC* - RMC 12.2kbps mode;





7.3.5. SAR Results [LTE Band 5]

SAR Values [LTE Band 5]									
Ch/ Freq. (MHz)	BW.	Channel Type	Test Position	Conducte d Power (dBm)	Maximu m Allowed Power (dBm)	Powe r Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
								Measure d	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)<1RB>									
20525/836.5	10M	QPSK 1RB_49	Rear side	23.93	24.00	0.05	1.016	0.599	0.609
20525/836.5	10M	QPSK 1RB_49	Right side	23.93	24.00	-0.14	1.016	0.501	0.509
20525/836.5	10M	QPSK 1RB_49	Top side	23.93	24.00	0.19	1.016	0.564	0.573
measured / reported SAR numbers - Body (Test data distance 0mm)<50%RB>									
20600/844	10M	QPSK 25RB_25	Rear side	23.18	24.00	0.08	1.208	0.475	0.574
20600/844	10M	QPSK 25RB_25	Right side	23.18	24.00	0.17	1.208	0.385	0.465
20600/844	10M	QPSK 25RB_25	Top side	23.18	24.00	0.18	1.208	0.436	0.527

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB447498 D01, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - $\leq 0.8\text{W/kg}$ for 1-g or 2.0W/kg for 10-g respectively, when the transmission band is $\leq 100\text{MHz}$.
 - $\leq 0.6\text{ W/kg}$ or 1.5 W/kg , for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz.
 - $\leq 0.4\text{ W/kg}$ or 1.0 W/kg , for 1-g or 10-g respectively, when the transmission band is $\geq 200\text{ MHz}$.





7.3.6. SAR Results [LTE Band 7]

SAR Values [LTE Band 7]									
Ch/ Freq. (MHz)	BW.	Channel Type	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
								Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)<1RB>									
21100/2535.5	20M	QPSK 1RB_49	Rear side	23.36	24.00	-0.15	1.159	0.675	0.782
21100/2535.5	20M	QPSK 1RB_49	Right side	23.36	24.00	0.17	1.159	0.644	0.746
21100/2535.5	20M	QPSK 1RB_49	Top side	23.36	24.00	0.08	1.159	0.655	0.59
measured / reported SAR numbers - Body (Test data distance 0mm)<50%RB>									
21100/2535.5	20M	QPSK 50RB_50	Rear side	22.49	23.00	-0.12	1.125	0.528	0.594
21100/2535.5	20M	QPSK 50RB_50	Right side	22.49	23.00	0.16	1.125	0.419	0.471
21100/2535.5	20M	QPSK 50RB_50	Top side	22.49	23.00	-0.19	1.125	0.468	0.526

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB447498 D01, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - $\leq 0.8\text{W/kg}$ for 1-g or 2.0W/kg for 10-g respectively, when the transmission band is $\leq 100\text{MHz}$.
 - $\leq 0.6\text{ W/kg}$ or 1.5 W/kg , for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz.
 - $\leq 0.4\text{ W/kg}$ or 1.0 W/kg , for 1-g or 10-g respectively, when the transmission band is $\geq 200\text{ MHz}$.



**7.3.7. SAR Results [LTE Band 38]**

SAR Values [LTE Band 38]									
Ch/ Freq. (MHz)	BW.	Channel Type	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
								Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)<1RB>									
38000/2595.0	20M	QPSK 1RB_0	Rear side	24.19	25.00	0.05	1.205	0.642	0.774
38000/2595.0	20M	QPSK 1RB_0	Right side	24.19	25.00	-0.19	1.205	0.562	0.677
38000/2595.0	20M	QPSK 1RB_0	Top side	24.19	25.00	-0.12	1.205	0.603	0.727
measured / reported SAR numbers - Body (Test data distance 0mm)<50%RB>									
38000/2595.0	20M	QPSK 50RB_0	Rear side	23.08	24.00	0.05	1.236	0.510	0.630
38000/2595.0	20M	QPSK 50RB_0	Right side	23.08	24.00	-0.18	1.236	0.322	0.398
38000/2595.0	20M	QPSK 50RB_0	Top side	23.08	24.00	0.06	1.236	0.487	0.602

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB447498 D01, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - $\leq 0.8\text{W/kg}$ for 1-g or 2.0W/kg for 10-g respectively, when the transmission band is $\leq 100\text{MHz}$.
 - $\leq 0.6\text{ W/kg}$ or 1.5 W/kg , for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz.
 - $\leq 0.4\text{ W/kg}$ or 1.0 W/kg , for 1-g or 10-g respectively, when the transmission band is $\geq 200\text{ MHz}$.





7.3.8. SAR Results [LTE Band 41]

SAR Values [LTE Band 41]									
Ch/ Freq. (MHz)	BW.	Channel Type	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
								Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)<1RB>									
40620/2593.0	20M	QPSK 1RB_0	Rear side	23.32	24.00	0.05	1.169	0.648	0.758
40620/2593.0	20M	QPSK 1RB_0	Right side	23.32	24.00	0.11	1.169	0.584	0.683
40620/2593.0	20M	QPSK 1RB_0	Top side	23.32	24.00	-0.13	1.169	0.621	0.726
measured / reported SAR numbers - Body (Test data distance 0mm)<50%RB>									
39750/2506	20M	QPSK 50RB_25	Rear side	22.17	23.00	0.08	1.211	0.535	0.648
39750/2506	20M	QPSK 50RB_25	Right side	22.17	23.00	0.04	1.211	0.465	0.563
39750/2506	20M	QPSK 50RB_25	Top side	22.17	23.00	-0.16	1.211	0.504	0.610

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB447498 D01, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - $\leq 0.8\text{W/kg}$ for 1-g or 2.0W/kg for 10-g respectively, when the transmission band is $\leq 100\text{MHz}$.
 - $\leq 0.6\text{ W/kg}$ or 1.5 W/kg , for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz.
 - $\leq 0.4\text{ W/kg}$ or 1.0 W/kg , for 1-g or 10-g respectively, when the transmission band is $\geq 200\text{ MHz}$.





7.3.9. SAR Results [WIFI 2.4G]

SAR Values [WIFI 2.4G]									
Ch/ Freq. (MHz)	Channel Type	Test Position	Duty Cycle	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
								Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)									
11/2462	802.11b	Rear side	1.008	15.66	16.00	0.03	1.081	0.455	0.496
11/2462	802.11b	Top side	1.008	15.66	16.00	0.14	1.081	0.432	0.471

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB 648474 D04, Product Specific 10-g SAR test is not required for this frequency band since hotspot mode 1-g reported SAR < 1.2 W/kg.
- 3) When the highest reported SAR for the initial test configuration is adjusted by the ratio of the subsequent test configuration to initial test configuration specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg, SAR test for the other 802.11 modes are not required.

7.3.10. SAR Results [WIFI 5.2G]

SAR Values [WIFI 5.2G]									
Ch/ Freq. (MHz)	Channel Type	Test Position	Duty Cycle Factor	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
								Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)									
48/5240	802.11a	Rear side	1.058	12.87	13.00	0.02	1.030	0.265	0.289
48/5240	802.11a	Top side	1.058	12.87	13.00	-0.16	1.030	0.251	0.274

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB 648474 D04, Product Specific 10-g SAR test is not required for this frequency band since hotspot mode 1-g reported SAR < 1.2 W/kg.
- 3) When multiple transmission modes (802.11a/g/n/ac) have the same specified maximum output power, largest channel bandwidth, lowest order modulation and lowest data rate, the lowest order 802.11 mode is selected; i.e., 802.11a is chosen over 802.11n then 802.11ac or 802.11g is chosen over 802.11n.

7.3.11. SAR Results [WIFI 5.3G]

SAR Values [WIFI 5.3G]									
Ch/ Freq. (MHz)	Channel Type	Test Position	Duty Cycle Factor	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
								Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)									
52/5260	802.11a	Rear side	1.058	12.48	12.50	0.05	1.005	0.229	0.243
52/5260	802.11a	Top side	1.058	12.48	12.50	-0.02	1.005	0.203	0.216

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB 648474 D04, Product Specific 10-g SAR test is not required for this frequency band since hotspot mode 1-g reported SAR < 1.2 W/kg.
- 3) When multiple transmission modes (802.11a/g/n/ac) have the same specified maximum output power, largest channel bandwidth, lowest order modulation and lowest data rate, the lowest order 802.11 mode is selected; i.e., 802.11a is chosen over 802.11n then 802.11ac or 802.11g is chosen over 802.11n.





7.3.12. SAR Results [WIFI 5.5G]

SAR Values [WIFI 5.5G]									
Ch/ Freq. (MHz)	Channel Type	Test Position	Duty Cycle Factor	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
								Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)									
100/5500	802.11a	Rear side	1.057	13.06	14.00	-0.02	1.242	0.302	0.396
100/5500	802.11a	Top side	1.057	13.06	14.00	-0.01	1.242	0.278	0.365

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB 648474 D04, Product Specific 10-g SAR test is not required for this frequency band since hotspot mode 1-g reported SAR < 1.2 W/kg.
- 3) When multiple transmission modes (802.11a/g/n/ac) have the same specified maximum output power, largest channel bandwidth, lowest order modulation and lowest data rate, the lowest order 802.11 mode is selected; i.e., 802.11a is chosen over 802.11n then 802.11ac or 802.11g is chosen over 802.11n.

7.3.13. SAR Results [WIFI 5.8G]

SAR Values [WIFI 5.8G]									
Ch/ Freq. (MHz)	Channel Type	Test Position	Duty Cycle Factor	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (dB)	Scaling Factor	SAR _{1-g} results(W/kg)	
								Measured	Reported
measured / reported SAR numbers - Body (Test data distance 0mm)									
165/5825	802.11a	Rear side	1.058	12.87	13.00	-0.11	1.030	0.255	0.278
165/5825	802.11a	Top side	1.058	12.87	13.00	-0.19	1.030	0.236	0.257

Note:

- 1) The maximum Scaled SAR value is marked in bold. Graph results refer to Appendix B.
- 2) Per KDB 648474 D04, Product Specific 10-g SAR test is not required for this frequency band since hotspot mode 1-g reported SAR < 1.2 W/kg.
- 3) When multiple transmission modes (802.11a/g/n/ac) have the same specified maximum output power, largest channel bandwidth, lowest order modulation and lowest data rate, the lowest order 802.11 mode is selected; i.e., 802.11a is chosen over 802.11n then 802.11ac or 802.11g is chosen over 802.11n.





7.4. Multiple Transmitter Evaluation

7.4.1. Simultaneous SAR test evaluation

Simultaneous Transmission Possibilities

NO.	Simultaneous Tx Combination	Body	Hotspot
1	GSM Voice/ DATA + BT	Yes	Yes
2	GSM Voice/ DATA + WiFi 2.4G	Yes	Yes
3	GSM Voice/ DATA + WiFi 5G	Yes	Yes
4	UMTS + BT	Yes	Yes
5	UMTS + WiFi 2.4G	Yes	Yes
6	UMTS + WiFi 5G	Yes	Yes
7	LTE + BT	Yes	Yes
8	LTE + WiFi 2.4G	Yes	Yes
9	LTE + WiFi 5G	Yes	Yes

Note:

- 1) Wi-Fi and Bluetooth share the same Tx antenna and can't transmit simultaneously.
- 2) The device does not support DTM function.





7.4.2. Estimated SAR

When the standalone SAR test exclusion is applied to an antenna that transmits simultaneously with other antennas, the standalone SAR must be estimated according to the following to determine simultaneous transmission SAR test exclusion:

- $(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm}) \cdot [\sqrt{f(\text{GHz})} / x] \text{ W/kg}$ for test separation distances $\leq 50 \text{ mm}$;

Where $x = 7.5$ for 1-g SAR, and $x = 18.75$ for 10-g SAR.

When the minimum test separation distance is $< 5 \text{ mm}$, a distance of 5 mm is applied to determine SAR test exclusion.

Estimated SAR Result

Freq. Band	Frequency (GHz)	Test Position	max. power (dBm)	max. power (mw)	Test Separation (mm)	Estimated
						1g SAR (W/kg)
Bluetooth	2.48	Body	2.00	1.58	5	0.067





7.4.3. Simultaneous Transmission SAR Summation Scenario

Test position		Main Antenna SARmax (W/kg)								WiFi/BT Antenna SARmax (W/kg)						Summed 1g SARmax (W/kg)
		GS M 850	GS M 1900	WCDMA Band II	WCDMA Band V	LTE Band 5	LTE Band 7	LTE Band 38	LTE Band 41	WLAN 2.4G	WLAN 5.2G	WLAN 5.3G	WLAN 5.5G	WLAN 5.8G	BT	
Body	Back side	0.490	0.697	0.701	0.500	0.609	0.782	0.774	0.758	0.496	0.289	0.243	0.396	0.278	0.067	1.278
	Left side	/	/	/	/	/	/	/	/	/	/	/	/	/	/	/
	Right side	0.397	0.582	0.608	0.404	0.509	0.746	0.677	0.683	/	/	/	/	/	/	0.746
	Top side	0.436	0.646	0.651	0.443	0.573	0.590	0.727	0.726	0.471	0.274	0.216	0.365	0.257	0.067	1.198
	Bottom side	/	/	/	/	/	/	/	/	/	/	/	/	/	/	/





7.5. Measurement Uncertainty

When the highest measured 1-g SAR within a frequency band is < 1.5 W/kg, the extensive SAR measurement uncertainty analysis described in IEEE Std 1528-2013 is not required in SAR reports submitted for equipment approval. to KDB 865664D01.





Appendix A: Detailed System Check Results

Appendix B: Detailed Test Results

Appendix C: Calibration certificate

Appendix D: Photographs

.....The End of Test Report.....

