DeKode

iE 10S

Quick User Guide

www.dk-music.cn

Scan the QR code for detailed instructions



1. 6.35 mm (1/4") mono input jack for connecting your instrument.
2. Press and hold the button to turn on/off; when powered on, short press to enable Bluetooth, double-click to disable Bluetooth.
   RGB LED Indicators:
   Blue blinking: Bluetooth device not connected
   Blue solid: Bluetooth device connected
   Red solid: Low battery
   Red blinking: Charging in progress
   PS: Bluetooth status has the highest priority, followed by battery display, and preset display has the lowest priority.
3. Press " + " / " - " to adjust the device volume;
   Press " + " and " - " simultaneously to mute.
4. Press " ◀ " / " ▶ " to switch presets within a group. Each group has 10 preset tones, with a total of 5 groups.
   The " ⟲ " button cycles through preset groups 1–5. When switching groups, the LED blinks for 3 seconds and then displays the current preset.
   Green → Sky blue → Yellow → Purple → White
5. Type-C USB port for charging, connecting to phones or computers for recording, and firmware updates.
6. 3.5mm (1/8") stereo headphone jack for connecting headphones, speakers, or effects processors.

Specifications

A/D/A Conversion: 24-bit
Sampling Rate: 44.1kHz
Signal-to-Noise Ratio: 103dB
Effect Modules: Supports up to 8 effect modules
Preset Quantity: 50 built-in factory presets

Analog Input Connection:
Input: 6.35mm (1/4") unbalanced input (TS) jack, impedance 1MΩ

Analog Output Connection:
Stereo (Headphone) Output: 3.5mm (1/8") TRS jack, impedance 100Ω

Digital Connection:
USB Port: USB 2.0 Type-C port

USB Recording Specifications:
Sampling Frequency: 44.1kHz
Bit Depth: 16-bit

Operating Frequency: 2402MHz—2480MHz
Max. RF Power: 1dBm

Dimensions & Weight:
Dimensions: 84.3mm (L) × 43.7mm (W) × 32.2mm (H)
Weight: 64g

Power Supply:
Power Requirement: USB Type-C, DC 5V
Built-in Battery: 1000mAh

FCC Caution:
This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.
If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.
The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

American agent information
Company Name: GLOCERTS TECHNOLOGY INC
FRN: 0036339737
Contact Name: Huiying Fan
Address: 19784 SUNKISSED RIDGE DR, RIVERSIDE, CA 92507
Telephone No: (626) 588-8039
Email: huiying.fan@glocerts.com