

FCC TEST REPORT

(PART 22)



Applicant:	Astronomy Data Processing Corporation
Address:	2228 Cotner Ave Los Angeles, CA 90064

Manufacturer or Supplier:	Astronomy Data Processing Corporation
Address:	2228 Cotner Ave Los Angeles, CA 90064
Product:	Edge Controller 01
Model Name:	EC-01
FCC ID	2BM4513EA
Date of tests	Dec. 22, 2025 - Feb. 05, 2026

The tests have been carried out according to the requirements of the following standard:

☒ FCC PART 22, Subpart H	☒ FCC Part 2
☒ ANSI/TIA/EIA-603-D	☒ ANSI C63.26-2015
☒ ANSI/TIA/EIA-603-E	

CONCLUSION: The submitted sample was found to COMPLY with the test requirement

Prepared by Carl Xie Engineer / Mobile Department	Approved by Simon Wang Manager / Mobile Department
	
Date: Feb. 05, 2026	Date: Feb. 05, 2026

BOOMWAVE TEST (SHENZHEN) CO., LTD. tested the above equipment in accordance with the requirements set forth in the above standards. The test results show that the equipment tested is capable of demonstrating compliance with the requirements as documented in this report. The results documented in this report apply only the tested sample, under the conditions and modes of operation as described herein. It is the manufacturer's responsibility to assure that additional production units of the model are manufactured with identical electrical and mechanical components. All sample tested were in good operating condition throughout the entire test program. Measurement Uncertainties are published for informational purposes only and were not taken into account unless noted otherwise. Without written approval of BOOMWAVE TEST (SHENZHEN) CO., LTD., the test report shall not be reproduced except in full.

TABLE OF CONTENTS

RELEASE CONTROL RECORD	3
1 SUMMARY OF TEST RESULTS.....	4
1.1 MEASUREMENT UNCERTAINTY	5
1.2 TEST SITE AND INSTRUMENTS	6
2 GENERAL INFORMATION	8
2.1 GENERAL DESCRIPTION OF EUT	8
2.2 CONFIGURATION OF SYSTEM UNDER TEST	11
2.3 DESCRIPTION OF SUPPORT UNITS	12
2.4 TEST ITEM AND TEST CONFIGURATION	13
2.5 EUT OPERATING CONDITIONS	15
2.6 GENERAL DESCRIPTION OF APPLIED STANDARDS	15
3 TEST TYPES AND RESULTS.....	16
3.1 OUTPUT POWER MEASUREMENT	16
3.1.1 LIMITS OF OUTPUT POWER MEASUREMENT	16
3.1.2 TEST PROCEDURES	16
3.1.3 TEST SETUP	17
3.1.4 TEST RESULTS	17
3.2 FREQUENCY STABILITY MEASUREMENT	34
3.2.1 LIMITS OF FREQUENCY STABILITY MEASUREMENT	34
3.2.2 TEST PROCEDURE	34
3.2.3 TEST SETUP	34
3.2.4 TEST RESULTS	34
3.3 OCCUPIED BANDWIDTH MEASUREMENT	35
3.3.1 LIMITS OF OCCUPIED BANDWIDTH MEASUREMENT	35
3.3.2 TEST SETUP	35
3.3.3 TEST PROCEDURES	35
3.3.4 TEST RESULTS	35
3.4 BAND EDGE MEASUREMENT	36
3.4.1 LIMITS OF BAND EDGE MEASUREMENT	36
3.4.2 TEST SETUP	36
3.4.3 TEST PROCEDURES	37
3.4.4 TEST RESULTS	37
3.5 CONDUCTED SPURIOUS EMISSIONS	38
3.5.1 LIMITS OF CONDUCTED SPURIOUS EMISSIONS MEASUREMENT	38
3.5.2 TEST PROCEDURE	38
3.5.3 TEST SETUP	38
3.5.4 TEST RESULTS	38
3.6 RADIATED EMISSION MEASUREMENT	39
3.6.1 LIMITS OF RADIATED EMISSION MEASUREMENT	39
3.6.2 TEST PROCEDURES	39
3.6.3 DEVIATION FROM TEST STANDARD	39
3.6.4 TEST SETUP	40
3.6.5 TEST RESULTS	42
3.7 PEAK TO AVERAGE RATIO	58
3.7.1 LIMITS OF PEAK TO AVERAGE RATIO MEASUREMENT	58
3.7.2 TEST SETUP	58
3.7.3 TEST PROCEDURES	58
3.7.4 TEST RESULTS	58
4 PHOTOGRAPHS OF THE TEST CONFIGURATION	59
5 INFORMATION ON THE TESTING LABORATORIES	60
6 MODIFICATIONS RECORDERS FOR ENGINEERING CHANGES TO THE EUT BY THE LAB	61



Test Report No.: RF260413B001

RELEASE CONTROL RECORD

ISSUE NO.	REASON FOR CHANGE	DATE ISSUED
RF260413B001	Original release	Feb. 05, 2026



Test Report No.: RF260413B001

1 SUMMARY OF TEST RESULTS

The EUT has been tested according to the following specifications:

APPLIED STANDARD: FCC Part 22 & Part 2			
STANDARD SECTION	TEST TYPE	RESULT	Test lab*
§22.913 (a)(5)	Equivalent Isotropic Radiated Power	Compliance	A
§2.1053 §22.917(a)	Radiated Spurious Emissions	Compliance	A

* Refer to KDB 971168 D01 Power Meas License Digital Systems v03r01.

*Test Lab Information Reference

Lab A:

Boomwave Test (Shenzhen) Co., Ltd.

Lab Address:

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd, Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen, Guangdong, Shenzhen, China

Accredited Test Lab Cert 7607.01


The FCC Site Registration No. is 646781; The Designation No. is CN1429.

1.1 MEASUREMENT UNCERTAINTY

Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the EUT as specified in CISPR 16-4-2:

MEASUREMENT	UNCERTAINTY
Maximum Peak Output Power	$\pm 2.06\text{dB}$
Frequency Stability	$\pm 76.97\text{Hz}$
Radiated emissions (9KHz~30MHz)	$\pm 2.68\text{dB}$
Radiated emissions (30MHz~1GHz)	$\pm 4.98\text{dB}$
Radiated emissions (1GHz ~6GHz)	$\pm 4.70\text{dB}$
Radiated emissions (6GHz ~18GHz)	$\pm 4.60\text{dB}$
Radiated emissions (18GHz ~40GHz)	$\pm 4.12\text{dB}$
Conducted emissions	$\pm 4.01\text{dB}$
Occupied Channel Bandwidth	$\pm 43.58\text{KHz}$
Band Edge Measurements	$\pm 4.70\text{dB}$
Peak to average ratio	$\pm 0.76\text{dB}$

This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of $k=2$.



The verdicts in this test report are given according the above diagram:

Case	Measured Value	Uncertainty Range	Verdict
1	below pass mark	below pass mark	Passed
2	below pass mark	within pass mark	Passed
3	above pass mark	within pass mark	Failed
4	above pass mark	above pass mark	Failed

That means, the laboratory applies, as decision rule (see ISO/IEC 17025:2017), the so-called shared risk principle.



Test Report No.: RF260413B001

1.2 TEST SITE AND INSTRUMENTS

Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Next Cal.
3m Semi-anechoic Chamber	ETS-LINDGREN	9m*6m*6m	Euroshieldpn-CT0001143-1216	2025/7/3	2026/7/2
BiConiLog Antenna	ETS-LINDGREN	3143B	161965	2025/7/17	2026/7/16
Horn Antenna	SCHWARZBECK	BBHA9120D	3297	2025/9/27	2026/9/26
Horn Antenna	STEATITE	QWH-SL-18-40-K-SG QMS-00361	15433	2025/7/19	2026/7/18
Preamplifier	Tonscend	TPA184045	AP24L8060388	2025/7/3	2026/7/2
MXE EMI Receiver	keysight	N9038B	MY50018017	2025/7/1	2026/6/30
MXG Vector Signal Generator	Keysight	N5183B	MY59100137	2025/6/30	2026/6/29
Preamplifier	Tonscend	TPA001330	806JSAPO40804251015	2025/6/30	2026/6/29
Preamplifier	Tonscend	TPA011845	AP24L8060392	2025/6/30	2026/6/29
Attenuator 6DB	SHX	TS2-6-6-A	230927166	2025/6/30	2026/6/29
Attenuator 6DB	SHX	TS2-6-6-A	230927165	2025/6/30	2026/6/29
Active Receive Loop Antenna	SCHWARZBECK	FMZB 1519 B	00173	2025/6/30	2026/6/29
Temp. & Humi. Recorder	Kejian	HTC-01	157246	2025/7/2	2026/7/1
HIGH pass FILTER_1-18	EWT	EWT-57-0222	EWT-57-0222	2025/6/30	2026/6/29
HIGH pass FILTER_7-18	EWT	EWT-57-0223	EWT-57-0223	2025/6/30	2026/6/29
HIGH pass FILTER_3-18	EWT	EWT-57-0221	EWT-57-0221	2025/6/30	2026/6/29
DC~1GHz Lowpass Filter	EWT	EWT-56-0649	EWT-56-0649	2025/7/3	2026/7/2
Cable 1	N/A	N/A	N/A	2025/9/28	2026/9/27
Cable 2	N/A	N/A	N/A	2025/9/28	2026/9/27
Cable 3	N/A	N/A	N/A	2025/9/28	2026/9/27
Wireless communication integrated tester	Rohde&Schwarz	CMW500	182016	2025/6/30	2026/6/29
EXA Signal Analyzer	KEYSIGHT	N9010B	MY62170156	2025/6/30	2026/6/29
RF Control Unit	Tonscend	JS0806-1	21K8060504	2025/6/16	2026/6/15
DC Power Supply	AGILENT	HMP2020	100598	2025/7/1	2026/6/30
10dB attenuator	JFW INDUSTRIES INC	50HF-010-SMA	50HF-010-SMA-1	2025/6/30	2026/6/29
10dB attenuator	JFW INDUSTRIES INC	50HF-010-SMA	50HF-010-SMA-2	2025/6/30	2026/6/29
hygrothermograph	Anymetrers	----	TH101B	2025/7/22	2026/7/21
Temperature Box	zhongkemeiqi	MA22040172	MQ-DTH50F-2	2025/7/1	2026/6/30

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com

**Test Report No.: RF260413B001**

power divider	WOKEN	71688	204-003180-01	2025/6/30	2026/6/29
---------------	-------	-------	---------------	-----------	-----------

NOTE:

1. The calibration interval of the above test instruments is 12 months and the calibrations are traceable to CEPREI/CHINA, GREGT/CHINA and NIM/CHINA.
2. The test was performed in 3m Semi-anechoic Chamber and RF Oven Room.
3. The horn antenna is used only for the measurement of emission frequency above 1GHz if tested.
4. The FCC Site Registration No. is 646781; The Designation No. is CN1429.

2 GENERAL INFORMATION

2.1 GENERAL DESCRIPTION OF EUT

PRODUCT*	Edge Controller 01	
ssMODEL NAME*	EC-01	
NOMINAL VOLTAGE*	19Vdc	
MODULATION TYPE	LTE	QPSK, 16QAM, 64QAM
FREQUENCY RANGE	LTE Band 5 (Channel Bandwidth: 1.4MHz)	824.7MHz ~ 848.3MHz
	LTE Band 5 (Channel Bandwidth: 3MHz)	825.5MHz ~ 847.5MHz
	LTE Band 5 (Channel Bandwidth: 5MHz)	826.5MHz ~ 846.5MHz
	LTE Band 5 (Channel Bandwidth: 10MHz)	829MHz ~ 844MHz
	LTE Band 26 (Channel Bandwidth: 1.4MHz)	824.7MHz ~ 848.3MHz
	LTE Band 26 (Channel Bandwidth: 3MHz)	825.5MHz ~ 847.5MHz
	LTE Band 26 (Channel Bandwidth: 5MHz)	826.5MHz ~ 846.5MHz
	LTE Band 26 (Channel Bandwidth: 10MHz)	829MHz ~ 844MHz
	LTE Band 26 (Channel Bandwidth: 15MHz)	831.5MHz ~ 841.5MHz
EMISSION DESIGNATORGOGN	LTE Band 5 (Channel Bandwidth: 1.4MHz)	QPSK: 1M11G7D
		16QAM: 1M11W7D
		64QAM: 1M11W7D
	LTE Band 5 (Channel Bandwidth: 3MHz)	QPSK: 2M70G7D
		16QAM: 2M70W7D
		64QAM: 2M70W7D
	LTE Band 5 (Channel Bandwidth: 5MHz)	QPSK: 4M48G7D
		16QAM: 4M48W7D
		64QAM: 4M48W7D
	LTE Band 5 (Channel Bandwidth: 10MHz)	QPSK: 8M94G7D
		16QAM: 8M94W7D
		64QAM: 8M94W7D
	LTE Band 26 (Channel Bandwidth: 1.4MHz)	QPSK: 1M11G7D
		16QAM: 1M11W7D
		64QAM: 1M10W7D
	LTE Band 26 (Channel Bandwidth: 3MHz)	QPSK: 2M71G7D
		16QAM: 2M70W7D
		64QAM: 2M70W7D
	LTE Band 26 (Channel Bandwidth: 5MHz)	QPSK: 4M48G7D
		16QAM: 4M48W7D
		64QAM: 4M49W7D

Test Report No.: RF260413B001

	LTE Band 26 (Channel Bandwidth: 10MHz)	QPSK: 8M96G7D
		16QAM: 8M95W7D
		64QAM: 8M95W7D
	LTE Band 26 (Channel Bandwidth: 15MHz)	QPSK: 13M5G7D
		16QAM: 13M5W7D
		64QAM: 13M5W7D
MAX. ERP POWER	LTE Band 5 (Channel Bandwidth: 1.4MHz)	161.81mW
	LTE Band 5 (Channel Bandwidth: 3MHz)	163.31mW
	LTE Band 5 (Channel Bandwidth: 5MHz)	163.31mW
	LTE Band 5 (Channel Bandwidth: 10MHz)	159.59mW
	LTE Band 26 (Channel Bandwidth: 1.4MHz)	121.06mW
	LTE Band 26 (Channel Bandwidth: 3MHz)	123.03mW
	LTE Band 26 (Channel Bandwidth: 5MHz)	127.06mW
	LTE Band 26 (Channel Bandwidth: 10MHz)	118.03mW
	LTE Band 26 (Channel Bandwidth: 15MHz)	122.18mW
ANTENNA GAIN*	☒ Provided by client	
	LTE B5	0.1dBi
	LTE B26	0.1dBi
ANTENNA TYPE*	PIFA Antenna	
HW VERSION*	1.0	
SW VERSION*	V1	
I/O PORTS*	Refer to user's manual	
CABLE SUPPLIED*	N/A	
EXTREME TEMPERATURE*	-20℃-60℃	
EXTREME VOLTAGE*	15V-20V	

NOTE:





1. *Since the above data and/or information is provided by the client relevant results or conclusions of this report are only made for these data and/or information, Test Lab is not responsible for the authenticity, integrity and results of the data and information and/or the validity of the conclusion.
2. For a more detailed features description, please refer to the manufacturer's specifications or the user's manual.
3. The EUT incorporates a SISO function. Physically, the EUT provides one completed transmitter and one receiver.

MODULATION MODE	TX FUNCTION
LTE	1TX/1RX

4. For the test results, the EUT had been tested with all conditions. But only the worst case was shown in the test report.

2.2 CONFIGURATION OF SYSTEM UNDER TEST

FOR RADIATION EMISSION





Test Report No.: RF260413B001

2.3 DESCRIPTION OF SUPPORT UNITS

The EUT has been tested as an independent unit together with other necessary accessories or support units. The following support units or accessories were used to form a representative test configuration during the tests.

NO.	PRODUCT	BRAND	MODEL NO.	SERIAL NO.	FCC ID
1	Laptop	Lenovo	ThinkPad E14	HRSW00024	N/A

NO.	SIGNAL CABLE DESCRIPTION OF THE ABOVE SUPPORT UNITS
1	N/A



Test Report No.: RF260413B001

2.4 TEST ITEM AND TEST CONFIGURATION

Pre-Scan has been conducted to determine the worst-case mode from all possible combinations between available modulations, data rates, XYZ axis and antenna ports. The worst case in ERP and radiated emission was found when positioned on X-plane for LTE. Following channel(s) was (were) selected for the final test as listed below:

EUT CONFIGURE MODE	DESCRIPTION
A	EUT + Adapter with LTE link
B	EUT + DC Supply with LTE link

LTE BAND 5 MODE

EUT CONFIGURE MODE	TEST ITEM	Available Channel	Tested Channel	Channel bandwidth	modulation	mode
A	ERP	20407 to 20643	20407, 20525, 20643	1.4MHz	QPSK, 16QAM, 64QAM	1 RB / 0 RB offset
		20415 to 20635	20415, 20525, 20635	3MHz	QPSK, 16QAM, 64QAM	1 RB / 0 RB offset
		20425 to 20625	20425, 20525, 20625	5MHz	QPSK, 16QAM, 64QAM	1 RB / 0 RB offset
		20450 to 20600	20450, 20525, 20600	10MHz	QPSK, 16QAM, 64QAM	1 RB / 0 RB offset

Note:

1. This device was tested under all bandwidths, RB configurations and modulations. The worst case was found in QPSK modulation.
2. LTE Band 5 are covered by LTE Band 26, Because it is a subset of LTE Band 26 with the same output power and supported bandwidths, So the RSE test data please refer to LTE Band 26

LTE BAND 26 MODE

EUT CONFIGURE MODE	TEST ITEM	Available Channel	Tested Channel	Channel bandwidth	modulation	mode
A	ERP	26797 to 27033	26797, 26915, 27033	1.4MHz	QPSK, 16QAM, 64QAM	1 RB / 0 RB offset
		26805 to 27025	26805, 26915, 27025	3MHz	QPSK, 16QAM, 64QAM	1 RB / 0 RB offset
		26815 to 27015	26815, 26915, 27015	5MHz	QPSK, 16QAM, 64QAM	1 RB / 0 RB offset
		26840 to 26990	26840, 26915, 26990	10MHz	QPSK, 16QAM, 64QAM	1 RB / 0 RB offset
		26865 to 26965	26865, 26915, 26965	15MHz	QPSK, 16QAM, 64QAM	1 RB / 0 RB offset
A	RADIATED EMISSION	26797 to 27033	26915	1.4MHz	QPSK	1 RB / 0 RB offset
		26805 to 27025	26915	3MHz	QPSK	1 RB / 0 RB offset
		26815 to 27015	26815, 26915, 27015	5MHz	QPSK	1 RB / 0 RB offset
		26840 to 26990	26915	10MHz	QPSK	1 RB / 0 RB offset
		26865 to 26965	26915	15MHz	QPSK	1 RB / 0 RB offset

Note: This device was tested under all bandwidths, RB configurations and modulations. The worst case was found in QPSK modulation.

TEST CONDITION			
TEST ITEM	ENVIRONMENTAL CONDITIONS	INPUT POWER	TESTED BY
ERP	23deg. C, 70%RH	DC 19V By Battery	Carl Xie
RADIATED EMISSION	23deg. C, 70%RH	AC 120V/60Hz	Carl Xie



Test Report No.: RF260413B001

2.5 EUT OPERATING CONDITIONS

The EUT makes a call to the communication simulator. The communication simulator station system controlled a EUT to export maximum output power under transmission mode and specific channel frequency

2.6 GENERAL DESCRIPTION OF APPLIED STANDARDS

The EUT is a RF product. According to the specifications of the manufacturer, it must comply with the requirements of the following standards:

FCC 47 CFR Part 2

FCC 47 CFR Part 22

KDB 971168 D01 Power Meas License Digital Systems v03r01

ANSI/TIA/EIA-603-D

ANSI/TIA/EIA-603-E

ANSI C63.26-2015

NOTE: All test items have been performed and recorded as per the above standards.

3 TEST TYPES AND RESULTS

3.1 OUTPUT POWER MEASUREMENT

3.1.1 LIMITS OF OUTPUT POWER MEASUREMENT

Mobile / Portable station are limited to 7 watts e.r.p.

3.1.2 TEST PROCEDURES

EIRP / ERP MEASUREMENT:

Per KDB 971168 D01 Power Meas License Digital Systems v03r01 or subclause 5.2.5.5 of ANSI C63.26-2015, the relevant equation for determining the ERP or EIRP from the conducted RF output power measured using the guidance provided above is:

$$\text{ERP or EIRP} = P_{\text{Meas}} + G_{\text{T}} - L_{\text{C}}$$

Where:

ERP or EIRP = effective radiated power or equivalent isotropically radiated power, respectively

(expressed in the same units as P_{Meas} , typically dBW or dBm);

P_{Meas} = measured transmitter output power or PSD, in dBm or dBW;

G_{T} = gain of the transmitting antenna, in dBd (ERP) or dBi (EIRP);

L_{C} = signal attenuation in the connecting cable between the transmitter and antenna, in dB.

CONDUCTED POWER MEASUREMENT:

The EUT was set up for the maximum power with WCDMA link data modulation and link up with simulator. Set the EUT to transmit under low, middle and high channel and record the power level shown on simulator.




Test Report No.: RF260413B001

3.1.3 TEST SETUP

EIRP / ERP Measurement:

CONDUCTED POWER MEASUREMENT:



3.1.4 TEST RESULTS

We have verified power. The test data is better than module report, so power test data please refer to module report (No. : SEWM2304000122RG01, FCC ID: XMR2023RM520NGL)

Considering antenna gain is changed compared with module, so we update ERP.



Test Report No.: RF260413B001

LTE Band5

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Gain(dBi)	ERP(dBm)	ERP(mW)	Limit(W)	Verdict
Band5	1.4MHz	QPSK	20407	1RB#0	24.14	0.1	22.09	161.81	7	PASS
Band5	1.4MHz	QPSK	20407	1RB#2	23.91	0.1	21.86	153.46	7	PASS
Band5	1.4MHz	QPSK	20407	1RB#5	23.86	0.1	21.81	151.71	7	PASS
Band5	1.4MHz	QPSK	20407	6RB#0	23.04	0.1	20.99	125.60	7	PASS
Band5	1.4MHz	QPSK	20525	1RB#0	23.89	0.1	21.84	152.76	7	PASS
Band5	1.4MHz	QPSK	20525	1RB#2	23.92	0.1	21.87	153.82	7	PASS
Band5	1.4MHz	QPSK	20525	1RB#5	23.91	0.1	21.86	153.46	7	PASS
Band5	1.4MHz	QPSK	20525	6RB#0	22.96	0.1	20.91	123.31	7	PASS
Band5	1.4MHz	QPSK	20643	1RB#0	23.89	0.1	21.84	152.76	7	PASS
Band5	1.4MHz	QPSK	20643	1RB#2	23.93	0.1	21.88	154.17	7	PASS
Band5	1.4MHz	QPSK	20643	1RB#5	23.93	0.1	21.88	154.17	7	PASS
Band5	1.4MHz	QPSK	20643	6RB#0	23.03	0.1	20.98	125.31	7	PASS
Band5	1.4MHz	16QAM	20407	1RB#0	23.19	0.1	21.14	130.02	7	PASS
Band5	1.4MHz	16QAM	20407	1RB#2	23.16	0.1	21.11	129.12	7	PASS
Band5	1.4MHz	16QAM	20407	1RB#5	23.08	0.1	21.03	126.77	7	PASS
Band5	1.4MHz	16QAM	20407	6RB#0	22.13	0.1	20.08	101.86	7	PASS
Band5	1.4MHz	16QAM	20525	1RB#0	23.07	0.1	21.02	126.47	7	PASS
Band5	1.4MHz	16QAM	20525	1RB#2	23.18	0.1	21.13	129.72	7	PASS
Band5	1.4MHz	16QAM	20525	1RB#5	23.23	0.1	21.18	131.22	7	PASS
Band5	1.4MHz	16QAM	20525	6RB#0	21.98	0.1	19.93	98.40	7	PASS
Band5	1.4MHz	16QAM	20643	1RB#0	23.00	0.1	20.95	124.45	7	PASS
Band5	1.4MHz	16QAM	20643	1RB#2	23.06	0.1	21.01	126.18	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

Band5	1.4MHz	16QAM	20643	1RB#5	23.02	0.1	20.97	125.03	7	PASS
Band5	1.4MHz	16QAM	20643	6RB#0	22.03	0.1	19.98	99.54	7	PASS
Band5	1.4MHz	64QAM	20407	1RB#0	22.24	0.1	20.19	104.47	7	PASS
Band5	1.4MHz	64QAM	20407	1RB#2	22.19	0.1	20.14	103.28	7	PASS
Band5	1.4MHz	64QAM	20407	1RB#5	22.01	0.1	19.96	99.08	7	PASS
Band5	1.4MHz	64QAM	20407	6RB#0	21.11	0.1	19.06	80.54	7	PASS
Band5	1.4MHz	64QAM	20525	1RB#0	22.10	0.1	20.05	101.16	7	PASS
Band5	1.4MHz	64QAM	20525	1RB#2	22.45	0.1	20.40	109.65	7	PASS
Band5	1.4MHz	64QAM	20525	1RB#5	22.25	0.1	20.20	104.71	7	PASS
Band5	1.4MHz	64QAM	20525	6RB#0	20.90	0.1	18.85	76.74	7	PASS
Band5	1.4MHz	64QAM	20643	1RB#0	22.04	0.1	19.99	99.77	7	PASS
Band5	1.4MHz	64QAM	20643	1RB#2	22.27	0.1	20.22	105.20	7	PASS
Band5	1.4MHz	64QAM	20643	1RB#5	22.24	0.1	20.19	104.47	7	PASS
Band5	1.4MHz	64QAM	20643	6RB#0	21.06	0.1	19.01	79.62	7	PASS
Band5	3MHz	QPSK	20415	1RB#0	23.91	0.1	21.86	153.46	7	PASS
Band5	3MHz	QPSK	20415	1RB#8	23.89	0.1	21.84	152.76	7	PASS
Band5	3MHz	QPSK	20415	1RB#14	23.83	0.1	21.78	150.66	7	PASS
Band5	3MHz	QPSK	20415	15RB#0	23.06	0.1	21.01	126.18	7	PASS
Band5	3MHz	QPSK	20525	1RB#0	24.13	0.1	22.08	161.44	7	PASS
Band5	3MHz	QPSK	20525	1RB#8	24.10	0.1	22.05	160.32	7	PASS
Band5	3MHz	QPSK	20525	1RB#14	24.03	0.1	21.98	157.76	7	PASS
Band5	3MHz	QPSK	20525	15RB#0	22.94	0.1	20.89	122.74	7	PASS
Band5	3MHz	QPSK	20635	1RB#0	24.18	0.1	22.13	163.31	7	PASS
Band5	3MHz	QPSK	20635	1RB#8	24.08	0.1	22.03	159.59	7	PASS
Band5	3MHz	QPSK	20635	1RB#14	23.94	0.1	21.89	154.53	7	PASS
Band5	3MHz	QPSK	20635	15RB#0	23.06	0.1	21.01	126.18	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com


Test Report No.: RF260413B001

Band5	3MHz	16QAM	20415	1RB#0	23.19	0.1	21.14	130.02	7	PASS
Band5	3MHz	16QAM	20415	1RB#8	23.13	0.1	21.08	128.23	7	PASS
Band5	3MHz	16QAM	20415	1RB#14	23.16	0.1	21.11	129.12	7	PASS
Band5	3MHz	16QAM	20415	15RB#0	22.12	0.1	20.07	101.62	7	PASS
Band5	3MHz	16QAM	20525	1RB#0	22.94	0.1	20.89	122.74	7	PASS
Band5	3MHz	16QAM	20525	1RB#8	23.08	0.1	21.03	126.77	7	PASS
Band5	3MHz	16QAM	20525	1RB#14	23.13	0.1	21.08	128.23	7	PASS
Band5	3MHz	16QAM	20525	15RB#0	21.97	0.1	19.92	98.17	7	PASS
Band5	3MHz	16QAM	20635	1RB#0	23.11	0.1	21.06	127.64	7	PASS
Band5	3MHz	16QAM	20635	1RB#8	23.16	0.1	21.11	129.12	7	PASS
Band5	3MHz	16QAM	20635	1RB#14	23.14	0.1	21.09	128.53	7	PASS
Band5	3MHz	16QAM	20635	15RB#0	22.09	0.1	20.04	100.93	7	PASS
Band5	3MHz	64QAM	20415	1RB#0	22.10	0.1	20.05	101.16	7	PASS
Band5	3MHz	64QAM	20415	1RB#8	22.30	0.1	20.25	105.93	7	PASS
Band5	3MHz	64QAM	20415	1RB#14	22.16	0.1	20.11	102.57	7	PASS
Band5	3MHz	64QAM	20415	15RB#0	21.06	0.1	19.01	79.62	7	PASS
Band5	3MHz	64QAM	20525	1RB#0	22.07	0.1	20.02	100.46	7	PASS
Band5	3MHz	64QAM	20525	1RB#8	22.30	0.1	20.25	105.93	7	PASS
Band5	3MHz	64QAM	20525	1RB#14	21.99	0.1	19.94	98.63	7	PASS
Band5	3MHz	64QAM	20525	15RB#0	20.97	0.1	18.92	77.98	7	PASS
Band5	3MHz	64QAM	20635	1RB#0	22.10	0.1	20.05	101.16	7	PASS
Band5	3MHz	64QAM	20635	1RB#8	22.16	0.1	20.11	102.57	7	PASS
Band5	3MHz	64QAM	20635	1RB#14	22.10	0.1	20.05	101.16	7	PASS
Band5	3MHz	64QAM	20635	15RB#0	21.06	0.1	19.01	79.62	7	PASS
Band5	5MHz	QPSK	20425	1RB#0	24.18	0.1	22.13	163.31	7	PASS
Band5	5MHz	QPSK	20425	1RB#12	23.92	0.1	21.87	153.82	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

Band5	5MHz	QPSK	20425	1RB#24	23.95	0.1	21.90	154.88	7	PASS
Band5	5MHz	QPSK	20425	25RB#0	23.13	0.1	21.08	128.23	7	PASS
Band5	5MHz	QPSK	20525	1RB#0	23.36	0.1	21.31	135.21	7	PASS
Band5	5MHz	QPSK	20525	1RB#12	24.04	0.1	21.99	158.12	7	PASS
Band5	5MHz	QPSK	20525	1RB#24	23.92	0.1	21.87	153.82	7	PASS
Band5	5MHz	QPSK	20525	25RB#0	23.02	0.1	20.97	125.03	7	PASS
Band5	5MHz	QPSK	20625	1RB#0	23.45	0.1	21.40	138.04	7	PASS
Band5	5MHz	QPSK	20625	1RB#12	23.96	0.1	21.91	155.24	7	PASS
Band5	5MHz	QPSK	20625	1RB#24	24.04	0.1	21.99	158.12	7	PASS
Band5	5MHz	QPSK	20625	25RB#0	22.98	0.1	20.93	123.88	7	PASS
Band5	5MHz	16QAM	20425	1RB#0	23.23	0.1	21.18	131.22	7	PASS
Band5	5MHz	16QAM	20425	1RB#12	23.18	0.1	21.13	129.72	7	PASS
Band5	5MHz	16QAM	20425	1RB#24	23.09	0.1	21.04	127.06	7	PASS
Band5	5MHz	16QAM	20425	25RB#0	22.04	0.1	19.99	99.77	7	PASS
Band5	5MHz	16QAM	20525	1RB#0	22.96	0.1	20.91	123.31	7	PASS
Band5	5MHz	16QAM	20525	1RB#12	23.20	0.1	21.15	130.32	7	PASS
Band5	5MHz	16QAM	20525	1RB#24	23.08	0.1	21.03	126.77	7	PASS
Band5	5MHz	16QAM	20525	25RB#0	22.04	0.1	19.99	99.77	7	PASS
Band5	5MHz	16QAM	20625	1RB#0	23.07	0.1	21.02	126.47	7	PASS
Band5	5MHz	16QAM	20625	1RB#12	22.98	0.1	20.93	123.88	7	PASS
Band5	5MHz	16QAM	20625	1RB#24	23.37	0.1	21.32	135.52	7	PASS
Band5	5MHz	16QAM	20625	25RB#0	21.91	0.1	19.86	96.83	7	PASS
Band5	5MHz	64QAM	20425	1RB#0	22.27	0.1	20.22	105.20	7	PASS
Band5	5MHz	64QAM	20425	1RB#12	22.32	0.1	20.27	106.41	7	PASS
Band5	5MHz	64QAM	20425	1RB#24	22.04	0.1	19.99	99.77	7	PASS
Band5	5MHz	64QAM	20425	25RB#0	21.08	0.1	19.03	79.98	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

Band5	5MHz	64QAM	20525	1RB#0	22.08	0.1	20.03	100.69	7	PASS
Band5	5MHz	64QAM	20525	1RB#12	22.05	0.1	20.00	100.00	7	PASS
Band5	5MHz	64QAM	20525	1RB#24	22.15	0.1	20.10	102.33	7	PASS
Band5	5MHz	64QAM	20525	25RB#0	20.96	0.1	18.91	77.80	7	PASS
Band5	5MHz	64QAM	20625	1RB#0	22.15	0.1	20.10	102.33	7	PASS
Band5	5MHz	64QAM	20625	1RB#12	22.24	0.1	20.19	104.47	7	PASS
Band5	5MHz	64QAM	20625	1RB#24	22.17	0.1	20.12	102.80	7	PASS
Band5	5MHz	64QAM	20625	25RB#0	20.88	0.1	18.83	76.38	7	PASS
Band5	10MHz	QPSK	20450	1RB#0	23.94	0.1	21.89	154.53	7	PASS
Band5	10MHz	QPSK	20450	1RB#24	23.97	0.1	21.92	155.60	7	PASS
Band5	10MHz	QPSK	20450	1RB#49	23.83	0.1	21.78	150.66	7	PASS
Band5	10MHz	QPSK	20450	50RB#0	23.04	0.1	20.99	125.60	7	PASS
Band5	10MHz	QPSK	20525	1RB#0	23.63	0.1	21.58	143.88	7	PASS
Band5	10MHz	QPSK	20525	1RB#24	24.01	0.1	21.96	157.04	7	PASS
Band5	10MHz	QPSK	20525	1RB#49	23.95	0.1	21.90	154.88	7	PASS
Band5	10MHz	QPSK	20525	50RB#0	23.00	0.1	20.95	124.45	7	PASS
Band5	10MHz	QPSK	20600	1RB#0	23.48	0.1	21.43	139.00	7	PASS
Band5	10MHz	QPSK	20600	1RB#24	24.08	0.1	22.03	159.59	7	PASS
Band5	10MHz	QPSK	20600	1RB#49	23.98	0.1	21.93	155.96	7	PASS
Band5	10MHz	QPSK	20600	50RB#0	23.10	0.1	21.05	127.35	7	PASS
Band5	10MHz	16QAM	20450	1RB#0	23.25	0.1	21.20	131.83	7	PASS
Band5	10MHz	16QAM	20450	1RB#24	23.08	0.1	21.03	126.77	7	PASS
Band5	10MHz	16QAM	20450	1RB#49	22.90	0.1	20.85	121.62	7	PASS
Band5	10MHz	16QAM	20450	50RB#0	21.95	0.1	19.90	97.72	7	PASS
Band5	10MHz	16QAM	20525	1RB#0	23.11	0.1	21.06	127.64	7	PASS
Band5	10MHz	16QAM	20525	1RB#24	23.12	0.1	21.07	127.94	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

Band5	10MHz	16QAM	20525	1RB#49	23.15	0.1	21.10	128.82	7	PASS
Band5	10MHz	16QAM	20525	50RB#0	22.02	0.1	19.97	99.31	7	PASS
Band5	10MHz	16QAM	20600	1RB#0	23.05	0.1	21.00	125.89	7	PASS
Band5	10MHz	16QAM	20600	1RB#24	23.12	0.1	21.07	127.94	7	PASS
Band5	10MHz	16QAM	20600	1RB#49	23.20	0.1	21.15	130.32	7	PASS
Band5	10MHz	16QAM	20600	50RB#0	22.12	0.1	20.07	101.62	7	PASS
Band5	10MHz	64QAM	20450	1RB#0	22.32	0.1	20.27	106.41	7	PASS
Band5	10MHz	64QAM	20450	1RB#24	22.02	0.1	19.97	99.31	7	PASS
Band5	10MHz	64QAM	20450	1RB#49	22.07	0.1	20.02	100.46	7	PASS
Band5	10MHz	64QAM	20450	50RB#0	21.07	0.1	19.02	79.80	7	PASS
Band5	10MHz	64QAM	20525	1RB#0	22.26	0.1	20.21	104.95	7	PASS
Band5	10MHz	64QAM	20525	1RB#24	22.30	0.1	20.25	105.93	7	PASS
Band5	10MHz	64QAM	20525	1RB#49	22.14	0.1	20.09	102.09	7	PASS
Band5	10MHz	64QAM	20525	50RB#0	20.98	0.1	18.93	78.16	7	PASS
Band5	10MHz	64QAM	20600	1RB#0	22.31	0.1	20.26	106.17	7	PASS
Band5	10MHz	64QAM	20600	1RB#24	22.12	0.1	20.07	101.62	7	PASS
Band5	10MHz	64QAM	20600	1RB#49	22.03	0.1	19.98	99.54	7	PASS
Band5	10MHz	64QAM	20600	50RB#0	21.13	0.1	19.08	80.91	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

LTE Band 26

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Gain(dBi)	ERP(dBm)	ERP(mW)	Limit(W)	Verdict
Band26	1.4MHz	QPSK	26797	1RB#0	22.75	0.1	20.70	117.49	7	PASS
Band26	1.4MHz	QPSK	26797	1RB#2	22.76	0.1	20.71	117.76	7	PASS
Band26	1.4MHz	QPSK	26797	1RB#5	22.72	0.1	20.67	116.68	7	PASS
Band26	1.4MHz	QPSK	26797	6RB#0	21.76	0.1	19.71	93.54	7	PASS
Band26	1.4MHz	QPSK	26915	1RB#0	22.86	0.1	20.81	120.50	7	PASS
Band26	1.4MHz	QPSK	26915	1RB#2	22.86	0.1	20.81	120.50	7	PASS
Band26	1.4MHz	QPSK	26915	1RB#5	22.88	0.1	20.83	121.06	7	PASS
Band26	1.4MHz	QPSK	26915	6RB#0	21.81	0.1	19.76	94.62	7	PASS
Band26	1.4MHz	QPSK	27033	1RB#0	22.76	0.1	20.71	117.76	7	PASS
Band26	1.4MHz	QPSK	27033	1RB#2	22.83	0.1	20.78	119.67	7	PASS
Band26	1.4MHz	QPSK	27033	1RB#5	22.83	0.1	20.78	119.67	7	PASS
Band26	1.4MHz	QPSK	27033	6RB#0	21.78	0.1	19.73	93.97	7	PASS
Band26	1.4MHz	16QAM	26797	1RB#0	22.20	0.1	20.15	103.51	7	PASS
Band26	1.4MHz	16QAM	26797	1RB#2	22.17	0.1	20.12	102.80	7	PASS
Band26	1.4MHz	16QAM	26797	1RB#5	22.08	0.1	20.03	100.69	7	PASS
Band26	1.4MHz	16QAM	26797	6RB#0	20.81	0.1	18.76	75.16	7	PASS
Band26	1.4MHz	16QAM	26915	1RB#0	22.22	0.1	20.17	103.99	7	PASS
Band26	1.4MHz	16QAM	26915	1RB#2	22.24	0.1	20.19	104.47	7	PASS
Band26	1.4MHz	16QAM	26915	1RB#5	22.17	0.1	20.12	102.80	7	PASS
Band26	1.4MHz	16QAM	26915	6RB#0	20.89	0.1	18.84	76.56	7	PASS
Band26	1.4MHz	16QAM	27033	1RB#0	22.19	0.1	20.14	103.28	7	PASS
Band26	1.4MHz	16QAM	27033	1RB#2	22.21	0.1	20.16	103.75	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

Band26	1.4MHz	16QAM	27033	1RB#5	22.42	0.1	20.37	108.89	7	PASS
Band26	1.4MHz	16QAM	27033	6RB#0	20.86	0.1	18.81	76.03	7	PASS
Band26	1.4MHz	64QAM	26797	1RB#0	20.93	0.1	18.88	77.27	7	PASS
Band26	1.4MHz	64QAM	26797	1RB#2	21.06	0.1	19.01	79.62	7	PASS
Band26	1.4MHz	64QAM	26797	1RB#5	21.03	0.1	18.98	79.07	7	PASS
Band26	1.4MHz	64QAM	26797	6RB#0	19.90	0.1	17.85	60.95	7	PASS
Band26	1.4MHz	64QAM	26915	1RB#0	21.02	0.1	18.97	78.89	7	PASS
Band26	1.4MHz	64QAM	26915	1RB#2	21.08	0.1	19.03	79.98	7	PASS
Band26	1.4MHz	64QAM	26915	1RB#5	21.17	0.1	19.12	81.66	7	PASS
Band26	1.4MHz	64QAM	26915	6RB#0	19.97	0.1	17.92	61.94	7	PASS
Band26	1.4MHz	64QAM	27033	1RB#0	20.94	0.1	18.89	77.45	7	PASS
Band26	1.4MHz	64QAM	27033	1RB#2	21.15	0.1	19.10	81.28	7	PASS
Band26	1.4MHz	64QAM	27033	1RB#5	21.02	0.1	18.97	78.89	7	PASS
Band26	1.4MHz	64QAM	27033	6RB#0	19.80	0.1	17.75	59.57	7	PASS
Band26	3MHz	QPSK	26805	1RB#0	22.03	0.1	19.98	99.54	7	PASS
Band26	3MHz	QPSK	26805	1RB#8	22.19	0.1	20.14	103.28	7	PASS
Band26	3MHz	QPSK	26805	1RB#14	22.15	0.1	20.10	102.33	7	PASS
Band26	3MHz	QPSK	26805	15RB#0	20.84	0.1	18.79	75.68	7	PASS
Band26	3MHz	QPSK	26915	1RB#0	22.23	0.1	20.18	104.23	7	PASS
Band26	3MHz	QPSK	26915	1RB#8	22.31	0.1	20.26	106.17	7	PASS
Band26	3MHz	QPSK	26915	1RB#14	22.08	0.1	20.03	100.69	7	PASS
Band26	3MHz	QPSK	26915	15RB#0	20.83	0.1	18.78	75.51	7	PASS
Band26	3MHz	QPSK	27025	1RB#0	22.15	0.1	20.10	102.33	7	PASS
Band26	3MHz	QPSK	27025	1RB#8	22.30	0.1	20.25	105.93	7	PASS
Band26	3MHz	QPSK	27025	1RB#14	22.10	0.1	20.05	101.16	7	PASS
Band26	3MHz	QPSK	27025	15RB#0	20.98	0.1	18.93	78.16	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

Band26	3MHz	16QAM	26805	1RB#0	21.02	0.1	18.97	78.89	7	PASS
Band26	3MHz	16QAM	26805	1RB#8	21.20	0.1	19.15	82.22	7	PASS
Band26	3MHz	16QAM	26805	1RB#14	20.94	0.1	18.89	77.45	7	PASS
Band26	3MHz	16QAM	26805	15RB#0	19.92	0.1	17.87	61.24	7	PASS
Band26	3MHz	16QAM	26915	1RB#0	21.09	0.1	19.04	80.17	7	PASS
Band26	3MHz	16QAM	26915	1RB#8	21.26	0.1	19.21	83.37	7	PASS
Band26	3MHz	16QAM	26915	1RB#14	21.07	0.1	19.02	79.80	7	PASS
Band26	3MHz	16QAM	26915	15RB#0	19.87	0.1	17.82	60.53	7	PASS
Band26	3MHz	16QAM	27025	1RB#0	21.07	0.1	19.02	79.80	7	PASS
Band26	3MHz	16QAM	27025	1RB#8	21.22	0.1	19.17	82.60	7	PASS
Band26	3MHz	16QAM	27025	1RB#14	21.04	0.1	18.99	79.25	7	PASS
Band26	3MHz	16QAM	27025	15RB#0	20.00	0.1	17.95	62.37	7	PASS
Band26	3MHz	64QAM	26805	1RB#0	22.81	0.1	20.76	119.12	7	PASS
Band26	3MHz	64QAM	26805	1RB#8	22.86	0.1	20.81	120.50	7	PASS
Band26	3MHz	64QAM	26805	1RB#14	22.78	0.1	20.73	118.30	7	PASS
Band26	3MHz	64QAM	26805	15RB#0	21.86	0.1	19.81	95.72	7	PASS
Band26	3MHz	64QAM	26915	1RB#0	22.89	0.1	20.84	121.34	7	PASS
Band26	3MHz	64QAM	26915	1RB#8	22.85	0.1	20.80	120.23	7	PASS
Band26	3MHz	64QAM	26915	1RB#14	22.76	0.1	20.71	117.76	7	PASS
Band26	3MHz	64QAM	26915	15RB#0	21.85	0.1	19.80	95.50	7	PASS
Band26	3MHz	64QAM	27025	1RB#0	22.95	0.1	20.90	123.03	7	PASS
Band26	3MHz	64QAM	27025	1RB#8	22.93	0.1	20.88	122.46	7	PASS
Band26	3MHz	64QAM	27025	1RB#14	22.73	0.1	20.68	116.95	7	PASS
Band26	3MHz	64QAM	27025	15RB#0	21.85	0.1	19.80	95.50	7	PASS
Band26	5MHz	QPSK	26815	1RB#0	21.09	0.1	19.04	80.17	7	PASS
Band26	5MHz	QPSK	26815	1RB#12	21.11	0.1	19.06	80.54	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

Band26	5MHz	QPSK	26815	1RB#24	21.07	0.1	19.02	79.80	7	PASS
Band26	5MHz	QPSK	26815	25RB#0	19.87	0.1	17.82	60.53	7	PASS
Band26	5MHz	QPSK	26915	1RB#0	21.14	0.1	19.09	81.10	7	PASS
Band26	5MHz	QPSK	26915	1RB#12	21.24	0.1	19.19	82.99	7	PASS
Band26	5MHz	QPSK	26915	1RB#24	21.19	0.1	19.14	82.04	7	PASS
Band26	5MHz	QPSK	26915	25RB#0	19.89	0.1	17.84	60.81	7	PASS
Band26	5MHz	QPSK	27015	1RB#0	21.16	0.1	19.11	81.47	7	PASS
Band26	5MHz	QPSK	27015	1RB#12	21.20	0.1	19.15	82.22	7	PASS
Band26	5MHz	QPSK	27015	1RB#24	21.13	0.1	19.08	80.91	7	PASS
Band26	5MHz	QPSK	27015	25RB#0	19.85	0.1	17.80	60.26	7	PASS
Band26	5MHz	16QAM	26815	1RB#0	23.09	0.1	21.04	127.06	7	PASS
Band26	5MHz	16QAM	26815	1RB#12	22.81	0.1	20.76	119.12	7	PASS
Band26	5MHz	16QAM	26815	1RB#24	22.79	0.1	20.74	118.58	7	PASS
Band26	5MHz	16QAM	26815	25RB#0	21.89	0.1	19.84	96.38	7	PASS
Band26	5MHz	16QAM	26915	1RB#0	22.80	0.1	20.75	118.85	7	PASS
Band26	5MHz	16QAM	26915	1RB#12	22.92	0.1	20.87	122.18	7	PASS
Band26	5MHz	16QAM	26915	1RB#24	22.83	0.1	20.78	119.67	7	PASS
Band26	5MHz	16QAM	26915	25RB#0	21.94	0.1	19.89	97.50	7	PASS
Band26	5MHz	16QAM	27015	1RB#0	22.88	0.1	20.83	121.06	7	PASS
Band26	5MHz	16QAM	27015	1RB#12	22.93	0.1	20.88	122.46	7	PASS
Band26	5MHz	16QAM	27015	1RB#24	22.83	0.1	20.78	119.67	7	PASS
Band26	5MHz	16QAM	27015	25RB#0	21.98	0.1	19.93	98.40	7	PASS
Band26	5MHz	64QAM	26815	1RB#0	22.05	0.1	20.00	100.00	7	PASS
Band26	5MHz	64QAM	26815	1RB#12	22.16	0.1	20.11	102.57	7	PASS
Band26	5MHz	64QAM	26815	1RB#24	21.97	0.1	19.92	98.17	7	PASS
Band26	5MHz	64QAM	26815	25RB#0	20.94	0.1	18.89	77.45	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com


Test Report No.: RF260413B001

Band26	5MHz	64QAM	26915	1RB#0	22.23	0.1	20.18	104.23	7	PASS
Band26	5MHz	64QAM	26915	1RB#12	22.18	0.1	20.13	103.04	7	PASS
Band26	5MHz	64QAM	26915	1RB#24	22.15	0.1	20.10	102.33	7	PASS
Band26	5MHz	64QAM	26915	25RB#0	20.92	0.1	18.87	77.09	7	PASS
Band26	5MHz	64QAM	27015	1RB#0	22.31	0.1	20.26	106.17	7	PASS
Band26	5MHz	64QAM	27015	1RB#12	22.20	0.1	20.15	103.51	7	PASS
Band26	5MHz	64QAM	27015	1RB#24	22.06	0.1	20.01	100.23	7	PASS
Band26	5MHz	64QAM	27015	25RB#0	20.88	0.1	18.83	76.38	7	PASS
Band26	10MHz	QPSK	26840	1RB#0	22.63	0.1	20.58	114.29	7	PASS
Band26	10MHz	QPSK	26840	1RB#24	22.67	0.1	20.62	115.35	7	PASS
Band26	10MHz	QPSK	26840	1RB#49	22.62	0.1	20.57	114.02	7	PASS
Band26	10MHz	QPSK	26840	50RB#0	21.84	0.1	19.79	95.28	7	PASS
Band26	10MHz	QPSK	26915	1RB#0	22.62	0.1	20.57	114.02	7	PASS
Band26	10MHz	QPSK	26915	1RB#24	22.76	0.1	20.71	117.76	7	PASS
Band26	10MHz	QPSK	26915	1RB#49	22.63	0.1	20.58	114.29	7	PASS
Band26	10MHz	QPSK	26915	50RB#0	21.81	0.1	19.76	94.62	7	PASS
Band26	10MHz	QPSK	26990	1RB#0	22.69	0.1	20.64	115.88	7	PASS
Band26	10MHz	QPSK	26990	1RB#24	22.77	0.1	20.72	118.03	7	PASS
Band26	10MHz	QPSK	26990	1RB#49	22.61	0.1	20.56	113.76	7	PASS
Band26	10MHz	QPSK	26990	50RB#0	21.87	0.1	19.82	95.94	7	PASS
Band26	10MHz	16QAM	26840	1RB#0	21.82	0.1	19.77	94.84	7	PASS
Band26	10MHz	16QAM	26840	1RB#24	22.07	0.1	20.02	100.46	7	PASS
Band26	10MHz	16QAM	26840	1RB#49	22.00	0.1	19.95	98.86	7	PASS
Band26	10MHz	16QAM	26840	50RB#0	20.83	0.1	18.78	75.51	7	PASS
Band26	10MHz	16QAM	26915	1RB#0	21.92	0.1	19.87	97.05	7	PASS
Band26	10MHz	16QAM	26915	1RB#24	22.13	0.1	20.08	101.86	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com


Test Report No.: RF260413B001

Band26	10MHz	16QAM	26915	1RB#49	22.04	0.1	19.99	99.77	7	PASS
Band26	10MHz	16QAM	26915	50RB#0	20.80	0.1	18.75	74.99	7	PASS
Band26	10MHz	16QAM	26990	1RB#0	21.94	0.1	19.89	97.50	7	PASS
Band26	10MHz	16QAM	26990	1RB#24	22.02	0.1	19.97	99.31	7	PASS
Band26	10MHz	16QAM	26990	1RB#49	21.84	0.1	19.79	95.28	7	PASS
Band26	10MHz	16QAM	26990	50RB#0	20.90	0.1	18.85	76.74	7	PASS
Band26	10MHz	64QAM	26840	1RB#0	20.87	0.1	18.82	76.21	7	PASS
Band26	10MHz	64QAM	26840	1RB#24	20.90	0.1	18.85	76.74	7	PASS
Band26	10MHz	64QAM	26840	1RB#49	20.86	0.1	18.81	76.03	7	PASS
Band26	10MHz	64QAM	26840	50RB#0	19.80	0.1	17.75	59.57	7	PASS
Band26	10MHz	64QAM	26915	1RB#0	20.64	0.1	18.59	72.28	7	PASS
Band26	10MHz	64QAM	26915	1RB#24	20.94	0.1	18.89	77.45	7	PASS
Band26	10MHz	64QAM	26915	1RB#49	20.89	0.1	18.84	76.56	7	PASS
Band26	10MHz	64QAM	26915	50RB#0	19.84	0.1	17.79	60.12	7	PASS
Band26	10MHz	64QAM	26990	1RB#0	20.84	0.1	18.79	75.68	7	PASS
Band26	10MHz	64QAM	26990	1RB#24	21.01	0.1	18.96	78.70	7	PASS
Band26	10MHz	64QAM	26990	1RB#49	21.06	0.1	19.01	79.62	7	PASS
Band26	10MHz	64QAM	26990	50RB#0	19.94	0.1	17.89	61.52	7	PASS
Band26	15MHz	QPSK	26865	1RB#0	22.20	0.1	20.15	103.51	7	PASS
Band26	15MHz	QPSK	26865	1RB#38	22.17	0.1	20.12	102.80	7	PASS
Band26	15MHz	QPSK	26865	1RB#74	22.08	0.1	20.03	100.69	7	PASS
Band26	15MHz	QPSK	26865	75RB#0	20.81	0.1	18.76	75.16	7	PASS
Band26	15MHz	QPSK	26915	1RB#0	22.22	0.1	20.17	103.99	7	PASS
Band26	15MHz	QPSK	26915	1RB#38	22.24	0.1	20.19	104.47	7	PASS
Band26	15MHz	QPSK	26915	1RB#74	22.17	0.1	20.12	102.80	7	PASS
Band26	15MHz	QPSK	26915	75RB#0	20.89	0.1	18.84	76.56	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

Band26	15MHz	QPSK	26965	1RB#0	22.19	0.1	20.14	103.28	7	PASS
Band26	15MHz	QPSK	26965	1RB#38	22.21	0.1	20.16	103.75	7	PASS
Band26	15MHz	QPSK	26965	1RB#74	22.42	0.1	20.37	108.89	7	PASS
Band26	15MHz	QPSK	26965	75RB#0	20.86	0.1	18.81	76.03	7	PASS
Band26	15MHz	16QAM	26865	1RB#0	20.93	0.1	18.88	77.27	7	PASS
Band26	15MHz	16QAM	26865	1RB#38	21.06	0.1	19.01	79.62	7	PASS
Band26	15MHz	16QAM	26865	1RB#74	21.03	0.1	18.98	79.07	7	PASS
Band26	15MHz	16QAM	26865	75RB#0	19.90	0.1	17.85	60.95	7	PASS
Band26	15MHz	16QAM	26915	1RB#0	21.02	0.1	18.97	78.89	7	PASS
Band26	15MHz	16QAM	26915	1RB#38	21.08	0.1	19.03	79.98	7	PASS
Band26	15MHz	16QAM	26915	1RB#74	21.17	0.1	19.12	81.66	7	PASS
Band26	15MHz	16QAM	26915	75RB#0	19.97	0.1	17.92	61.94	7	PASS
Band26	15MHz	16QAM	26965	1RB#0	20.94	0.1	18.89	77.45	7	PASS
Band26	15MHz	16QAM	26965	1RB#38	21.15	0.1	19.10	81.28	7	PASS
Band26	15MHz	16QAM	26965	1RB#74	21.02	0.1	18.97	78.89	7	PASS
Band26	15MHz	16QAM	26965	75RB#0	19.80	0.1	17.75	59.57	7	PASS
Band26	15MHz	64QAM	26865	1RB#0	22.80	0.1	20.75	118.85	7	PASS
Band26	15MHz	64QAM	26865	1RB#38	22.76	0.1	20.71	117.76	7	PASS
Band26	15MHz	64QAM	26865	1RB#74	22.70	0.1	20.65	116.14	7	PASS
Band26	15MHz	64QAM	26865	75RB#0	21.85	0.1	19.80	95.50	7	PASS
Band26	15MHz	64QAM	26915	1RB#0	22.92	0.1	20.87	122.18	7	PASS
Band26	15MHz	64QAM	26915	1RB#38	22.90	0.1	20.85	121.62	7	PASS
Band26	15MHz	64QAM	26915	1RB#74	22.85	0.1	20.80	120.23	7	PASS
Band26	15MHz	64QAM	26915	75RB#0	21.85	0.1	19.80	95.50	7	PASS
Band26	15MHz	64QAM	26965	1RB#0	22.83	0.1	20.78	119.67	7	PASS
Band26	15MHz	64QAM	26965	1RB#38	22.87	0.1	20.82	120.78	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

Band26	15MHz	64QAM	26965	1RB#74	22.74	0.1	20.69	117.22	7	PASS
Band26	15MHz	64QAM	26965	75RB#0	21.94	0.1	19.89	97.50	7	PASS
Band26	1.4MHz	256QAM	26797	1RB#0	22.80	0.1	20.75	118.85	7	PASS
Band26	1.4MHz	256QAM	26797	1RB#2	22.76	0.1	20.71	117.76	7	PASS
Band26	1.4MHz	256QAM	26797	1RB#5	22.70	0.1	20.65	116.14	7	PASS
Band26	1.4MHz	256QAM	26797	6RB#0	21.85	0.1	19.80	95.50	7	PASS
Band26	1.4MHz	256QAM	26915	1RB#0	22.92	0.1	20.87	122.18	7	PASS
Band26	1.4MHz	256QAM	26915	1RB#2	22.90	0.1	20.85	121.62	7	PASS
Band26	1.4MHz	256QAM	26915	1RB#5	22.85	0.1	20.80	120.23	7	PASS
Band26	1.4MHz	256QAM	26915	6RB#0	21.85	0.1	19.80	95.50	7	PASS
Band26	1.4MHz	256QAM	27033	1RB#0	22.83	0.1	20.78	119.67	7	PASS
Band26	1.4MHz	256QAM	27033	1RB#2	22.87	0.1	20.82	120.78	7	PASS
Band26	1.4MHz	256QAM	27033	1RB#5	22.74	0.1	20.69	117.22	7	PASS
Band26	1.4MHz	256QAM	27033	6RB#0	21.94	0.1	19.89	97.50	7	PASS
Band26	3MHz	256QAM	26805	1RB#0	22.12	0.1	20.07	101.62	7	PASS
Band26	3MHz	256QAM	26805	1RB#8	22.18	0.1	20.13	103.04	7	PASS
Band26	3MHz	256QAM	26805	1RB#14	22.20	0.1	20.15	103.51	7	PASS
Band26	3MHz	256QAM	26805	15RB#0	20.90	0.1	18.85	76.74	7	PASS
Band26	3MHz	256QAM	26915	1RB#0	22.34	0.1	20.29	106.91	7	PASS
Band26	3MHz	256QAM	26915	1RB#8	22.28	0.1	20.23	105.44	7	PASS
Band26	3MHz	256QAM	26915	1RB#14	22.22	0.1	20.17	103.99	7	PASS
Band26	3MHz	256QAM	26915	15RB#0	20.93	0.1	18.88	77.27	7	PASS
Band26	3MHz	256QAM	27025	1RB#0	22.37	0.1	20.32	107.65	7	PASS
Band26	3MHz	256QAM	27025	1RB#8	22.23	0.1	20.18	104.23	7	PASS
Band26	3MHz	256QAM	27025	1RB#14	22.29	0.1	20.24	105.68	7	PASS
Band26	3MHz	256QAM	27025	15RB#0	20.90	0.1	18.85	76.74	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

Band26	5MHz	256QAM	26815	1RB#0	21.05	0.1	19.00	79.43	7	PASS
Band26	5MHz	256QAM	26815	1RB#12	21.07	0.1	19.02	79.80	7	PASS
Band26	5MHz	256QAM	26815	1RB#24	21.05	0.1	19.00	79.43	7	PASS
Band26	5MHz	256QAM	26815	25RB#0	19.93	0.1	17.88	61.38	7	PASS
Band26	5MHz	256QAM	26915	1RB#0	21.10	0.1	19.05	80.35	7	PASS
Band26	5MHz	256QAM	26915	1RB#12	21.02	0.1	18.97	78.89	7	PASS
Band26	5MHz	256QAM	26915	1RB#24	21.04	0.1	18.99	79.25	7	PASS
Band26	5MHz	256QAM	26915	25RB#0	19.92	0.1	17.87	61.24	7	PASS
Band26	5MHz	256QAM	27015	1RB#0	21.02	0.1	18.97	78.89	7	PASS
Band26	5MHz	256QAM	27015	1RB#12	21.17	0.1	19.12	81.66	7	PASS
Band26	5MHz	256QAM	27015	1RB#24	20.97	0.1	18.92	77.98	7	PASS
Band26	5MHz	256QAM	27015	25RB#0	19.88	0.1	17.83	60.67	7	PASS
Band26	10MHz	256QAM	26840	1RB#0	22.75	0.1	20.70	117.49	7	PASS
Band26	10MHz	256QAM	26840	1RB#24	22.76	0.1	20.71	117.76	7	PASS
Band26	10MHz	256QAM	26840	1RB#49	22.72	0.1	20.67	116.68	7	PASS
Band26	10MHz	256QAM	26840	50RB#0	21.76	0.1	19.71	93.54	7	PASS
Band26	10MHz	256QAM	26915	1RB#0	22.86	0.1	20.81	120.50	7	PASS
Band26	10MHz	256QAM	26915	1RB#24	22.86	0.1	20.81	120.50	7	PASS
Band26	10MHz	256QAM	26915	1RB#49	22.88	0.1	20.83	121.06	7	PASS
Band26	10MHz	256QAM	26915	50RB#0	21.81	0.1	19.76	94.62	7	PASS
Band26	10MHz	256QAM	26990	1RB#0	22.76	0.1	20.71	117.76	7	PASS
Band26	10MHz	256QAM	26990	1RB#24	22.83	0.1	20.78	119.67	7	PASS
Band26	10MHz	256QAM	26990	1RB#49	22.83	0.1	20.78	119.67	7	PASS
Band26	10MHz	256QAM	26990	50RB#0	21.78	0.1	19.73	93.97	7	PASS
Band26	15MHz	256QAM	26865	1RB#0	22.03	0.1	19.98	99.54	7	PASS
Band26	15MHz	256QAM	26865	1RB#38	22.19	0.1	20.14	103.28	7	PASS

Boomwave Test (Shenzhen)
Co., Ltd.

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com



Test Report No.: RF260413B001

Band26	15MHz	256QAM	26865	1RB#74	22.15	0.1	20.10	102.33	7	PASS
Band26	15MHz	256QAM	26865	75RB#0	20.84	0.1	18.79	75.68	7	PASS
Band26	15MHz	256QAM	26915	1RB#0	22.23	0.1	20.18	104.23	7	PASS
Band26	15MHz	256QAM	26915	1RB#38	22.31	0.1	20.26	106.17	7	PASS
Band26	15MHz	256QAM	26915	1RB#74	22.08	0.1	20.03	100.69	7	PASS
Band26	15MHz	256QAM	26915	75RB#0	20.83	0.1	18.78	75.51	7	PASS
Band26	15MHz	256QAM	26965	1RB#0	22.15	0.1	20.10	102.33	7	PASS
Band26	15MHz	256QAM	26965	1RB#38	22.30	0.1	20.25	105.93	7	PASS
Band26	15MHz	256QAM	26965	1RB#74	22.10	0.1	20.05	101.16	7	PASS
Band26	15MHz	256QAM	26965	75RB#0	20.98	0.1	18.93	78.16	7	PASS

REMARKS: ERP Output Power (dBm) = EIRP (dBm) -2.15(dB).

3.2 FREQUENCY STABILITY MEASUREMENT

3.2.1 LIMITS OF FREQUENCY STABILITY MEASUREMENT


1.5 ppm is for base and fixed station. 2.5 ppm is for mobile station.

3.2.2 TEST PROCEDURE

- Device is placed at the oven room. The oven room could control the temperatures and humidity. Power warm up is at least 15 min and power applied should perform before recording frequency error.
- EUT is connected the external power supply to control the DC input power. The test voltage range is from minimum to maximum working voltage. Each step shall be record the frequency error rate.
- The temperature range step is 10 degrees in this test items. All temperature levels shall be hold the $\pm 0.5^{\circ}\text{C}$ during the measurement testing. The each temperature step shall be at least 0.5 hours, consider the EUT could be test under the stability condition.

NOTE: The frequency error was recorded frequency error from the communication simulator.

3.2.3 TEST SETUP



3.2.4 TEST RESULTS


Please Refer to WWAN module(model name: RM520N-GL) test report(NO.: SEWM2304000122RG01,FCC ID: XMR2023RM520NGL).

3.3 OCCUPIED BANDWIDTH MEASUREMENT

3.3.1 LIMITS OF OCCUPIED BANDWIDTH MEASUREMENT

The width of a frequency band such that, below the lower and above the upper frequency limits, the mean powers emitted are each equal to a specified percentage 0.5 %of the total mean power of a given emission.

3.3.2 TEST SETUP



3.3.3 TEST PROCEDURES

- The conducted occupied bandwidth used the power splitter via EUT RF power connector between simulation base station and spectrum analyzer.
- Use OBW measurement function of Spectrum analyzer to measure 99 % occupied bandwidth.

3.3.4 TEST RESULTS


Please Refer to WWAN module(model name: RM520N-GL) test report(NO.: SEWM2304000122RG01,FCC ID: XMR2023RM520NGL).

3.4 BAND EDGE MEASUREMENT

3.4.1 LIMITS OF BAND EDGE MEASUREMENT

Power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB. In the 1 MHz bands immediately outside and adjacent to the frequency block a resolution bandwidth of at least one percent of the emission bandwidth of the fundamental emission of the transmitter may be employed.

3.4.2 TEST SETUP





Test Report No.: RF260413B001

3.4.3 TEST PROCEDURES

- a) All measurements were done at low and high operational frequency range
- b) Connect the transmitter to the spectrum analyzer via coaxial cable while ensuring proper impedance matching.
- c) Tune the analyzer to the nominal center frequency of the emission bandwidth

(EBW)
- d) .Set the resolution bandwidth (RBW) $\geq 1\%$ EBW in the 1MHz band immediately outside and adjacent to the band edge.
- e) Beyond the 1MHz band from the band edge, RBW=1MHz was used.
- f) Set the video bandwidth (VBW) to $\geq 3 \times$ RBW.
- g) Select the average power (RMS) display detector.
- h) Set the number of measurement points to ≥ 1001 .
- i) Use auto-coupled sweep time.
- j) Perform the measurement over an interval of time when the transmission is continuous and at its maximum power level.
- k) The RF fundamental frequency should be excluded against the limit line in the operating frequency band and use RBW is 10KHz or 100KHz.
- l) Record the max trace plot into the test report.

3.4.4 TEST RESULTS

Please Refer to WWAN module(model name: RM520N-GL) test report(NO.: SEWM2304000122RG01,FCC ID: XMR2023RM520NGL).

3.5 CONDUCTED SPURIOUS EMISSIONS


3.5.1 LIMITS OF CONDUCTED SPURIOUS EMISSIONS MEASUREMENT

The power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB. The emission limit equal to -13dBm .

3.5.2 TEST PROCEDURE

- The EUT makes a phone call to the communication simulator. All measurements were done at low, middle and high operational frequency range.
- Measuring frequency range is from 9kHz up to a frequency including its 10th harmonic. 10dB attenuation pad is connected with spectrum. RBW=1MHz and VBW=3MHz is used for conducted emission measurement.

3.5.3 TEST SETUP



3.5.4 TEST RESULTS

NOTE : The 9K~30MHz amplitude of spurious emissions attenuated more than 20 dB below the permissible value is not required in the report.

Please Refer to WWAN module(model name: RM520N-GL) test report(NO.: SEWM2304000122RG01,FCC ID: XMR2023RM520NGL).



Test Report No.: RF260413B001

3.6 RADIATED EMISSION MEASUREMENT

3.6.1 LIMITS OF RADIATED EMISSION MEASUREMENT

The power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB. The emission limit equal to -13dBm .

3.6.2 TEST PROCEDURES

- a. Substitution method is used for E.I.R.P measurement. In the semi-anechoic chamber, EUT placed on the 0.8m height of Turn Table, rotated the table around 360 degrees to search the maximum radiation power and receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum polar radiated power. The "Read Value" is the spectrum reading the maximum power value.
- b. The substitution horn antenna is substituted for EUT at the same position and signals generator export the CW signal to the substitution antenna via a TX cable. Rotated the Turn Table and moved receiving antenna to find the maximum radiation power. Adjust output power level of S.G to get a Value of spectrum reading equal to "Read Value " of step a. Record the power level of S.G
- c. $\text{EIRP} = \text{Output power level of S.G} - \text{TX cable loss} + \text{Antenna gain of substitution horn}$.
- d. E.R.P power can be calculated form E.I.R.P power by subtracting the gain of dipole, $\text{E.R.P power} = \text{E.I.P.R power} - 2.15\text{dBi}$.


NOTE: The resolution bandwidth and video bandwidth of test receiver/spectrum analyzer is 1MHz/3MHz.

3.6.3 DEVIATION FROM TEST STANDARD


No deviation


3.6.4 TEST SETUP

< Frequency Range below 30MHz >



< Frequency Range 30MHz~1GHz >





Note: Above 1G is a directional antenna

Depends on the EUT height and the antenna 3dB beamwidth both, refer to section 7.3 of CISPR 16-2-3.

For the actual test configuration, please refer to the attached file (Test Setup Photo).



Test Report No.: RF260413B001

3.6.5 TEST RESULTS


NOTE : The 9K~30MHz amplitude of spurious emissions attenuated more than 20 dB below the permissible value is not required in the report.

BELOW 1GHz WORST-CASE DATA

LTE Band 26			
MODE	TX channel 26915	FREQUENCY RANGE	Below 1000MHz
ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH	INPUT POWER	120Vac 60HZ
TESTED BY	Carl Xie		

ANTENNA POLARITY & TEST DISTANCE: HORIZONTAL AT 3 M

NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	34.0748	-59.19	-62.29	-3.10	-13.00	49.29	Horizontal	PK	PASS
2	49.5979	-53.40	-62.56	-9.16	-13.00	49.56	Horizontal	PK	PASS
3	123.1386	-49.17	-68.20	-19.03	-13.00	55.20	Horizontal	PK	PASS
4	249.2639	-57.12	-64.28	-7.16	-13.00	51.28	Horizontal	PK	PASS
5	399.2559	-64.67	-66.90	-2.23	-13.00	53.90	Horizontal	PK	PASS
6	592.7125	-65.43	-66.58	-1.15	-13.00	53.58	Horizontal	PK	PASS



Boomwave Test (Shenzhen)
Co., Ltd.


Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com

MODE	TX channel 26915	FREQUENCY RANGE	Below 1000MHz
ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH	INPUT POWER	120Vac 60HZ
TESTED BY	Carl Xie		

ANTENNA POLARITY & TEST DISTANCE: VERTICAL AT 3 M

NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	33.8808	-48.44	-59.96	-11.52	-13.00	46.96	Vertical	PK	PASS
2	66.8674	-46.36	-65.23	-18.87	-13.00	52.23	Vertical	PK	PASS
3	136.7213	-57.89	-66.37	-8.48	-13.00	53.37	Vertical	PK	PASS
4	248.2937	-60.98	-73.39	-12.41	-13.00	60.39	Vertical	PK	PASS
5	537.9936	-66.02	-65.81	0.21	-13.00	52.81	Vertical	PK	PASS
6	721.9424	-57.45	-58.35	-0.90	-13.00	45.35	Vertical	PK	PASS






Test Report No.: RF260413B001

ABOVE 1GHz DATA

Note: For higher frequency, the emission is too low to be detected.



Boomwave Test (Shenzhen)
Co., Ltd.


Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com

CHANNEL BANDWIDTH	1.4MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: VERTICAL AT 3 M

NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1664.1328	-56.53	-66.11	-9.58	-13.00	53.11	Vertical	PK	PASS
2	2494.6989	-61.57	-67.50	-5.93	-13.00	54.50	Vertical	PK	PASS






Test Report No.: RF260413B001

CHANNEL BANDWIDTH	3MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: HORIZONTAL AT 3 M

NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1664.1328	-56.98	-66.53	-9.55	-13.00	53.53	Horizontal	PK	PASS
2	2494.6989	-61.68	-67.74	-6.06	-13.00	54.74	Horizontal	PK	PASS



Boomwave Test (Shenzhen)
Co., Ltd.


Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email: shimin.wang@boomw
avelab.com

CHANNEL BANDWIDTH	3MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: VERTICAL AT 3 M

NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1664.1328	-56.77	-66.35	-9.58	-13.00	53.35	Vertical	PK	PASS
2	2494.6989	-60.54	-66.48	-5.94	-13.00	53.48	Vertical	PK	PASS



CHANNEL BANDWIDTH	5MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: HORIZONTAL AT 3 M			
---	--	--	--

NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1633.7267	-56.68	-66.13	-9.45	-13.00	53.13	Horizontal	PK	PASS
2	2449.89	-61.17	-67.44	-6.27	-13.00	54.44	Horizontal	PK	PASS


FCC PART 22

Legend: — Limit • Final Test — Horizontal

CHANNEL BANDWIDTH	5MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: VERTICAL AT 3 M

NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	2449.89	-61.16	-67.29	-6.13	-13.00	54.29	Vertical	PK	PASS






Test Report No.: RF260413B001

CHANNEL BANDWIDTH	5MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: HORIZONTAL AT 3 M

NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1664.1328	-57.48	-67.04	-9.56	-13.00	54.04	Horizontal	PK	PASS
2	2494.6989	-62.01	-68.06	-6.05	-13.00	55.06	Horizontal	PK	PASS



Boomwave Test (Shenzhen)
Co., Ltd.


Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd,
Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen,
Guangdong, Shenzhen, China

Mobile: +86 15118052731
Email:shimin.wang@boomw
avelab.com

CHANNEL BANDWIDTH	5MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: VERTICAL AT 3 M


NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1664.1328	-54.66	-64.24	-9.58	-13.00	51.24	Vertical	PK	PASS
2	2494.6989	-61.05	-66.98	-5.93	-13.00	53.98	Vertical	PK	PASS



CHANNEL BANDWIDTH	5MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: HORIZONTAL AT 3 M


NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1694.5389	-56.95	-66.60	-9.65	-13.00	53.60	Horizontal	PK	PASS
2	2539.5079	-61.84	-67.68	-5.84	-13.00	54.68	Horizontal	PK	PASS



CHANNEL BANDWIDTH	5MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: VERTICAL AT 3 M


NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1694.5389	-57.20	-66.83	-9.63	-13.00	53.83	Vertical	PK	PASS
2	2539.5079	-60.25	-66.00	-5.75	-13.00	53.00	Vertical	PK	PASS



CHANNEL BANDWIDTH	10MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: HORIZONTAL AT 3 M


NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1664.1328	-56.95	-66.51	-9.56	-13.00	53.51	Horizontal	PK	PASS
2	2494.6989	-60.32	-66.38	-6.06	-13.00	53.38	Horizontal	PK	PASS



CHANNEL BANDWIDTH	10MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: VERTICAL AT 3 M


NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1664.1328	-56.32	-65.90	-9.58	-13.00	52.90	Vertical	PK	PASS
2	2494.6989	-60.77	-66.70	-5.93	-13.00	53.70	Vertical	PK	PASS



CHANNEL BANDWIDTH	15MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: HORIZONTAL AT 3 M


NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1664.1328	-56.51	-66.07	-9.56	-13.00	53.07	Horizontal	PK	PASS
2	2494.6989	-60.36	-66.42	-6.06	-13.00	53.42	Horizontal	PK	PASS



CHANNEL BANDWIDTH	15MHz/QPSK	MODE	TX channel 26915
FREQUENCY RANGE	Above 1000MHz	ENVIRONMENTAL CONDITIONS	23deg. C, 70%RH
INPUT POWER	120Vac 60HZ	TESTED BY	Carl Xie

ANTENNA POLARITY & TEST DISTANCE: VERTICAL AT 3 M

NO.	Frequency [MHz]	Reading [dBm]	Level [dBm]	Factor [dB]	Limit [dBm]	Margin [dB]	Polarity	Detector	Verdict
1	1664.1328	-56.28	-65.86	-9.58	-13.00	52.86	Vertical	PK	PASS
2	2494.6989	-60.71	-66.64	-5.93	-13.00	53.64	Vertical	PK	PASS




3.7 PEAK TO AVERAGE RATIO

3.7.1 LIMITS OF PEAK TO AVERAGE RATIO MEASUREMENT

In measuring transmissions in this band using an average power technique, the peak to-average ratio (PAR) of the transmission may not exceed 13 dB

3.7.2 TEST SETUP



3.7.3 TEST PROCEDURES

1. Set resolution/measurement bandwidth $\geq$ signal's occupied bandwidth;
2. Set the number of counts to a value that stabilizes the measured CCDF curve;
3. Record the maximum PAPR level associated with a probability of 0.1%.

3.7.4 TEST RESULTS

Please Refer to WWAN module(model name: RM520N-GL) test report(NO.: SEWM2304000122RG01,FCC ID: XMR2023RM520NGL).



Test Report No.: RF260413B001

4 PHOTOGRAPHS OF THE TEST CONFIGURATION

Please refer to the attached file (Test Setup Photo).



Test Report No.: RF260413B001

5 INFORMATION ON THE TESTING LABORATORIES

We, Boomwave Test (Shenzhen) co., Ltd., were founded in 2025 to provide our best service in EMC, Radio, Telecom and Safety consultation. Our laboratories are accredited and approved according to ISO/IEC 17025.

Boomwave Test (Shenzhen) Co., Ltd.

Lab Address:

Rm B38, Warehouse A5(Chiwan #1), #3 Chiwan 4th Rd, Chiwan Comm, Zhaoshang St, Nanshan Dist, Shenzhen, Guangdong, Shenzhen, China

Accredited Test Lab Cert 7607.01

Shenzhen EMC/RF Lab:

Mobile: +86 15118052731

Email: shimin.wang@boomwavelab.com



Test Report No.: RF260413B001

6 MODIFICATIONS RECORDERS FOR ENGINEERING CHANGES TO THE EUT BY THE LAB

No any modifications are made to the EUT by the lab during the test.