

CONTENTS	
SAFETY INFORMATION	01
PACKING LIST	03
PRODUCT INTRODUCTION	04
OPERATING INSTRUCTIONS	07
POWER SUPPLYING(FOR REFERENCE ONLY)	10
MAINTENANCE AND CARE	10
PRODUCT SPECIFICATIONS	11
TROUBLESHOOTING GUIDE	12
WARRANTY & CUSTOMER SERVICE	12
WARNINGS	13

11. DO NOT cover the product with cloth, paper or any other materials when the portable power station is working.



12. "DO NOT expose the product to fire, heat sources, direct sunlight, or temperatures exceeding 70°C (158°F), as this may result in an explosion."






13. We assume no liability or responsibility for any fire, explosion or electrical shock caused by improper operation.



PACKING LIST




Main Unit *1



50W AC Adapter *1



User Manual *1



12V/521DC Car Cigarette
Lighter Adapter (Female)

- j. Real-time power display symbol, when the device is supplying power to other devices, it displays the current real-time output power.
- k. Battery life display symbol, When the device is supplying power to other devices, it displays the sustainable output time at the current power. When [Hrs] is on, the continuous output time is in minutes, and when [Hours] is on, the continuous output time is in hours.

OPERATING INSTRUCTIONS

1.Charging

For first-time use, please use the included power adaptor to fully charge the device before use.
When the battery level drops below 15%, please charge the device promptly.

- Tips:
- It will take 7-8 hours to reach a full charge.
- Please do not touch the adaptor when charging.
- Unplug the AC adaptor once the portable power station is fully-charged.
- Please be away from the TV, radio or other equipment when charging the unit.
- You can also use a phone PD fast charger to charge the device.

2.Wireless Charging, DC, USB-C, USB-A Output

Short press the power button to turn on the Wireless Charging, DC, USB-C, and USB-A outputs(the LCD screen will light up at this time, the USB-A+USB-C+DC icon will light up). Press and hold the power button again for 5 seconds to turn off the output ports and the LED display will turn off.

PRODUCT SPECIFICATIONS		TROUBLESHOOTING GUIDE	
Battery Capacity	500W 266Wh	Q1. Why can't I charge my device via the Dc Output or USB Output?	
Battery Indicator	LED screen displays current battery percentage	* Please make sure to press the On/Off button to turn on the power for the Dc outputs and USB outputs. * Make sure the portable power station has enough power.	
Input USB-C1	5V/9V/12V/15V=3A, 20V/28V=5A(Max 140W)	Q2. Why can't I charge my device via the AC Output?	
USB-A Output	USB-A1: USB-A2, 5V/3A (MAX)	* Please make sure to long press the power button to turn on the power of the AC output. * Make sure the portable power station has enough power.	
USB-C1 Output	5V/9V/12V/15V=3A, 20V/28V=5A(Max 140W)	Q3. Is this portable power station allowed in airplanes?	
USB-C2 Output	5V/9V/12V/15V=3A, 20V=2.25A(Max 45W)	No. According to the regulation of the International Civil Aviation Organization, the Lithium-Ion battery under 100 Watt-hour is ok with carry-on ONLY.	
USB-C3 Output	5V/9V/12V/15V=3A, 20V=2.25A(Max 45W)	Q4. Can the portable power station supply power to external devices when it's charging?	
DC (φ 5.5*2.1mm) Output	DC12V=10A(Max)	* It's feasible for DC outputs and USB outputs, but not for AC outputs. However, to extend the battery life, it's not recommended to do so.	
AC Output	120V/300W/60Hz, peak power500W	THANK YOU FOR YOUR PURCHASE	
Wireless Charging	15W	Congratulations on your purchase and welcome to AOC!	
Dimensions	222.5*153.5*152mm	To get the most of your product and enjoy all AOC has to offer.	
Weight	2.5kg	⚠ Note:	
Operating Temperature	Charging: 0~40°C; Discharging: -10~50°C;	Please read the safety instructions in the "Safety & Precaution" section before use.	
Cycle Life	500+Times		

111

112

authorized service centre. 4. For the components that would be the property of our available beyond the municipal limits of the available service centre, it is the responsibility of the Customer to bring the Portable Power Station to the nearest service center at his/her own risk and expenses. 5. For any Portable Power Station repaired or replaced during the warranty period, the repaired or replaced Portable Power Station shall continue to be within warranty period for the remaining time of the original warranty period of original Portable Power Station. 6. The warranty will be declared void under the following circumstances: a) The Portable Power Station serial number, the accessory date code, the power indicator or the warranty seal has been removed, erased defaced, altered or is illegible; b) Deterioration of the product due to normal wear and tear; c) Usage other than accordance with the user manual, rough handling, ingestion off exposure to any kind of liquid (water, beverages, oil, etc.), exposure to moisture, dampness or exposure to extreme thermal or environmental conditions, corrosion, oxidation, unauthorized repairs, unauthorized spare parts usage, accidents, forces of nature, or other beyond the reasonable control of warrantior was cause directly by defects in material or workmanship. The Warranty will also not cover. 7. Any claim under the Warranty is subject to notification to an AOC authorized service center for the alleged defect within a reasonable time of its occurrence and in no event later that the expiry of the warranty period. The warranty terms state the entire warranty given by AOC to the customer. 8. Our authorized service center reserves the right to charge a service fee for repair/service of any nature that is not covered by this warranty.	9. Our obligation under this warranty shall be limited to repair or provide replacement of parts only. The maximum claim entitlement by the warrantior will be subject to maximum retail price of the Extended Display purchased or the purchase price, whichever is lower. 10. In event of any unforeseen circumstances, there is unavailability of certain spare parts, prevailing depreciation rules will be binding on the purchaser to accept as a commercial solution in lieu of repairs. 11. If you have any questions or require assistance, please don't hesitate to reach out. Our dedicated customer service team is available around the clock. 24/7, via email at aoc-after-sales@customerafter-sales.com and through Amazon Messages. WARNINGS RISK OF EXPLOSION IF BATTERY IS REPLACED BY AN INCORRECT TYPE. DISPOSE OF USED BATTERIES ACCORDING TO THE INSTRUCTIONS --- The symbol indicates DC voltage FCC Warning This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
--	---

--	--