



Appendix B

RF Test Data for BT LE(Conducted Measurement)

Product Name: AI SMART PHONE

Test Model: NM-D1001U

Environmental Conditions

Temperature:	23.6°C
Relative Humidity:	54.8%
ATM Pressure:	100.0 kPa
Test Engineer:	Jerry Chu
Supervised by:	Paddi Chen





B.1-6dB Bandwidth


Condition	Mode	Frequency (MHz)	Antenna	-6 dB Bandwidth (MHz)	Limit -6 dB Bandwidth (MHz)	Verdict
NVNT	BLE	2402	Ant1	0.713	≥ 0.5	Pass
NVNT	BLE	2440	Ant1	0.653	≥ 0.5	Pass
NVNT	BLE	2480	Ant1	0.68	≥ 0.5	Pass






Test Graphs

-6dB Bandwidth NVNT BLE 2402MHz Ant1



-6dB Bandwidth NVNT BLE 2440MHz Ant1




Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





B.2 Maximum Peak Conducted Output Power


Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Limit (dBm)	Verdict
NVNT	BLE	2402	Ant1	2	30	Pass
NVNT	BLE	2440	Ant1	2.58	30	Pass
NVNT	BLE	2480	Ant1	2.72	30	Pass







Test Graphs

Power NVNT BLE 2402MHz Ant1



Power NVNT BLE 2440MHz Ant1







B.3 Maximum Power Spectral Density Level


Condition	Mode	Frequency (MHz)	Antenna	Conducted PSD (dBm/3kHz)	Limit (dBm/3kHz)	Verdict
NVNT	BLE	2402	Ant1	-14.81	8	Pass
NVNT	BLE	2440	Ant1	-13.66	8	Pass
NVNT	BLE	2480	Ant1	-14.1	8	Pass






Test Graphs

PSD NVNT BLE 2402MHz Ant1



PSD NVNT BLE 2440MHz Ant1




Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





B.4 Band Edge


Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE	2402	Ant1	-58.23	-20	Pass
NVNT	BLE	2480	Ant1	-58.4	-20	Pass






Test Graphs

Band Edge NVNT BLE 2402MHz Ant1 Ref



Band Edge NVNT BLE 2402MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Band Edge NVNT BLE 2480MHz Ant1 Ref



Band Edge NVNT BLE 2480MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



B.5 Conducted RF Spurious Emission


Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE	2402	Ant1	-54.05	-20	Pass
NVNT	BLE	2440	Ant1	-55.27	-20	Pass
NVNT	BLE	2480	Ant1	-54.49	-20	Pass






Test Graphs

Tx. Spurious NVNT BLE 2402MHz Ant1 Ref



Tx. Spurious NVNT BLE 2402MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT BLE 2440MHz Ant1 Ref



Tx. Spurious NVNT BLE 2440MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT BLE 2480MHz Ant1 Ref



Tx. Spurious NVNT BLE 2480MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



B.6 Duty Cycle


Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	BLE	2402	Ant1	85.12	0.7	0.47
NVNT	BLE	2440	Ant1	85.1	0.7	0.47
NVNT	BLE	2480	Ant1	85.1	0.7	0.47






Test Graphs

Duty Cycle NVNT BLE 2402MHz Ant1



Duty Cycle NVNT BLE 2440MHz Ant1




Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





B.7 Restrict Band


Condition	Mode	Frequency (MHz)	Antenna	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	Duty Factor (dB)	E (dBuV/m)	Detector	Limit (dBuV/m)	Verdict
NVNT	BLE	2402	Ant1	2310	-51.13	2	-	46.13	Peak	74	Pass
NVNT	BLE	2402	Ant1	2310	-58.82	2	0.7	39.14	Average	54	Pass
NVNT	BLE	2402	Ant1	2373.264	-47.49	2	-	49.77	Peak	74	Pass
NVNT	BLE	2402	Ant1	2389.968	-58.09	2	0.7	39.87	Average	54	Pass
NVNT	BLE	2402	Ant1	2390	-51.46	2	-	45.8	Peak	74	Pass
NVNT	BLE	2402	Ant1	2390	-58.09	2	0.7	39.87	Average	54	Pass
NVNT	BLE	2480	Ant1	2483.5	-49.35	2	-	47.91	Peak	74	Pass
NVNT	BLE	2480	Ant1	2483.5	-57.77	2	0.7	40.19	Average	54	Pass
NVNT	BLE	2480	Ant1	2485.744	-46.96	2	-	50.3	Peak	74	Pass
NVNT	BLE	2480	Ant1	2484.328	-57.6	2	0.7	40.36	Average	54	Pass
NVNT	BLE	2480	Ant1	2500	-49.71	2	-	47.55	Peak	74	Pass
NVNT	BLE	2480	Ant1	2500	-58.25	2	0.7	39.71	Average	54	Pass






Test Graphs

Restrict Band NVNT BLE 2402MHz Ant1 Peak



Restrict Band NVNT BLE 2402MHz Ant1 Average



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Restrict Band NVNT BLE 2480MHz Ant1 Peak



Restrict Band NVNT BLE 2480MHz Ant1 Average



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity