


Duty Cycle


Condition	Mode	Frequency (MHz)	On Time (ms)	Period (ms)	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)	Max Variation (%)
NVNT	a	5500	2.088	2.136	97.75	0.1	0.48	0.22
NVNT	a	5580	2.088	2.136	97.75	0.1	0.48	0.21
NVNT	a	5700	2.088	2.136	97.75	0.1	0.48	0.23
NVNT	n20	5500	4.017	4.065	98.82	0.05	0.25	/
NVNT	n20	5580	4.017	4.065	98.82	0.05	0.25	/
NVNT	n20	5700	4.017	4.065	98.82	0.05	0.25	/
NVNT	n40	5510	3.995	4.045	98.76	0.05	0.25	/
NVNT	n40	5550	3.995	4.04	98.89	0.05	0.25	/
NVNT	n40	5670	3.99	4.04	98.76	0.05	0.25	/
NVNT	ac20	5500	4.005	4.053	98.82	0.05	0.25	/
NVNT	ac20	5580	4.002	4.05	98.81	0.05	0.25	/
NVNT	ac20	5700	4.002	4.05	98.81	0.05	0.25	/
NVNT	ac40	5510	3.98	4.025	98.88	0.05	0.25	/
NVNT	ac40	5550	3.98	4.03	98.76	0.05	0.25	/
NVNT	ac40	5670	3.98	4.03	98.76	0.05	0.25	/
NVNT	ac80	5530	3.978	4.026	98.81	0.05	0.25	/
NVNT	ac80	5610	3.975	4.023	98.81	0.05	0.25	/

Test Graphs

Duty Cycle NVNT a 5500MHz



Duty Cycle NVNT a 5580MHz




Duty Cycle NVNT a 5700MHz

Duty Cycle NVNT n20 5580MHz


Duty Cycle NVNT n40 5510MHz

Duty Cycle NVNT n40 5670MHz

Duty Cycle NVNT ac20 5580MHz



Duty Cycle NVNT ac20 5700MHz



Duty Cycle NVNT ac40 5510MHz

Duty Cycle NVNT ac40 5670MHz


Duty Cycle NVNT ac80 5610MHz

Maximum Conducted Output Power


Condition	Mode	Frequency (MHz)	Conducted Power (dBm)	Correction Factor (dB)	Total Power (dBm)	Limit (dBm)	Verdict
NVNT	a	5500	11.69	0.1	11.79	<=24	Pass
NVNT	a	5580	10.74	0.1	10.84	<=24	Pass
NVNT	a	5700	10.31	0.1	10.41	<=24	Pass
NVNT	n20	5500	11.96	-	11.96	<=24	Pass
NVNT	n20	5580	11.2	-	11.2	<=24	Pass
NVNT	n20	5700	10.18	-	10.18	<=24	Pass
NVNT	n40	5510	11.75	-	11.75	<=24	Pass
NVNT	n40	5550	10.96	-	10.96	<=24	Pass
NVNT	n40	5670	10.78	-	10.78	<=24	Pass
NVNT	ac20	5500	11.3	-	11.3	<=24	Pass
NVNT	ac20	5580	10.27	-	10.27	<=24	Pass
NVNT	ac20	5700	10.11	-	10.11	<=24	Pass
NVNT	ac40	5510	11.99	-	11.99	<=24	Pass
NVNT	ac40	5550	11.29	-	11.29	<=24	Pass
NVNT	ac40	5670	11.07	-	11.07	<=24	Pass
NVNT	ac80	5530	11.79	-	11.79	<=24	Pass
NVNT	ac80	5610	10.9	-	10.9	<=24	Pass

Test Graphs


Power NVNT a 5500MHz




Power NVNT a 5580MHz




Power NVNT a 5700MHz




Power NVNT n20 5500MHz




Power NVNT n20 5580MHz




Power NVNT n20 5700MHz




Power NVNT n40 5510MHz




Power NVNT n40 5550MHz




Power NVNT n40 5670MHz




Power NVNT ac20 5500MHz




Power NVNT ac20 5580MHz




Power NVNT ac20 5700MHz




Power NVNT ac40 5510MHz




Power NVNT ac40 5550MHz




Power NVNT ac40 5670MHz



Power NVNT ac80 5530MHz






-26dB Bandwidth


Condition	Mode	Frequency (MHz)	-26 dB Bandwidth (MHz)	Verdict
NVNT	a	5500	24.3	Pass
NVNT	a	5580	23.01	Pass
NVNT	a	5700	24.47	Pass
NVNT	n20	5500	24.26	Pass
NVNT	n20	5580	23.75	Pass
NVNT	n20	5700	24.28	Pass
NVNT	n40	5510	43.45	Pass
NVNT	n40	5550	41.87	Pass
NVNT	n40	5670	42.78	Pass
NVNT	ac20	5500	24.1	Pass
NVNT	ac20	5580	23.62	Pass
NVNT	ac20	5700	24.3	Pass
NVNT	ac40	5510	42.2	Pass
NVNT	ac40	5550	43.24	Pass
NVNT	ac40	5670	42.99	Pass
NVNT	ac80	5530	84.19	Pass
NVNT	ac80	5610	84.55	Pass

Test Graphs


-26dB Bandwidth NVNT a 5500MHz




-26dB Bandwidth NVNT a 5580MHz




-26dB Bandwidth NVNT a 5700MHz




-26dB Bandwidth NVNT n20 5500MHz




-26dB Bandwidth NVNT n20 5580MHz




-26dB Bandwidth NVNT n20 5700MHz




-26dB Bandwidth NVNT n40 5510MHz




-26dB Bandwidth NVNT n40 5550MHz




-26dB Bandwidth NVNT n40 5670MHz




-26dB Bandwidth NVNT ac20 5500MHz




-26dB Bandwidth NVNT ac20 5580MHz




-26dB Bandwidth NVNT ac20 5700MHz




-26dB Bandwidth NVNT ac40 5510MHz




-26dB Bandwidth NVNT ac40 5550MHz




-26dB Bandwidth NVNT ac40 5670MHz



-26dB Bandwidth NVNT ac80 5530MHz






Occupied Channel Bandwidth


Condition	Mode	Frequency (MHz)	99% OBW (MHz)
NVNT	a	5500	16.684
NVNT	a	5580	16.552
NVNT	a	5700	16.799
NVNT	n20	5500	17.761
NVNT	n20	5580	17.653
NVNT	n20	5700	17.787
NVNT	n40	5510	36.084
NVNT	n40	5550	35.945
NVNT	n40	5670	36.07
NVNT	ac20	5500	17.748
NVNT	ac20	5580	17.69
NVNT	ac20	5700	17.796
NVNT	ac40	5510	36.061
NVNT	ac40	5550	35.925
NVNT	ac40	5670	36.084
NVNT	ac80	5530	74.976
NVNT	ac80	5610	75.124

Test Graphs


OBW NVNT a 5500MHz




OBW NVNT a 5580MHz




OBW NVNT a 5700MHz




OBW NVNT n20 5500MHz




OBW NVNT n20 5580MHz




OBW NVNT n20 5700MHz




OBW NVNT n40 5510MHz




OBW NVNT n40 5550MHz




OBW NVNT n40 5670MHz




OBW NVNT ac20 5500MHz




OBW NVNT ac20 5580MHz




OBW NVNT ac20 5700MHz




OBW NVNT ac40 5510MHz




OBW NVNT ac40 5550MHz




OBW NVNT ac40 5670MHz



OBW NVNT ac80 5530MHz






Maximum Power Spectral Density Level


Condition	Mode	Frequency (MHz)	Conducted PSD (dBm)	Correction Factor (dB)	Total PSD (dBm)	Limit (dBm)	Verdict
NVNT	a	5500	1.984	0.1	2.084	<=11	Pass
NVNT	a	5580	0.89	0.1	0.99	<=11	Pass
NVNT	a	5700	0.619	0.1	0.719	<=11	Pass
NVNT	n20	5500	2.065	-	2.065	<=11	Pass
NVNT	n20	5580	1.42	-	1.42	<=11	Pass
NVNT	n20	5700	0.297	-	0.297	<=11	Pass
NVNT	n40	5510	-1.53	-	-1.53	<=11	Pass
NVNT	n40	5550	-2.178	-	-2.178	<=11	Pass
NVNT	n40	5670	-2.264	-	-2.264	<=11	Pass
NVNT	ac20	5500	1.273	-	1.273	<=11	Pass
NVNT	ac20	5580	0.415	-	0.415	<=11	Pass
NVNT	ac20	5700	0.051	-	0.051	<=11	Pass
NVNT	ac40	5510	-1.477	-	-1.477	<=11	Pass
NVNT	ac40	5550	-1.926	-	-1.926	<=11	Pass
NVNT	ac40	5670	-2.041	-	-2.041	<=11	Pass
NVNT	ac80	5530	-4.166	-	-4.166	<=11	Pass
NVNT	ac80	5610	-5.058	-	-5.058	<=11	Pass

Test Graphs


PSD NVNT a 5500MHz




PSD NVNT a 5580MHz




PSD NVNT a 5700MHz




PSD NVNT n20 5500MHz




PSD NVNT n20 5580MHz




PSD NVNT n20 5700MHz




PSD NVNT n40 5510MHz




PSD NVNT n40 5550MHz




PSD NVNT n40 5670MHz




PSD NVNT ac20 5500MHz




PSD NVNT ac20 5580MHz




PSD NVNT ac20 5700MHz




PSD NVNT ac40 5510MHz



PSD NVNT ac40 5550MHz



PSD NVNT ac40 5670MHz



PSD NVNT ac80 5530MHz

