1. はじめに

お買い上げありがとうございます。ご使用の前に「取扱説明書」をよくお読みの上、正しくお使いください。

もくじ

1. はじめに……2
2. 注意事項……3-5
3. 付属品……6
4. 仕様……6
5. 各部名称……7
6. 使用方法……8-13
6-1. 充電ケーブルの接続……8
6-2-A. ワイヤレス充電の場合……9-10
6-4. 本製品への充電……11
6-5. パススルー充電……12-13
6-6. マグネットおよび直接のワイヤレス充電について……13-14
7. Find My機能……14-15
8. 製品保証……16-17

2

2.注意事項

⚠警告 死亡や重傷に結びつく恐れがある内容です。

⚠注意 重傷を負う可能性及び、物的損害に結びつく恐れがある内容です。

⚠警告

- 本製品で発音や異常な発熱、異臭、損傷、または異物の侵入が確認された場合、すぐに使用停止してください。
- 分解及び改造は絶対に行わないでください。火災・感電・怪我の原因となります。
- お子様だけでご使用、放置の不適切なことが絶対にないでください。
- 本製品をおもちゃ、湿ったようなところでしてください。発熱・発火・火災・感電・怪我・故障の原因となります。
- 直流による長時間での使用、放置、保管は避けてください。また、ものへ反しないでください。
- 本製品を落としたり、重いものを上に置いたり、衝撃を与えたりしないでください。感電・故障・怪我・発熱・発火の原因となります。
- 本製品は熱を発する装置から遠くに使用してください。
- 直射日光の当たる場所や車中など、高温の場所に放置しないでください。発熱、発火の原因となります。

3

3.製品概要

ワイヤレス充電・有線充電に対応

ワイヤレス充電と有線充電に対応しています。
※ワイヤレス充電と有線充電の同時利用等には対応していません。
また、本製品を充電しながら、デバイスをワイヤレス充電できるパススルー充電に対応しています。

NovaCore C3搭載

サイクルカウントをもとにバッテリーの寿命を管理します。
所定のサイクル数に達すると、より安全にお使いいただくため、デバイスへの充電機能が停止します。
※製品に異常がないことを確認のうえ、所定の操作で充電機能の停止を解除できます。詳しくはスマートフォンご確認ください。

アプリでバッテリーの状態を確認

専用アプリから、本製品のバッテリー残量やサイクルカウントを確認できます。

4.NovaCore C3 機能概要

NovaCore C3とは

NovaCore C3は、サイクルカウント（モバイルバッテリーの充放電回数）をもとに、バッテリーの寿命を管理する仕組みです。所定のサイクル数に達すると、より安全にお使いいただくため、本製品からデバイスを充電する機能が停止します。

*バッテリー容量の100%に相当する電力を使用すると「1サイクル」としてカウントします。実際に充電した回数や、ケーブルを抜き差しした回数とは異なります。

充電機能の停止後について

充電機能が停止した場合は、本製品の使用を終了してください。一時的に使用する必要がある場合は、製品に発熱や破損などの異常がないことを確認のうえ、所定の操作（5ページ参照）で充電機能の停止を解除できます。
解除後は、20%イクルごとにお知らせを表示します。製品に異常が見られる場合は、直ちに使用を中止してください。

※所定のサイクル数に達した製品は、製品保証の対象外となります。

5.各部名称

LEDインジケーターの表示について



紫色点灯：デバイス充電中
紫色点滅(約1秒間隔)：低電流モード
紫色点滅(高速点滅)：異物検知機能 動作中
青色点灯：アプリ接続時
赤色点滅または点灯：サイクルカウント表示時

6.本製品への充電



同梱のUSB-Cケーブルを使用し、本製品とUSB充電器を接続して充電してください。

【パススルー充電について】
パススルー充電時は、通常の充電時に比べて本製品の充電に時間が必要です。
※端色のLEDインジケーターが点灯します。
※ワイヤレス充電時は、本製品はスタンドとなり使用する場合があります。



7.デバイスへの充電

ワイヤレスまたはUSB-Cケーブルで、本製品とデバイスを接続して充電してください。
※ワイヤレス充電時は、本製品およびスマートフォンが発熱する場合があります。

【低電流モードについて】
本製品と小型デバイス(ワイヤレスイヤホンなど)をUSB-Cケーブルで接続してください。
ボタンを3秒長押しすると、紫色のLEDインジケーターが点滅します。
充電開始から約2時間経過、またはボタンを2回押すと充電が停止します。
※本製品は同時充電に対応しています。
ワイヤレス充電と有線充電を同時に行うと、有線出力での充電を優先します。

8.本製品とアプリの接続

スマートフォンやタブレットにアプリをダウンロードすると、有線接続でバッテリー残量や状況の確認を行えます。

※本アプリは常ご使用いただくには「会員登録」（メールアドレス・パスワード）が必要です。
アカウントをお持ちでない方、パスワードが不明な方は、
このQRのより新規登録またはパスワードの再発行をお願いいたします。

本製品やアプリの操作方法はこちら→

アプリのダウンロードはこちら→ GET IT ON Google play / Download on the App Store

*IOS is a trademark or registered trademark of Cisco in the US, and other countries and is used under license.
*Android is a trademark of Google LLC.

9.付属品

■ 本製品 ■ 取扱説明書 ■ USB-C to USB-Cケーブル

10.仕様

SMARTCOBY ULTRA SLIM SS5K
型番: CIO-MB20W1C-SS5K-USWL7
バッテリー容量: 5000mAh/3.85V/19.25Wh
定格容量: 2800mAh(5V⎓3A)
USB-C入力: 5V⎓3A/9V⎓1.67A
USB-C出力: 5V⎓3A/9V⎓2.22A
PPS: 5-11V⎓1.8A
ワイヤレス出力: 5W/7.5W(EPP15W)
サイズ: 約101.4 × 69.4 × 6.83 mm
重量: 約112g
くり返し使用上限:約300回
充電時間: 約120分

*USB Type-C® and USB-C® are registered trademarks of USB Implementers Forum.

11.よくあるご質問

Q. LEDインジケーターの左端が赤く光っています。故障でしょうか？
A. LEDインジケーターの左端が赤く光っている状態は、サイクルカウントを表示していることを意味します。表示を消してご使用になる場合は以下の操作を行ってください。

注意表示の消し方 ：ボタンを2秒以内に3回押す
警告表示の解除方法：ボタンを2秒以内に10回押す

注意表示 警告表示

Q. くり返し使用上限の回数を超えても使えますか？
A. くり返し使用上限の回数を超えても、以下の操作をしていただくことで引き続きご使用いただけます。

ロックの解除方法：ボタンを6秒以内に10回押す

ただし、本製品を落下させて強い衝撃を与えた場合など、くり返し使用上限の回数前に比べて故障のリスクが高くなります。
また、くり返し使用上限を超えてご使用いただいた場合につきましては、保証サービスによる交換対応をいたしかねます。
※熱の伝導性が良くないことにつきましては、製品が発熱していない場合に限ご利用いただけます。

Q. アプリを使わなくても本製品は使えますか？
A. はい、本体のボタン操作のみでも、出力モードの切替などをお使いいただけます。専用アプリを使用しない場合は、スマートフォンの画面上で充電状況の確認や各種設定などを行うことはできません。

Cover	Contents	3. Product Overview	4. NovaCore C3 Overview	5. Parts and Functions	6. Charging the Power Bank	7. Charging a Device	8. Connecting to the App	9. Package Contents / 10. Specifications	11. Frequently Asked Questions	FCC Warning Statement	FCC Warning Statement	Warranty / LINE / YouTube
SMARTCOBY ULTRA SLIM SS 5K Instruction Manual Model: CIO-MB20W1C-SS5K-USWL7	Contents 3. Product Overview 4. NovaCore C3 Overview 5. Parts and Functions 6. Charging the Power Bank 7. Charging a Device 8. Connecting the Product to the App 9. Package Contents 10. Specifications 11. Frequently Asked Questions FCC Warning Statement Product Warranty / LINE / YouTube	Supports Wireless and Wired Charging This product supports both wireless and wired charging. Note: Simultaneous wireless and wired charging of two devices is not supported. This product also supports pass-through charging, allowing you to wirelessly charge a device while charging the power bank itself. Equipped with NovaCore C3 NovaCore C3 manages battery life based on the cycle count. When the specified number of cycles is reached, the device charging function will stop for safer use. Check Battery Status with the App The dedicated app allows you to check the remaining battery level and cycle count.	What is NovaCore C3? NovaCore C3 is a battery life management system that manages battery life based on the cycle count.* When the specified number of cycles is reached, the function for charging connected devices will stop to help ensure safer use. * One cycle is counted when an amount of power equivalent to 100% of the battery capacity has been used. This differs from the actual number of charging sessions or cable connections. After the Charging Function Stops If the charging function stops, discontinue use. If temporary use is necessary, check the product for swelling or physical damage before performing the specified unlock operation. After unlocking, a notification is displayed every 20 cycles. Note: Products that have reached the specified cycle count are no longer covered by the product warranty.	LED Indicator Status Purple, solid: Charging a device Purple, flashing (approx. once per second): Low Current Mode Purple, rapidly flashing: Foreign Object Detection (FOD) active Blue, solid: Connected to the app Red, flashing or solid: Cycle count indication Four white LEDs: Remaining battery level / cycle count [Product illustration and callout labels to be inserted from final artwork.]	Use the included USB-C cable to connect this product to a USB charger and charge the power bank. About Pass-Through Charging When using pass-through charging, charging the power bank itself will take longer than during normal charging. Note: Please use a USB charger that supports an output of 20 W or higher.	Connect this product to your device wirelessly or using a USB-C cable. During wireless charging, the leftmost LED indicator lights solid purple. Note: This product and the smartphone may become warm during wireless charging. Note: This product does not support simultaneous charging of two devices. If wireless and wired charging are used at the same time, wired charging takes priority. Low Current Mode Connect a small device such as wireless earphones using a USB-C cable. Press and hold the button for 3 seconds. The purple LED flashes. Charging stops after approximately 2 hours, or when the button is pressed twice.	Download the app to your smartphone or tablet to check the remaining battery level and product status through a wired connection. Note: A registered account (email address and password) is required. If you do not have an account or have forgotten your password, register or reset it through the CIO official website. [QR: Operation instructions] [QR: iOS] [QR: Android] iOS is a trademark or registered trademark of Cisco in the U.S. and other countries and is used under license. Android is a trademark of Google LLC.	Package Contents • Power bank • Instruction manual • USB-C to USB-C cable Product Name: SMARTCOBY ULTRA SLIM SS 5K Model: CIO-MB20W1C-SS5K-USWL7 Battery Capacity: 5000mAh / 3.85V / 19.25Wh Rated Capacity: 2800mAh (5V⎓3A) USB-C Input: 5V⎓3A / 9V⎓1.67A USB-C Output: 5V⎓3A / 9V⎓2.22A PPS: 5-11V⎓1.8A Wireless Output: 5W / 7.5W / EPP 15W Dimensions: Approx. 101.4 × 69.4 × 6.83 mm Weight: Approx. 112 g Cycle Limit: Approx. 300 cycles Charging Time: Approx. 120 minutes *The USB-C output and wireless output of the power bank cannot be output simultaneously.	Q. Can I continue using the product after the cycle limit has been exceeded? A. Yes. Perform the operation below. Unlock: Press the button 10 times within [TBD] seconds. Products used beyond the cycle limit are not eligible for replacement under the warranty service. Note: The CIO collection discount service is available only if the product is not swollen. Q. Can I use the product without the app? A. Yes. Basic functions can be operated using the button on the product. Without the app, charging status and various settings cannot be checked or changed on a smartphone. Q. The leftmost LED is red. Is this a malfunction? A. No. It indicates the cycle count. Clear caution indication: Press the button 3 times within [TBD] seconds. Clear warning/unlock indication: Press the button 10 times within [TBD] seconds.	FCC WARNING STATEMENT This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.	However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: -- Reorient or relocate the receiving antenna. -- Increase the separation between the equipment and receiver. -- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. -- Consult the dealer or an experienced radio/TV technician for help. FCC Radiation Exposure Statement The device has been evaluated to meet general RF exposure requirement.	PRODUCT WARRANTY / SUPPORT Use the corresponding approved English common text from the existing instruction-manual master. LINE / YouTube Retain the existing official QR-code blocks and common English labels. Note: Warranty wording must remain consistent with the NovaCore C3 cycle-limit conditions.