

Prüfbericht-Nr.: <i>Test report no.:</i>	CN26LMQK 004	Auftrags-Nr.: <i>Order no.:</i>	168584454	Seite 1 von 10 Page 1 of 10
Kunden-Referenz-Nr.: <i>Client reference no.:</i>	N/A	Auftragsdatum: <i>Order date:</i>	2025-11-17	
Auftraggeber: <i>Client:</i>	Moga Technology Co., Ltd. 6-201 Room, business street, Huashan Road, Longshan district, Economic and Technological Development Area, Wuhu 241000 Anhui, P.R. China			
Prüfgegenstand: <i>Test item:</i>	AiMOGA Argos			
Bezeichnung / Typ-Nr.: <i>Identification / Type no.:</i>	X1			
Auftrags-Inhalt: <i>Order content:</i>	Test Report			
Prüfgrundlage: <i>Test specification:</i>	CFR Title 47 FCC Part 2: Section 2.1091 RSS-102 Issue 6 December 2023			
Wareneingangsdatum: <i>Date of sample receipt:</i>	2025-12-16	Please refer to photo documents		
Prüfmuster-Nr.: <i>Test sample no.:</i>	A004155645-001~007			
Prüfzeitraum: <i>Testing period:</i>	2026-01-20 - 2026-01-30			
Ort der Prüfung: <i>Place of testing:</i>	TÜV Rheinland (Shenzhen) Co., Ltd.			
Prüflaboratorium: <i>Testing laboratory:</i>	TÜV Rheinland (Shenzhen) Co., Ltd.			
Prüfergebnis*: <i>Test result*:</i>	Pass			
geprüft von: <i>tested by:</i>			genehmigt von: <i>authorized by:</i>	
Datum: <i>Date:</i>	2026-02-05 Signed by: Bell Hu	Ausstellungsdatum: <i>Issue date:</i>	2026-02-05 Signed by: Jonathan Li	
Stellung / Position:	Sachverständige(r)/Expert		Stellung / Position:	Sachverständige(r)/Expert
Sonstiges / <i>Other:</i>	FCC ID: 2BTJ8ARGOSX1 IC: 34938-ARGOSX1 HVIN: X1			
Zustand des Prüfgegenstandes bei Anlieferung: <i>Condition of the test item at delivery:</i>	Prüfmuster vollständig und unbeschädigt <i>Test item complete and undamaged</i>			
* Legende:	P(ass) = entspricht o.g. Prüfgrundlage(n)	F(ail) = entspricht nicht o.g. Prüfgrundlage(n)	N/A = nicht anwendbar	N/T = nicht getestet
* Legend:	P(ass) = passed a.m. test specification(s)	F(ail) = failed a.m. test specification(s)	N/A = not applicable	N/T = not tested
Dieser Prüfbericht bezieht sich nur auf das o.g. Prüfmuster und darf ohne Genehmigung der Prüfstelle nicht auszugsweise vervielfältigt werden. Dieser Bericht berechtigt nicht zur Verwendung eines Prüfzeichens. <i>This test report only relates to the above mentioned test sample. Without permission of the test center this test report is not permitted to be duplicated in extracts. This test report does not entitle to carry any test mark.</i>				

Prüfbericht-Nr.: CN26LMQK 004
Test report no.:

Seite 2 von 10
Page 2 of 10

Anmerkungen
Remarks

1	Alle eingesetzten Prüfmittel waren zum angegebenen Prüfzeitraum gemäß eines festgelegten Kalibrierungsprogramms unseres Prüfhauses kalibriert. Sie entsprechen den in den Prüfprogrammen hinterlegten Anforderungen. Die Rückverfolgbarkeit der eingesetzten Prüfmittel ist durch die Einhaltung der Regelungen unseres Managementsystems gegeben. Detaillierte Informationen bezüglich Prüfkonditionen, Prüfequipment und Messunsicherheiten sind im Prüflabor vorhanden und können auf Wunsch bereitgestellt werden. <i>The equipment used during the specified testing period was calibrated according to our test laboratory calibration program. The equipment fulfils the requirements included in the relevant standards. The traceability of the test equipment used is ensured by compliance with the regulations of our management system. Detailed information regarding test conditions, equipment and measurement uncertainty is available in the test laboratory and could be provided on request.</i>
2	Wie vertraglich vereinbart, wurde dieses Dokument nur digital unterzeichnet. Der TÜV Rheinland hat nicht überprüft, welche rechtlichen oder sonstigen diesbezüglichen Anforderungen für dieses Dokument gelten. Diese Überprüfung liegt in der Verantwortung des Benutzers dieses Dokuments. Auf Verlangen des Kunden kann der TÜV Rheinland die Gültigkeit der digitalen Signatur durch ein gesondertes Dokument bestätigen. Diese Anfrage ist an unseren Vertrieb zu richten. Eine Umweltgebühr für einen solchen zusätzlichen Service wird erhoben. Informationen zur Verifizierung der Authentizität unserer Dokumente erhalten Sie auf folgender Webseite: go.tuv.com/digital-signature <i>As contractually agreed, this document has been signed digitally only. TUV Rheinland has not verified and unable to verify which legal or other pertaining requirements are applicable for this document. Such verification is within the responsibility of the user of this document. Upon request by its client, TUV Rheinland can confirm the validity of the digital signature by a separate document. Such request shall be addressed to our Sales department. An environmental fee for such additional service will be charged. For information on verifying the authenticity of our documents, please visit the following website: go.tuv.com/digital-signature</i>
3	Prüfklausel mit der Note * wurden an qualifizierte Unterauftragnehmer vergeben und sind unter der jeweiligen Prüfklausel des Berichts beschrieben. Abweichungen von Prüfspezifikation(en) oder Kundenanforderungen sind in der jeweiligen Prüfklausel im Bericht aufgeführt. <i>Test clauses with remark of * are subcontracted to qualified subcontractors and described under the respective test clause in the report.</i> <i>Deviations of testing specification(s) or customer requirements are listed in specific test clause in the report.</i>
4	Die Entscheidungsregel für Konformitätserklärungen basierend auf numerischen Messergebnissen in diesem Prüfbericht basiert auf der "Null-Grenzwert-Regel" und der "Einfachen Akzeptanz" gemäß ILAC G8:2019 und IEC Guide 115:2023, es sei denn, in der auf Seite 1 dieses Berichts genannten angewandten Norm ist etwas anderes festgelegt oder vom Kunden gewünscht. Dies bedeutet, dass die Messunsicherheit nicht berücksichtigt wird und daher auch nicht im Prüfbericht angegeben wird. Zu weiteren Informationen bezüglich des Risikos durch diese Entscheidungsregel siehe ILAC G8:2019. <i>The decision rule for statements of conformity, based on numerical measurement results, in this test report is based on the "Zero Guard Band Rule" and "Simple Acceptance" in accordance with ILAC G8:2019 and IEC Guide 115:2023, unless otherwise specified in the applied standard mentioned on Page 1 of this report or requested by the customer. This means that measurement uncertainty is not taken in account and hence also not declared in the test report. For additional information to the resulting risk based of this decision rule please refer to ILAC G8:2019.</i>

Prüfbericht - Nr.: CN26LMQK 004
Test Report No.:

Seite 3 von 10
Page 3 of 10

Test Summary

3.1.1 RF EXPOSURE COMPLIANCE
RESULT: Pass

Contents

1.	TEST SITES.....	5
1.1	TEST FACILITIES.....	5
1.2	TRACEABILITY.....	5
1.3	CALIBRATION.....	5
1.4	LOCATION OF ORIGINAL DATA.....	5
1.5	STATUS OF FACILITY USED FOR TESTING.....	5
2.	GENERAL PRODUCT INFORMATION.....	6
2.1	GENERAL DESCRIPTION.....	6
2.2	RATING AND SYSTEM DETAILS.....	6
3.	TEST RESULTS.....	8
3.1	RF EXPOSURE EVALUATION.....	8
3.1.1	RF Exposure Compliance.....	8

1. Test Sites

1.1 Test Facilities

TÜV Rheinland (Shenzhen) Co., Ltd.

2-3F, 101 & 102, No.2, Nuclear Power Industrial Park, Fuming Community, Fucheng Street, Longhua District, Shenzhen 518000, China

FCC Accreditation Designation No.: 694916

ISED wireless device testing laboratory: 25069

1.2 Traceability

All measurement equipment calibrations are traceable to NIST or where calibration is performed outside the United States, to equivalent nationally recognized standards organizations.

1.3 Calibration

Equipment requiring calibration is calibrated periodically by the manufacturer or according to manufacturer's specifications. Additionally all equipment is verified for proper performance on a regular basis using in house standards or comparisons.

1.4 Location of Original Data

The original copies of all test data taken during actual testing were attached at Appendixes of this report and delivered to the applicant. A copy has been retained in the TÜV Rheinland (Shenzhen) file for certification follow-up purposes.

1.5 Status of Facility Used for Testing

The TÜV Rheinland (Shenzhen) Co., Ltd. Test facility located at 2-3F, 101 & 102, No.2, Nuclear Power Industrial Park, Fuming Community, Fucheng Street, Longhua District, Shenzhen 518000, China is listed on the US Federal Communications Commission list of facilities approved to perform measurements.

2. General Product Information

2.1 General Description

The Product is an AiMOGA Argos which support 2.4GHz Wi-Fi, 5GHz Wi-Fi and Lora wireless technologies.

For details refer to the User Manual, Technical Description and Circuit Diagram.

2.2 Rating and System details

Table 1: Technical Specification of EUT

General Information of EUT	Value
Kind of Equipment:	AiMOGA Argos
Type Designation:	X1
FCC ID:	2BTJ8ARGOSX1
IC:	34938-ARGOSX1
HVIN:	X1
Operating Voltage:	Battery operated (28.8Vdc)
Radiofrequency operating mode:	1) 2.4GHz Wi-Fi: operating within 2400-2483.5MHz 2) 5GHz Wi-Fi: operating within 5150-5250 MHz 3) Lora: 902-928MHz
Technical Specification of Lora	
Operating Frequency:	902.83-926.83 MHz
Channel Number:	31
Channel Separation:	800kHz
Antenna Type:	Integral Antenna
Antenna Number:	1Tx1Rx
Antenna Gain:	5 dBi (Provided by the Client)
Technical Specification of 2.4GHz Wi-Fi	
Operating Frequency:	2412 - 2462 MHz for 802.11b/g/n(HT20)/ax(HE20) 2422 - 2452 MHz for 802.11n(HT40)/ax(HE20)
Type of Modulation:	DSSS, OFDM, OFDMA
Data Rate:	1/2/5.5/11 Mbps for 802.11b 6/9/12/18/24/36/48/54 Mbps for 802.11g MCS0~MCS 7 for 802.11n(HT20/40) MCS0~MCS 11 for 802.11ax(HE20/40) (All data rates considered, only the Worst-cases reported, only Full RU supported in 802.11ax.)
Channel Number:	11 channels for 802.11b/g/n(HT20)/ax(HE20) 7 channels for 802.11n(HT40)/ax(HE40)
Channel Separation:	5 MHz
Antenna Type:	Integral Antenna
Antenna Number:	2Tx2Rx
Antenna Gain:	Antenna 1: 0.87 dBi

Prüfbericht - Nr.: **CN26LMQK 004**
Test Report No.:Seite 7 von 10
Page 7 of 10

	Antenna 2: 0.16 dBi (Provided by the Client)
Technical Specification of 5GHz Wi-Fi	
Operating Frequency:	5180-5240MHz
Protocol:	802.11 a/n20/n40/ac20/ac40/ac80/ax20/ax40/ax80
Channel Number:	4 channels for 20MHz 2 channels for 40MHz 1 channel for 80MHz
Type of Modulation:	OFDM(BPSK/QPSK/16QAM/64QAM/256QAM/1024QAM)
Data Rate:	6/9/12/18/24/36/48/54 Mbps for 802.11a MCS0~MCS7 for 802.11n MCS0~MCS9 for 802.11ac MCS0 ~ MCS11 for 802.11ax (All data rates considered, only the Worst-cases reported. Only Full RU supported in 802.11ax)
Channel Separation:	20MHz, 40MHz, 80MHz
Antenna Type:	Integral Antenna
Antenna Number:	2Tx2Rx
Antenna Gain:	Antenna 1: 1.45 dBi Antenna 2: 1.05 dBi (Provided by the Client)

3. Test Results

3.1 RF Exposure Evaluation

3.1.1 RF Exposure Compliance

RESULT:
Pass

Test standard : CFR Title 47 FCC Part 2.1091
KDB 447498 D01 General RF Exposure Guidance
v06
RSS-102 Issue 6

Limit : Table 1 of CFR Title 47 FCC Part 1.1310
Section 6.6 of RSS-102 Issue 6

This device is mobile device, and the applicant declares that the minimum separation distance is greater than 20cm. Therefore, MPE measurement or computational modelling should be used to determine compliance.

3.1.1.1 RF Exposure Compliance Requirement for FCC

a) Radio Frequency Exposure Limit

According to ANSI/IEEE C95.1-1992, the criteria listed in Table 1 shall be used to evaluate the environmental impact of human exposure to radio frequency (RF) radiation as specified in §1.1310.

Frequency range (MHz)	Electric field strength (V/m)	Magnetic field strength (A/m)	Power density (mW/cm ²)	Averaging time (minutes)
(A) Limits for Occupational/Controlled Exposures				
0.3-3.0	614	1.63	*(100)	6
3.0-30	1842/f	4.89/f	*(900/f ²)	6
30-300	61.4	0.163	1.0	6
300-1500			f/300	6
1500-100,000			5	6
(B) Limits for General Population/Uncontrolled Exposure				
0.3-1.34	614	1.63	*(100)	30
1.34-30	824/f	2.19/f	*(180/f ²)	30
30-300	27.5	0.073	0.2	30
300-1500			f/1500	30
1500-100,000			1.0	30

b) Radio Frequency Exposure Calculation Formula

$$S = \frac{PG}{4\pi R^2}$$

where: S = power density (in appropriate units, e.g. mW/cm²)
P = power input to the antenna (in appropriate units, e.g., mW)
G = power gain of the antenna in the direction of interest relative to an isotropic radiator
R = distance to the center of radiation of the antenna (appropriate units, e.g., cm)

or:

$$S = \frac{EIRP}{4\pi R^2}$$

where: EIRP = equivalent (or effective) isotropically radiated power

c) RF Exposure Calculations for FCC, stand-alone mode

Operating Mode	Max. Peak power incl. tune-up (dBm)	Max. EIRP (dBm)	Distance (cm)	MPE P _d (mW/cm ²)	Limit (mW/cm ²)	Verdict
2.4GHz Wi-Fi	25.5	26.03	20	0.08	1.0	Pass
5GHz Wi-Fi	20.0	21.45	20	0.03	1.0	Pass
Lora	23.0	28.0	10	0.13	0.6	Pass

d) RF Exposure Calculations for FCC, Simultaneous mode

Co-location Mode	Sum of the MPE Ratios	Limit	Verdict
2.4GHz Wi-Fi + Lora	0.08/1.0+0.13/0.6=0.29	1.0	Pass

e) Conclusion

Therefore the maximum calculations result of above are meet the requirement of Radio Frequency Exposure (MPE) limit.

3.1.1.2 RSS-102 Exemption Limits for Routine Evaluation – RF Exposure Evaluation

The EUT shall comply with the requirement of RSS-102 section 6.6.

Exemption from Routine Evaluation Limits – RF Exposure Evaluation

RF exposure evaluation is required if the separation distance between the user and/or bystander and the device's radiating element is greater than 20 cm, except when the device operates as follows:

at or above 300 MHz and below 6 GHz and the source-based, time-averaged maximum e.i.r.p. of the device is equal to or less than $1.31 \times 10^{-2} f^{0.6834}$ W (adjusted for tune-up tolerance), where f is in MHz;

In these cases, the information contained in the RF exposure technical brief may be limited to information that demonstrates how the e.i.r.p. was derived.

a) RF Exposure Calculations for ISSED, Stand-alone mode

Operating Mode	Max. EIRP incl. tune-up (dBm)	Maximum EIRP (W)	Distance (cm)	Threshold power (W)	Verdict
2.4GHz Wi-Fi	26.03	0.401	20	2.68	Pass
5GHz Wi-Fi	21.45	0.140	20	4.53	Pass
Lora	28	0.631	20	1.37	Pass

Note: The maximum EIRP lower than the threshold power in section 6.6, thus compliant.

b) RF Exposure Calculations for ISSED, Simultaneous mode

Co-location Mode	Sum of the MPE Ratios	Limit	Verdict
2.4GHz Wi-Fi + Lora	$0.401/2.68 + 0.631/1.37 = 0.61$	1.0	Pass

c) Conclusion

“RF Radiation Exposure Statement Caution: This Transmitter must be installed to provide a separation distance of at least 20 cm from all persons.”