






BLUETOOTH CEILING SPEAKER



Product Details:




Features:

- The stereo wireless Bluetooth transmission solution utilizes the JL7034A chip from JL as the module, providing high-quality sound quality and compatibility, resulting in superior overall performance;
- AC100V~AC240V power supply with adapter;
- Transmission distance 15 meters;
- Digital Class D amplifier;
- 2-way coaxial system
- Frame-mounted spring-loaded clamps provide secure, low-noise connections and easy installation;
- Attractive color ABS resin finish with white grille suits any decor.


Specifications:

Rated power: 2CH amplifier 2*30W
 Frequency Response: 90Hz-18KHz (± 3 dB) ;
 THD: <0.05% at 1kHz, 1/3 rated power;
 S/N: >80dB;
 Protocols: HFPV1.5, A2DPV1.2, AVRCPV1.4,
 HSP1.2, GAVDP1.2, IOP;
 Speaker unit: full range 6" * 1" * 1";
 Power Consumption: 2CH(75W) ;
 Installation: in ceiling;
 Finish : white; baffle & Enclosure: ABS resin,
 grille & mounting hardware steel alloy;
 Power supply: adapter AC100V~AC240V $\pm 10\%$ 50-60Hz;
 Dimension: $\Phi 236 \times 95$;
 Cutting hole: $\Phi 205$;
 Gross weight: 2CH(3.5Kg);

Installation:




Connection:



Mobile Phone Pairing:

1. Open Bluetooth of mobile phone.
2. "MT30" will be shown then click to connect it


Computer Pairing :




1. Enter the "SETTING" of "START" menu.



3. Open "Bluetooth".



2. Enter the "SETTING" menu.



4. Make connection.



Note: please prepare separate Bluetooth adapter if computer does not have one built-in!

FCC WARNING

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To maintain compliance with FCC's RF Exposure guidelines, This equipment should be installed and operated with minimum 20cm distance between the radiator and your body: Use only the supplied antenna.