

80MM

120MM


Quick-operation Manual

2.4G WIFI

Coziwow Pet Camera mini1
Model: CWP0467
Input: DC 5V 1A
Power: 5W



1. Main Function Description



2. Download for App

Search for "Smart Life" in App Store/App Market, or scan the QR code below to download.



Scan QR code to download



1

3. Register / Log in with existing account

1. Register

If you do not have an App account yet, you can register an account or log in via SMS verification code. Please read the current page and the next page for the description of registration process.

Click "Create New Account", enter Privacy Policy page on Smart Life, click to Agree and enter the registration page for Mobile number or E-mail address.



2. Log in with existing account

If you already have registered an account, you can skip the creating a new account. Click "Log in with existing account", enter the log in page.

(1) The system automatically select the current Country/Region, or you can manually select the Country/Region.

(2) Enter your registered mobile number or e-mail address, enter your password to log in the system.

Log in with social media account.

If your phone has installed Wechat App or QQ App, click Wechat/QQ icon in the log in with social media account area. After accessing the authorization page, log in the system.

2

4. Add Device

A. BLE net-pairing(Recommended)

The product only support 2.4GHz Wi-Fi network. It does not support 5GHz Wi-Fi network. Before configuring Wi-Fi, please set the router parameters and turn on the Bluetooth switch on your phone. When configuring Wi-Fi, make sure your router, mobile and device are as close as possible for a quick configuration of the device.

● Power the camera, and you can hear the broadcast "Please use... to config the device". If you heard nothing at all, please click "Reset" to restore the factory settings.

● When the mobile phone connecting to Wi-Fi and Bluetooth turned on, on the Home of the App, click "Add Device" (figure 0), or on the "Add Device" page of the App, click the camera icon (figure 1).

● Enter Wi-Fi account and password, click "Next" (figure 2).

● When you hear "connecting to the network", wait for connecting (figure 3).

● Device added successfully (figure 4), you can choose the device name and room name.

3



figure 0

figure 1

figure 2




figure 3

figure 4

B. AP mode net-pairing

The product only support 2.4GHz Wi-Fi network. It does not support 5GHz Wi-Fi network. Before configuring Wi-Fi, please set the router parameters. When configuring Wi-Fi, make sure your router, mobile and device are as close as possible for a quick configuration of the device.

● Power the camera, and you can hear the broadcast "Please use... to config the device". If you heard nothing at all, please click "Reset" to restore the factory settings.

● When the mobile phone connecting to Wi-Fi, click "Add Device" (figure 0) on the Home of the App, select "Camera icon" (figure 1), click "Smart Camera", click the button in the upper right corner (figure 7) - select "Wi-Fi Mode", click "Next" three times (figure 8) - select "AP Mode" (figure 9).



figure 5

figure 6

figure 7

5



figure 8

figure 9



figure 10

● Click the return button in the upper left corner (figure 11) - click "Go To Connect" (figure 12) - connect phone to the hotspot "SmartLifeXXXX" (figure 13), the password of hotspot is "12345678".

6



figure 11

figure 12

figure 13

- When you hear "connecting to the network", wait for connecting (figure 14).
- Device added successfully (figure 15), you can choose the device name and room name.



figure 14

figure 15

7


5. Function description

Real-time preview interface

1. Setting Management
2. Wi-Fi signal strength
3. Sound switch
4. SD card
5. Full screen
6. Screenshot
7. Voice chat
8. Record live view
9. Playback of video

(10) PTZ control: The camera can be automatically rotated to give you a different perspective. You can move it up and down, replace any corner you want to view.

(11) Motion detection alarm (abnormal report notification through intelligent direction of sound) in home. You can go out to work and play confidently. To set the alarm level according to the camera's field of view can make the alarm more accurate.



6. 9 Click "Me" in the upper right corner of the control page for the management and setting of the device.

Device Name—can modify the device name and device location.

Share Device—can share this device to other people, enter the people's mobile phone number. Note: the entered mobile phone number should be registered with a Type App account.

8

- Device Information—can view Device ID, Wi-Fi signal strength, IP address, MAC address, Device time zone.
- Echo-amazon Alexa Echo-amazon Alexa (figure 10).
- Motion detection—can set the motion detection switch and motion detection alarm sensitivity.
- Memory card settings—switch.
- Value-added Service Purchase—OTA Remote Upgrade (Do not disconnect during upgrade).




figure 9

figure 10

7. Click "Me" on the Home of the App for more services

1. Voice Service: click on the corresponding speech key for the connection description.

2. Other Services:

(1) PTZ: How to connect to PTZ.

(2) Value-added Service Orders: you can check the purchasing record of purchased value-added services.

(3) AI smart detection: push the event picture reported by the smart camera.

9

(4) Video cloud storage: after purchasing the service, the device can encrypt and upload the video record data to the server, and the user can view the recorded video at any time on the App.

(5) Mobile phone notification: after purchasing the service, the device can automatically notify the user's mobile phone when the notification condition is triggered. The device is enabled for multiple-number notification, protecting the safety of you and your family any time and any where.

Q: How to add device during net-pairing?

A: Please make sure the mobile phone and device are connected to 2.4GHz router. Make sure the correct Wi-Fi password is entered.

Q: Still fail to add device after re-connecting?

A: If fail to add device, it is recommended to restart the device or power off the device, and try again.

Q: Why the device is still on the list after restarting the device?

A: The device resetting only resets the camera's network configuration and cannot change the configuration on the App. You must log in the App to delete the camera from the list.

Q: How to connect the camera to another router?

A: First log in the App to delete and reset the device, and configure the device again through the App.

Q: Why the device cannot identify SD card?

A: It is recommended to insert and remove the SD card at the power off the device. Check if the SD card is under normal service conditions and the format is FAT32. The App still support: could not find SD card under use. Take the back of the mobile phone or the device.

Q: The device is online and has an alarm event, but the mobile phone cannot receive the information?

A: First confirm that App allows notification in the settings of your mobile phone, under normal circumstances, when an anomaly is detected, a message will appear in the notification bar of your mobile phone. You should set a notification sound or vibration in your mobile phone.

In addition, when viewing the real-time video in the App, you cannot receive alarm of the camera being viewed. Because the device defaults the camera being viewed indicating that the user is focusing on the monitoring video, and there is no need for an alarm.

Q: The device is online and has an alarm event, but the mobile phone cannot receive the information?

A: First confirm that App allows notification in the settings of your mobile phone, under normal circumstances, when an anomaly is detected, a message will appear in the notification bar of your mobile phone. You should set a notification sound or vibration in your mobile phone.

In addition, when viewing the real-time video in the App, you cannot receive alarm of the camera being viewed. Because the device defaults the camera being viewed indicating that the user is focusing on the monitoring video, and there is no need for an alarm.

Q: The device is online and has an alarm event, but the mobile phone cannot receive the information?

A: First confirm that App allows notification in the settings of your mobile phone, under normal circumstances, when an anomaly is detected, a message will appear in the notification bar of your mobile phone. You should set a notification sound or vibration in your mobile phone.

In addition, when viewing the real-time video in the App, you cannot receive alarm of the camera being viewed. Because the device defaults the camera being viewed indicating that the user is focusing on the monitoring video, and there is no need for an alarm.

Q: The device is online and has an alarm event, but the mobile phone cannot receive the information?

A: First confirm that App allows notification in the settings of your mobile phone, under normal circumstances, when an anomaly is detected, a message will appear in the notification bar of your mobile phone. You should set a notification sound or vibration in your mobile phone.

In addition, when viewing the real-time video in the App, you cannot receive alarm of the camera being viewed. Because the device defaults the camera being viewed indicating that the user is focusing on the monitoring video, and there is no need for an alarm.

Q: The device is online and has an alarm event, but the mobile phone cannot receive the information?

A: First confirm that App allows notification in the settings of your mobile phone, under normal circumstances, when an anomaly is detected, a message will appear in the notification bar of your mobile phone. You should set a notification sound or vibration in your mobile phone.

In addition, when viewing the real-time video in the App, you cannot receive alarm of the camera being viewed. Because the device defaults the camera being viewed indicating that the user is focusing on the monitoring video, and there is no need for an alarm.

Q: The device is online and has an alarm event, but the mobile phone cannot receive the information?

A: First confirm that App allows notification in the settings of your mobile phone, under normal circumstances, when an anomaly is detected, a message will appear in the notification bar of your mobile phone. You should set a notification sound or vibration in your mobile phone.

In addition, when viewing the real-time video in the App, you cannot receive alarm of the camera being viewed. Because the device defaults the camera being viewed indicating that the user is focusing on the monitoring video, and there is no need for an alarm.

Q: The device is online and has an alarm event, but the mobile phone cannot receive the information?

A: First confirm that App allows notification in the settings of your mobile phone, under normal circumstances, when an anomaly is detected, a message will appear in the notification bar of your mobile phone. You should set a notification sound or vibration in your mobile phone.

In addition, when viewing the real-time video in the App, you cannot receive alarm of the camera being viewed. Because the device defaults the camera being viewed indicating that the user is focusing on the monitoring video, and there is no need for an alarm.

Q: The device is online and has an alarm event, but the mobile phone cannot receive the information?

A: First confirm that App allows notification in the settings of your mobile phone, under normal circumstances, when an anomaly is detected, a message will appear in the notification bar of your mobile phone. You should set a notification sound or vibration in your mobile phone.

In addition, when viewing the real-time video in the App, you cannot receive alarm of the camera being viewed. Because the device defaults the camera being viewed indicating that the user is focusing on the monitoring video, and there is no need for an alarm.

Q: The device is online and has an alarm event, but the mobile phone cannot receive the information?

A: First confirm that App allows notification in the settings of your mobile phone, under normal circumstances, when an anomaly is detected, a message will appear in the notification bar of your mobile phone. You should set a notification sound or vibration in your mobile phone.

In addition, when viewing the real-time video in the App, you cannot receive alarm of the camera being viewed. Because the device defaults the camera being viewed indicating that the user is focusing on the monitoring video, and there is no need for an alarm.

Q: The device is online and has an alarm event, but the mobile phone cannot receive the information?

A: First confirm that App allows notification in the settings of your mobile phone, under normal circumstances, when an anomaly is detected, a message will appear in the notification bar of your mobile phone. You should set a notification sound or vibration in your mobile phone.

In addition, when viewing the real-time video in the App, you cannot receive alarm of the camera being viewed. Because the device defaults the camera being viewed indicating that the user is focusing on the monitoring video, and there is no need for an alarm.

10

Using the advanced intelligent alarm push algorithm to ensure that the alarm message will not be frequently, but the camera will record all the alarm messages and videos."

After-sale instructions

1. Please refer to the real product, the manual is for reference only.

2. The product is updated in real time, it will upgrade without prior notice, please go to the official website for query.

3. The manual contains the basic function description of the product, please check the operation.

4. If there is any problem when using the camera, please contact the supplier or company in time.

5. We have tried our best to ensure the comprehensive and accurate manual content, but there may still be deviation from the actual situation. If there are any questions or disputes, please refer to the final interpretation of the company.

6. If you do not follow the instruction manual, any loss caused by it will be borne by yourself.

This manual is suitable for consumer products.

Product warranty card

Product name	Model
Date of purchase	Distributor
Shipping mail	
Customer name	Occupation
Telephone	Zip code
Work unit	
Contact address	

Instructions for warranty

Warranty period: one year. This warranty card is applicable to the series of products you purchased by our company.

In order to better serve you, please take good care of this card.

11

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

This device has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This device generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this device does cause harmful interference to radio or television reception, which can be determined by turning the device off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

—Reorient or relocate the receiving antenna.

—Increase the separation between the device and receiver.

—Connect the device into an outlet on a circuit different from that to which the receiver is connected.

—Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

FCC Radiation Exposure Statement.

The antennas used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be co-located for operating in conjunction with any other antenna or transmitter.

12