

FCC Appendix RF Test Data for 2.4GWIFI

FCC ID : 2BVHS-A-ONE

Company : Trinity Electronic Trading Co., Ltd.

EUT : Dashcam

Model Number : A-One

Report No. : CTA26020600102

Reviewed By : Eric Wang

Appendix A: DTS Bandwidth

Test Result

TestMode	Antenna	Frequency[MHz]	DTS BW [MHz]	FL[MHz]	FH[MHz]	Limit[MHz]	Verdict
11B	Ant1	2412	10.240	2406.920	2417.160	0.5	PASS
		2437	10.200	2431.960	2442.160	0.5	PASS
		2462	10.200	2456.920	2467.120	0.5	PASS
11G	Ant1	2412	15.920	2404.080	2420.000	0.5	PASS
		2437	15.760	2429.120	2444.880	0.5	PASS
		2462	15.840	2454.120	2469.960	0.5	PASS
11N20SISO	Ant1	2412	16.400	2403.640	2420.040	0.5	PASS
		2437	16.800	2428.600	2445.400	0.5	PASS
		2462	16.800	2453.400	2470.200	0.5	PASS
11N40SISO	Ant1	2422	35.680	2404.160	2439.840	0.5	PASS
		2437	35.600	2419.240	2454.840	0.5	PASS
		2452	35.600	2434.160	2469.760	0.5	PASS

Test Graphs


11B_Ant1_2412



11B_Ant1_2437



11B_Ant1_2462



11G_Ant1_2412



11G_Ant1_2437



11G_Ant1_2462



11N20SISO_Ant1_2412



11N20SISO_Ant1_2437




11N20SISO_Ant1_2462



11N40SISO_Ant1_2422



11N40SISO_Ant1_2437



11N40SISO_Ant1_2452




Appendix B: Occupied Channel Bandwidth

Test Result


TestMode	Antenna	Channel Frequency[MHz]	OCB [MHz]	FL[MHz]	FH[MHz]	Limit[MHz]	Verdict
11B	Ant1	2412	13.402	2405.3508	2418.7528	---	---
		2437	13.390	2430.3463	2443.7363	---	---
		2462	13.417	2455.3109	2468.7279	---	---
11G	Ant1	2412	16.849	2403.6338	2420.4828	---	---
		2437	16.875	2428.6032	2445.4782	---	---
		2462	16.772	2453.6812	2470.4532	---	---
11N20SISO	Ant1	2412	17.922	2403.0754	2420.9974	---	---
		2437	17.886	2428.0867	2445.9727	---	---
		2462	17.916	2453.0645	2470.9805	---	---
11N40SISO	Ant1	2422	36.084	2404.0575	2440.1415	---	---
		2437	36.026	2419.0736	2455.0996	---	---
		2452	36.062	2434.0286	2470.0906	---	---

Test Graphs


11B_Ant1_2412




11B_Ant1_2437




11B_Ant1_2462




11G_Ant1_2412




11G_Ant1_2437




11G_Ant1_2462




11N20SISO_Ant1_2412




11N20SISO_Ant1_2437




11N20SISO_Ant1_2462




11N40SISO_Ant1_2422



11N40SISO_Ant1_2437



11N40SISO_Ant1_2452



Appendix C: Maximum conducted output power

Test Result Peak

Test Mode	Antenna	Frequency[MHz]	Peak power [dBm]	Limit [dBm]	Verdict
11B	Ant1	2412	13.71	≤30.00	PASS
		2437	13.86	≤30.00	PASS
		2462	14.08	≤30.00	PASS
11G	Ant1	2412	13.72	≤30.00	PASS
		2437	13.99	≤30.00	PASS
		2462	14.18	≤30.00	PASS
11N20SISO	Ant1	2412	13.66	≤30.00	PASS
		2437	13.87	≤30.00	PASS
		2462	13.96	≤30.00	PASS
11N40SISO	Ant1	2422	14.00	≤30.00	PASS
		2437	14.29	≤30.00	PASS
		2452	14.29	≤30.00	PASS

Appendix D: Maximum power spectral density

Test Result


TestMode	Antenna	Frequency[MHz]	Result[dBm/3-100kHz]	Limit[dBm/3kHz]	Verdict
11B	Ant1	2412	-12.42	≤8.00	PASS
		2437	-11.62	≤8.00	PASS
		2462	-11.51	≤8.00	PASS
11G	Ant1	2412	-17.47	≤8.00	PASS
		2437	-17.80	≤8.00	PASS
		2462	-17.26	≤8.00	PASS
11N20SISO	Ant1	2412	-18.26	≤8.00	PASS
		2437	-17.66	≤8.00	PASS
		2462	-17.31	≤8.00	PASS
11N40SISO	Ant1	2422	-20.12	≤8.00	PASS
		2437	-20.04	≤8.00	PASS
		2452	-20.38	≤8.00	PASS

Test Graphs

11B_Ant1_2412




11B_Ant1_2437




11B_Ant1_2462




11G_Ant1_2412




11G_Ant1_2437




11G_Ant1_2462




11N20SISO_Ant1_2412




11N20SISO_Ant1_2437




11N20SISO_Ant1_2462




11N40SISO_Ant1_2422



11N40SISO_Ant1_2437



11N40SISO_Ant1_2452




Appendix E: Band edge measurements

Test Result


TestMode	Antenna	Channel Name	Frequency[MHz]	RefLevel[dBm]	Result[dBm]	Limit[dBm]	Verdict
11B	Ant1	Low	2412	1.64	-47.83	≤-18.36	PASS
		High	2462	1.79	-56.55	≤-18.21	PASS
11G	Ant1	Low	2412	-2.67	-33.06	≤-22.67	PASS
		High	2462	-2.34	-58.22	≤-22.34	PASS
11N20SISO	Ant1	Low	2412	-2.93	-35.22	≤-22.93	PASS
		High	2462	-2.64	-57.86	≤-22.64	PASS
11N40SISO	Ant1	Low	2422	-5.90	-34.09	≤-25.9	PASS
		High	2452	-5.73	-57.73	≤-25.73	PASS

Test Graphs


11B_Ant1_Low_2412




11B_Ant1_High_2462




11G_Ant1_Low_2412




11G_Ant1_High_2462




11N20SISO_Ant1_Low_2412




11N20SISO_Ant1_High_2462



11N40SISO_Ant1_Low_2422



11N40SISO_Ant1_High_2452



Appendix F: Conducted Spurious Emission

Test Result


TestMode	Antenna	Frequency[MHz]	FreqRange [Mhz]	RefLevel [dBm]	Result [dBm]	Limit [dBm]	Verdict
11B	Ant1	2412	Reference	-0.18	-0.18	---	PASS
			30~1000	-0.18	-67.81	≤-20.18	PASS
			1000~26500	-0.18	-54.84	≤-20.18	PASS
		2437	Reference	1.34	1.34	---	PASS
			30~1000	1.34	-67.2	≤-18.66	PASS
			1000~26500	1.34	-55.49	≤-18.66	PASS
		2462	Reference	2.02	2.02	---	PASS
			30~1000	2.02	-67.97	≤-17.98	PASS
			1000~26500	2.02	-55.27	≤-17.98	PASS
11G	Ant1	2412	Reference	-2.89	-2.89	---	PASS
			30~1000	-2.89	-67.42	≤-22.89	PASS
			1000~26500	-2.89	-54.72	≤-22.89	PASS
		2437	Reference	-3.62	-3.62	---	PASS
			30~1000	-3.62	-68.29	≤-23.62	PASS
			1000~26500	-3.62	-54.98	≤-23.62	PASS
		2462	Reference	-2.82	-2.82	---	PASS
			30~1000	-2.82	-67.59	≤-22.82	PASS
			1000~26500	-2.82	-55.3	≤-22.82	PASS
11N20SISO	Ant1	2412	Reference	-4.12	-4.12	---	PASS
			30~1000	-4.12	-68.22	≤-24.12	PASS
			1000~26500	-4.12	-55.19	≤-24.12	PASS
		2437	Reference	-2.39	-2.39	---	PASS
			30~1000	-2.39	-67.43	≤-22.39	PASS
			1000~26500	-2.39	-54.19	≤-22.39	PASS
		2462	Reference	-2.61	-2.61	---	PASS
			30~1000	-2.61	-67.6	≤-22.61	PASS
			1000~26500	-2.61	-54.68	≤-22.61	PASS
11N40SISO	Ant1	2422	Reference	-5.96	-5.96	---	PASS
			30~1000	-5.96	-67.98	≤-25.96	PASS
			1000~26500	-5.96	-54.72	≤-25.96	PASS
		2437	Reference	-6.32	-6.32	---	PASS
			30~1000	-6.32	-68.27	≤-26.32	PASS
			1000~26500	-6.32	-55.51	≤-26.32	PASS
		2452	Reference	-6.05	-6.05	---	PASS
			30~1000	-6.05	-68.18	≤-26.05	PASS
			1000~26500	-6.05	-55.2	≤-26.05	PASS

Test Graphs


11B_Ant1_2412_0~Reference



11B_Ant1_2412_30~1000




11B_Ant1_2412_1000~26500




11B_Ant1_2437_0~Reference



11B_Ant1_2437_30~1000




11B_Ant1_2437_1000~26500




11B_Ant1_2462_0~Reference



11B_Ant1_2462_30~1000




11B_Ant1_2462_1000~26500




11G_Ant1_2412_0~Reference



11G_Ant1_2412_30~1000




11G_Ant1_2412_1000~26500




11G_Ant1_2437_0~Reference



11G_Ant1_2437_30~1000




11G_Ant1_2437_1000~26500




11G_Ant1_2462_0~Reference



11G_Ant1_2462_30~1000



11G_Ant1_2462_1000~26500



11N20SISO_Ant1_2412_0~Reference



11N20SISO_Ant1_2412_30~1000

