



Product Parameter:

Bluetooth Standard: Bluetooth V6.0

Support: a2dp\avctp\avdtp\avrcp\hfp\spp\smp\att\gap\gatt\rfcomm\sdp\l2cap profile

Working Distance Range: 10m

Speaker Unit: 40mm

Working frequency Range: 2.402GHz-2.480GHz

Battery Specifications: 3.7V/500mAh

Charging Voltage: 5V/1A

Charging Time: About 2.5 hours

Items Included:

1. One Charging Line
2. One Aux-in Line
3. One Instruction
4. On E-EPA275 Bluetooth Headphone

Bluetooth Mode Operation:

Bluetooth pairing: Long press the “Mode” button for three seconds to turn on the headphone, it will enter the pairing mode automatically, indicator light flashes with white and orange. Turn on the smart device's Bluetooth searching function and select the device “E-EPA275”, no password is required, after successfully pairing, the LED indicator light stays white, voice prompts “Connected”.

Button Description:

- 1) Play/pause the music: Short press the “MFB knob” to play or pause the music
- 2) Answer/end of the call: Short press the “MFB knob” to answer or end of the call
- 3) Reject the call: Long press the “MFB knob” for 2 seconds
- 4) Next song: Double-click the “MFB knob”
- 5) Previous song: Triple-click the “MFB knob”
- 6) Increase volume: Turn the “MFB knob” counterclockwise
- 7) Decrease volume: Turn the “MFB knob” clockwise
- 8) Voice assistant: Triple-click the “Mode” button to activate the voice assistant
- 9) Clean pairing: Long press the “MFB knob” and the “Mode” button for 3 seconds at the same time to clean the paired device, voice prompts “di” , then enter the pairing mode

automatically, voice prompts “Bluetooth Mode”

10) Power off: Long press the “Mode” button for 3 seconds to turn off the headphone

ANC MODE:

Short press the “Mode” button to switch the ANC mode, voice prompts “ANC Mode”.

Short press the “Mode” button again to turn off the ANC mode, voice prompts “ANC Off”.

Low Latency Mode:

Press the “Mode” button for four times to turn on the low latency mode, voice prompts “Game Mode”.

Press the “Mode” button for four times again to turn off the low latency mode, voice prompts “Music Mode”.

“.

Spatial Mode:

Double press the “Mode” button to switch the Spatial Mode, voice prompts “Spatial Audio”.

Double press the “Mode” button again to turn off the Spatial Mode, voice prompts “Spatial Audio Off”.

LED Indicator Light Status:

Charging Status	LED indicator light stays orange when charging. When fully charged, LED indicator light stays white.
Pairing Status	LED indicator light alternating flashes white and orange.
Playing Status	LED indicator flashes white every 5 seconds.
ANC Status	LED indicator stays green.

Note:

If no pairing connection after the Bluetooth headset enters the pairing mode, please turn off the headset to save power.

Do not perform other operations when searching Bluetooth to prevent the program error.

Please select a proper volume while using to prevent damage to your ears.

Please note that a good environment for using the Bluetooth headsets, that can avoid damage to the headsets.

Please charge the headset after a long time none-use.

FCC Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver. -- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.

The RF exposure assessment was conducted 5 mm away from the human body.