


# Wireless Microphone

## User Manual




## ID Diagram



- ① Windproof Net
- ② Connection indicator light
- ③ Mute indicator light
- ④ Noise reduction indicator light
- ⑤ Battery indicator
- ⑥ Microphone Type-c charging port
- ⑦ Microphone clip
- ⑧ Switch key
- ⑨ port to connect phone
- ⑩ TRRS interface
- ⑪ Receiver switch button
- ⑫ Receiver power indicator light
- ⑬ Receiver connection indicator light
- ⑭ Headphone jack
- ⑮ Charging interface at the receiving end

## How to use

- Step 1: Connect the receiver to phone with port.
- Step 2: Press and hold the power on button of the microphone, and the indicator light will turn on green, indicating successful startup.
- Step 3: The indicator light for the connection between the receiver and transmitter remains on, and the phone can use the microphone to listen by opening apps such as camera live streaming videos.



Note: oppo / vivo / iqoo / realm brand mobile phones can be used normally only when they go to the settings (search "OTG" - turn on OTG power supply)

## About UI

### Microphone Transmitter

| Function                            | Button                                           | LED                                                                                              |
|-------------------------------------|--------------------------------------------------|--------------------------------------------------------------------------------------------------|
| Power on                            | Long press the 3S button K1                      | Connection indicator light green flashing slowly                                                 |
| Power off                           | Long press the 3S button K1                      | All the lights went out                                                                          |
| Unconnected                         |                                                  | Connection indicator light green flashing slowly                                                 |
| Connected                           |                                                  | The connection indicator light remains on                                                        |
| Noise reduction/ acoustic switching | Click button K1 to turn on/off noise reduction   | Off: Noise reduction indicator light off<br>On: Noise reduction indicator light on               |
| Reverberation                       | Three click button K1 to turn on/off reverb      | Off: Noise reduction indicator light breathing flash<br>On: Restore the previous lighting effect |
| Silent mode                         | Double click button K1 to pause/resume recording | Off: Mute indicator light off<br>On: Mute indicator light on                                     |
| Charging                            |                                                  | The charging red light is always on, and all lights are off when fully charged                   |
| LOW BATTERY                         |                                                  | The charging indicator light flashes once every 5 seconds                                        |

Note: If there is no connection for more than three minutes, it will automatically shut down. By default, the noise reduction are turned on when turned on.

### Receiver

| Function                 | Operate | LED                                           |
|--------------------------|---------|-----------------------------------------------|
| Power on                 |         | light flashing                                |
| Connect a transmitter    |         | One light stays on, while the other turns off |
| Connect two transmitters |         | Two lights are constantly on at the same time |

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
  - Increase the separation between the equipment and receiver.
  - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
  - Consult the dealer or an experienced radio/TV technician for help.
- NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.