

PetYoYo C8 AI Pet Camera Quick Start Guide

1. Product Introduction


PetYoYo C8 is an intelligent pet monitoring camera designed for cats, dogs, and other household pets, featuring simultaneous multi-pet recognition. Whether you're at work, traveling, or away from home, you can remotely view real-time video via your smartphone, engage in two-way voice communication, and receive instant alerts for pet activities and unusual behavior. The device also includes remote voice soothing, laser play, access to pet health records, and AI online health consultation,24/7 peace of mind for your pets.

2. Product Components

2.1 Package Contents

- PetYoYo C8 AI Pet Camera × 1
 - Magnetic Privacy Cover × 1
 - Magnetic Base × 1
 - Magnetic Iron Sheets × 2
- Power Adapter × 1 (Model varies by region)
 - Type-C Anti-Chew Power Cable × 1
 - Quick Start Guide (including built-in warranty card & quality certificate) × 1

2.2 Product Structure



- 01 Magnetic Privacy Cover
- 02 Reset Button
- 03 Type-C Power Port
- 04 microSD Card Slot

3. Quick Installation & Network Setup

3.1 Installation Location Recommendations

The PetYoYo C8 uses a close-range AI algorithm for Multi-Pet Recognition. For best recognition accuracy, place the device flat or magnetically attach it in your pet's daily activity area, ensuring the lens can fully capture their face. Suitable for floors, walls, feeders, litter boxes, and other flat surfaces.

Magnetic Installation Steps

1. Wipe the installation surface clean with a dry cloth. Oil, dust, or dirt will reduce adhesive strength and may cause the iron sheet to fall off.

2. Take out the magnetic plate, remove the protective films on both sides, then firmly stick the adhesive side onto a clean, flat surface.

Recommended installation height: 0–30 cm. Avoid pointing it directly at reflective surfaces such as glass, white walls, or mirrors. Do NOT use outdoors or in damp, extreme-temperature environments.

3. Attach the magnetic base to the back of the camera, then mount it onto the iron sheet for a secure hold.
4. For privacy, only install in common areas such as living rooms or entryways. Do NOT place in bedrooms, bathrooms, or dressing rooms.


Three Mounting Options



Back Magnetic Mount



Inverted Magnetic Mount



Upright Placement

3.2 Powering On

1. If using local storage, insert a microSD card (not included) into the slot on the back of the device with the metal contacts facing upward. Requires Class 10 or higher microSD card.
2. Use the provided power cable to connect the camera.
3. Connect the power adapter to the power supply.
4. The device powers on automatically. The indicator flashes orange rapidly, indicating pairing mode is active.
5. After pairing, create a pet profile to finish setup. You can now start using your camera.

3.3 Light Indicator Status

Light Status	Device State
Solid Blue	Connected, device running normally
Flashing Blue	Network connection abnormal
Fast Flashing Orange	Ready for pairing
Slow Flashing Orange	Firmware upgrading

3.4 App Pairing Steps

1. Download & Install the App
- Scan download the PetYoYo App.



App Download



Quick Start Guide

- Download Website: <https://www.petyoyocam.com/pages/download>
- Quick Start Guide: <https://www.petyoyocam.com/pages/guides>

2. Account Login

Email and major third-party social accounts supported.

3. Add Your Device

- Open the Camera Plugin page in the app, tap [+] at the top-right to add a device.
 - Select [Add Device], confirm the device is in fast flashing orange ready for pairing mode, then tap [AP Mode].
 - Enter your 2.4G/5G dual-band Wi-Fi name and password carefully.
4. Select the device hotspot from the list. The hotspot name in format such as PetYoYo-C8-xxxx.
 5. When the screen shows “Device Activated Successfully,” pairing is complete.

3.5 Adding Pets Profile

Open the Pet Plugin page in the app , tap [+] at the top-right to enter the “My Pets” page, then tap [Add Pet] at the bottom-right. Follow the on-screen prompts to enter your pet's information and sync it to the camera. Multi-Pet Recognition function will only activate after synchronization is complete.

3.6 Factory Reset

Long-press Reset Button for approx. 10s until light turns off. Fast-flashing orange light indicates reset complete.

4. Technical Specifications

Product Name	AI Pet Camera	Brand Name	PetYoYo
Model	C8	Dimensions	57.6 × 56.3 × 140.6 mm
Power Input	DC 5V / 2A	Video Codec	H.265
Resolution	2560 × 1440	Local Storage	microSD Card
Operating Temp	-10°C – 45°C	Wireless	Wi-Fi 802.11 a/b/g/n/ac, 2.4GHz & 5GHz Dual-Band
Net Weight	Approx. 213g (with base & cover)	Mobile OS	Android & iOS

5. Safety Precautions

5.1 Privacy Policy

For full details on how we handle personal information and data:
Official Website: <https://www.petyoyocam.com/policies/privacy-policy>

- 5.2 This device is for indoor use only. Do NOT expose it to rain, direct sunlight, or prolonged damp conditions.

5.3 Laser Safety Warning

Class 2 visible laser, Complies with IEC 60825-1 and FDA 21 CFR 1040.10. Wavelength 650 nm, max output ≤1mW.

Do not stare into laser beam. Do not allow children to operate the laser function unsupervised. Avoid prolonged continuous operation of the laser. NEVER aim the laser at people's or pets' eyes. Prolonged exposure may cause irreversible retinal eye damage.

- 5.4 Please use the original power adapter to ensure stable and safe operation.

- 5.5 Dispose of the product through appropriate e-waste recycling channels to prevent environmental contamination.

5.6 FCC Compliance Information

FCC ID: 2BXWE-C8

FCC Statement:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference
- (2) This device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: Reorient or relocate the receiving antenna.

—Increase the separation between the equipment and receiver.

—Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

—Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

5.7 RF Exposure Statement

This equipment shall be installed and operated with a minimum distance of 20cm between the radiator and the human body.

6. After-Sales Service

6.1 Warranty Policy

Limited warranty is valid only in the original purchasing region. This shall not override your statutory consumer rights. Full warranty terms, please visit <https://www.petyoyocam.com/policies/refund-policy>.

6.2 Exclusions from Free Warranty Coverage

The following circumstances are expressly excluded from free warranty service:

- ①Unauthorized disassembly or modification of the equipment;
- ②Damage caused by liquid ingress, drops, or physical impact;
- ③Malfunctions resulting from the use of non-genuine or incompatible power adapters;
- ④Damage attributable to force majeure events, including but not limited to earthquakes and floods.

6.3 Contact Us

Email: petyoyo.support@pixsmart.cn

7. Certificate of Conformity

Manufacturer: Shenzhen Super Pixel Intelligent Technology Co., Ltd.

Address: I2D, Building 1#, ShenInternational South China Digital Valley, Minxin Community Minzhi Street, Longhua District, Shenzhen City

8. Warranty Card

Please read, complete, and store this warranty card safely after purchase. Lost cards will not be reissued.

Item	Detail	Remarks
Customer Name		
Contact Info		
Product Model		
Serial Number		
Purchase Date		
Purchase Channel		
Invoice No.		
Repair Records		
Date	Fault Description & Cause	Resolution

PetYoYo — Your Pet's AI Health Guardian

© 2026 Shenzhen Super Pixel Intelligent Technology Co., Ltd. All Rights Reserved.