

* RF Exposure

1. Regulation

According to §15.247(i), systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess of the Commission's guidelines. See § 1.1307(b)(1) of this Chapter.

Limits for Maximum Permissible Exposure: RF exposure is calculated.

Frequency Range	Electric Field Strength [V/m]	Magnetic Field Strength [A/m]	Power Density [mW/cm ²]	Averaging Time [minute]
Limits for General Population / Uncontrolled Exposure				
0.3 ~ 1.34	614	1.63	*(100)	30
1.34 ~ 30	824/f	2.19/f	*(180/f ²)	30
30 ~ 300	27.5	0.073	0.2	30
300 ~ 1 500	/	/	f/1 500	30
1 500 ~ 15 000	/	/	1.0	30

f=frequency in MHz, * = plane-wave equivalent power density

MPE (Maximum Permissible Exposure) Prediction

Predication of MPE limit at a given distance: Equation from page 18 of OET Bulletin 65, Edition 97-01

$$S = PG/4\pi R^2 \quad (\Rightarrow R = \sqrt{PG/4\pi S})$$

S = power density [mW/cm²]

P = Power input to antenna [mW]

G = Power gain of the antenna in the direction of interest relative to an isotropic radiator

R = distance to the center of radiation of the antenna [cm]

2. RF Exposure Compliance Issue

The information should be included in the user's manual:

This appliance and its antenna must not be co-located or operation in conjunction with any other antenna or transmitter. A minimum separation distance of 20 cm must be maintained between the antenna and the person for this appliance to satisfy the RF exposure requirements.

3. Calculation Result of RF Exposure

-EPS10R4-16

Mode	Target power [dBm]	Tune up tolerance [dB]	Max tune up power [dBm]	Max tune up power [mW]	Ant Gain [dBi]	Ant Gain [mW]	Power Density at 20 cm [mW/cm ²]	Limit [mW/cm ²]
Lowest_ANT 1	0.00	±3.00	3.00	2.00	3.25	2.11	0.000 84	1.000 00
Total	-						0.000 84	1.000 00

- EPS10R4-08

Mode	Target power [dBm]	Tune up tolerance [dB]	Max tune up power [dBm]	Max tune up power [mW]	Ant Gain [dBi]	Ant Gain [mW]	Power Density at 20 cm [mW/cm ²]	Limit [mW/cm ²]
Lowest_ANT 1	0.00	±3.00	3.00	2.00	3.25	2.11	0.000 84	1.000 00
Total	-						0.000 84	1.000 00

4. Target power and tolerance, Max tuneup power

-EPS10R4-16

Mode	Target power [dBm]	Tolerance [dB]	Max tuneup power [dBm]	Average Power [dBm]
Lowest_ANT 1	0.00	±3.00	3.00	1.50
Middle_ANT 1	0.00	±3.00	3.00	1.06
Highest_ANT 1	0.00	±3.00	3.00	0.65
Lowest_ANT 2	0.00	±3.00	3.00	1.20
Middle_ANT 2	0.00	±3.00	3.00	0.76
Highest_ANT 2	0.00	±3.00	3.00	0.28

- EPS10R4-08

Mode	Target power [dBm]	Tolerance [dB]	Max tuneup power [dBm]	Average Power [dBm]
Lowest_ANT 1	0.00	±3.00	3.00	1.44
Middle_ANT 1	0.00	±3.00	3.00	1.02
Highest_ANT 1	0.00	±3.00	3.00	0.69
Lowest_ANT 2	0.00	±3.00	3.00	1.16
Middle_ANT 2	0.00	±3.00	3.00	0.73
Highest_ANT 2	0.00	±3.00	3.00	0.31